

### TRANSMITTAL LETTER

TO: Rick Jones City of Dover, NH  : ,  We are sending you: Enclosed/	Attached	DATE: FROM: PROJECT: PROJECT #:	March 1, 2010
We are sending you:  Shop Drawings Plans Specifications Damper Schedules Valve Schedules	Produc Copy o Sample	et Data Sheets	Copy of Letter Submittals Operations & Maint. Manuals Device Schedules
This material/information is being sent:  per your request. for your review and approval. for your review and comment.	for you approv	or record purposes ed as submitted. ed as noted.	for correction & resubmittal. for issue to subcontractors.
Information Sent  1. Ice Arena: 2. Chiller 3. Dehumidifier 4. Infared 5. Aluma Zorb 6.  Message/Comments: sent via email	# of Copies	Pate Above Action Required By	Comments
Delivered by: Aaron Alibrio Received by:			Date: 2/19/10 Date:

We are pleased to submit on the following:

#### Rink Chiller

#### One (1)

Carrier model 30HXC246RA-6--TA Water Cooled Screw Chiller, 460v/3ph, including:

- Microprocessor controls
- Dual independent refrigerant circuits
- Standard factory charge R134a refrigerant
- Standard pass cooler
- Suction service valves
- Across the line starter
- Factory brine option for chilled water temperatures to 15-deg. F.
- Head insulation kit
- Vibration isolation mounting pads
- Condenser water temperature thermisters with wells
- Factory start-up and first year warranty labor  $2^{nd} 5^{th}$  Year extended compressor parts warranty

#### Refrigerant Monitor

#### One (1)

Genesis International Inc. Sherlock 402 Refrigerant Gas Monitoring System, including:

- Sherlock 402 Control Module
- Sherlock 82-0101 R-134a CMOS Room Sensor
- Sherlock 88-0150 R-134a CMOS Vent Line Sensor
- Sherlock 88-0233 Combo Strobe/Horn

Date:	Supersedes:	30HXC076-271 WATER-COOLED LIQUID CHILLER	30HXC	Rev: -8SB				
JOB NA	AME:	LOCATION:						
BUYER	<b>R</b> :	BUYER P.O. #	BUYER P.O. # CARRIER #					
UNITN	IUMBER:	MODEL NUMBER:						
PERFO	RMANCE DATA CERTIFIED I	BY:	DATE:					

#### DESCRIPTION

Packaged water-cooled liquid chillers are factory wired, piped, and charged with HFC-134a.

#### **FEATURES**

Cooler is mechanically cleanable shell-and-tube type with removable heads. It is tested and stamped in accordance with ASME Code for a refrigerant working side pressure of 235 psig (1620 kPa) and a minimum water side pressure of 300 psig (2068 kPa) (250 psig [1720 kPa] in Canada).

Compressor is semi-hermetic twin screw design with refrigerant gas cooled motor and integral oil filter and discharge gas muffler.

Complete thermal and electrical protection is provided.

Water-cooled condenser is mechanically cleanable shell-and-tube type with removable heads and is tested and stamped in accordance with ASME Code for a refrigerant working side pressure of 235 psig

(1620 kPa) and a minimum water side pressure of 300 psig (2068 kPa) (250 psig [1720 kPa)] in Canada).

Each refrigerant circuit includes oil separator, high side pressure relief device, liquid and discharge line shutoff valve, filter drier, moisture indicating sight glass, expansion valve.

Microprocessor control includes keypad, system status (including temperatures, pressures and % loading) and the alarm conditions.

Automatic circuit lead/lag.

Capacity control based on leaving chilled water temperature with return water temperature sensing.

7-day time scheduling of pump(s) and chiller.

### 30 Series Chillers Performance Summary

Project Name: Untitled Company Name: Carrier Northeast

2/1/2010 2:31:06 PM

	Untitled
Location	
Buyer P.O.	
Date	2/1/2010
Version 2.92	
Unit Size	30HXC246***6***
Capacity, Tons	141.2
Compressor Input Power, kw	158.0
Unit Input Power, kw	158.0
Capacity control steps	8
Minimum Capacity, %	13.0
Input kw/Ton	1,119
Unit EER	10.73
Refrigerant	R134a
Cooler Data	
Fluid Type	Ethylene glycol
Fluid concentration, %	35.0
Fluid Entering Temperature, °F	20,1
Fluid Leaving Temperature, °F	15.0
Fluid Flow Rate, gpm	750.0
Fluid Pressure Drop, it wg	35.7
Fluid Velocity, ft/s	7.1
Fouling Factor, (hr-sqft-F)/Btu	0.0001
Foul, Fact. Temp. Adj., °F	.35
Saturated Suction Temp., °F	(1.7.7)
Circuit A	9.7
Circuit B	10.5
Outside Surface Area, sqft	465,9
Condenser Data	
Fluid Type	Fresh Water
Fluid Entering Temperature, °F	75.0
Fluid Leaving Temperature, °F	85.0
Fluid Flow Rate, gpm	439.1
Fluid Pressure Drop, It wg	8.2
Fluid Velocity, ft/s	3.7
Fouling Factor, (hr-sqft-F)/Blu	0.00025
Foul. Fact. Temp. Adj., °F	.46
Saturated Discharge Temp., °F	
Circuit A	86.1
Circuit B	, 87.6
Outside Surface Area, sqft	547.7
Factory Options	
Flow Control Type	EXV
Chiller Electrical Data	
Nameplate Voltage, volts	460
Elec. Power Frequency, hertz	60
Power supply to control circuit, volts	115
Power supply to control circuit,	1
Minimum circuit amps	303
MOCP, amps	400
Max Instant, Current Flow (ICF), amos	950

Max Instant, Current Flow (ICF), amps

859

### 30 Series Chillers Performance Summary

Project Name: Untitled Company Name: Carrier Northeast

2/1/2010 2:31:06 PM

Control circuit fuse amps

15

Factory Installed Options

Suction Service Valve **Evaporator Passes** 

No Standard

Condenser Passes Start option

Standard Across the line

Minimum load control

None

Control transformer


None

ARI Rating

Outside the scope of ARI Standard 550/590-2003.

# **Dimensions (cont)**





# **Electrical data (cont)**



#### ELECTRICAL DATA, 30HXC UNITS (cont)

	UNIT VO	LTAG	E	POWER	NO. POWER			UNIT V	OLTAGI	E		CONTROL CI			RCUIT	
UNIT 30HXC	V-Hz	Sup	plied	SUPPLY	SUPPLY			ICF		Rec Fu	se Size	V-Hz	Sup	plied	MCA and	
00/1/(0	(3 Ph)	Min	Max	QTY. REQD.	CONDUCTORS	MCA	МОСР	XL	WD	XL	WD	(Single Ph)	Min	Max	MOCP	
171	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	6 6 3 3 3 6	428.4 476.0 215.0 171.8 260.2 266.6	600 700 300 250 350 350	771.1 616.8 861.2 961.8	604.5 623.6 302.1 241.8 343.2 375.8	250 200 300 300	500 600 250 200 300 300	115-60 115-60 115-60 115-60 230-60 230-50	104 104 104 104 207 198	127 127 127 127 127 254 254	15 15 15 15 15 15	
186	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1	6 6 3 3 3 3	440.4 462.3 513.7 232.0 185.4 280.8 289.4 478.1	600 700 300 250 400 400 600	788.1 630.4 881.8 984.6	638.5 661.3 319.1 255.4 363.8 398.6 644.5	300 225 350 350	500 600 300 225 350 350 600	230-50 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	254 127 127 127 127 254 254 254	15 15 15 15 15 15 15 15	
206	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1	6 6 3 3 3 6	524.5 582.8 263.2 210.4 318.6 326.8 539.8	700 800 350 250 400 450 700	819.3 655.4 919.6 1022.0	700.7 730.4 350.3 280.4 401.6 436.0 706.2	300 250 350 400	600 700 300 250 350 400 600	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15	
246	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1	6633336	604.1 671.3 303.2 242.3 367.0 377.6 623.8	800 800 400 300 450 500 800	859,3 687,3 968,0 1072,8	780.3 818.9 390.3 312.3 450.0 486.8 790.2	350 300 400 450	700 800 350 300 400 450 700	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15	
261	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1	6633666	633.8 704.3 318.1 254.2 385.0 395.2 652.9	800 800 400 300 500 500 800	874.2 699.2 986.0 1090.4	810.0 851.9 405.2 324.2 468.0 504.4 819.3	350 300 450 450	700 800 350 300 450 450 800	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15	
271	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	6 6 3 3 6 6 6	667.8 742.0 335.1 267.8 405.6 418.0 690.6	800 800 400 350 500 500 800	891.2 712.8 1006.6 1113.2	843.9 889.6 422.2 337.8 488.6 527.2 857.0	 400 300 450 500	800 800 400 300 450 500 800	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15	

#### LEGEND

Maximum Instantaneous Current Flow during start-up (the point in the starting sequence where the sum of the LRA for the start-up compressor, plus the total RLA for all running compressors is at a maximum)
Locked Rotor Amps
Minimum Circuit Ampacity (for wire sizing)
Maximum Overcurrent Protection
Rated Load Amps
Wye-Delta Start
Across-the-Line Start

LRA MCA MOCP

RLA WD XL Across-the-Line Start

NOTES:

1. Each main power source must be supplied from a field-supplied fused electrical service with a (factory-installed or field-installed) disconnect located in sight from the unit.

2. Control circuit power must be supplied from a separate source through a field-supplied disconnect (except for 380/415-50 units). An accessory control transformer may be used to provide control circuit power from the main unit power supply.

- Maximum incoming wire size for each terminal block is 500 kcmil.
   Maximum allowable phase imbalance is: voltage, 2%; amps, 5%.
   Use copper conductors only.
   The MOCP is calculated as follows:

 $\label{eq:mocp} \begin{array}{l} \text{MOCP} = (2.25) \text{ (largest RLA)} + \text{the sum of the other RLAs. Size the fuse} \\ \text{one size down from the result. The RLAs are listed on the nameplate.} \end{array}$ 

The recommended fuse size in amps (RFA) is calculated as follows: RFA = (1.50) (largest RLA) + the sum of the other RLAs. Size the fuse one size up from the result. The RLAs are listed on the nameplate.








# Product Data

### 30HXA,HXC076-271 Condenserless and Water-Cooled Liquid Chillers 50/60 Hz

75 to 265 Tons (264 to 931 kW)

# ComfortLink



ASHRAE

Water-cooled and condenserless chillers designed from the ground up to meet the needs of today and tomorrow:

- Unit fits through a standard door with no disassembly required
- Chlorine-free HFC-134a refrigerant
- Dual independent refrigerant circuits
- Smooth compression using twin screw compressors
- ARI certified efficiencies to 0.53 kW/ton

### Features/Benefits

Quality design and construction make the 30HXC (Water-Cooled) and 30HXA (Condenserless) units the preferred choice

#### Easy installation

The 30HX chiller has a compact design that fits through a standard door opening and requires minimal indoor space. The 30HX chiller is delivered as a complete package for easy installation. There are no extra controls, clocks, starters, or other items to install.

The 30HX unit also provides a single location electrical power entrance (using the accessory field-installed control power transformer) and quick, easy piping (using victaulic-type clampon couplings).

The 30HX 208/230-v, 230-v, 460-v and 575-v units are designed in accordance with UL (Underwriters' Laboratory, U.S.A.) and UL, Canada (Underwriters' Laboratory, Canada) standards to minimize electrical inspection time.



A quick start-up is assured once installation is complete, since each 30HX unit is manufactured at an ISO 9001:2000 listed manufacturing facility to guarantee quality. In addition, all 30HXC units are tested under load at the factory to provide reliable start-up. NOTE: Units shipped with optional nitrogen charge are tested for proper operation of the electrical components but are not run-tested at the factory.

#### Easy operation

The 30HX units have a quiet, lowvibration design featuring screw compressors.

Efficiency levels of the 30HX units meet or exceed energy efficiency requirements of ASHRAE (American Society of Heating, Refrigeration and Air Conditioning Engineers) 90.1-2001 and CSA (Canadian Standards Association) for both full-load and part-load operation, thus saving on operating costs through lower electrical costs. All 30HX units are also rated in accordance with ARI (Air Conditioning and Refrigeration Institute, U.S.A.) standards. The 60 Hz 30HXC units are ARI certified.


The 30HX controls are fully automatic. The leaving-fluid temperature is directly controlled to within .5° F (.3° C), and the entering-fluid temperature is continuously monitored to detect load and flow changes.

Dual, independent refrigerant circuits provide reliable, dependable cooling, and the 30HX units use medium-pressure HFC-134a refrigerant to

minimize stress on the compressors and ensure a long life.

From a service standpoint, the 30HX units offer the following features:

- Use of HFC-134a refrigerant, which has no planned phase-out in its future
- Mechanically cleanable cooler and condenser (30HXC units)
- Twin-screw compressors, which require no routine service or maintenance
- Easily accessed service information includes suction and discharge pressure and temperature using standard Navigator™ display module
- All parts are available through Totaline parts stores.



# **ARI\*** capacity ratings



#### 30HXC WATER-COOLED CHILLER ARI RATINGS (60 Hz ONLY)

SIZE		PACITY	INPUT POWER	COOLER	RFLOW	PRESS DRO	SURE	CONDE		CONDE PRESS DRO	URE	FULL-LOAD EFFICIENCY	IPLV†
30HXC	Tons	Output kW	(kW)	GPM .	L/s	Ft of Water	kPa	GPM	L/S	Ft of Water	kPa	(kW/Ton)	(kW/Ton)
076	75.4	265.2	53.7	181.0	11.4	12.6	37.7	226.2	14.3	8.0	23.9	0.712	0.512
086	83.1	292.3	60.4	199.4	12.6	15.1	44.9	249.3	15.7	9.6	28.6	0.727	0.523
096	94.0	330.5	67.0	225.5	14.2	14.9	44.6	281.9	17.8	9.9	29.4	0.713	0.513
106	104.3	366.8	75.3	250.3	15.8	13.4	40.1	312.9	19.7	12.0	35.7	0.722	0.521
116	113.6	399.4	79.9	272.6	17.2	11.7	34.9	340.7	21.5	15.3	45.5	0.703	0.509
126	123.0	432.6	86.8	295.2	18.6	13.5	40.3	369.0	23.3	17.7	52.7	0.706	0.509
136	136.5	479.9	97.0	327.5	20.7	12.8	38.3	409.4	25.8	16.7	49.9	0.711	0.527
146	145.9	513.2	105.1	350.2	22.1	14.5	43.3	437.8	27.6	19.0	56.5	0.720	0.533
161	156.5	550.6	111.7	375.7	23.7	12.0	35.7	469.6	29.6	19.4	57.9	0.714	0.520
171	165.9	585.3	118.2	398.1	25.1	13.3	39.6	497.6	31.4	15.9	47.4	0.712	0.538
186	177.2	623.1	126.7	426.2	26.8	12.1	36.2	531.6	33.5	18.0	53.7	0.715	0.562
206	211.6	744.0	146.4	507.7	32.0	12.8	38.2	634.7	40.0	19.0	56.7	0.692	0.510
246	248.6	874.1	172.4	596.5	37.6	14.1	42.1	745.7	47.0	20.1	59.9	0.693	0.522
261	257.2	904.6	180.5	617.3	38.9	15.0	44.8	771.6	48.7	21.4	63.9	0.702	0.523
271	267.4	940.3	189.5	641.7	40.5	16.1	48.0	802.1	50.6	23.0	68.7	0.709	0.525

LEGEND

IPLV — Integrated Part-Load Value

\*Air Conditioning and Refrigeration Institute (U.S.A.). †IPLV shown is the lower of Sequence A or Sequence B unloading.

1. Rated (60 Hz only) in accordance with ARI Standard 550/590-98

3.0 gpm per ton (0.054 L/s per kW)

Flow: 2.4 gpm per ton (0.043 L/s processed to the conditions: Entering Water temperature: 85 F (29.4 C) Flow: 3.0 gpm per ton (0.054 L/s processed to the conditions of the co

IPLV is a single number part-load efficiency value calculated from the system full-load efficiency values and corrected for a typical building air-conditioning application.

All data in this table is rated (60 Hz only) in accordance with ARI Standard 550/590-98 as represented in the ECOLOGIC™ Chiller Selection Program (E-Cat) version 2.80.

Contact Carrier for custom ratings.



Rated in accordance with ARI Standard 550/590-98.

60 Hz only





#### **ENGLISH** (cont)

UNIT SIZE 30HX	161	171	186	206	246	261	271
UNIT OPERATING WEIGHT (Ib)				200	240	201	2/1
Water-Cooled (HXC)	7452	7660	7854	10,581	10,969	10.992	11.029
Condenserless (HXA)	5752	5777	5946	7,485	7,621	7,621	7,621
COMPRESSORS				Hermetic, Twir			•
Quantity Nominal Capacity per Compressor (tons)	2 80/56	66/80	80/80	3	3	3	3
Economizer	Yes	Yes	Yes	66/39/80 Yes	80/56/80 Yes	80/66/80 Yes	80/80/80 Yes
No. Capacity Steps			100	100	103	163	165
Standard Optional (maximum)	6 8	6	6	8	8	8	8
Minimum Step Capacity (%)	8	8	8	11	11	11	11
Standard	20	20	20	13	13	13	13
Optional	10	10	10	7	7	7	7
REFRIGERANT	100.000.000.000.000	V97-1179-11200 - 1179-11		R-134a			
Charge* (lb) Circuit A/Circuit B	157/110	119/140	135/135	220/135	220/135	220/135	220/135
COOLER TYPE Part No. 10HX400-	004		Shell and Tube	with Enhance	d Copper Tube		
Net Fluid Volume (gal)	601 28.5	611 28.5	621	631	632	632	632
Maximum Refrigerant Pressure (psig)	220	220	220	43.1 220	47.2 220	47.2 220	47.2 220
Maximum Water-Side Pressure (psig)	300	300	300	300	300	300	300
Water Connections Inlet and Outlet (in.) (Standard Pass)	5	-	_		5-67750	220,000	
Drain (NPT) (Standard Pass)	3/8	5 3/8	5 3/8	6 3/8	6 3/8	6	6
Relief Valve	/*	78	78	9/8	9/8	3/8	3/8
Connection (in. NPTF)	3/4	3/4	3/4	3/4	3/4	3/4	3/4
Flow Capacity (lb air/min) Relief Setting (psig)	31.7 220	31.7	31.7	31.7	31.7	31.7	31.7
Standard Number of Passes	220	220	220 2	220	220 2	220	220 2
30HXA OIL SEPARATOR							
Part No. 09RX400-	215	214	214	213	213	213	213
Maximum Refrigerant Pressure (psig) Refrigerant Connections (in.)	320	320	320	320	320	320	320
Discharge Circuit A/B	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	01/ /01/	01/ /01/	01/ /01/
Liquid Circuit A/B	13/8/13/8	13/8/13/8	13/8/13/8	15/8/13/8	2 <sup>1</sup> / <sub>8</sub> /2 <sup>1</sup> / <sub>8</sub> 1 <sup>5</sup> / <sub>8</sub> /1 <sup>3</sup> / <sub>8</sub>	21/ <sub>8</sub> /21/ <sub>8</sub> 15/ <sub>8</sub> /13/ <sub>8</sub>	21/ <sub>8</sub> /21/ <sub>8</sub> 15/ <sub>8</sub> /13/ <sub>8</sub>
Relief Valve	1504 1050	1		14-13-14-011-1-00-0	2000	178/178	178/178
Connection (in. SAE Flare) Flow Capacity (ib air/min)	<sup>5</sup> / <sub>8</sub> 21.6	5/8	5/8	5/8	5/8	5/8	5/8
Relief Setting (psig)	320	21.6 320	21.6 320	21.6 320	21.6 320	21.6 320	21.6
CONDENSER (HXC)	020		hell and Tube				320
Part No. 09RX400-	261	262	1 262 I	263 I	264 I	S 264 I	264
Net Fluid Volume (gal)	30.6	37.6	37.6	47.6	55.1	55.1	55.1
Maximum Refrigerant Pressure (psig) Maximum Water-Side Pressure (psig)	220 300	220	220	220	220	220	220
Water Connections (in.)	300	300	300 Victar	300   lic Type Conne	300	300	300
Inlet and Outlet (Standard Pass)	6	6	6 1	8 I	8 1	8 1	8
Drain (NPT) (Standard Pass)	3/8	3/8	3/8	3/8	3/8	3/8	3/8
Relief Valve Connection (in. NPTF)	3/4	3/4	3/	3/	2,	21	25
Flow Capacity (Ib air/min)	31.7	31.7	3/ <sub>4</sub> 31.7	3/ <sub>4</sub> 31.7	<sup>3</sup> / <sub>4</sub> 31.7	<sup>3</sup> / <sub>4</sub> 31.7	<sup>3/</sup> 4 31.7
Relief Setting (psig)	220	220	220	220	220	220	220
Standard Number of Passes	2	2	2	2	2	2	2
DISCHARGE LINE†							
Relief Valve Connection (in. SAE Flare)	3/8	3/8	3/8	3/	2/	2,	0.7
Flow Capacity (lb alr/min)	6.3	6.3	6.3	<sup>3/8</sup> 6.3	<sup>3/8</sup> 6.3	<sup>3/8</sup> 6.3	<sup>3/8</sup> 6.3
Setting (psig)	350	350	350	350	350	350	350
LECEND							

LEGEND

NPTF — National Pipe Thread Female SAE — Society of Automotive Engineers

<sup>\*</sup>Charges listed are for 30HXC units. The 30HXA units are shipped with a holding charge only. To determine the refrigerant charge requirements for 30HXA units see the System Refrigerant Charge for Start-Up table in the Application Data on page 28. †Only on units with factory-installed suction service valves.

### Application data

#### Unit location

Unit should be level (particularly in its major lengthwise dimension) to assure proper oil return.

The unit should be located indoors in an area of temperature greater than  $50 \, \text{F}$  (10 C).

Good acoustic design practice should be followed, i.e., unit should not be located adjacent to sound-sensitive areas unless appropriate consideration has been made.

#### Cooler fluid temperature

- Maximum leaving water (fluid) temperature (LWT) is 60 F (21 C). Unit can start and pull down with up to 95 F (35 C) entering water (fluid) temperature due to MOP (maximum operating pressure) feature of the expansion valve. For sustained operation, it is recommended that entering fluid temperature not exceed 70 F (21.1 C).
- Minimum LWT is 40 F (4.4 C) for standard units.
  The brine option is required for operation with
  leaving fluid temperatures in the range of 39 to 12 F
  (4 to -9 C). For ratings below 40 F (4.4 C) LWT,
  contact your local Carrier representative.
- 3. Minimum entering water (fluid) temperature (EWT) is 45 F (7.2 C). Maximum EWT is 70 F (21.1 C).

#### Leaving-fluid temperature reset

The accessory reset sensor can be applied to the chiller to provide reset of in LWT constant fluid flow systems. Reset reduces compressor power usage at part load when design LWT is not necessary. Humidity control should be considered, since higher coil temperatures resulting from reset will reduce latent heat capacity. Three reset applications are offered:

From return-fluid temperature — Increases LWT set point as return (or entering) fluid temperature decreases (indicating load decrease). Reset from return fluid may be used in any application where return fluid provides accurate load indication. Limitation of return-fluid reset is that the LWT may only be reset to value of design return-fluid temperature. No additional hardware is required.

From outdoor-air temperature — Increases LWT as outdoor ambient temperature decreases (indicating load decrease). This reset should be applied only where outdoor ambient temperature is an accurate indication of load. A field-supplied thermistor is required.

From occupied space temperature — Increases LWT as space temperature decreases (indicating load decrease). This reset should be applied only where space temperature is an accurate indication of load. A field-supplied thermistor is required.

Temperature can also be reset using a 4 to 20 mA signal from the control system. This type of reset requires the Energy Management Module Accessory.

#### Condenser fluid temperature

 Maximum leaving condenser fluid temperature is 105 F (40.5 C) on all 30HXC units.



2. Standard 30HXC units will start at entering condenser fluid temperatures above 55 F (12.8 C). In general, however, continuous machine operation with entering condenser fluid temperatures below 70 F (21.1 C) is not recommended. When the entering condenser fluid temperature is expected to drop below 70 F (21.1 C), it is recommended that some form of condenser flow control be used to optimize performance. Tower pump, bypass valves, or flow regulating valves may be controlled by a 4 to 20 mA output from the 30HXC control (60-second open to close time recommended for actuator).

# Cooler and water-cooled condenser temperature rise

Ratings and performance data in this publication are for a cooling temperature rise of  $10^{\circ}$  F (5.6° C). Units may be operated at a different temperature rise, provided flow limits are not exceeded and corrections to capacity, etc., are made. For minimum flow rates, see the Minimum Flow Rates table. High flow rate is limited by pressure drop that can be tolerated.

**Minimum cooler flow** — Flow (maximum cooler temperature rise) is shown in the Minimum Flow Rates table. Minimum flow rate must be maintained to prevent fouling. When gpm (L/s) required is lower (or rise is higher), follow recommendations below:

- 1. Multiple smaller chillers can be applied in series, each providing a portion of the design temperature rise.
- Chilled fluid can be recirculated to raise flow rate. However, mixed temperature entering cooler must be maintained at a minimum of at least 5° F (2.8° C) above the leaving chilled fluid temperature.
- Special plus one-pass cooler can be used. Contact your Carrier representative for further information.

Maximum cooler flow (> 5 gpm/ton or <  $5^{\circ}$  F rise [> 0.09 L/s  $\cdot$  kW or <  $2.7^{\circ}$  C rise]) — Maximum flow results in practical maximum pressure drop through cooler. Special minus-one-pass cooler can be used to reduce pressure drop. Contact your Carrier representative.

Return fluid can bypass the cooler to keep pressure drop through cooler within acceptable limits. This permits a higher  $\Delta T$  with lower fluid flow through cooler and mixing after the cooler. Contact your Carrier representative if pressure drop appears excessive.

Variable cooler flow rates — These variable rates may be applied to standard 30HX series chillers. However, the unit will attempt to maintain a constant leaving chilled-fluid temperature. In such cases, minimum fluid loop volume must be in excess of 3 gal per ton (3.2 L per kW) and flow rate must change in steps of less than 10% per minute. Apply 6 gal per ton (6.5 L per kW) fluid loop volume minimum if flow rate changes more rapidly.

**Minimum water-cooled condenser flow** — This value (maximum rise) is shown in Minimum Flow Rates table. Ensure leaving-fluid temperature does not exceed 105 F (40.5 C).

# Application data (cont)

#### MINIMUM FLOW RATES

No. of Passes	DEVICE	UNIT	l	OLER	M FL	IN. OW TE*	TE	OLER EMP ERENCE
1	DEVICE	30HX		Туре	1.55	T		T
1				Minus 1	136.0	8.6	13	7.4
1		076	3		90.0		-	_
2   Minus 1   149.0   9.4   13   7.4			4		68.0	_		_
O86			2		149.0	_	15165	
A		086	3		170000000000000000000000000000000000000	_	_	-
2   Minus 1   169.0   10.7   13   7.4			4	Plus 1	75.0	4.7	27	_
A			2	Minus 1	169.0	10.7	13	_
COOLER    4		096	3	Standard	113.0	7.1	20	11.1
106   3   Standard   125.0   7.9   20   11.1     4			4	Plus 1	85.0	5.3	27	
106			2	Minus 1	188.0	11.8	13	7.4
A		106	3	Standard	125.0	7.9	20	100000000000000000000000000000000000000
COOLER    116			4	Plus 1	94.0	5.9	27	_
COOLER    116			1	Minus 1	272.0	_	10	_
COOLER    3		116	2	Standard				<del></del>
1						0.000.000	100000	0.0000000000000000000000000000000000000
COOLER    126				Transformer of		100,000,000		
COOLER    3		126				-		_
COOLER    136		057006						
COOLER    136			1			200000000000000000000000000000000000000		-
COOLER    146     1   Minus 1   350.0   22.1   10   5.6     30   16.7		136		Transcription and Transcription		10000000	7.000	
COOLER    146   2   Standard   175.0   11.0   20   11.1     3   Plus 1   117.0   7.4   30   16.7     1   Minus 1   376.0   23.7   10   5.6     161   2   Standard   188.0   11.9   20   11.1     3   Plus 1   125.0   7.9   30   16.7     1   Minus 1   399.0   25.2   10   5.6     171   2   Standard   199.0   12.6   20   11.1     3   Plus 1   133.0   8.4   30   16.7     1   Minus 1   339.0   25.2   10   5.6     186   2   Standard   199.0   12.6   20   11.1     3   Plus 1   133.0   8.4   30   16.7     1   Minus 1   426.0   26.9   10   5.6     186   2   Standard   213.0   13.4   20   11.1     3   Plus 1   142.0   9.0   30   16.7     1   Minus 1   508.0   32.1   10   5.6     2   Standard   254.0   16.0   20   11.1     3   Plus 1   169.0   10.7   30   16.7     1   Minus 1   597.0   37.7   10   5.6     2   Standard   309.0   18.8   20   11.1     3   Plus 1   199.0   12.6   30   16.7     4   Minus 1   642.0   40.5   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     4   Minus 1   642.0   40.5   10   5.6     2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   Minus 1   642.0   40.5   10   5.6     2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   Minus 1   642.0   40.5   10   5.6     5   CONDENSER   161   2		(3.50)		1007			_	_
COOLER  146  2 Standard 175.0 11.0 20 11.1 3 Plus 1 117.0 7.4 30 16.7 1 Minus 1 376.0 23.7 10 5.6 161 2 Standard 188.0 11.9 20 11.1 3 Plus 1 125.0 7.9 30 16.7 1 Minus 1 399.0 25.2 10 5.6 171 2 Standard 199.0 12.6 20 11.1 3 Plus 1 133.0 8.4 30 16.7 1 Minus 1 426.0 26.9 10 5.6 2 Standard 213.0 13.4 20 11.1 3 Plus 1 142.0 9.0 30 16.7 1 Minus 1 508.0 32.1 10 5.6 2 Standard 254.0 16.0 20 11.1 3 Plus 1 169.0 10.7 30 16.7 1 Minus 1 597.0 37.7 10 5.6 2 Standard 309.0 18.8 20 11.1 3 Plus 1 199.0 12.6 30 16.7 1 Minus 1 597.0 37.7 10 5.6 2 Standard 309.0 18.8 20 11.1 3 Plus 1 199.0 12.6 30 16.7 1 Minus 1 618.0 39.0 10 5.6 2 Standard 309.0 19.5 20 11.1 3 Plus 1 206.0 13.0 30 16.7 1 Minus 1 642.0 40.5 10 5.6 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 2 Standard 321.0 20.3 20 11.1 3 Plus 1 214.0 13.5 30 16.7 271 3 Plus 1 214.0 13.5 30 16.7			7250		-			
3   Plus 1   117.0   7.4   30   16.7	COOLER	146	2				200-000	
1					1502500000		90000	
161							_	1
3   Plus 1   125.0   7.9   30   16.7     1   Minus 1   399.0   25.2   10   5.6     171   2   Standard   199.0   12.6   20   11.1     3   Plus 1   133.0   8.4   30   16.7     1   Minus 1   426.0   26.9   10   5.6     186   2   Standard   213.0   13.4   20   11.1     3   Plus 1   142.0   9.0   30   16.7     1   Minus 1   508.0   32.1   10   5.6     2   Standard   254.0   16.0   20   11.1     3   Plus 1   169.0   10.7   30   16.7     1   Minus 1   597.0   37.7   10   5.6     2   Standard   309.0   18.8   20   11.1     3   Plus 1   199.0   12.6   30   16.7     1   Minus 1   618.0   39.0   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     1   Minus 1   642.0   40.5   10   5.6     271   2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     076,086   2     105   6.6       096,106   2     135   8.5       136,146   2     170   10.7       136,146   2     170   10.7       136,146   2     170   10.7       136,146   2     235   14.8       171,186   2     255   16.1       246   2     333   21.0       246   2     333   21.0       261   2     333   21.0		161						_
1   Minus 1   399.0   25.2   10   5.6		101			50000000000000		-	
171		-		7000	5300000000000			-
3		171				_		_
1								
186   2   Standard   213.0   13.4   20   11.1     3   Plus 1   142.0   9.0   30   16.7     1   Minus 1   508.0   32.1   10   5.6     2   Standard   254.0   16.0   20   11.1     3   Plus 1   169.0   10.7   30   16.7     4   Minus 1   597.0   37.7   10   5.6     2   Standard   309.0   18.8   20   11.1     3   Plus 1   199.0   12.6   30   16.7     4   Minus 1   618.0   39.0   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     4   Minus 1   642.0   40.5   10   5.6     2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   Minus 1   642.0   40.5   10   5.6     5   Minus 1   642.0   40.5   10   5.6     6   Minus 1   642.0   40.5   10   5.6     6   Minus 1   642.0   40.5   10   5.6     6   Minus 1   642.0   40.5   10   5.6     7   Minus 1   642.0   40.5   10   5.6     7   Minus 1   642.0   40.5   10   5.6     8   Minus 1   642.0   40.5   10   5.6     9   Minus 1				100000000000000000000000000000000000000	10,000,000,000		_	
3		186						
1   Minus 1   508.0   32.1   10   5.6		1.77						
206   2   Standard   254.0   16.0   20   11.1     3   Plus 1   169.0   10.7   30   16.7     4   1   Minus 1   597.0   37.7   10   5.6     246   2   Standard   309.0   18.8   20   11.1     3   Plus 1   199.0   12.6   30   16.7     1   Minus 1   618.0   39.0   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     4   Minus 1   642.0   40.5   10   5.6     271   2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   Minus 1   642.0   40.5   10   5.6     5   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   Minus 1   642.0   40.5   10   5.6     5   Standard   321.0   20.3   20   11.1     6   2   - 105   6.6       116,126   2   - 170   10.7       136,146   2   - 195   12.3       161   2   - 235   14.8       171,186   2   - 255   16.1       206   2   - 273   17.2       246   2   - 333   21.0       261   2   - 333   21.0       3   Tin Plus   21.0       2   2   3   3   3   3   3   3   3     4   Minus 1   169.0   10.7   10.7   -     5   Minus 1   10.7   10.7   10.7   10.7   10.7     6   7   7   7   7   7   7   7     7   7				The second second	100000000000000000000000000000000000000		-	
3		206			0.9000 (40) (60) (60)	CARROLL TO		
246   2   Standard   309.0   18.8   20   11.1     3   Plus 1   199.0   12.6   30   16.7     4   1   Minus 1   618.0   39.0   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     4   2   Standard   309.0   19.5   20   11.1     5   2   Standard   309.0   300   16.7     6   2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   3   Plus 1   214.0   13.5   30   16.7     5   6   6       6   2     105   6.6       6   16   2     170   10.7       136,146   2     195   12.3       6   16   2     235   14.8       7   17,186   2     255   16.1       206   2     273   17.2       246   2     333   21.0       261   2     333   21.0       7   7   7   7   7   7   7   7     7   7							-	
246   2   Standard   309.0   18.8   20   11.1     3   Plus 1   199.0   12.6   30   16.7     4   Minus 1   618.0   39.0   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     4   Minus 1   642.0   40.5   10   5.6     271   2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   2   Standard   321.0   20.3   20   11.1     5   6   6       6   6   6   6       706,086   2     105   6.6       116,126   2     170   10.7       136,146   2     195   12.3       161   2     235   14.8       171,186   2     255   16.1       206   2     273   17.2       246   2     333   21.0       261   2     333   21.0       30   16.7     70   70   70   70     70   70   70			2000		11000000000000	12/10/2-24		-
3   Plus 1   199.0   12.6   30   16.7     1   Minus 1   618.0   39.0   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     1   Minus 1   642.0   40.5   10   5.6     271   2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     076,086   2     105   6.6       096,106   2     135   8.5       116,126   2     170   10.7       136,146   2     195   12.3       161   2     235   14.8       171,186   2     255   16.1       206   2     273   17.2       246   2     333   21.0       261   2     333   21.0		246					000000000	
261   2   Standard   309.0   10   5.6     2   Standard   309.0   19.5   20   11.1     3   Plus 1   206.0   13.0   30   16.7     4   Minus 1   642.0   40.5   10   5.6     2   Standard   321.0   20.3   20   11.1     3   Plus 1   214.0   13.5   30   16.7     4   3   Plus 1   214.0   13.5   30   16.7     5   076,086   2     105   6.6       6   096,106   2     135   8.5       116,126   2     170   10.7       136,146   2     195   12.3       161   2     235   14.8       171,186   2     255   16.1       206   2     273   17.2       246   2     333   21.0       261   2     333   21.0       261   2     333   21.0				100 No.			-	
261 2 Standard 309.0 19.5 20 11.1  3 Plus 1 206.0 13.0 30 16.7  1 Minus 1 642.0 40.5 10 5.6  271 2 Standard 321.0 20.3 20 11.1  3 Plus 1 214.0 13.5 30 16.7  076,086 2 — 105 6.6 — —  096,106 2 — 135 8.5 — —  116,126 2 — 170 10.7 — —  136,146 2 — 195 12.3 — —  161 2 — 235 14.8 — —  171,186 2 — 255 16.1 — —  206 2 — 273 17.2 — —  246 2 — 333 21.0 — —						-	15-50,07,0	
3		261						
1   Minus 1   642.0   40.5   10   5.6					The property of the last	10.000/0.30	-	
271 2 Standard 321.0 20.3 20 11.1  3 Plus 1 214.0 13.5 30 16.7  076,086 2 — 105 6.6 — —  096,106 2 — 135 8.5 — —  116,126 2 — 170 10.7 — —  136,146 2 — 195 12.3 — —  161 2 — 235 14.8 — —  171,186 2 — 255 16.1 — —  206 2 — 273 17.2 — —  246 2 — 333 21.0 — —				111.00000000000000000000000000000000000				= -
3		271						A CONTRACTOR OF THE PARTY OF TH
CONDENSER  076,086 2							2000000	
096,106     2     —     135     8.5     —     —       116,126     2     —     170     10.7     —     —       136,146     2     —     195     12.3     —     —       161     2     —     235     14.8     —     —       171,186     2     —     255     16.1     —     —       206     2     —     273     17.2     —     —       246     2     —     333     21.0     —     —       261     2     —     333     21.0     —     —		076,086			100000000000000000000000000000000000000			
CONDENSER  116,126 2 — 170 10.7 — —  136,146 2 — 195 12.3 — —  161 2 — 235 14.8 — —  171,186 2 — 255 16.1 — —  206 2 — 273 17.2 — —  246 2 — 333 21.0 — —  261 2 — 333 21.0 — —								
CONDENSER   136,146   2   -   195   12.3   -   -								
CONDENSER 161 2 — 235 14.8 — — 171,186 2 — 255 16.1 — — 206 2 — 273 17.2 — — 246 2 — 333 21.0 — — 261 2 — 333 21.0 — —	1							
171,186   2   -   255   16.1   -   -					-			
206     2     —     273     17.2     —     —       246     2     —     333     21.0     —     —       261     2     —     333     21.0     —     —	CONDENSER							
246     2     —     333     21.0     —     —       261     2     —     333     21.0     —     —							_	
261 2 — 333 21.0 — —				5-0				
		20000000					==-	
1 2/1   2   -   333   21.0   -   -		271	2		333	21.0		

<sup>\*</sup>Based on 20 F (11.1 C) temperature difference at ARI conditions.

NOTES:


1. The 30HX units will start with loop temperatures up to 95 F (35 C).

2. Minimum flow rate shown is based on ARI Ratings and is for reference only.

20 F (11.1 C) is the maximum cooler temperature differential that will determine actual minimum flow rate.

3. To obtain proper temperature control, loop fluid volume must be at least 3 gal/ton (3.23 L/kW) of chiller nominal capacity for air conditioning and at least 6 gal/ton (6.5 L/kW) for process applications.





#### Oversizing chillers

Oversizing chillers by more than 15% at design conditions must be avoided as the system operating efficiency will be adversely affected (resulting in greater and/or excessive electrical demand and cycling of compressors). When future expansion of equipment is anticipated, install a single chiller to meet present load requirements, and install a second chiller to meet the additional load demand.

It is also recommended that the installation of 2 smaller chillers be considered where operation at minimum load is critical. The operation of 2 small chillers at higher loading is preferred to operating a single chiller at or near its minimum recommended value.

The minimum load control accessory should not be used as a means to allow oversizing chillers. Minimum load control should be given consideration where substantial operating time is anticipated below the minimum unloading step.

#### Parallel chillers

Where chiller capacities greater than can be supplied by a single 30HX chiller are required, or where stand-by capability is desired, chillers may be installed in parallel. Units may be of the same or different sizes. However, cooler and condenser flow rates must be balanced to ensure proper flow to each chiller. The standard 30HX ComfortLink™ control can be configured to provide lead/lag control for two chillers. The accessory Chillervisor™ System Manager III control may be used for proper leaving chilled fluid temperature control and to ensure proper staging sequence of up to 8 chillers. Refer to the accessory Chillervisor System Manager III installation instructions for further details.

#### Series chillers

Chillers in series may be used for capacities greater than those supplied by a single 30HX chiller. Using the Minus-One-Pass Cooler Head option, fluid pressure drop across the cooler can be held to reasonable levels. The leaving fluid temperature sensors need not be relocated. However, the cooler minimum entering fluid temperature limitations should be considered for the chillers located downstream of other chillers. The standard 30HX control can control two 30HX chillers in series. Condensers should be piped in parallel to maximize capacity and efficiency. This should also minimize condenser pressure drop and saturated condensing temperatures. However, if condensers are piped in series, ensure that the leaving fluid temperature does not exceed 105 F (40.5 C).



#### **Energy management**

Demand limiting and load shedding are popular techniques used to reduce peak electric demands typically experienced during hot summer days when air conditioning loads are highest. When utility electricity demands exceed a certain level, electrical loads are turned off to keep the peak demands below a prescribed maximum limit. Compressor unloading reduces electrical demand while allowing the chiller to operate under part-load capacity and to maintain partial chilled fluid cooling.

Electrical demand can be limited through demand limit input to chiller control which unloads the chiller to a predetermined percentage of the load. One stage of unloading can be initiated by a remote signal to significantly reduce the chiller power consumption. This power reduction applies to the full load power at nominal conditions. The demand limit control should not be cycled less than 10 minutes on and 5 minutes off.

#### **Duty cycling**

Duty cycling will cycle an electrical load at regular intervals, regardless of electrical demand. This reduces the electrical demand by "fooling" demand measuring devices. Duty cycling of the entire compressor is **NOT** recommended since motor windings and bearings will be damaged by constant cycling.

#### Wye-delta start

Wye-delta start is standard on 30HX 208/230-v, 60-Hz units and 230-v, 50-Hz units and optional on all other 30HX units. This feature is not always required on 30HX units due to the use of multiple compressors that allow small electrical load increments, but is available if required. Maximum instantaneous current flow (see ICF in Electrical Data tables on pages 59-62) should be used in determining need.

#### Vibration isolation

External vibration isolators are available as field-installed accessories.


#### Strainers

A strainer with a minimum screen size of 20 mesh must be installed in both the cooler and condenser fluid lines, within 10 ft (3 m) of the inlets to both the cooler and condenser. For 30 HXA units, this requirement applies only to the cooler.

#### Chilled fluid loop volume

The chilled fluid loop volume in circulation must equal or exceed 3 gal per nominal ton of cooling (3.2 L per kW) for temperature stability and accuracy in normal air conditioning applications. For example, a 30HXC096 with a nominal capacity of 94.0 tons would require 282 gal (1067.4 L) in circulation in the system loop.

For process jobs where accuracy is vital, or for operation at ambient temperatures below 32 F (0° C) with low unit loading conditions, there should be from 6 to 10 gal per ton (6.5 to 10.8 L per kW). To achieve this volume, it is often necessary to install a tank in the loop. Tank should be baffled to ensure there is no stratification, and that water (or brine) entering the tank is adequately mixed with liquid in the tank. See Tank Installation drawing.



#### Fouling factor

The factor used to calculate tabulated ratings for the cooler is  $0.00010~{\rm ft^2}\cdot{\rm hr}\cdot{\rm F/Btu}~(0.000018~{\rm m^2}\cdot{\rm K/W}),$  and for the condenser is  $0.00025~{\rm ft^2}\cdot{\rm hr}\cdot{\rm F/Btu}~(0.00044~{\rm m^2}\cdot{\rm K/W}).$  As fouling factor is increased, unit capacity decreases and compressor power increases. To determine selections at other fouling factors, use the chiller program in the electronic catalog.

# Cooler and water-cooled condenser freeze protection

If chiller refrigerant or fluid lines are in an area where ambient conditions fall below 32 F (0° C), it is recommended that an antifreeze solution be added to protect the unit and fluid piping to a temperature 12° F (6.7° C) below the lowest anticipated temperature. For corrections to performance, refer to the chiller program in the electronic catalog.

Use only antifreeze solutions approved for heat exchanger duty. Use of automotive antifreezes is not recommended because of the fouling that can occur once their relatively short-lived inhibitors break down.

If the system will not be used during freezing weather conditions and the chiller and fluid piping are not protected with an antifreeze solution, it is recommended that the chiller and outdoor piping be drained.

Refer to Cooler Fluid Temperature section, page 21, for leaving fluid temperature for brine units. When leaving chilled fluid temperatures will be lower than 40 F (4.4 C), an appropriate antifreeze solution must be used in the cooler. In addition, the following special installation instructions will apply:

- In addition to the factory-mounted chilled water flow switch, a field-supplied condenser water flow switch must be installed.
- 2. The chiller must control both the chilled water pump and the condenser pump. The cooler pump must operate for a minimum of 10 minutes after the chiller has shut down and the condenser pump must operate for a minimum of 30 minutes after the chiller has shut down. In the event of a loss of condenser water flow, the flow of chilled fluid to the evaporator must be stopped or the isolation valve must be closed. This is necessary to reduce the possibility of condenser freeze-up.

# **Application data (cont)**

3. Condenser head pressure control valves must not reduce condenser flow below 0.75 gallons per ton (0.4 L/s per kW) or the lowest detectable flow level of the condenser water flow switch. For further information, refer to the 30HX Installation Instructions or contact your Carrier representative.

#### 30HXA remote condenser requirements

- Do not manifold independent refrigerant circuits into a single condenser circuit.
- Ensure each refrigerant circuit has its own head pressure control.
- Condensing pressure control must be provided on condensers used with 30HXA to maintain a minimum 75 F (24 C) saturated discharge temperature at light loads.
- Condenser must provide 15° F (8.3° C) subcooling, a maximum of 40° F (22.2° C) difference between saturated condensing temperature and outdoor ambient temperature (to prevent overload at high ambient temperatures), and a minimum of 20° F (11.1° C) difference (to assure subcooling).
- Minimum saturated discharge temperature (SDT) is 90 F (32.2 C). Maximum SDT is 135 F (57.2 C) at full load.
- 6. Condenser should not be located more than 15 ft (4.6 m) below chiller to maintain subcooling.
- 7. Design discharge and liquid piping according to Carrier System Design Manual. Piping must be sized for HFC-134a. Refer to the ASHRAE Refrigeration Handbook for R-134a sizing tables. Also see 30HX Installation instructions and the Typical 30HXA Refrigerant Piping to Remote Condenser diagrams on page 29.
- 8. Maximum interconnecting refrigerant line length is 200 ft (61 m) actual.
- Liquid line solenoid valves are required.
- If accessory sound enclosure is installed, run lines along the floor so the sound enclosure can be notched to clear lines.

Refrigerant pipe sizing for 30HXA with Carrier 09D condenser combinations — For refrigerant pipe sizing of the 30HXA follow these directions:

#### Discharge line:


- For applications at conditions of 40 F (4.4 C) or higher, use the Refrigerant Line Sizes for 30HXA Chiller/09DK Condenser Combinations tables on pages 25 and 26.
  - For applications using brine, other condensers, or LWT below 40 F (4.4 C), size lines using the ASHRAE Refrigeration Handbook, or other suitable design guide.
- Install horizontal lines level or pitched slightly toward the base of discharge riser and the condenser (in the direction of flow).
- If chiller is below the condenser, loop the discharge line to at least one inch (25.4 mm) above the top of condenser.



- 4. A double discharge riser (as shown in Refrigerant Line Sizes, Double Discharge Riser Pipe Sizes table on page 26) is required if any of the following conditions exist:
  - a. Unit is equipped with minimum load control.
  - Chiller is located below condenser.
  - Discharge line size is in shaded area in Refrigerant Line Sizes, Recommended Refrigerant Pipe Sizes table on page 25.
- 5. Minimize line length and restrictions to minimize pressure drop and refrigerant charge.
- If accessory sound enclosure is applied, run lines along the floor so sound enclosure may be notched to clear lines.
- 7. Lines should not be buried underground.

#### Liquid line:

- For applications at conditions of 40 F (4.4 C) or higher LWT, use the Refrigerant Line Sizes for 30HXA Chiller/09DK Condenser Combinations tables on pages 25 and 26.
  - For applications using brine, other condensers, or LWT below 40 F (4.4 C), size lines using the ASHRAE Refrigeration Handbook, or other suitable design guide.
- If chiller is above condenser, maximum vertical separation is 15 ft (4.6 m).
- Minimize line length and restrictions to minimize pressure drop and refrigerant charge.
- Field-supplied liquid line solenoid valves are required.
   The solenoid valves must be located close to the chiller.
- If sound enclosure is applied, run lines along floor so sound enclosure may be notched to clear lines.
- 6. In-line receivers are NOT recommended due to their negative effect on system subcooling. Where the use of a receiver is desired for service purposes, the receiver should be piped in parallel with the main liquid line and equipped with shut-off valves to isolate it during unit operation. See sketch below.
- 7. Filter driers (field supplied) are required.



#### Relief valve vent lines

- Vent per local code requirements.
- Each chiller has a minimum of 4 refrigerant relief valves: 2 on the cooler, 2 on the condenser (30HXC) or oil separator (30HXA). Units with factory-installed suction service valves also have one relief valve on each compressor discharge line. See Dimensions section on pages 11-18 for specific locations.
- 3. If sound enclosure is applied, run lines along floor so sound enclosure may be notched to clear lines.

### **Controls**

The standard microprocessor-based control in the 30HX units provides the following functions:

- leaving fluid temperature control (using both entering and leaving fluid sensors)
- 7-day time sequence of both pump and chiller
- temperature reset from return fluid (standard) or from outdoor ambient (accessory), occupied space temperature (accessory), 4 to 20 mA signal (accessory), or via the optional Carrier Comfort Network (CCN)
- automatic compressor lead-lag switching based on compressor accumulated run times and number of cycles
- automatic temperature range across the cooler adjustment
- · fully automatic control of the chiller components


A 4-line, 20-character per line display is used to accomplish the following (see figure below):

- · set schedules and set points
- · identify operating mode
- display current temperatures and pressures being used by the control for internal calculations
- · identify abnormal (alarm or alert) conditions

#### Sequence of operation

The control has a 44 F (6.2 C) leaving fluid temperature (LWT) set point as shipped from the factory. If temperature reset or demand limiting is in effect, this set point may change.

**Start-up** — The chiller will start when the circulating pump is energized. (If the flow switch is applied, the chiller starts after the flow has been proven.) The compressor starts unloaded.





NOTE: Which compressor starts first is determined by the automatic lead/lag feature.

If the entering fluid temperature is  $85 \, \text{F}$  (29 C) or higher, the maximum operating pressure (MOP) feature limits the suction pressure to keep the chiller on line.

**Normal operation** — The entering fluid temperature sensor monitors changes in entering fluid temperature to anticipate changes in the cooling load. Based on leaving fluid temperature, the control adds or subtracts capacity to maintain a constant leaving fluid temperature.

**Dual chiller control** — The Dual Chiller Routine is available for the control of two units supplying chilled fluid on a common loop.

In parallel flow applications, an additional leaving fluid temperature thermistor must be installed and connected to the lead chiller.

**Transition to off** — The chiller unloads once the "time-to-stop" signal has been given. This signal can be either internal or external.

**Safeties** — The 30HX control as shipped from the factory automatically deenergizes any active compressor that experiences any of the following:

- electrical overload
- thermal overload protection
- high pressure
- · low oil pressure
- loss of refrigerant charge
- loss of phase protection
- reverse rotation (control prevents compressor start)
- current imbalance
- ground current
- low chilled fluid temperature

#### Additional information

Detailed information on controls and operation is available in the Controls, Start-Up, Operation and Troubleshooting guide included with each unit. Packaged Service Training programs are also available. Contact your Carrier representative for more information.

### SHERLOCK 402 Refrigerant Gas Monitoring System





#### Monitoring Panel

The Sherlock 402 Control Module is a hard wired, electronic control panel that is capable of monitoring the analog output signal of up to eight Sherlock Refrigerant Gas Sensors or seven Sherlock Refrigerant Gas Sensors and one Sherlock Oxygen Depletion Sensors and two digital dry-contact switches. The Control Module will activate four Form C SPDT relay contacts based upon the programmed alarm setpoints of each sensor. The relays are referred to as K1A, K1B for the first alarm level and K2A, K2B for the second alarm level. There is optional zone isolation alarm relay (A-H) for each Sensor. The Control Module can be located in the area to be monitored, or in a separate location, typically outside of the monitored room.

#### Monitoring Points

Each monitoring point consists of an analog signal generating sensor connected to the control module via discrete, three conductor cable. Each sensor can be mounted up to 800 feet (longer run with special cable) away in locations where leaked refrigerant is likely to concentrate.

The gas sensors are available in three varieties:

Ceramic Metal Oxide Semiconductor (CMOS) or Solid State Sensor

Non-Dispursive, Pyro-Electric Infrared Sensor.

Oxygen Depletion Electro-chemical Sensor.

#### Alarm Level Settings

The Sherlock 402 allows you to set a unique Level 1 Alarm Setpoint and Level 2 Alarm Setpoint for each individual sensor. When an Alarm Setpoint is exceeded, corresponding alarm relays are activated Each Alarm Setpoint has a programmable Alarm Delay, 1 to 120 minutes. Sensor readings are required to exceed an Alarm Setpoint for the programmed amount of time before the control activates the corresponding alarm relay contacts. For example, if the Alarm Setpoint is 200 and the Alarm Delay is five minutes, the control will enter an alarm condition only if the sensor detects a level of 200 or higher for more than five minutes.

#### Alarm Indication

All alarms are logged to indicate which sensor went in and out of any of the two alarm levels, the time and date of the alarm. The alarm log stores the last 32 alarms. When a sensor is in alarm, an alarm LED for this sensor on the front panel will turn to red color, the on-board beeper will be beeping and the display will show the activated alarm level.

#### Alarm Relay Contacts

The Sherlock 402 provides two fused SPDT (Single Pole Double Throw) relay outputs for each alarm level that switch positions in the event of an alarm condition. Level 1 Alarm activates K1A and K1B relays. Level 2 Alarm activates K2A and K2B relays. Level 2 alarm on each individual sensor can be disabled. One alarm relay on each level (K1B/K2B) can be silenced (returned to non-alarm state) when the SILENT button on the front panel is pushed. The other alarm relay will remain active until the alarm condition is cleared. The Sherlock 402 can be programmed so that the alarm is cleared automatically when the afr is cleared below the alarm setpoint (UNLATCHED) The relays can also be programmed so the alarm is latched "ON" until the alarm is manually reset. The K1/K2 alarm level can be configured so the relays are "Energized to Alarm" (where the C-NC contacts open on alarm) or "De-Energized to Alarm" (where the relay is energized during normal operations and the C-NC contacts close on alarm). Optional zone isolation alarm relay(A-H) for each sensor can be programmed to activate by level 1 or level 1&2 alarm.

#### Sensor Failure Monitoring

The Sherlock 402 constantly monitors the wiring to the sensors. Should any of the activated sensor wires be cut or disconnected, "OPEN" will appear on the SHERLOCK display, the K1A and K1B relays will be activated and the condition is logged.

#### Setback Alarm Settings

In some locations the sensor may be expected to function in two different environments. For example, the sensor may have to perform in still air (i.e. with the exhaust fan off) and in moving air (i.e. with the exhaust fan on), or the sensor may be used in a location where changes in air quality, perhaps caused by the use of propane powered floor buffers, elevates the sensor readings. The *Sherlock* 402 provides a feature called SETBACK to accommodate alternate environments under which the sensor would operate. SETBACK provides a second ALARM SETPOINT and a second ALARM DELAY enabling the sensor to perform in this second environment. The *Sherlock* 402 switches to the second set of parameters when a dry contact (i.e. air flow, sall switch or timer) closes or on a daily time schedule.

Each sensor can be programmed with one of five SETBACK options:

- 1) No SETBACK
- 2) SETBACK triggered by setback input 1 and the Setback Clock
- 3) SETBACK triggered by setback input 2 only

Each sensor can be programmed with only one SETBACK option; however, different sensors may be programmed to follow different options.

### SHERLOCK 402 Refrigerant Gas Monitoring System





ETL Listed Conforms To UL Std. 3111-1 Certified To CANICSA C22.2 Std. No. 1010.1

MODEL #	NEMA/IP RATING	ELECTRICAL CATEGORY	POLLUTION PROTECTION
402	1	II	2
402-4	4X/IP67	II	3
402-PM	1	11	2

**NEMA 1 Compliant Enclosure** - This enclosure is intended for indoor use only primarily to provide a degree of protection against contact with the enclosed equipment. The enclosure is not designed to provide protection from water or to be placed in a hazardous environment. Mount only in Pollution Level 2 environments, i.e. environmentally controlled offices, control rooms, or environmentally controlled machine rooms.

DIMENSIONS 12"H x 9.25"W x 5.25"D Nema 1

<u>NEMA 4X Compliant Enclosure</u> - This enclosure is intended for either indoor or outdoor use, 0 to 50 °C, to provide a degree of protection against corrosion, windblown dust and rain, splashing water, and hose directed water.

DIMENSIONS 14"H x 12"D x 7"D Nema 4X

<u>NEMA 1 Panel Mount Option</u> - The control and display assembles must be suitably mounted in an enclosure. The Faceplate may be surface mounted onto a Nema 1 enclosure. The IO Board Assembly must be mounted within an enclosure providing at least Nema 1 protection.

DIMENSIONS 10.2"H x 8.5" W x 2"D PM Faceplate 10.6"H x 8.5"W x 3"D PM Backplate

POWER

90 to 250VAC, 50/60 Hz, 1.0 Amps

INPUTS

Four (4) SHERLOCK sensor Cmos or IR

or

Three (3) SHERLOCK sensor Cmos or IR

One Oxygen Depletion Sensor

Two dry contacts -- Setback 1 / Setback 2

OUTPUTS Four SPDT, 1 Form C relays 250VAC, 3.15Amp Slo-Blo fuse

Optional Zone Isolation Relays - Four SPDT, 1 Form C relays 250VAC, 3.15Amp Slo-Blo fuse

OPERATING TEMPERATURE 45°F - 99°F

OPERATING HUMIDITY 30% - 90% RH, non- condensing

ALARMS Two Alarm Levels, two SPDT Relays per level.

One Silenceable when in alarm

Optional One (1) Zone Isolation alarm relay per each sensor.

DISPLAY 2 lines by 20 characters Alphanumeric LCD with back light

Alarm Indication LED -- indicates active alarm

KEYPAD 5 tactile key switches: Scroll up, Scroll down, Select/Change, Exit,

Alarm Silence/Clear

ALARM INDICATORS

LCD DISPLAY Name, description, and current reading of alarming sensor

BUZZER Piezo-electric, 90db @10ft, silenceable

STATUS LED Four on front panel of control. Indicates alarm status of

each sensor

STROBE LIGHT (Optional) Mounted on top of the housing, activates during any alarm condition.

### Horn-Strobe

Audible and Visual signal to alert the user in alarm condition. Makes any alarm visible during an emergency.

- Patented Self-contained, 80hm 15 watt Indoor/Outdoor Armored Speaker.
- Can be mounted within a mechanical machinery room for Mechanical Code alarm requirements
- The full featured armored speaker consists of a light weight rust proof aluminum die-cast housing and a dual-action plunger switch for tamper supervision for a normally closed loop.
- Can be connected to most security or energy management systems.
- The armored speaker DOES NOT require additional metal boxes, tamper switches, special tools, or training to install and operate.
- Comes completely assembled and ready for installation.
- Operates on 5 to 14VDC.
- Easy installation and mounting.
- Clear dome lens. Available in BLUE (Standard), RED and AMBER.
- High-powered "U" shaped Xenon bulb flash is visible for miles.
- High-Impact plastic case is moisture and corrosion-resistant.
- Flash rate is approx. 60 to 100 flashes per minute, depending upon the operating voltage.



**ENCLOSURE RATING:** 

Indoor/Outdoor 5.8 in X 8.1 in X 4.8 in

POWER:

12V DC, 865mA

STARTING VOLTAGE:

9.6V DC

OPERATING VOLTAGE: 9.6V to 14.4V DC

SOUND OUTPUT:

105dB(A) @ 10 FT

FLASHING RATE:

20 - 100 flashes/min (Voltage Dependent)

#### **OPERATING ENVIRONMENT:**

Temperature:

14 TO 140 °F (-10 TO 60 °C)

Humidity:

0 TO 95% RH Non-condensing

LENS COLOR:

BLUE

#### **Features**

Aluminum diaphragm

Rust free Beige color aluminum die-cast housing

8 ohm

Dual-action tamper switch using reed switch

Up-front screw terminals for easier field wiring

Mounts directly to the wall or to a 4 5/16" square back box



Series



Air-Cooled and Water-Cooled Chillers with ComfortLink™ Controls 50/60 Hz

# Controls Start-Up, Operation Service, and Troubleshooting

#### SAFETY CONSIDERATIONS

Installing, starting up, and servicing this equipment can be hazardous due to system pressures, electrical components, and equipment location (roof, elevated structures, etc.). Only trained, qualified installers and service mechanics should install, start up, and service this equipment.

When working on this equipment, observe precautions in the literature, and on tags, stickers, and labels attached to the equipment, and any other safety precautions that apply. Follow all safety codes. Wear safety glasses and work gloves. Use care in handling, rigging, and setting this equipment, and in handling all electrical components.

#### **A WARNING**

Electrical shock can cause personal injury and death. Shut off all power to this equipment during installation and service. There may be more than one disconnect switch. Tag all disconnect locations to alert others not to restore power until work is completed.

#### **A** CAUTION

This unit uses a microprocessor-based electronic control system. Do not use jumpers or other tools to short out components, or to bypass or otherwise depart from recommended procedures. Any short-to-ground of the control board or accompanying wiring may destroy the electronic modules or electrical components.

#### **A WARNING**

To prevent potential damage to heat exchanger tubes always run fluid through heat exchangers when adding or removing refrigerant charge. Use appropriate brine solutions in cooler and condenser fluid loops to prevent the freezing of heat exchangers when the equipment is exposed to temperatures below 32 F (0° C).

DO NOT VENT refrigerant relief valves within a building. Outlet from relief valves must be vented outdoors in accordance with the latest edition of ANSI/ASHRAE (American National Standards Institute/American Society of Heating, Refrigeration and Air Conditioning Engineers) 15 (Safety Code for Mechanical Refrigeration). The accumulation of refrigerant in an enclosed space can displace oxygen and cause asphyxiation. Provide adequate ventilation in enclosed or low overhead areas. Inhalation of high concentrations of vapor is harmful and may cause heart irregularities, unconsciousness or death. Misuse can be fatal. Vapor is heavier than air and reduces the amount of oxygen available for breathing. Product causes eye and skin irritation. Decomposition products are hazardous.

#### **▲ WARNING**

DO NOT attempt to unbraze factory joints when servicing this equipment. Compressor oil is flammable and there is no way to detect how much oil may be in any of the refrigerant lines. Cut lines with a tubing cutter as required when performing service. Use a pan to catch any oil that may come out of the lines and as a gage for how much oil to add to system. DO NOT re-use compressor oil. Do NOT leave refrigerant system open to air any longer than necessary. Seal circuits being serviced and charge with dry nitrogen to prevent oil contamination when timely repairs cannot be completed.

#### CONTENTS

	Pa	ge
SAFETY CONSIDERATIONS		. 1
GENERAL	2	) 3
MAJOR SYSTEM COMPONENTS	2	1
Main Base Board (MRR)		2
Screw Compressor Board (SCB)		3
Screw Compressor Board (SCB) Electronic Expansion Valve (EXV) Board		3
ComfortLink Compressor Protection	• • • • • •	~
(CCP) Board		3
Energy Management Module (EMM)		3
Enable/Off/Remote Connect Switch		3
Emergency On/Off Switch		3
Board Addresses		2
Control Module Communication	270 700 10	3
Carrier Comfort Network (CCN) Interface		3
OPERATION DATA	1-1	n
Electronic Expansion Valve (EXV)		4
EXV OPERATION	• • • • •	•
<ul> <li>ECONOMIZER OPERATION</li> </ul>		
Oil Pumps		5
Motor Cooling		5
Back Pressure Valve (30GXN.R		
and 30HXA only)		5
Sensors		5
ComfortLink Compressor Protection		
(CCP) Board		7
• OUTPUTS		
• INPUTS		
Wye-Delta vs Across-the-Line (XL)		
Starting Option		8
Capacity Control	8	3
MINUTES LEFT FOR START		
MINUTES OFF TIME		
LOADING SEQUENCE		
• CLOSE CONTROL		
• LEAD/LAG DETERMINATION		
· CAPACITY SEQUENCE DETERMINATION		
MINIMUM LOAD VALVE		
<ul> <li>CAPACITY CONTROL OVERRIDES</li> </ul>		

CONTENTS (cont	
Page   Head Pressure Control	
<ul> <li>AIR-COOLED UNITS (30GXN,R)</li> <li>WATER-COOLED UNITS (30HXC)</li> <li>CONDENSERLESS UNITS (30HXA)</li> <li>09DK AIR-COOLED CONDENSERS</li> <li>09AZ AIR-COOLED CONDENSERS</li> <li>OPERATION SEQUENCE</li> </ul>	
VARIABLE SPEED FAN CONTROL     ADJUSTING PID ROUTINES     Control Methods	
<ul><li>SWITCH</li><li>7-DAY SCHEDULE</li><li>OCCUPANCY</li></ul>	
• CCN Cooling Setpoint Select	
Cooler and Condenser (30HXC) Pump Control	
Flow Sensor	6
Navigator Display Module Usage	
Control         19           Alarms/Alerts         36           Run Hours and Starts         36           Temperature Reset         36	
DEMAND LIMIT (2-Stage Switch Controlled)     EXTERNALLY POWERED DEMAND LIMIT	
DEMAND LIMIT (CCN Loadshed Controlled) Cooling Set Point (4 to 20 mA)	
Unit Shutoff	
Single Circuit Stoppage	
Compressor Alarm/Alert Circuit	
EXPANSION VALVES  • BRAZED-PLATE ECONOMIZERS  SERVICE	
<ul> <li>TUBE PLUGGING</li> <li>RETUBING</li> <li>TIGHTENING COOLER/CONDENSER HEAD BOLTS</li> </ul>	
Inspecting/Cleaning Heat Exchangers	
Water Treatment 53 Condenser Coils (30GXN,R Only) 53 COIL CLEANING CLEANING E-COATED COILS	
Condenser Fans (30GXN,R Only)	
REPLACING THE EXTERNAL OIL FILTER     REPLACING THE INTERNAL OIL FILTER	
Compressor Changeout Sequence57	

Page
BURNOUT CLEAN-UP PROCEDURE
Moisture-Liquid Indicator59
Filter Drier 50
Liquid Line Service Valve
Thermistors59
LOCATION
<ul> <li>THERMISTOR REPLACEMENT</li> </ul>
Pressure Transducers 65
• TROUBLESHOOTING
<ul> <li>FLOW SENSOR</li> </ul>
Safety Devices
<ul> <li>COMPRESSOR PROTECTION</li> </ul>
<ul> <li>OIL SEPARATOR HEATERS (30GX)</li> </ul>
<ul> <li>COOLER PROTECTION</li> </ul>
Relief Devices
PRESSURE RELIEF VALVES
Control Modules68
<ul> <li>MAIN BASE BOARD (MBB), SCREW COMPRESSOR</li> </ul>
BOARD (SCB), EXPANSION VALVE BOARD (EXV),
ENERGY MANAGEMENT MODULE (EMM),
COMFORTLINK™ COMPRESSOR PROTECTION
BOARD (CCP), AND THE NAVIGATOR
• RED LED
GREEN LED
• YELLOW LED
Carrier Comfort Network (CCN) Interface 69
Replacing Defective Processor Module69
Winter Shutdown Preparation
Maintenance70
PRE-START-UP PROCEDURE71
System Check71
START-UP AND OPERATION71,72
Actual Start-up
Operating Sequence71
FIELD WIRING72-74
APPENDIX A
(Compressor Must Trip Amps)
(Capacity Loading Sequence)
APPENDIX C (Available Accessories) 90,91
APPENDIX D (Building Interface)
APPENDIX E (Cooler and
Condenser Pressure Drop) 95-100
APPENDIX F
(Typical System Components) 101-112
APPENDIX G (CCN Configuration) 113-125
APPENDIX H (30GXN,R Duplex Combinations) 126
APPENDIX I (Motormaster® V
Operation Instructions) 127-129
APPENDIX J (Maintenance Log)
START-UP CHECKLIST (For 30GX,HX
Liquid Chiller)

#### **GENERAL**

IMPORTANT: These units use refrigerant R-134a. Compressor oil used with R-134a is Castrol Icematic SW-220, Carrier Specification #PP47-32.

This publication contains Controls Start-Up, Service, Operation and Troubleshooting data for the 30GXN,R080-528 and 30HXA,C076-271 screw chillers.

Circuits are identified as circuits A and B, and compressors are identified as A1 or A2 in circuit A, and B1 or B2 in circuit B. Refer to Appendix H for Duplex unit combinations.

The 30GXN,GXR,HX Series chillers feature microprocessor-based electronic controls and electronic expansion valves (EXV) in each refrigeration circuit.

The control system cycles compressor loaders and/or compressors to maintain the selected leaving fluid temperature set point. The system automatically positions the EXV to maintain the specified discharge gas superheat temperature in the circuit. The system also has capabilities to control a condenser water valve to maintain suitable discharge pressure for the 30HXC unit. Safeties are continuously monitored to prevent the unit from operating under unsafe conditions. A scheduling function can be programmed by the user to control the unit's occupied and unoccupied schedules. The control also operates a test function and a manual control function that allows the operator to check output signals and ensure components are operable.

#### **MAJOR SYSTEM COMPONENTS**

Main Base Board (MBB) — This board contains the majority of the control system operating software and controls the operation of the machine. It has 11 input channels and 11 output channels.

The MBB continuously monitors input/output channel information received from all the modules and controls all output signals for all output channels. The processor module also controls the EXV driver module, commanding it to open or close each EXV in order to maintain the proper cooler level. Information is transmitted between the MBB; ComfortLinkTM Compressor Protection (CCP) boards, the EXV driver module, the Screw Compressor Board (SCB), the Energy Management Module (EMM) and the Navigator modules through a 3-wire communications bus called the Local Equipment Network (LEN). The remote enhanced display is connected to the MBB through a 3-wire communications bus, but uses a different communication bus called the Carrier Comfort Network (CCN). The CCN bus is also used to communicate to other CCN devices when the unit is installed in a network application.

Screw Compressor Board (SCB) — The SCB has 8 inputs along with 2 analog and 5 discrete outputs. The SCB module communicates the status of the inputs with the MBB and operates the oil heater (30GXN,R only), cooler heater (30GXN,R only) and oil pump outputs.

Electronic Expansion Valve (EXV) Board — The EXV board has 4 inputs and 2 outputs. It receives signals from the MBB and operates the electronic expansion devices. The electronic expansion valve board also sends the MBB the status of its 4 input channels,

ComfortLink Compressor Protection (CCP Board — The CCP board monitors the high-pressure switch status, running current and motor temperature for each compressor. Each CCP board controls up to 2 compressors. The CCP board also controls the motor cooling solenoid, oil solenoid and contactor outputs. A pre-punched configuration header for each compressor determines the must trip amps setting. Each CCP board sends the MBB each compressor's motor temperature, relay status and running current as a percentage of the must trip amps value. The CCP board also communicates any alarm conditions as the feedback value.

Energy Management Module (EMM) — The EMM is available as a factory-installed option or as a field-installed accessory. The EMM receives 4 to 20 mA inputs for the temperature reset, cooling set point reset and demand limit functions. The EMM also receives the switch inputs for the field-installed 2-stage demand limit and ice done functions. The EMM communicates the status of all inputs with the MBB, and the MBB adjusts the control point, capacity limit, and other functions according to the inputs received.

Enable/Off/Remote Contact Switch — The Enable/Off/Remote Contact switch is a 3-position switch used to control the chiller (see Table 1). When switched to the Enable

position the chiller is under its own control. Move the switch to the Off position to shut the chiller down. Move the switch to the Remote Contact position and a field-installed dry contact can be used to start the chiller. The contacts must be capable of handling a 24-vac, 20-mA load. In the Enable and Remote Contact (dry contacts closed) positions, the chiller is allowed to operate and respond to the scheduling configuration, CCN configuration and set point data.

Emergency On/Off Switch — The Emergency On/Off switch should only be used when it is required to shut the chiller off immediately. Power to the MBB, EMM, EXV, SCB and Navigator display is interrupted when this switch is off and all outputs from these modules will be turned off.

Board Addresses — The Main Base Board (MBB) has an Instance jumper that must be set to '1'. The EXV, SCB and EMM boards have 4-position DIP switches that must be set to 'On' for all boards. The CCP address has a 4-position DIP switch. Switches 3 and 4 set the address.

#### **Control Module Communication**

RED LED — Proper operation of the control boards can be visually checked by looking at the red status LEDs (light-emitting diodes). When operating correctly, the red status LEDs should be blinking in unison at a rate of once every 2 seconds. If the red LEDs are not blinking in unison, verify the board address and that correct power is being supplied to all modules. Be sure that the Main Base Board (MBB) is supplied with the current software. If necessary, reload current software. If the problem still persists, replace the MBB. A board LED that is lit continuously or blinking at a rate of once per second or faster indicates that the board should be replaced.

GREEN LED — The MBB has one green LED. The Local Equipment Network (LEN) LED should always be blinking whenever power is on. All other boards have a LEN LED that should be blinking whenever power is on. Check LEN connections for potential communication errors at the board J3 and/or J4 connectors. Communication between modules is accomplished by a 3-wire bus. These 3 wires run in parallel from module to module. The J5 connector on the MBB provides both power and communication directly to the Navigator.

YELLOW LED — The MBB has one yellow LED. The Carrier Comfort Network (CCN) LED will blink during times of network communication.

Carrier Comfort Network (CCN) Interface — The 30GXN,R and 30HX chiller units can be connected to the CCN if desired. The communication bus wiring is a shielded, 3-conductor cable with drain wire and is supplied and installed in the field. The system elements are connected to the communication bus in a daisy chain arrangement. The positive pin of each system element communication connector must be wired to the positive pins of the system elements on either side of it. This is also required for the negative and signal ground pins of each system element. Wiring connections for CCN should be made at TB3. Consult the CCN Contractor's Manual for further information.

NOTE: Conductors and drain wire must be 20 AWG (American Wire Gage) minimum stranded, tinned copper. Individual conductors must be insulated with PVC, PVC/nylon, vinyl, Teflon, or polyethylene. An aluminum/polyester 100% foil shield and an outer jacket of PVC, PVC/nylon, chrome vinyl, or Teflon with a minimum operating temperature range of -20 C to 60 C is required. Wire manufactured by Alpha (2413 or 5463), American (A22503), Belden (8772), or Columbia (02525) meets the above mentioned requirements. It is important when connecting to a CCN communication bus that a color-coding scheme be used for the entire network to simplify the installation. It is recommended that red be used for the signal positive, black for the signal negative and white for the signal ground. Use a similar scheme for cables containing

different colored wires. At each system element, the shields of its communication bus cables must be tied together. If the communication bus is entirely within one building, the resulting continuous shield must be connected to a ground at one point only. If the communication bus cable exits from one building and enters another, the shields must be connected to grounds at the lightning suppressor in each building where the cable enters or exits the building (one point per building only).

To connect the unit to the network:

- 1. Turn off power to the control box.
- Cut the CCN wire and strip the ends of the red (+), white (ground), and black (-) conductors. (Substitute appropriate colors for different colored cables.)
- Connect the red wire to (+) terminal on TB3, the white wire to COM terminal, and the black wire to the (-) terminal.
- The RJ-14 CCN connector on TB3 can also be used, but is only intended for temporary connection (for example: a laptop computer running Service Tool).

Table 1 — Unit Mode from Control/Enable/Off/ Remote Contact and CCN State

SWITCH POSITION	REMOTE CONTACTS	CCN CONFIGURATION	CCN STATE	UNIT
descriptions are a terror		DISABLE	NR	LOCAL ON
ENABLE	NR	ENABLE	RUN	CCN ON
		LIVABLE	STOP	CCN OFF
OFF	NR	NR	NR	LOCAL OFF
	OPEN	NR	NR	LOCAL OFF
REMOTE CONTACT		DISABLE	NR	LOCAL ON
	CLOSED	ENABLE	RUN	CCN ON
		LIVABLE	STOP	CCN OFF

LEGEND

CCN — Carrier Comfort Network
NR — Input Not Read by Processor

NOTE: If the unit is configured for a clock, then the unit is under clock control if it is in an ON mode.

#### **OPERATION DATA**

**Electronic Expansion Valve (EXV)** — The MBB controls the EXV through the EXV board. The EXV (electronic expansion valve) is a device that contains a linear actuator stepper motor. See Fig. 1.

EXV OPERATION — High-pressure liquid refrigerant enters the valve through the side. A series of calibrated slots are located inside the orifice assembly. As refrigerant passes through the orifice, the pressure drops and the refrigerant changes to a 2-phase condition (liquid and vapor). To control refrigerant flow for different operating conditions, the sleeve moves up and down over the orifice, thereby changing orifice size. The sleeve is moved by a linear stepper motor. The stepper motor moves in increments and is controlled directly by the processor module. As the stepper motor rotates, motion is transferred into linear movement by the lead screw. Through the stepper motor and lead screw, 15,000 discrete steps of motion are obtained. The large number of steps and long stroke result in very accurate control of refrigerant flow.

Each compressor has a discharge gas temperature sensor mounted vertically in the top of the muffler assembly. The discharge gas temperature sensor monitors the discharge gas temperature leaving each compressor and sends this information to the MBB through LEN communication with the EXV board. At initial start-up, the EXV position is at zero. After that, the microprocessor keeps accurate track of the valve position in order to use this information as input for the other control functions. The processor does this by initializing the EXVs at start-up. The processor sends out enough closing pulses to the valve to move it from fully open to fully closed, then resets the position counter to zero. From this point, until




Fig. 1 — Electronic Expansion Valve (EXV)

the next initialization, the processor counts the total number of open and closed steps it has sent to each valve.

ECONOMIZER OPERATION — Economizers are factory installed on 30GXN,R108,118-350 and associated modular units and 30HXA,C161-271 units. All other sizes use standard EXVs. The economizer is a brazed plate heat exchanger designed to improve chiller capacity and efficiency as well as providing compressor motor cooling. See Fig. 2. On 30GX chillers the economizer is active when any compressor is fully loaded. On 30HXA,C chillers the economizer is active all the time.

Liquid refrigerant is supplied from the condenser to the top of the economizer. As the refrigerant passes through the economizer, its pressure is reduced to an intermediate level. Next, the refrigerant flows to the EXV which regulates flow to the cooler to maintain the discharge superheat setpoint.

The increase in performance is achieved by diverting a small amount of liquid through a thermostatic expansion valve to a second circuit in the brazed-plate heat exchanger. This will further subcooling the liquid in the first circuit as the refrigerant flashes to vapor. This increase in subcooling provides additional capacity. Also, since the additional power required to accomplish this is minimal; the efficiency of the machine improves. The vapor that flashes leaves the top of the economizer where it passes to the compressor and is used to provide motor cooling. After passing over the motor windings, the refrigerant reenters the cycle at an intermediate port in the compression cycle.




Fig. 2 — Brazed Plate Economizer

Oil Pumps — The 30GXN,GXR,HX screw chillers use one externally mounted prelubricating oil pump per circuit. This pump is operated as part of the start-up sequence. On 30GXN,R units, the pumps are mounted above the base rails on the oil separator side of the unit (see Fig. 3). The pumps are mounted to a bracket on the condensers of 30HXC units and to the oil separator on 30HXA units.

When a circuit is required to start, the controls energize the oil pump first and read the oil pressure transducer reading. The pump is operated for a period of 20 seconds, after which the oil solenoid is energized to open the oil inlet valve at the compressor. The control again reads the pressure from the oil pressure transducer. If the pump has built up sufficient oil pressure, the compressor is allowed to start after 15 seconds.

Once the compressor has started, the oil pump will continue to run for 120 seconds.

If the pump is not able to build up enough oil pressure, the pump is turned off. Within 3 seconds, the pump is re-energized and makes two additional attempts, if necessary, to build oil pressure. The control generates an alarm if the third attempt fails.

The oil pump is also used to supplement system pressure under certain operating conditions. The oil flow requirements of the compressor vary based on pressure differential across the compressor. The oil pump is designed to provide differential oil pressure during low pressure differential conditions. It is not designed to overcome high pressure drop across filters during high pressure differential conditions.

If the differential oil pressure (oil pressure – economizer pressure) for a compressor is too low the oil pump will be started. Just before the oil pump is started the control measures the pressure differential between the discharge pressure and oil pressure (oil system pressure drop). The oil system pressure drop is saved and used to determine when the oil pump should be shut off.

When the oil pump is operating, it is capable of increasing oil pressure from 0 psi to 50 psi depending on the oil flow requirements of the compressor. For example, if the compressor needs 2 gpm (high pressure differential condition) and the oil pump is capable of 1.2 gpm, there is no pressure rise and the oil flow will bypass the check valve and supply the 2 gpm to the compressor. If the compressor requires .75 gpm, the oil pump will increase pressure to satisfy the oil pressure requirement.

The pump will continue to operate until the discharge pressure minus economizer pressure is greater then 17 psi plus the oil system pressure drop.

Example:

Discharge pressure	80 psi
Oil pressure	65 psi
Oil system pressure drop	80 - 65 = 15  psi
Economizer pressure	55 psi
Differential oil pressure	(65 - 55) = 10  psi
Suction pressure	40 psi

Based on the above conditions the oil pump will be started because differential oil pressure equals 10 psi. See Table 2.




Fig. 3 — Oil Pump

Table 2 — Oil Pump Suction Pressure Requirements

SUCTION PRESSURE (SP)	OIL PUMP TURNS ON WHEN DIFFERENTIAL PRESSURE IS LESS THAN:
≤35 psig	12 psig
35 psig < SP < 51 psig	14.5 psig
≥51 psig	17 psig

The oil pump will continue to operate until the discharge pressure minus economizer pressure (which equals 25) is greater than 17 plus 15 (oil system loss before pump was started). The only way this can be satisfied is if the discharge pressure increases or the compressor unloads at which point the oil pump will be shut off.

Motor Cooling — Compressor motor winding temperatures are controlled to a set point of 200 F (93.3 C). The control accomplishes this by cycling the motor cooling solenoid valve to allow liquid refrigerant to flow across the motor windings as needed. On 30GXN,R units equipped with economizers, flash gas leaves the top of the economizer (when the circuit is fully loaded for 30GXN,R models only) and continually flows to the motor windings. All refrigerant used for motor cooling reenters the rotors through a port located midway along the compression cycle and is compressed to discharge pressure.

Back Pressure Valve (30GXN,R and 30HXA only) — This valve is located on the oil separator outlet on 30GXN,R units and mounted on the oil separator shell of 30HXA units. The valve's function is to ensure that there is sufficient system differential pressure to allow for oil to be driven back to the compressor. A small copper line (economizer pressure) is connected to the top of the valve, which contains an internal spring that closes a piston if the pressure in the oil separator is not at least 15 psig greater than the economizer pressure.

**Sensors** — The 30GXN,GXR,HX *Comfort*Link<sup>TM</sup> control system gathers information from sensors to control the operation of the chiller. The units use up to 10 standard pressure transducers and up to 10 standard thermistors (including 4 motor temperature thermistors). The sensors are listed in Table 3.

Table 3 — Thermistor and Transducer Locations

	THE	RMISTORS	
Sensor	Description	Location	Connection Terminals
T1	Cooler Leaving Fluid Temp	Cooler Head Leaving Fluid Side	MBB, J8-13,14
T2	Cooler Entering Fluid Temp	Cooler Head Entering Fluid Side	MBB, J8-11,12
Motor Temp A1	Motor Temperature A1	Compressor A1 Junction Box	CCP1, plug J5
Motor Temp A2*	Motor Temperature A2	Compressor A2 Junction Box	CCP2, plug J5
Motor Temp B1	Motor Temperature B1	Compressor B1 Junction Box	CCP1, plug J9
Motor Temp B2†	Motor Temperature B2	Compressor B2 Junction Box	CCP2, plug J9
T5	Discharge Gas Temp Comp A1	Top of Comp A1 Discharge Line	EXV, J5-11,12
T6	Discharge Gas Temp Comp B1	Top of Comp B1 Discharge Line	EXV, J5-9,10
T3*	Discharge Gas Temp Comp A2	Top of Comp A2 Discharge Line	EXV, J5-7,8
T4†	Discharge Gas Temp Comp B2	Top of Comp B2 Discharge Line	EXV, J5-5,6
T9 (optional)**	Outdoor Air Thermistor/Dual LWT	Outside Air Stream/Common Leaving Fluid	TB5, terminals 7,8
T10 (optional)**	Space Temperature	Conditioned Space	TB5, terminals 7,8
COND EWT (optional)**	Condenser Entering Water Thermistor	Condenser Entering Fluid Line	TB2, terminals 1,2
COND LWT (optional)**	Condenser Leaving Water Thermistor	Condenser Leaving Fluid Line	TB2, terminals 1,2
		TRANSDUCERS	162, terminais 3,4
Sensor	Description	Location	Connection Terminals
DPT-A	Discharge Pressure Circuit A	Top of Condenser Separator Circuit A	
SPT-A	Suction Pressure Circuit A	Top of Cooler Circuit A	MBB, J8-21,22,23
EPT-A	Economizer Pressure Circuit A	Economizer Line Entering Comp A	MBB, J8-24,25,26
OPT-A1	Oil Pressure Compressor A1	Compressor A1 Oil Connection	SCB, J5-7,8,9
OPT-A2*	Oil Pressure Compressor A2	Compressor A2 Oil Connection	SCB, J5-4,5,6
PT-B	Discharge Pressure Circuit B	Top of Oil Separator Circuit B	SCB, J5-1,2,3
ВРТ-В	Suction Pressure Circuit B	Top of Cooler Circuit B	MBB, J8-15,16,17
РТ-В	Economizer Pressure Circuit B	Economizer Line Entering Comp B	MBB, J8-18,19,20
PT-B1	Oil Pressure Compressor B1	Compressor B1 Oil Connection	SCB, J6-7,8,9
PT-B2+	Oil Pressure Compressor B2	Compressor B1 Oil Connection	SCB, J6-4,5,6

Compressor B1 Oil Connection

SCB, J6-1,2,3

OPT-B2†

Oil Pressure Compressor B2

<sup>\*30</sup>HX206-271 and 30GXN,R204-350, 370-528 only. †30GXN,R281-350 only. \*\*Sensors are available as accessories for field installation (30HXC only).

# ComfortLink™ Compressor Protection (CCP Board — One CCP board controls up to 2 compressors. The CCP provides the following functions:

compressor main contactor control

Wye-Delta contactor transition

· compressor ground current protection

· motor temperature reading

· high-pressure protection

· reverse rotation protection

current imbalance protection

· compressor oil solenoid control

· motor cooling solenoid control

· LEN communications

· starting and running overcurrent protection

# The CCP has the following 4 output relays and 3 inputs: OUTPUTS:

· compressor contactor

· compressor oil solenoid

compressor motor cooling solenoid

Wye-Delta transition relay

#### INPUTS:

- · motor temperature
- · three-phase current
- · high-pressure switch

A diagram of the CCP board is shown in Fig. 4. One CCP board is installed on 30GXN,R080-178 and 30HXA,C076-186 units and two CCP boards are installed on 30GXN,R204-350 and 30HXA,C206-271 units. The address for each CCP board is set using DIP (dual in-line package) switches. For CCP1 (compressor A1 and B1), DIP switch 1 should be set to 'L' ('On' position for LEN communication). Switches 2, 3 and 4 should be set to '0' ("OFF" position). For CCP2 (compressor A2 for 30GXN,R204-268 and 30HXA,C206-271 and compressor B2 for 30GXN,R281-350), switch 1 should be set to 'L' and switches 3 and 4 should be set to '1' ("ON" position). Switch 2 should be set to '0' ("OFF" position). See Table 4 for CCP board connections. The CCP has a reset button located between the DIP switch and the J10 connector.

Each compressor's MTA (must trip amps) setting is communicated to the MBB during the initialization period. See Table 5 for DIP switch settings.




Fig. 4 — ComfortLink™ Compressor Protection (CCP) Board

Table 4 — ComfortLink™ Compressor Protection (CCP) Board Plug Connections

CCP PLUG	DESCRIPTION
J1	24-vac Power Input
J2, J6	Compressor Contactor(s)
J3, J7	High Pressure Switch, Oil and Motor Cooling Solenoids
J4, J8	Current Sensor Input
J5, J9	Compressor Motor Temperature Input
J10, J11	Communication Connections

NOTE: Plugs J2-J5 are for compressors A1 (CCP1) or A2 (CCP2). Plugs J6-J9 are for compressor B1 (CCP1) or B2 (CCP2).

Table 5 — CCP Address DIP Switch Settings

UNIT	CCP1				CCP2			
ONT	1	2	3	4	1	2	3	4
30GXN,R080-178 30HXA076-186 30HXC076-186	L	OFF	0	0	-	-	-	-
30GXN,R204-350 30HXA206-271 30HXC206-271	L	OFF	0	0	L	OFF	1	1

To verify proper must trip amps header configuration, use the Navigator and the Configuration mode portion of Appendix A to locate the items CM.A1, CM.A2, CM.B1 and CM.B2 in the UNIT sub-mode. See Appendix A for correct settings. If the values do not match those in Appendix A, verify that the configuration headers have been properly punched out.

The CCP communicates on the LEN (Local Equipment Network) bus to the MBB. Proper operation of the CCP board can be verified by observing the 2 LEDs located on the board. The red LED blinks at a rate of once every 1 to 2 seconds. This indicates that the module is powered and operating correctly. The green LED blinks when the module is satisfactorily communicating with the MBB. The CCP communicates status of its inputs and outputs and reports 13 different alarm conditions to the MBB.

#### **A** CAUTION

The CCP module has many features that are specifically designed to protect the compressor, including reverse rotation protection. Do not attempt to bypass or alter any of the factory wiring. Any compressor operation in the reverse direction will result in a compressor failure that will require compressor replacement.

The MBB will generate an alert when it receives an alarm input from the CCP. The alert will be generated as T051, T052, T055, or T056 (for Compressors A1, A2, B1, B2 respectively). Press the representation on the Navigator simultaneously to expand the full meaning of the alert. For example, the Navigator will read: T055 CIRCUIT B, COMPRESSOR 1 FAILURE-HIGH PRESSURE SWITCH TRIP.

The high-pressure switch is wired in series with the relay coils of the 8 relays on the CCP. If this switch opens during operation, all relays on the CCP are deenergized and the compressor is stopped. The failure is reported to the MBB and the processor module locks off the compressor from restarting until the alarm is manually reset.

Wye-Delta vs Across-the-Line (XL) Starting Option — All 30GXN,R and 30HX chillers operating at voltages of 230-3-60, 208/230-3-60 or 230-3-50 (4, 5, or 8 at

Position 12 in model number) are supplied with factory-installed Wye-Delta starters. All other voltage options can be ordered with either Wye-Delta or XL starting options. The XL starting method is the most cost effective and simply starts the compressor motor in a Delta configuration (the motors are designed for continuous operation in this configuration) using a single contactor. See Fig. 5. This is the simplest starting method to use and is ideal where starting current does not require limiting.

Where current limitations exist, the Wye-Delta option may be used. See Fig. 6. This option uses a factory-installed starter assembly for each compressor, which consists of 3 contactors labelled 1M, 2M, and S. As the compressor is started, the CCP module energizes contactors 1M and S, which connects and energizes the motor windings in a Wye configuration. The starting current required will be approximately 60% less than that required for an XL start due to the higher impedance of the motor windings when Wye connected. The compressor will attain about 100% of its normal operating speed (approximately 3 to 5 seconds) before the CCP module deenergizes the S contactor and energizes the 2M contactor, switching the compressor windings to a Delta wiring configuration. The S and 2M contactors in the starter assembly are both mechanically and electrically interlocked so that they will not both be energized at the same time.

Do not alter the factory-installed power wiring from the control box terminal block to the compressor junction block. Doing so will cause permanent damage to the compressor and will require that the compressor be replaced.

Capacity Control — The control system cycles compressors, loaders, and minimum load control valves to maintain the user-configured leaving chilled fluid temperature set point. Entering fluid temperature is used by the microprocessor to determine the temperature drop across the cooler and is used in determining the optimum time to add or subtract capacity stages. The chilled fluid temperature set point can be automatically reset by the return fluid temperature, space temperature or outdoor-air temperature reset features. It can also be reset from an external 4 to 20 mA signal (requires optional EMM), or from a network signal.

The capacity control algorithm runs every 30 seconds. The algorithm attempts to maintain the Control Point at the desired set point. Each time it runs, the control reads the entering and leaving fluid temperatures. The control determines the rate at which conditions are changing and calculates 2 variables based on these conditions. Next, a capacity ratio (SMZ, Outputs under Sub-mode GEN.O) is calculated using the 2 variables to determine whether or not to make any changes to the current stages of capacity. This ratio value ranges from -100 to + 100%. If the next stage of capacity is a compressor, the control starts (stops) a compressor when the ratio reaches + 100% (-100%). If the next stage of capacity is a loader, the control energizes (deenergizes) a loader when the ratio reaches + 60% (-60%). Loaders are allowed to cycle faster than compressors, to minimize the number of starts and stops on each compressor. A delay of 90 seconds occurs after each capacity step change.

MINUTES LEFT FOR START — This value is displayed in the Status subfunction and represents the amount of time to elapse before the unit is started. This value can be zero without the machine running in many situations. This can include being unoccupied, Remote Contact/Off/Enable switch in the OFF position, CCN not allowing unit to start, Demand Limit in effect, no call for cooling due to no load, and alarm or alert conditions present. If the machine should be running and none of the above are true, a minimum off time may be in effect. The machine should start normally once the time limit has expired.




Fig. 5 — Across-the-Line (XL) Compressor Wiring




Fig. 6 — Wye-Delta Compressor Wiring

MINUTES OFF TIME (DELY, Configuration mode under sub-mode OPT2) — This user-configurable time period is used by the control to determine how long unit operation is delayed after power is applied/restored to the unit. Typically, this time period is configured when multiple machines are located on a single site. For example, this gives the user the ability to prevent all the units from restarting at once after a power failure. A value of zero for this variable does not mean that the unit should be running.

LOADING SEQUENCE — The 30GXN,GXR,HX compressor efficiency is greatest at full load. Therefore, the following sequence list applies to capacity control.

- The next compressor is not started until all others are running at 100%.
- The second unloading stage is only used during initial capacity staging of the unit at start-up.
- Whenever a compressor is started in a circuit, the loaders in the circuit are deenergized for 15 seconds before the compressor is started. The loaders are energized 90 seconds after the compressor is started.

CLOSE CONTROL (CLS.C, Configuration mode under sub-mode OPT2) — When configured for Close Control, the control is allowed to use any loading/capacity control devices

required to maintain better leaving fluid temperature regulation. All stages of unloading are available. See Appendix B for an example.

LEAD/LAG DETERMINATION (LLCS, Configuration mode under sub-mode OPT2) — This is a configurable choice and is factory set to be automatic. The value can be changed to Circuit A or Circuit B leading, as desired. Set at automatic, the circuit with the lowest hours is started first. Changes to which circuit is the lead circuit and which is the lag are made when shutting off compressors.

On 30HX206-271 and 30GXN,R204-350 units set for staged loading, the control fully loads the lead circuit before starting the lag circuit and unloads the lag circuit first. When these units are set for equal loading, the control maintains nearly equal capacities in each circuit when the chiller is loading and unloading.

CAPACITY SEQUENCE DETERMINATION (LOAD, Configuration mode, under sub-mode OPT2) — This is configurable as equal circuit loading or staged circuit loading with the default set at staged. The control determines the order in which the steps of capacity for each circuit are changed. This control choice does NOT have any impact on machines with only 2 compressors.

MINIMUM LOAD VALVE (MLVS, Configuration mode under sub-mode OPT1) — When this option is installed and configured, the first stage of capacity is altered by energizing the Minimum Load valve relay. Once the control requires more capacity, the minimum load valve is deenergized and normal capacity staging resumes with loaders and compressors. Similarly, the Minimum Load valve relay will be energized for the last stage of capacity to be used before the circuit is shut down.

<u>Configure Unit for Minimum Load Control</u> — The chiller must be configured for minimum load control operation. This may be done using the Navigator. Set the Enable/Off/Remote Contact switch in the Off position.

- 1. Press until 'Select a Menu Item' is displayed.
- 2. Press to illuminate the Configuration mode LED.
- 3. Press ENTER and ▼ to select 'OPT1'. Press Interest and then ▼ to select 'MLV'.
- 4. Press and enter the Password (use arrow keys and press for each digit) if required.
- 5. Use to change the flashing 'No' to 'Yes'. Press and the display says 'MLV Yes'.

The chiller is now configured for minimum load valve control. <u>Test Minimum Load Relay Outputs</u> — After the unit is configured, test the operation of the relay and solenoid valve using the Service Test mode.

- Switch the Enable/Off/Remote Contact switch to the 'Off' position.
- 2. Press on the Navigator to display 'Select a Menu Item' and press ▼ to illuminate the Service Test LED.
- 3. Press and 'TEST OFF' will be displayed.
- 4. Press enter (enter Password if required), and then enter to display 'TEST ON'.
- 5. Switch the EOR (Enable/Off/Remote Contact) switch to the "Enable" position.
- 6. Press to select 'COMP' and press ENTER
- 7. Press to select 'MLV OFF'. Press ollowed by and sagain. The minimum load valve output will be turned on. Both circuits' solenoids are turned on at the same time.
- 8. Press [STER], followed by wand and again to turn the valve output off.

<u>Adjust Setting of Minimum Load Ball Valve</u> — The minimum load ball valve must be adjusted to suit the application. Calibrate one circuit at a time as follows:

- 1. Adjust the ball valve so that it is approximately half open.
- Operate the chiller in Manual Control mode, with one circuit operating, and all compressor loaders deenergized.
- Record the cooler ΔT (the difference between cooler entering fluid temperature and cooler leaving fluid temperature) at this fully unloaded condition.
- 4. Use the Manual Control feature to enable the minimum load valve for the circuit that is operating.
- 5. Observe and record the cooler  $\Delta T$  with the minimum load valve energized.

- Adjust the minimum load ball valve until the cooler temperature difference reading from Step 5 is equal to half of the temperature difference reading from Step 3.
- 7. Open the ball valve to decrease the temperature difference or close the ball valve to increase the temperature difference (ΔT). When the valve is adjusted correctly, the difference between cooler entering and leaving fluid temperatures when the minimum load control is energized must be at least half of the temperature difference when the minimum load control is deenergized. For example, if the difference between the cooler entering and leaving water temperature is 3° F with the valve deenergized, then the difference between cooler entering and leaving water temperature must be at least 1.5° F with the valve energized.

Once the outputs have been tested and the ball valve adjusted, the installation is complete. Disable manual control and return chiller to desired operational status.

CAPACITY CONTROL OVERRIDES — The following overrides will modify the normal operation of the routine.

Deadband Multiplier — The user configurable Deadband Multiplier (Z.GN, Configuration mode under sub-mode SLCT) has a default value of 2.0. The range is from 1.0 to 4.0. When set to other than 1.0, this factor is applied to the capacity Load/Unload Factor. The larger this value is set, the longer the control will delay between adding or removing stages of capacity. Figure 7 shows how compressor starts can be reduced over time if the leaving water temperature is allowed to drift a larger amount above and below the set point. This value should be set in the range of 3.0 to 4.0 for systems with small loop volumes. The Main Base Board (MBB) closely follows the rate of compressor cycling for each circuit.

<u>First Stage Override</u> — If the current capacity stage is zero, the control will modify the routine with a 1.2 factor on adding the first stage to reduce cycling. This factor is also applied when the control is attempting to remove the last stage of capacity.

Slow Change Override — The control prevents the capacity stages from being changed when the leaving fluid temperature is close to the set point (within an adjustable deadband) and moving towards the set point.

Ramp Loading — (RL.S, Configuration mode under submode SLCT) — Limits the rate of change of leaving fluid temperature. If the unit is in a Cooling mode and configured for Ramp Loading, the control makes 2 comparisons before deciding to change stages of capacity. The control calculates a temperature difference between the control point and leaving fluid temperature. If the difference is greater than 4° F (2.2° C) and the rate of change (°F or °C per minute) is more than the configured Cooling Ramp Loading value (CRMP, Configuration mode under sub-mode SLCT), the control does not allow any changes to the current stage of capacity.

Low Entering Fluid Temperature Unloading — When the entering fluid temperature is below the control point, the control will attempt to remove 25% of the current stages being used. If exactly 25% cannot be removed, the control removes an amount greater than 25%, but no more than necessary. The lowest stage will not be removed.

Low Discharge Superheat — If a circuit's discharge superheat is less than 15° F (8.3° C), the control does not increase the current capacity stage. If the discharge superheat is less than 5° F (2.8° C) and decreasing, the circuit is unloaded every 30 seconds until the superheat is greater than 5° F (2.8° C). The final capacity stage is not unloaded unless an alarm condition exists. This override is ignored for the first 3 minutes after a compressor is started.




Fig. 7 — Deadband Multiplier

<u>Low Saturated Suction Temperature</u> — To avoid freezing the cooler, the control will compare the circuit Saturated Suction temperature with a predetermined freeze point.

For water [brine] circuits, if the Saturated Suction temperature falls below 34 F (1.1 C) [the Brine Freeze Point], the unit capacity will not increase. If the Saturated Suction temperature falls below 28 F (-2.2 C), [the Brine Freeze Point minus 6° F (3.3° C)], for 90 seconds, all loaders in the circuit are turned off. If this condition continues for a total of 3 minutes, the circuit will alarm and shut down.

For Brine applications, the Brine Freeze Point (Configuration Mode, SERV sub-mode, BR.FZ) must be configured for the freeze point of the brine solution. The control will use the Brine Freeze Point value minus 6° F (3.3° C) as the point to compare with the Saturated Suction Temperature. The default for the Brine Freeze Point is 34 F (1.1 C), which means the control will use 28 F (-2.2 C) as the freeze point. The Brine Freeze Point is adjustable from -20 F to 34 F (-29 C to 1.1 C). Failure to set the Brine Freeze Point correctly will cause improper unit operation.

High Condensing Temperature Unloading — Every 10 seconds the control checks for the conditions below. Loaders will be cycled as needed to control the saturated condensing temperature below the configured maximum condensing temperature. Configured maximums are 154 F (67.8 C) for 30GXN,R, 152 F (66.7 C) for 30HXA, and 122 F (50 C) for 30HXC units. If a circuit's saturated condensing temperature is more than 12° F (6.7° C) below the maximum condensing temperature, the circuit capacity is not allowed to increase. If the saturated condensing temperature is more than 2° F (1.1° C) above the maximum condensing temperature for 60 seconds, a loader is turned off. If the saturated condensing temperature rises to more than 5° F (2.8° C) above the maximum condensing temperature during the 60 seconds, a loader is turned off immediately. If all the loaders were already off, the compressor is shut down and an alarm is generated.

MOP (Maximum Operating Pressure) Override — The control monitors saturated condensing and suction temperature for each circuit as well as differential oil pressure. Based on a configurable maximum operating set point (saturated suction temperature), set maximum condensing temperature, and minimum differential oil pressure, the control may reduce the number of capacity stages being used and/or may lower the EXD position when system pressures approach the set parameters.

#### **Head Pressure Control**

GENERAL — The microprocessor controls the condenser fans (30GXN,R) to maintain the saturated condensing temperature to a configurable set point. The 30HXA condenserless units with a 09DK condenser use a combination of factory-supplied

fan cycling pressure switches (shipped in the 30HXA control box), temperature switches, and an accessory Motormaster® control to maintain head pressure independent of 30HXA unit control. The fans are staged or speed varied (30GXN,R) or water valve controlled (30HXC) based on each circuit's saturated condensing temperature and compressor status. Water cooled units (30HXC) operating at less than 70 F (21.1 C) for entering condenser water require the use of head pressure control.

The chiller must be field configured for the options shown in Table 6. Fan stage settings are shown in Table 7.

AIR-COOLED UNITS (30GXN,R) — See Fig. 8 for condenser fan locations.

Without Motormaster V Control — The first stage of fans are turned on based on compressor status or a Head Pressure Set Point based on Saturated Condensing Temperature (SCT). Additional fan stages are added when the SCT exceeds the Head Pressure Set Point. The Head Pressure Set Point is configurable in the Set Point sub-mode. The default is 113 F (45 C). Once a fan stage has been added, the software temporarily modifies the head pressure set point by adding 15° F (8.3° C) for 35 seconds. A fan stage will be removed when the Saturated Condensing Temperature has been less than the Head Pressure Set Point minus 35° F (19.4° C) for 2 minutes. The control uses the higher of the 2 Saturated Condensing Temperature values for 30GXN,R080-160 units. For the 30GXN,R153, 163-350 units, each circuit's fan stages are independently controlled based on the circuit Saturated Condensing Temperature. Refer to Table 8 for condenser fan control information. See Fig. 9A for operational information.

With Motormaster V Control — For low-ambient operation, the lead fan in each circuit can be equipped with the optional or accessory Motormaster head pressure controller. If factory installed, the controller will be configured for 4 to 20 mA control. With the Variable Head Pressure Select option set to 1 (4 to 20 mA), the MBB module calculates the required output based on Saturated Condensing temperature, Head Pressure set point, and a PID (proportional integral derivative) loop calculation. This 4 to 20 mA output is driven through the SCB. Proportional, Integral, and Derivative gain parameters for air-cooled controls are adjustable and can be found in the SERV sub-mode under the Configuration mode. Only certified Carrier Comfort Network technicians should perform checkout and adjustment of the PID loop. To obtain this accessory for field installation, order by part number 30GX-900---071, 072, 073 for a single controller package (30GXN,R080-160). Order part number 30GX-900---074, 075, 076 for a dual controller package (30GXN,R153, 163-350). These packages contain all the hardware required to install this accessory. See Fig. 9B for operational information.

The control will use the higher of the 2 Saturated Condensing Temperature values for 30GXN,R080-160 units. For the 30GXN,R153, 163-350 units, each circuit's fan stages are independently controlled based on the circuit's Saturated Condensing Temperature. Refer to Table 9 for condenser fan staging information.

WATER-COOLED UNITS (30HXC) — The 30HXC chiller can be configured to control direct acting water valves that are controlled by a 4 to 20 mA (2 to 10 vdc) signal. A 0 to 20 mA (0 to 10 vdc) or 20 to 0 mA (10 to 0 vdc) can also be configured. Installing a 500-ohm  $^{1}/_{2}$  watt resistor across the 2 output terminals of the mA signal enables the use of the vdc signal. Set this configuration (VHPT, configuration mode under sub-mode OPT1) to 1 (4 to 20 mA or 2 to 10 vdc), 2 (0 to 20 mA or 0 to 10 vdc), or 3 (20 to 0 mA or 10 to 0 vdc) as desired depending on valve type. Signal connections are made at terminal block TB2, terminals 14 and 15. The control scheme reads the saturated condensing temperature and uses a PID (proportional integral derivative) loop to control the head pressure. Proportional, Integral and Derivative gain parameters for the water-cooled controls are adjustable and can be found in the SERV sub-mode under the Configuration mode. Only certified Carrier Comfort Network technicians should perform checkout and adjustment of the PID loop.

CONDENSERLESS UNITS (30HXA) — The 30HXA unit is often applied with an 09DK air-cooled condenser. The remote condenser fans are controlled by 2 relay outputs. These connections are in the 30HXA control box. See Field Wiring section on page 72 for wiring details. The 30HXA control must be configured to turn the 09DK fans on and/or off. To set the 30HXA control for this configuration, Unit Type (TYPE, Configuration mode under sub-mode UNIT) must be configured to 3 (Split System). The Head Pressure Control Type

(HPCT under sub-mode OPT1) must be configured to 1 (air-cooled), and Condenser Pump control must be set to 0 (CNPC must be set to No control, Configuration mode under sub-mode OPT1).

Low ambient head pressure control can be accomplished with fan cycling pressure switches (09DK054-094), temperature switches (09DK044, 074-094), and Motormaster® control. The Motormaster control requires a temperature sensor input to control condenser fan cycling. The Motormaster V control also requires a temperature sensor input or the 4 to 20 mA output signal from the *Comfort*link<sup>TM</sup> control system. See accessory installation instructions for further information.

The Head Pressure Control Type (HPCT under sub-mode OPT1) may be set to control various types of head pressure control devices. HPCT may be set to 0 (No Control), 1 (Air Cooled), 3 (Common Condenser), or 4 (Independent Condenser).

The 30HXA chillers also support the use of a 4 to 20 mA (2 to 10 vdc), 0 to 20 mA (0 to 10 vdc), or 20 to 0 mA (10 to 0 vdc) for fan speed control. Installing a 500-ohm <sup>1</sup>/<sub>2</sub> watt resistor across the 2 output terminals of the mA signal enables the use of the vdc signal. Set this configuration (VHPT, configuration mode under sub-mode OPT1) to 1 (4 to 20 mA or 2 to 10 vdc), 2 (0 to 20 mA or 0 to 10 vdc), or 3 (20 to 0 mA or 10 to 0 vdc) as desired depending on control type. For common output applications (single output for both circuits), the signal connections are made at terminal block TB2, terminals 14 and 15. For independent (one output for each circuit) applications, the signal connections are made at terminal block TB2, terminals 14 and 15 for circuit A, and terminals 12 and 13 for circuit B.

Table 6 — Field Configured Head Pressure Control Options

UNIT	CONFIGURATION OPTION	DESCRIPTION	POINT NAME	FACTORY CONFIGURATION
	Head Pressure Control Type	Method of controlling head pressure	HPCT	Air Cooled (30GX Default, Do not modify)
	Fan Staging Select	Method of controlling fan staging	FAN.S	See Table 7
30GX	Variable Head Pressure Select	Method of controlling variable head pressure	VHPT	0 = None (Default) 1 = 4 to 20 mA (Default if Motormaster FIOP is installed.) Set to 4 to 20 mA if Motormaster accessory is installed.
	Head Pressure Control Type	Method of controlling head pres- sure	HPCT	Water Cooled (30HXC Default, Do not modify)
30HXC	Variable Head Pressure Select	Method of controlling.variable head pressure	VHPT	0=None 1 = 4 to 20 mA (*2 to 10 vdc) 2 = 0 to 20 mA (*0 to 10 vdc) 3 = 20 to 0 mA (*10 to 0 vdc)
зонха	Head Pressure Control Type	Method of controlling head pressure	НРСТ	No Control Air Cooled (30HXA Default) Common Condenser Independent Condenser
	Variable Head Pressure Select	Method of controlling variable head pressure	VHPT	0=None 1 = 4 to 20 mA (*2 to 10 vdc) 2 = 0 to 20 mA (*0 to 10 vdc) 3 = 20 to 0 mA (*10 to 0 vdc)

<sup>\*</sup>A vdc signal can be generated by installing a 500-ohm 1/2-watt resistor across the 2 output terminals of the mA signal.

Table 7 — Fan Staging Select Configuration Settings for Air Cooled (30GXN,R) Units

UNIT 30GXN,R	COMPUTER SOFTWARE DISPLAY	NAVIGATOR DISPLAY	DESCRIPTION
080,090*	6	(1 STAGE COM)	1st stage compressor status and SCT set point 2nd stage common control based on highest SCT
083,093,106,108, 114,125,135*	7	(2 STAGE COM)	1st stage compressor status and SCT set point 2nd and 3rd stage common control based on highest SCT
118,128,138, 150,160*	8	(3 STAGE COM)	1st stage compressor status and SCT set point 2nd through 4th stage common control based on highest SCT
153,174, 204,225*	4	(A2B1 IND)	1st stage each circuit, compressor status 2nd stage Circuit B independent 2nd and 3rd stage Circuit A independent
163,178*	2	(2 STAGE IND)	1st stage each circuit, compressor status 2nd and 3rd stage each circuit independent
249,264*	5	(A3B2 IND)	1st stage each circuit, compressor status 2nd stage Circuit B independent 2nd, 3rd and 4th stage Circuit A independent
208,228 253,268,281-350*	3	(3 STAGE IND)	1st stage each circuit, compressor status 2nd, 3rd and 4th stage each circuit independent

LEGEND

\*And associated modular sizes.

SCT — Saturated Condensing Temperature





Fig. 8 — 30GX Condenser Fan Locations

### 30GXN,R UNITS — MOTORMASTER V CONTROL NOT INSTALLED



LEGEND
SCT — Saturated Condensing Temperature

Fig. 9A — 30GXN,R Units Head Pressure Control Without Motormaster® V Control

### 30GXN,R UNITS — MOTORMASTER V CONTROL INSTALLED




Fig. 9B — 30GXN,R Units Head Pressure Control With Motormaster V Control

Table 8 — Control Methods and Cooling Set Points

CONTROL TYPE (CTRL)	OCCUPANCY	COOLING SET POINT SELECT (CLSP)					
	STATE	Single	Dual, Switch	Dual, 7 day	Dual, CCN Occ	4 to 20 mA	
Switch	Occupied	ON,CSP1	ON*	ON,CSP1	ON,CSP1	ON	
	Unoccupied	ON,CSP1	ON*	ON,CSP2	ON,CSP2	ON	
7 Day Occ	Occupied	ON,CSP1	ON*	Illegal	Illegal	ON	
	Unoccupied	OFF	OFF	Illegal	Illegal	OFF	
Occupancy	Occupied	ON,CSP1	ON*	Illegal	Illegal	ON	
Occupancy	Unoccupied	OFF	OFF	Illegal	Illegal	OFF	
CCN	Occupied	ON,CSP1	ON*	ON,CSP1	ON,CSP1	ON	
	Unoccupied	ON,CSP1	ON*	ON,CSP2	ON,CSP2	ON	

<sup>\*</sup>Dual set point switch input used. CSP1 used when switch input is open. CSP2 used when switch input is closed. †Cooling set point determined from 4 to 20 mA input to Energy Management Module (EMM) to terminals TB6-3,5.

Table 9 — 30GXN,R080-350 Condenser Fan Staging (Main Base Board Controlled)

30GXN,R UNIT SIZE	FAN TYPE	NAVIGATOR OUTPUT POINT NAME	FAN CONTACTOR	FANS CONTROLLER
	Standard	Fan 1	FC-1	1, 2
080, 090		Fan 2	FC-2	3, 4
	High Static	Fan 1	FC-1, 1A	1, 2
		Fan 1	FC-2, 2A FC-1	3, 4
	Standard	Fan 2	FC-2	1, 2
000 000 400 444 407 407		Fan 3	FC-3	3, 4 5, 6
083, 093, 106-114, 125, 135		Fan 1	FC-1, 1A	1, 2
	High Static	Fan 2	FC-2, 2A	3,4
		Fan 3	FC-3, 3A	5, 6
		Fan 1	FC-1	1, 2
	Standard	Fan 2	FC-2	3, 4
	Otaridard	Fan 3	FC-3	5, 6
118, 128, 138, 150, 160		Fan 3	FC-4	7, 8
,,,		Fan 1	FC-1, 1A	1, 2
	High Static	Fan 2	FC-2, 2A	3, 4
194		Fan 3	FC-3, 3A	5, 6
		Fan 3	FC-4, 4A	7, 8
		Comp. B1 contactor*	FC-1	1, 2
	Standard	Fan 2 Fan 3	FC-2	3, 4
	Sandard	Comp. A1/A2 contactor*	FC-3 FC-4	5, 6
450 474 005 555	1 1	Fan 1	FC-5	7, 8
153, 174, 204, 225		Comp. B1 contactor*	FC-1, 1A	9, 10
		Fan 2	FC-2, 2A	1, 2
	High Static	Fan 3	FC-3, 3A	5, 6
		Comp. A1/A2 contactor*	FC-4, 4A	7, 8
	1 1	Fan 1	FC-5, 5A	9, 10
		Comp. B1 contactor*	FC-1	1, 2
		Fan 2	FC-2	3, 4
	Standard	Fan 4	FC-3	5, 6
	Standard	Comp. A1 contactor*	FC-4	7, 8
		Fan 1	FC-5	9, 10
163, 178		Fan 3	FC-6	11, 12
ಜ್ಞಾನ್ನು ಎ.ಎ.ಇ.	n n	Comp. B1 contactor*	FC-1, 1A	1, 2
		Fan 2	FC-2, 2A	3, 4
	High Static	Fan 4	FC-3, 3A	5, 6
		Comp. A1 contactor*	FC-4, 4A	7, 8
	0	Fan 1	FC-5, 5A	9, 10
	<del>                                     </del>	Fan 3	FC-6, 6A	11, 12
	1	Comp. B1 contactor*	FC-1	1, 2
	1 1	Fan 2 Fan 1	FC-2	3, 4
	Standard -	Comp. A1/A2 contactor*	FC-3	5, 6
	1	Fan 3	FC-4 FC-5	7, 8
		Fan 3	FC-6	9, 10
249, 264		Comp. B1 contactor*	FC-1, 1A	11, 12 1, 2
	1	Fan 2	FC-2, 2A	3, 4
	I link out	Fan 1	FC-3, 3A	5, 6
	High Static	Comp. A1/A2 contactor*	FC-4, 4A	7, 8
	1	Fan 3	FC-5, 5A	9, 10
<u> </u>	(2)	Fan 3	FC-6, 6A	11, 12
		Comp. B1 contactor*	FC-1	1
	1 [	Fan 1	FC-2	2, 4
	1 [	Fan 2	FC-3	3
	Standard	Fan 4	FC-4	5, 7
		Fan 3	FC-5 .	6, 8
		Comp. A1/A2 contactor*	FC-6	9, 10
		Fan 3	FC-7	11, 12
208, 228		Fan 3	FC-8	13, 14
25		Comp. B1 contactor*	FC-1	1
		Fan 1	FC-2, 2A	2, 4
		Fan 2	FC-3	3
	High Static -	Fan 4	FC-4, 4A	5, 7
		Fan 3	FC-5, 5A	6, 8
		Comp A1/A0 contactant		
	-	Comp. A1/A2 contactor* Fan 3	FC-6, 6A FC-7, 7A	9, 10 11, 12

LEGEND

Comp. — Compressor FC — Fan Contactor \*Proper rotation of these fans to be checked when compressor(s) is running. See Fig. 8 for condenser fan locations when viewing from the control box end.

NOTE: For 30GXN,R153, 163-350 units, fan relays Fan 1 and Fan 3 energize Circuit A fans. Fan relays Fan 2 and Fan 4 energize Circuit B fans.

Table 9 — 30GXN,R080-350 Condenser Fan Staging (Main Base Board Controlled) (cont)

30GXN,R UNIT SIZE	FÀN TYPE	NAVIGATOR OUTPUT POINT NAME	FAN CONTACTOR	FANS CONTROLLED
		Comp. B1 contactor*	FC-1	
	18	Fan 1	FC-2	2,4
		Fan 2	FC-3	3
	MARKS 1 0001 1001	Fan 4	FC-4	5,7
	Standard	Fan 3	FC-5	6,8
		Comp. A1/A2 contactor*	FC-6	9,10
		Fan 3	FC-7	11,12
	Χ ,	Fan 3	FC-8	13,14
253, 268		Fan 1	FC-9	15,16
		Comp. B1 contactor*	FC-1	15,16
		Fan 1	FC-2, 2A	2,4
		Fan 2	FC-3	3
		Fan 4	FC-4, 4A	5,7
	High Static	Fan 3	FC-5, 5A	
		Comp. A1/A2 contactor*	FC-6, 6A	6,8
		Fan 3	FC-7, 7A	9,10
	1 1	Fan 3	FC-8, 8A	11,12
	1	Fan 1	FC-9, 9A	13,14
		Comp. B1/B2 contactor*	FC-1	15,16
		Fan 2	FC-2	1,2
		Fan 4	FC-3	3,4
	0 1	Fan 4	FC-4	5,6
	Standard	Fan 1	FC-5	7,8
	1 1	Comp. A1/A2 contactor*	FC-6	9,10
lg .	l	Fan 3	FC-7	11,12
281-350		Fan 3	FC-8	13,14
201-350		Comp. B1/B2 contactor*	FC-1, 1A	15,16
¥ 6		Fan 2		1,2
81	1 1	Fan 4	FC-2, 2A	3,4
(96)	-	Fan 4	FC-3, 3A	5,6
	High Static -	Fan 1	FC-4, 4A	7,8
	1 -	Comp. A1/A2 contactor*	FC-5, 5A	9,10
	1 -	Fan 3	FC-6, 6A	11,12
	. l . l .	Fan 3	FC-7, 7A	13,14
LEGEND		1013	FC-8, 8A	15,16

LEGEND

Comp. — Compressor FC — Fan Contactor

#### 09DK AIR-COOLED CONDENSERS

<u>09DK044 Units</u> — The 09DK044 units have accessory provision for fully automatic intermediate-season head pressure control through condenser fan cycling. Fan number 2 and 3 cycling is controlled by outdoor-air temperature through air temperature switches (ATS) 1 and 2.

The air temperature switches are located in the lower divider panel underneath the coil header. The sensing element is exposed to air entering the no. 1 fan compartment through a hole in the panel. Fan no. 1 is non-cycling.

The air temperature switch controls the fans as shown in Table 10.

Table 10 — Air Temperature Switch Control (09DK044 Units)

FAN	FAN SWITCH	TEMPERATURE
	100000	Above 65 ± 3 F (18.3 ± 1.7 C)
FAN 2	ON	Between 55 and 65 F (12.8 and 18.3 C) and temperature falling
MIL		Below 55 ± 3 F (12.8 ± 1.7 C)
	OFF	Between 55 and 65 F (12.8 and 18.3 C) and temperature rising
		Above 80 ± 3 F (26.7 ± 1.7 C)
FAN 3	ON	Between 70 and 80 F (21.1 and 26.7 C) and temperature falling
	2000000	Below 70 ± 3 F (21.1 ± 1.7 C)
	OFF	Between 70 and 80 F (21.1 and 26.7 C) and temperature rising

\*Proper rotation of these fans to be checked when compressor(s) is running. See Fig. 8 for condenser fan locations when viewing from the control box end.

NOTE: For 30GXN,R153, 163-350 units, fan relays Fan 1 and Fan 3 energize Circuit A fans. Fan relays Fan 2 and Fan 4 energize Circuit B fans.

09DK054-094 — The capacity of an air-cooled condenser increases with increased temperature difference (defined as saturated condensing temperature minus entering outdoor-air temperature) and decreases with decreased temperature difference. A drop in entering outdoor-air temperature results in a lower saturated condensing temperature. When outdoor-air temperature drops below the minimum temperature for standard units, additional head pressure control is required.

Model 09DK units have fully automatic intermediate-season head pressure control through condenser fan cycling using electromechanical fan cycling controls. Standard head pressure controls regulate the 100 and 50/50% condenser capacity applications. Head pressure can also be controlled by fan cycling controls supplemented by the accessory Motormaster® V solid-state head pressure control. See Motormaster V installation instructions for more information.

In the standard control scheme, fans 1 and 2 are on when there is a call for cooling from the respective coil circuits. Fans 1 and 2 are non-cycling. On 054 and 064 units, fans 3 and 4 are controlled by using a fan cycling pressure switch on each of the primary coil circuits in response to condensing pressure. Fan cycling switches must be replaced with the switches supplied in the control box of the 30HXA chiller.

The fan cycling pressure switch controls the fans as follows: Fans 3 and 4 are on above  $185 \pm 10$  psig  $(1276 \pm 69 \text{ kPa})$  and off below  $97 \pm 10$  psig  $(669 \pm 69 \text{ kPa})$ . If pressure is rising between 97 psig (669 kPa) and 185 psig (1276 kPa), fans 3 and 4 are off. If pressure is falling from 185 psig (1276 kPa) to 97 psig (669 kPa) fans 3 and 4 are on.

The 09DK054-094 condensers are supplied with fan cycling pressure switches suitable for use with R-22 refrigerant. Fan cycling pressure switches that are compatible with R-134a refrigerant pressures are shipped with the 30HXA chillers. These fan cycling pressure switches must be installed in place of the 09DK factory-installed switches before charging to ensure proper head pressure control.

The air temperature switch controls the fans as follows: On the 074-094 condensers, below  $70\pm3$  F (21.1  $\pm$  1.7 C) outdoor ambient, fans 5 and 6 are off; above  $80\pm3$  F (26.7  $\pm$  1.7 C) fans 5 and 6 are on. Between 70 F (21.1 C) and 80 F (26.7 C), whether fans 5 and 6 are on or off depends on whether temperature is rising or falling. If the temperature is rising from 70 F (21.1 C) to 80 F (26.7 C), fans 5 and 6 are off. If the temperature is falling from 80 F (26.7 C) to 70 F (21.1 C), fans 5 and 6 are on.

09AZ AIR-COOLED CONDENSERS — The 09AZV091-182 units are designed to operate specifically with 30HXA chillers, using R-134a refrigerant. Units with 8 fans have 2 direct controlled (applied to optional variable speed), 4 refrigerant pressure and 2 ambient temperature controlled fans. Units with 10 fans have 2 direct controlled (applied to optional variable speed), 4 refrigerant pressure and 4 ambient temperature controlled fans. Units with 12 fans have 2 direct controlled (applied to optional variable speed), 6 refrigerant pressure and 4 ambient temperature controlled fans. Field adjust 09AZ switch settings as follows:

PRESSURE	AMBIENT
Cut in 175 psi	Cut in 70 F
Cut out 145 psi	Cut out 60 F

OPERATION SEQUENCE — All condenser fans are allowed to operate once a call for cooling comes from the chiller. Direct fans will operate while refrigerant pressure and ambient temperature control fans maintain refrigerant head pressure based on existing refrigerant pressure and ambient temperature conditions. Optional variable speed control will ramp direct fan motor speed for improved low ambient performance.

VARIABLE SPEED FAN CONTROL — All units, when ordered with fan head pressure control are furnished with the number 1 condenser motor as a single-phase motor for use with head pressure control. The optional factory-mounted motor head pressure control contains a fan head pressure control device activated by a pressure sensor. The kit controls condenser-fan motor speed in response to the saturated condensing pressure.

ADJUSTING PID ROUTINES — The 30GXN,R, 30HXA and 30HXC head pressure control routines use PID (proportional integral derivative) loops to maintain a user-configurable head pressure set point. Gain defaults values are located in the SERV sub-mode under the Configuration mode (items H.PGN, H.IGN and H.DGN). The control calculates a new fan speed (30GXN,R) or water valve position (30HXC) every 5 seconds based on these gain values and an error term equal to saturated condensing temperature minus head pressure set point. If the control routine is not responding fast enough to large changes (circuit starting, for example), increase the proportional term.

When the routine is making too great a change to valve position or fan speed, decrease the proportional term. To minimize hunting, keep the integral term positive and as low as possible. This value is used to control "droop," which is common in master/submaster control schemes. The default for the derivative term is zero. The value should not need to be changed.

For more information on tuning PID loops, consult the Comfort Controller Installation manual, catalog number 808-890. Follow the instructions under Tuning Control loops.

#### **Control Methods**

SWITCH — Unit is started and stopped manually by switching the ENABLE/OFF/REMOTE CONTACT switch from OFF to ENABLE or by external contacts with the switch in the

REMOTE position. The unit can be enabled and disabled by this action or all control methods.

7-DAY SCHEDULE — Unit is started and stopped in accordance with the schedule configured under Time Clock mode. This schedule can be configured from the Navigator or from CCN.

OCCUPANCY — Unit is started and stopped in accordance with the local occupancy schedule accessible only from CCN. Schedule Number in Table SCHEDOVR must be configured to 1 to utilize the local occupancy schedule, or 65-99 to utilize a global schedule. If the Schedule Number is set to 0 the unit will operate in a continuous 24-hr Occupied mode.

CCN — Unit is started and stopped by communication over the CCN bus. The CHIL\_S\_S point in the A\_UNIT table is provided for this purpose.

Table 8 illustrates how the control method and cooling setpoint select variables direct the operation of the chiller and the set point to which it controls. The illustration also shows the ON/OFF state of the machine for the given combinations.

#### **Cooling Set Point Select**

SINGLE — Unit operation is based on Cooling Setpoint 1 (CSP1).

DUAL SWITCH — Unit operation is based on Cooling Setpoint 1 (CSP.1) when the Dual Setpoint switch contacts are open and Cooling Setpoint 2 (CSP.2) when they are closed.

DUAL 7 DAY — Unit operation is based on Cooling Setpoint 1 (CSP.1) during the occupied mode and Cool Setpoint 2 (CSP.2) during the unoccupied mode as configured under Time Clock mode. Control method must be configured for Switch.

DUAL CCN OCCUPIED — Unit operation is based on Cooling Setpoint 1 (CSP.1) during the Occupied mode and Cooling Setpoint 2 (CSP.2) during the Unoccupied mode as configured under the local occupancy schedule accessible only from CCN. Schedule Number in Table SCHEDOVR must be configured to 1. If the Schedule Number is set to 0 the unit will operate in a continuous 24-hr Occupied mode. Control method must be configured for Switch.

4 TO 20 mA INPUT — Unit operation is based on an external 4 to 20 mA signal input to the Energy Management Module (EMM).

Ice Mode — When Ice Mode is enabled Cooling Setpoint Select must be set to Dual Switch, Dual 7 day or Dual CCN Occupied and the Energy Management Module (EMM) must be installed. Unit operation is based on Cooling Setpoint 1 (CSP.1) during the Occupied mode, Ice Setpoint (CSP.3) during the Unoccupied mode with the Ice Done contacts open and Cooling Setpoint 2 (CSP.2) during the Unoccupied mode with the Ice Done contacts closed. These 3 set points can be utilized to develop your specific control strategy.

Cooler and Condenser (30HXC) Pump Control — The 30GXN,R and 30HX chillers can be configured for cooler and condenser (30HXC) pump control. Inputs for a cooler pump interlock and condenser flow switch or interlock are provided.

COOLER PUMP CONTROL (CPC, Configuration Mode/sub-mode OPT1) — Proper configuration of the cooler pump control is required to prevent possible cooler freeze-up. A cooler flow switch is factory installed to prevent operation without flow through the cooler. It is also recommended that the chiller be interlocked with the chiller water pump starter to provide additional protection. See page 72 of the Field Wiring section for proper connection of the cooler pump interlock.

The factory default setting for cooler pump control is "OFF." It is recommended for all chillers that the cooler pump control be utilized unless the chilled water pump runs continuously or the chilled water system contains a suitable antifreeze solution.

When the cooler pump control is "ON," the cooler pump relay will be energized when the chiller enters an "ON" mode (i.e., ON LOCAL, ON TIME, ON CCN). The cooler pump relay will remain energized for 30 seconds after all compressors stop due to off command. In the event a freeze protection alarm is generated, the cooler pump relay will be energized whether cooler pump control is configured "ON" or "OFF." The cooler pump relay is also energized anytime a compressor is started as well as when certain alarms are generated. The cooler pump relay should be used as an override to the external pump control if cooler pump control is not utilized.

IMPORTANT: If the cooler pump control relay output is not wired to control or override the operation of the chilled water pump an OFF DELAY of 10 minutes must be provided after the chiller is disabled to maintain cooler water flow during the pump down period.

30HXC brine applications below 32 F (0° C) leaving brine temperature require cooler pump control. To reduce the possibility of condenser freeze-up the cooler pump must be stopped or isolation valve closed in the event of loss of condenser water flow.

If cooler pump control is turned "OFF" or "ON" and the chilled water flow switch/interlock does not close within 5 minutes after the unit is enabled and in an "ON" mode, alarm A200 will be generated. If cooler pump control is turned "ON" and the chilled water flow switch/interlock is closed when the unit is enabled and enters an "ON" mode alarm A202 will be generated. Alarm A201 will be generated whenever the cooler pump interlock is open for at least 10 seconds during chiller operation. CONDENSER PUMP CONTROL (CNP.I AND CNPC, Configuration Mode/sub-mode OPT1) - Factory defaults for both condenser pump control and condenser flow switch are set to "NO CONTROL" and "OFF," respectively. The condenser pump can be controlled in one of two ways: In the first method, (CNPC set to "ON WHEN OCCUPIED") the pump can be controlled like the cooler pump. It is turned on whenever the machine is in an "ON" mode and turned off 30 seconds after all compressors stop and the machine is in an "OFF" mode. The second method (CNPC set to "ON WITH COMPRESSORS"), will energize the condenser pump output when the first compressor is started and deenergize the output 30 seconds after the last compressor stops.

When configured for a condenser flow switch/interlock (CNPI set to "ON"), an alarm A159 is generated if the input does not close within one minute after the machine enters an "ON" mode, or within one minute after the condenser pump relay is energized when configured "ON". Alarm A159 is also generated if the flow switch/interlock opens for more than 10 seconds during chiller operation.

30HXC brine applications below 32 F (0° C) leaving brine temperature require condenser pump control to be configured to "ON WHEN OCCUPIED" and condenser pump interlock to be "ON". A condenser water flow switch must be installed and wired to TB2 terminals 5 and 6. The condenser pump output remains energized for 30 minutes after the Enable/Off/Remote Contact switch is placed in the "OFF" position or the Remote Contacts are opened allowing refrigerant pressure equalization.

BRN.L (Configuration Mode, sub-mode SLCT) must be configured to YES if Brine FIOP is installed. This will energize liquid line solenoid valves on brine units when the condenser pump is "ON" and when the compressors are "OFF". Liquid line solenoids are included as part of the Brine FIOP.

Flow Sensor — The factory-installed flow sensor/switch should not require adjustment.

Proper operation of this sensor/switch is necessary to allow the unit to operate and provide running freeze protection for the unit. When power is supplied to the switch, the amber LED in the center of the display will be illuminated. When there is chilled water flow, but the flow is inadequate to close the switch and allow unit operation, one red LED will illuminate. A red LED can also indicate inoperative pump(s), closed valve, clogged strainer or air in the system.

When the first green LED is illuminated, the switch is closed and the unit will start and run. Various conditions can cause variations in flow and allow the switch to open and cause a "nuisance trip". Greater constant flow will help reduce nuisance tips.

Measure the pressure drop across the cooler and use Appendix E to determine the cooler flow rate then determine if the flow rate is adequate for the application. A green LED does not mean minimum flow requirements have been met.

Cooler Heater Control — Factory-installed cooler heaters can be ordered for the 30GXN,R chillers. The number of heaters depends on the size of the machine. The control system operates the heaters in response to the saturated suction temperature of each circuits as well as Entering and Leaving Water Temperature.

The cooler heater will be energized if the unit is OFF (no mechanical cooling) and either of the following two conditions has been met:

- The Saturated Suction Temperature in either circuit is less than BR.FZ Brine Freeze Point (Configuration Mode, Sub-mode SERV), and the unit has been off for more than 30 seconds.
- Entering or Leaving Water Temperature is less than BR.FZ + 3 °F (1.7 °C). The heaters will remain on until both Entering and Leaving Water Temperatures equal or exceed 120 °F (48.9 °C). The heaters will energize again when both water temperatures are below 110 °F (43.3 °C). Cooler flow must be established in order to de-energize the cooler heaters.

If the Entering or Leaving Water Thermistor has failed, the heaters will stay on.

If after 15 minutes of operation, the Saturated Suction Temperature for both circuits is not greater than  $BR.FZ+10\,^{\circ}F$  (5.6 °C), the Cooler Pump will be commanded ON in attempt to increase the water temperature.

The cooler heaters will be deenergized if the unit is ON (mechanical cooling is ON) or if the Saturated Suction Temperature for both circuits is greater than BR.FZ +  $10 \,^{\circ}$ F (5.6  $^{\circ}$ C) for at least 10 minutes.

Oil Heater Control (30GXN,R Units Only) — Standard feature that controls oil temperature based on the discharge gas temperature (DGT) thermistor. Heaters turn on when DGT < 95 F (35 C) and turn off when DGT > 100 F (37.8 C) and compressors are off. The heater is deenergized if the oil level switch is open.

Navigator Display Module Usage (See Fig. 10 and Tables 11-24B) — The Navigator module provides a mobile user interface to the *Comfort*Link<sup>TM</sup> control system. The display has up and down arrow keys, an secure key, and an key. These keys are used to navigate through the different levels of the display structure. See Table 11. Press the key until 'Select a Menu Item' is displayed to move through the top 11 mode levels indicated by LEDs on the left side of the display.

Pressing the ESCAPE and EMTEP keys simultaneously will put the Navigator into expanded text mode where full meaning of all sub-modes, items and their values can be displayed. Pressing the SCAPE and EMTEP keys when the display says 'Select a Menu Item' (Mode LED level) will return the Navigator to its default menu of rotating display items (those items in the VIEW sub-mode under the Run Status mode). In addition, the



Fig. 10 — Navigator Module

password will be disabled requiring that it be entered again before changes can be made to password protected items.

The Service Test function should be used to verify proper protected items. Press the key to exit out of the expanded text mode.

NOTE: When the LANG variable is changed, all appropriate display expansions will immediately change to the new language. No power-off or control reset is required when reconfiguring languages.

When a specific item is located, the item name appears on the left of the display, the value will appear near the middle of the display and the units (if any) will appear on the far right of the display. Press the was a changeable item and the value will begin to flash. Items in the Configuration and Service Test modes are password protected. The password can be changed utilizing the Navigator or through CCN devices such as ComfortWORKS®, ComfortVIEWTM and Service Tool. The words 'Enter Password' will be displayed when required, with the default password also being displayed. Use the mand arrow keys to enter the 4 digits of the password. The default password is 1111. Use the following procedure to change the password:

- Enter the correct password under PASS, Service Password (Configuration Mode, Sub-mode DISP).
- Change PAS.E Password Enable (Configuration Mode, Sub-mode DISP) to DSBL.
- Return to the PASS, Service Password, and change the password to the desired value. For example, 2222. Once changed, the screen will show the new value, 2222.
- 4. Return to the PAS.E *Password Enable*, and change the value to ENBL.

The password has been changed. If the password is required, the machine will show the default 1111 as the password. Use the up or down arrow keys to change the value to the correct password.

Changing item values or testing outputs is accomplished in the same manner. Locate and display the desired item. Press so that the item value flashes. Use the arrow keys to change the value or state of a item and press the key to accept it. Press the key to return to the next higher level of structure. Repeat the process as required for other items. See Tables 12-25 for further details.


Two items, OAT Outside Air Temperature (Temperature Mode, Sub-mode UNIT) and SPT Space Temperature (Temperature Mode, Sub-mode UNIT) can be forced to a value at the Navigator. If one of these two points has been forced, a flashing "f" will appear next to the value indicating a forced value. To remove the force, select the item and press the temperature was that the value is flashing. Press the up and down arrow keys simultaneously and the force will be removed.

Service Test (See Table 13) — Both main power and control circuit power must be on. The Service Test function should be used to verify proper operation of the compressors, loaders, pumps, solenoids, fans, heaters, etc. To access the Service Test mode, the Enable/Off/Remote Contact switch must be in the Off position. Use the display keys to enter the Service Test mode and display 'TEST OFF'. Press the key and 'Off' will flash (Enter the password if required). Use either arrow key to change the 'Off' to 'On' and press | SATER |. Switch the Enable/Off/Remote Contact switch to the Enable position. Use the arrow keys to select either sub-mode OUTS or COMP. Test the expansion valves, oil pumps, fans, cooler heaters, cooler/condenser pump relays, remote alarm relay. head pressure control, and compressor oil and motor cooling solenoids under the OUTS sub-mode. Note that condenser-fan motors are NOT started during VH.PA or VH.PB test on 30GXN,R units with Motormaster® control. Measure 4 to 20 mA dc output using meter in series with violet or pink wire to controller. Refer to the Field Wiring section. These discrete outputs are then turned off if there is no keypad activity for 10 minutes. Test the compressors, loaders, minimum load valves and oil heaters under the COMP sub-mode. Compressor loaders, minimum load valve and oil heaters can be tested with compressors on or off. All compressor outputs can be turned on, but the control will limit the rate by staging one compressor per minute. The relays under the COMP sub-mode will stay on for 10 minutes if there is no keypad activity. Compressors will stay on until they are turned off by the operator. The Service Test mode will remain enabled as long as there is more than one compressor turned on. All safeties are monitored during this test and will turn a compressor, circuit or motor off if necessary. Any other mode or sub-mode can be viewed or changed during the TEST mode. The STAT item (Run Status mode under sub-mode VIEW) will display 'SERVICE TEST' as long as the Service mode is enabled. The TEST sub-mode value must be changed back to OFF before the chiller can be switched to Enable or Remote contact for normal operation.

Configuring and Operating Dual Chiller Control (See Table 24A and 24B) — The dual chiller routine is available for the control of two units supplying chilled fluid on a common loop. This control is designed for either series or parallel fluid flow (PARA, Configuration mode under sub-mode RSET) arrangements. One chiller must be configured as the master chiller, the other as the slave chiller. For series fluid flow, the master chiller is installed so that it receives entering fluid from the slave chiller and its leaving fluid supplies the load. See Fig. 11. For parallel flow applications, an additional leaving water temperature thermistor (Dual Chiller LWT) must be installed as shown in Fig. 12 and 13 and connected to the master chiller. Refer to Thermistors section for sensor wiring.



Fig. 11 — Dual Chiller Piping Arrangement (Series Fluid Flow)



Depending on piping sizes, use either:
HH79NZ014 sensor/10HB50106801 well (3-in. sensor/well)
HH79NZ029 sensor/10HB50106802 well (4-in. sensor/well)

Fig. 12 — Dual Chiller Thermistor Location Parallel Fluid Flow

To configure the two chillers for operation, follow the example shown in Tables 24A and 24B. The master chiller will be configured with a slave chiller at address 2. Also in this example, the master chiller will be configured to use Lead/Lag Balance to even out the chiller runtimes weekly. The Lag Start Delay feature will be set to 10 minutes. The chillers will be configured for parallel fluid flow. The master and slave chillers cannot have the same CCN address (CCNA, Configuration mode under OPT2). In addition, the chillers must be connected together on the same CCN bus. Connections can be made to the CCN screw terminals on TB3 in both chillers. The master chiller will determine which chiller will be Lead and which will be Lag. The master chiller controls the slave chiller by forcing the slave chiller ON and OFF, and forcing the control

point of the slave chiller. The master chiller will also split demand limiting function appropriately between the two chillers, if demand limiting is enabled.

The master chiller is now configured for dual chiller operation. To configure the slave chiller, only the LLEN, PARA and MSSL variables need to be set. Enable the Lead/Lag chiller variable (LLEN) as shown in Tables 24A and 24B. Similarly, set the Master/Slave Select variable (MSSL) to SLVE. The parallel variable (PARA) must be configured the same as the master chiller. The slave chiller does not use the variables LLBL, LLBD and LLDY.

It is recommended to set the cooling set points to the same setting on both Master and Slave chillers for series flow (Duplex) applications. If outdoor air reset is required the outdoor air thermistor must be connected to the Slave chiller (TB5 term. 7 and 8). Outdoor Air Broadcast (BCST, OAT.B) must be configured "ON". Remote contacts should be connected to both Master and Slave to control unit operation. Optional control inputs and Energy Management Module (EMM) should be connected to the Master chiller.

PART	DIMENSIO	NS in. (mm)
NUMBER	Α	В
10HB50106801	3.10 (78.7)	1.55 (39.4)
10HB50106802	4.10 (104.1)	1.28 (32.5)
1/4 N.P.T.	6" MIN	0.505/0.495

Fig. 13 — Dual Leaving Water Thermistor Well

Table 11 — Navigator Display Menu Structure

STATUS	SERVICE TEST	TEMPERATURES	PRESSURES	SET POINTS	INPUTS	OUTPUTS	CONFIGURATION	TIME	OPERATING MODES	ALARMS
Auto Display (VIEW)	Manual Mode On/Off (TEST)	Unit Temperatures (UNIT)	Ckt A Pressures (PRC.A)	Cooling (COOL)	Unit Discrete (GEN.I)	Unit Discrete (GEN.O)	Display (DISP)	Unit Time (TIME)	Modes (MODE)	Current (CRNT)
Machine Hours/Starts (RUN)	(OUTS)	Ckt A Temperatures (CIR.A)	Ckt B Pressures (PRC.B)	Heating (HEAT)	Ckt A/B (CRCT)	Ckt A (CIR.A)	Machine (UNIT)	Unit Date (DATE)		Reset Alarms
Compressor Run Hours (HOUR)	Compressor Tests (COMP)	Ckt B Temperatures (CIR.B)	ii	Head Pressure (HEAD)	Unit Analog (4-20)	Ckt B (CIR.B)	Options 1 (OPT1)	Daylight Savings Time (DST)		(RCRN) Alarm History (HIST)
Starts (STRT)	v						Options 2 (OPT2)	Schedule (SCHD)		
Software Version (VERS)							Temperature Reset (RSET)			di
							Set Point Select (SLCT)			(1
		0					Service Configuration (SERV)			
LEGEND							Broadcast Configuration (BCST)			-

LEGEND

Ckt - Circuit

Table 12 — Configuration Mode and Sub-Mode Directory

SUB- MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
DISP	ENTER	TEST	ON/OFF	TEST DISPLAY LEDS	See Backlight and Contrast adjustment in Tables 21 and 22.
		METR	ON/OFF	METRIC DISPLAY	Off = English On = Metric
ž	LANG		Х	LANGUAGE SELECTION	Default: English English Espanol Francais Portuguese
		PAS.E	ENBL/DSBL	PASSWORD ENABLE	
		PASS	XXXX	SERVICE PASSWORD	Default: 1111
UNIT		TYPE	Х	UNIT TYPE	Air Cooled (GXN,R) Water Cooled (HXC) Split (HXA) Heat Machine Heat Reclaim
		TONS	XXX	UNIT SIZE	
		CAPA	XXX %	CIRCUIT A % CAPACITY	30GXN,R 080, 083, 135, 138 = 54 090, 093, 108, 114, 125, 128, 153 = 59 106 = 63 150 (60 Hz) = 41 160 = 45 174, 178, 281-350 = 50 204 = 64 225 = 61 249, 253 = 71 264, 268 = 67 228 = 72 30HXA,C 076, 186 = 50 086, 126 = 54 096, 116, 136, 161 = 59 106, 246 = 63 146 = 55 171 = 45 206 = 57 261 = 65 271 = 67
		CMP.A	Х	NUMBER CIRC A COMPRESSOR	HXA,C076-186 = 1 HXA,C206-271 = 2 GXN,R080-178 = 1 GXN,R204-350 = 2
		CMP.B	Х	NUMBER CIRC B COMPRESSOR	HXA,C076-271 = 1 GXN,R080-268 = 1 GXN,R281-350 = 2
	▼	DIS.S	XX.X °F	DISCHARGE SUPER SETPOINT	Default: 22° F DISCHARGE SUPERHEAT
		FAN.S .	X	FAN STAGING SELECT	None (30HXA, 30HXC)  1 STAGE IND 2 STAGE IND (30GXN,R163, 178) 3 STAGE IND (30GXN,R281-350, 208, 228, 253, 268) A2B1 IND (30GXN,R153, 174, 204, 225) A3B2 IND (30GXN,R249, 264) 1 STAGE COM (30GXN,R080, 090) 2 STAGE COM (30GXN,R083, 093, 106, 108, 114, 125, 135) 3 STAGE COM (30GXN,R118, 128, 138, 150, 160)
	ENTER	CM.A1	XXX AMPS	COMPR. A1 MUST TRIP AMPS	Verify with Appendix A
	ENTER	CM.A2	XXX AMPS	COMPR. A2 MUST TRIP AMPS	Verify with Appendix A
	ENTER	CM.B1	XXX AMPS	COMPR. B1 MUST TRIP AMPS	Verify with Appendix A
	ENTER	CM.B2	XXX AMPS	COMPR. B2 MUST TRIP AMPS	Verify with Appendix A

Table 12 — Configuration Mode and Sub-Mode Directory (cont)

SUB- MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
OPT1 ENTER		FLUD	X	COOLER FLUID	Default: Water Water Medium Temperature Brine
*		MLVS	YES/NO	MIN LOAD VALVE SELCT	Low Temperature Brine (30HX only) Minimum Load Valve
gr.		НРСТ	х	HEAD PRESS CONTROL TYPE	No Control Air Cooled (30GXN,R, 30HXA default) Water Cooled (30HXC default) Common Cond (30HXA Common Condenser Ind Cond (30HXA Independent Condenser)
98		VHPT	×	VAR HEAD PRESSURE SELECT	None (30HX, 30GX No Motormaster) 4-20 mA (2-10 vdc)(30GX with Motormaster) 0-20 mA (0-10 vdc) 20-0 mA (10-0 vdc)
		PRTS	YES/NO	PRESSURE TRANSDUCERS	Default: Yes
		CPC	ON/OFF	COOLER PUMP CONTROL	Default: Off
		CNP.I	ON/OFF	CONDENSER PUMP INTERLOCK	Default: Off (Does not require condenser pump control)
	▼	CNPC	Х	CONDENSER PUMP CONTROL	Default: No Control No Control On when occupied On with compressor(s)
		CWT.S	YES/NO	CONDENSER FLUID SENSORS	Default: No
		ЕММ	YES/NO	EMM MODULE INSTALLED	
OPT2	ENTER	CTRL	X	CONTROL METHOD	Default: Switch Switch = Enable/Off/Remote Contact 7 Day Occ = 7 Day Schedule Occupancy = CCN Occupancy CCN = CCN Control
		CCNA	XXX	CCN ADDRESS	Default: 1 Range: 1 to 239
		CCNB	XXX	CCN BUS NUMBER	Default: 0 Range: 0 to 239
		BAUD	х	CCN BAUD RATE	Default: 9600 2400 4800 9600 19,200 38,400
	$\blacksquare$	LOAD	X	LOADING SEQUENCE SELECT	Default: Equal Equal Staged
	<b>V</b>	LLCS	X	LEAD/LAG SEQUENCE SELECT	Default: Automatic Automatic Circuit A Leads Circuit B Leads
		CP.SQ	х	COMPRESSOR SEQUENCE	Default: Automatic Automatic Compressor 1 Leads Compressor 2 Leads
		LCWT	XX.X ΔF	HIGH LCW ALERT LIMIT	Default: 60 Range: 2 to 60 F
		DELY	xx	MINUTES OFF TIME	Default: 0 Minutes Range: 0 to 15 Minutes
		CLS.C	ENBL/DSBL	CLOSE CONTROL SELECT	Default: Disable
		ICE.M	ENBL/DSBL	ICE MODE ENABLE	Default: Disable
		C.UNB	XX %	CURRENT UNBALANCE SETPOINT	Default: 15% Range: 10 to 25%
		NO.FL	ENBL/DSBL	ENABLE NO FLOW DETECTION	Default: Enable
		W.MSG	ENBL/DSBL	WINTERIZE ALERT CONFIG	Default: Enable
		ALR.C	X	ALARM RELAY USAGE	Default: Alerts + Alarms Alerts + Alarms Alarms Only Off

Table 12 — Configuration Mode and Sub-Mode Directory (cont)

SUB- MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
RSET	ENTER	CRST	X	COOLING RESET TYPE	Default: No Reset No Reset 4 to 20 mA Input Outdoor Air Temperature Return Fluid Space Temperature
		CRT1	XXX.X °F	NO COOL RESET TEMP	Default: 125 F Range: 0° to 125 F For return fluid reset use cooler ΔΤ
		CRT2	XXX.X °F	FULL COOL RESET TEMP	Default: 0° F Range: 0° to 125 F For return fluid reset use cooler ΔΤ
		DGRC	XX.X ΔF	DEGREES COOL RESET	Default: 0° F Range: -30 to 30 F
		HRST	X	HEATING RESET TYPE	Default: No Reset No Reset 4 to 20 mA Input Outdoor Air Temperature Return Fluid Space Temperature
		HRT1	XXX.X °F	NO HEAT RESET TEMP	Default: 0° F Range: 0° to 125 F
¥	. 🔻	HRT2	XXX.X °F	FULL HEAT RESET TEMP	Default: 125 F Range: 0° to 125 F
		DGRH	XX.X ΔF	DEGREES HEAT RESET	Default: 0° F Range: -30 to 30 F
		DMDC	х	DEMAND LIMIT SELECT	Default: None None Switch 4 to 20 mA Input CCN Loadshed
		DM20	XXX %	DEMAND LIMIT AT 20 mA	Default: 100% Range: 0 to 100%
		SHNM	XXX	LOADSHED GROUP NUMBER	Default: 0 Range: 0 to 99
		SHDL	XXX %	LOADSHED DEMAND DELTA	Default: 0% Range: 0 to 60%
	$\blacksquare$	SHTM	XXX	MAXIMUM LOADSHED TIME	Default: 60 Minutes Range: 0 to 120 Minutes
		DLS1	XXX %	DEMAND LIMIT SWITCH 1	Default: 80% Range: 0 to 100%
		DLS2	XXX %	DEMAND LIMIT SWITCH 2	Default: 50% Range: 0 to 100%
-	$\blacksquare$	LLEN	ENBL/DSBL	LEAD/LAG CHILLER ENABLE	Default: Disable
-		MSSL	SLVE/MAST	MASTER/SLAVE SELECT	Default: Master
1		SLVA	XXX	SLAVE ADDRESS	Default: 0 Range: 0 to 239
		LLBL	X	LEAD/LAG BALANCE SELECT	Default: Master Leads Master Leads Slave Leads Automatic
		LLBD	XXX	LEAD/LAG BALANCE DELTA	Default: 168 hours Range: 40 to 400 hours
		LLDY	XXX	LAG START DELAY	Default: 5 minutes Range: 0 to 30 minutes
		PARA	YES/NO	PARALLEL CONFIGURATION	Default: No (Series Flow)

Table 12 — Configuration Mode and Sub-Mode Directory (cont)

SUB MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
SLCT	ЕНТЕЯ	CLSP	х	COOLING SETPOINT SELECT	Default: Single Single Dual Switch Dual 7 day Dual CCN Occupied 4 to 20 mA Input (requires EMM)
e e	7	HTSP	X	HEATING SETPOINT SELECT	Default: Single Single Dual Switch Dual 7 day Dual CCN Occupied 4 to 20 mA Input (requires EMM)
		RL.S	ENBL/DSBL	RAMP LOAD SELECT	Default: Enable
		CRMP	X.X	COOLING RAMP LOADING	Default: 1.0 Range: 0.2 to 2.0
		HRMP	X.X	HEATING RAMP LOADING	Default: 1.0 Range: 0.2 to 2.0
		HCSW	COOL/HEAT	HEAT COOL SELECT	Default: Cool
		Z.GN	X.X	DEADBAND MULTIPLIER	Default: 2.0 Range: 1.0 to 4.0
4		BRN.L	YES/NO	HXC BRINE CONFIG LOCK	Default: No Yes, if brine FIOP is installed (liquid line solenoid valves).
SERV	ENTER '	H.PGN	XX.X	HEAD PRESSURE P GAIN	Default: 1.0 Range: -20 to 20
		H.IGN	XX.X	HEAD PRESSURE I GAIN	Default: 0.1 Range: -20 to 20
		H.DGN	XX.X	HEAD PRESSURE D GAIN	Default: 0.0 Range: -20 to 20
_		H.MIN	XXX.X	WATER VALVE MINIMUM POS.	Default: 20% Range: 0 to 100%
	7 W	MT.SP	XXX.X °F	MOTOR TEMP SETPOINT	Default: 200 F (170 F for Brine)
		BR.FZ	XXX.X °F	BRINE FREEZE POINT	Default: 34 F Range: -20 to 34 F
		MC.SP	XXX.X °F	MAX. COND. TEMP SETPOINT	Default: 152 F (GXN,R) 145 F (HXA) 118 F (HXC) Range: 100 F To Default
1		EX.S.A	XX.X %	EXVA START POSITION	Default: 20 % Range: 0 T0 40 %
		EX.S.B	XX.X %	EXVB START POSITION	Default: 20 % Range: 0 To 40 %
L		EN.A1	ENBL/DSBL	ENABLE COMPRESSOR A1	Default: Enable (All)
		EN.A2	ENBL/DSBL	ENABLE COMPRESSOR A2	Disable (HX076-186, GXN,R080-178) Enable (HX206-271, GXN,R204-350)
200		EN.B1	ENBL/DSBL	ENABLE COMPRESSOR B1	Default: Enable (All)
		EN.B2	ENBL/DSBL	ENABLE COMPRESSOR B2	Disable (HX076-271, GXN,R080-268 Enable (GXN,R281-350)
1		W.DNE	YES/NO	WINTERIZATION PERFORMED	
		ECON	YES/NO	ECONOMIZED	No (30HX076-146, 30GXN,R080-106,114) Yes (30HX161-271,30GXN,R108,118-350)
_		EVPS	X	NUMBER OF EVAP. PASSES	Range: 1 To 4
L		LWTC	A/B	CIRCUIT WITH LWT SENSOR	According to number of cooler passes.
		AP.SP	XXX.X °F	APPROACH SETPOINT	Default: 3.0 F Range: 0.1 to 20.0 F
всет	ENTER	TD.B.C	ON/OFF	CCN TIME/DATE BROADCAST	Default: Off
		OAT.B	ON/OFF	CCN OAT BROADCAST	Default: Off
		GS.BC	ON/OFF	GLOBAL SCHEDULE BROADCAST	Default: Off
		BC.AK	ON/OFF	BROADCAST ACKNOWLEDGER	Default: Off

Table 13 — Service Test Mode and Sub-Mode Directory

SUB- MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
TEST	ENTER		ON/OFF	SERVICE TEST MODE	To Enable Service Test Mode, move Enable/Off/ Remote Contact switch to OFF. Change TEST to ON. Move switch to ENABLE.
OUTS	ENTER	EXV.A	XXX %	EXV % OPEN	
		VH.PA	XXX %	VAR HEAD PRESS %	
		OL.P.A	ON/OFF	OIL PUMP	
		MC.A1	ON/OFF	MOTOR COOLING SOLENOID A1	
		MC.A2	ON/OFF	MOTOR COOLING SOLENOID A2	
		OS.A1	ON/OFF	OIL SOLENOID A1	
		OS.A2	ON/OFF	OIL SOLENOID A2	5.
		EXV.B	XXX %	EXV % OPEN	
		VH.PB	XXX %	VAR HEAD PRESS %	
		OL.P.B	ON/OFF	OIL PUMP	
		MC.B1	ON/OFF	MOTOR COOLING SOLENOID B1	
		MC.B2	ON/OFF	MOTOR COOLING SOLENOID B2	2
		OS.B1	ON/OFF	OIL SOLENOID B1	
		OS.B2	ON/OFF	OIL SOLENOID B2	
		FAN1	ON/OFF	FAN 1 RELAY	Fans 1, 2 (080-150,160) Fans 2, 4 (208, 228, 253, 268) Fans 5, 6 (249, 264) Fans 9, 10 (153, 163-178, 204,225,281-350) Fans 15, 16 (253, 268)
		FAN2	ON/OFF	FAN 2 RELAY	Fans 3, 4 (080-178, 204, 225, 249, 264, 281-350) Fan 3 (208, 228, 253, 268)
		FAN3	ON/OFF	FAN 3 RELAY	Fans 5, 6 (083, 093-160, 174, 204, 225) Fans 6, 8 (253, 268) Fans 7, 8 (118, 128, 138, 150, 160) Fans 9, 10 (249, 264) Fans 11, 12 (163, 178, 208, 228-268) Fans 13, 14 (208, 228, 253, 268-350) Fans 15, 16 (281-350)
		FAN4	ON/OFF	FAN 4 RELAY	Fans 5, 7 (208, 228, 253, 268) Fans 5, 6, 7, 8 (281-350) Fans 11, 12 (163, 178)
		CLR.P	ON/OFF	COOLER PUMP RELAY	
		CLR.H	ON/OFF	COOLER HEATER	
		CND.P	ON/OFF	CONDENSER PUMP RELAY	
		RMT.A	ON/OFF	REMOTE ALARM RELAY	
COMP	ENTER	CC.A1	ON/OFF	COMPRESSOR A1 RELAY	3
		CC.A2	ON/OFF	COMPRESSOR A2 RELAY	
		LD.A1	ON/OFF	LOADER A1 RELAY	
		LD.A2	ON/OFF	LOADER A2 RELAY	
		MLV	ON/OFF	MINIMUM LOAD VALVE	Energizes circuit A and B solenoids
		OL.H.A	ON/OFF	OIL HEATER	
i.e.		CC.B1	ON/OFF	COMPRESSOR B1 RELAY	
		CC.B2	ON/OFF	COMPRESSOR B2 RELAY	
	. 🔻	LD.B1	ON/OFF	LOADER B1 RELAY	
		LD.B2	ON/OFF	LOADER B2 RELAY	
		OL.H.B	ON/OFF	OIL HEATER	

Table 14 — Temperature Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
UNIT	ENTER	CEWT	XXX.X °F	COOLER ENTERING FLUID	
		CLWT	XXX.X °F	COOLER LEAVING FLUID	
	$\blacksquare$	OAT	XXX.X °F	OUTSIDE AIR TEMPERATURE	
	$\blacksquare$	SPT	XXX.X °F	SPACE TEMPERATURE	
		CNDE	XXX.X °F	CONDENSER ENTERING FLUID	
		CNDL	XXX.X °F	CONDENSER LEAVING FLUID	
		DLWT	XXX.X °F	LEAD/LAG LEAVING FLUID	
CIR.A	ENTER	SCT.A	XXX.X °F	SATURATED CONDENSING TMP	
		SST.A	XXX.X °F	SATURATED SUCTION TEMP	
		SH.A	XXX.X ^F	DISCHARGE SUPERHEAT TEMP	
***		DGT.A	XXX.X °F	DISCHARGE GAS TEMP	Average of A1/A2 values for GXN,R204-350 and HX206-271
		DGA.1	XXX.X °F	DISCHARGE GAS TEMP - A1	
		DGA.2	XXX.X °F	DISCHARGE GAS TEMP - A2	GXN,R204-350 and HX206-271 only
		MT.A1	XXX.X °F	A1 MOTOR TEMPERATURE	
		MT.A2	XXX.X °F	A2 MOTOR TEMPERATURE	GXN,R204-350 and HX206-271 only
CIR.B	ENTER	SCT.B	XXX.X °F	SATURATED CONDENSING TMP	
		SST.B	XXX.X °F	SATURATED SUCTION TEMP	
		SH.B	XXX.X ^F	DISCHARGE SUPERHEAT TEMP	8
		DGT.B	XXX.X °F	DISCHARGE GAS TEMP	Average of B1/B2 values for GXN,R281-350
		DGB.1	XXX.X °F	DISCHARGE GAS TEMP - B1	0
		DGB.2	XXX.X °F	DISCHARGE GAS TEMP - B2	GXN,R281-350 only
		MT.B1	XXX.X °F	B1 MOTOR TEMPERATURE	
		MT.B2	XXX.X °F	B2 MOTOR TEMPERATURE	GXN,R281-350 only

Table 15 — Pressure Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
PRC.A	ENTER	DP.A	XXX.X PSIG	DISCHARGE PRESSURE	18
		SP.A	XXX.X PSIG	SUCTION PRESSURE	У
		ECN.A	XXX.X PSIG	ECONOMIZER PRESSURE	
2		OP.A1	XXX.X PSIG	A1 OIL PRESSURE	
		OP.A2	XXX.X PSIG	A2 OIL PRESSURE	
		DO.A1	XXX.X PSI	A1 OIL PRESSURE DIFF.	Equals oil pressure minus Economizer pressure
		DO.A2	XXX.X PSI	A2 OIL PRESSURE DIFF.	Equals oil pressure minus Economizer pressure
		FD.A1	XXX.X PSI	A1 OIL FILTER DIFF. PRESS	Equals discharge pressure minus oil pressure
		FD.A2	XXX.X PSI	A2 OIL FILTER DIFF. PRESS	Equals discharge pressure minus oil pressure
		PS.A1	XX.X PSI	CALCULATED OIL PRESS A1	CKT A oil pressure setpoint (See notes for Table 32)
		PS.A2	XX.X PSI	CALCULATED OIL PRESS A2	CKT A oil pressure setpoint (See notes for Table 32)
PRC.B	ENTER	DP.B	XXX.X PSIG	DISCHARGE PRESSURE	
		SP.B	XXX.X PSIG	SUCTION PRESSURE	9 2
		ECN.B	XXX.X PSIG	ECONOMIZER PRESSURE	3.3
		OP.B1	XXX.X PSIG	B1 OIL PRESSURE	
		OP.B2	XXX.X PSIG	B2 OIL PRESSURE	
		DO.B1	XXX.X PSI	B1 OIL PRESSURE DIFF.	Equals oil pressure minus Economizer pressure
		DO.B2	XXX.X PSI	B2 OIL PRESSURE DIFF.	Equals oil pressure minus Economizer pressure
	$\blacksquare$	FD.B1	XXX.X PSI	B1 OIL FILTER DIFF.	Equals discharge pressure minus oil pressure
<i>2</i>		FD.B2	XXX.X PSI	B2 OIL FILTER DIFF.	Equals discharge pressure minus oil pressure
	■.	PS.B1	XX.X PSI	CALCULATED OIL PRESS B1	CKT B oil pressure setpoint 1 (See notes for Table 32)
		PS.B2	XX.X PSI	CALCULATED OIL PRESS B2	CKT B oil pressure setpoint 2 (See notes for Table 32)

Table 16 — Set Point Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
COOL	ENTER	CSP.1	XXX.X °F	COOLING SETPOINT 1	Default: 44 F
		CSP.2	XXX.X °F	COOLING SETPOINT 2	Default: 44 F
		CSP.3	XXX.X °F	ICE SETPOINT	Default: 32 F
HEAT	ENTER	HSP.1	XXX.X °F	HEATING SETPOINT 1	Default: 100 F
		HSP.2	XXX.X °F	HEATING SETPOINT 2	Default: 100 F
HEAD	ENTER	HD.P.A	XXX.X °F	HEAD PRESSURE SETPOINT A	Default: 113 F (30GX,HXA) 85 F (30HXC)
3	$\blacksquare$	HD.P.B	XXX.X °F	HEAD PRESSURE SETPOINT B	Default: 113 F (30GX,HXA) 85 F (30HXC)

Table 17 — Inputs Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
GEN.I	ENTER	STST	STRT/STOP	START/STOP SWITCH	
		FLOW	ON/OFF	COOLER FLOW SWITCH	
		CND.F	ON/OFF	CONDENSER FLOW SWITCH	
	~	DLS1	ON/OFF	DEMAND LIMIT SWITCH 1	
		DLS2	ON/OFF	DEMAND LIMIT SWITCH 2	
		ICED	ON/OFF	ICE DONE	
		DUAL	ON/OFF	DUAL SETPOINT SWITCH	7 11
CRCT	EMTER	FKA1	ON/OFF	COMPRESSOR A1 FEEDBACK	
		FKA2	ON/OFF	COMPRESSOR A2 FEEDBACK	944
		OIL.A	OPEN/CLSE	OIL LEVEL SWITCH	
		A1.CR	XXX AMPS	COMP A1 RUNNING CURRENT	
		A2.CR	XXX AMPS	COMP A2 RUNNING CURRENT	
		FKB1	ON/OFF	COMPRESSOR B1 FEEDBACK	
		FKB2	ON/OFF	COMPRESSOR B2 FEEDBACK	
		OIL.B	OPEN/CLSE	OIL LEVEL SWITCH	1.
		B1.CR	XXX AMPS	COMP B1 RUNNING CURRENT	
		B2.CR	XXX AMPS	COMP B2 RUNNING CURRENT	
4-20	ENTER	DMND	XX.X MA	4-20 MA DEMAND SIGNAL	
		RSET	XX.X MA	4-20 MA RESET SIGNAL	
		CSP	XX.X MA	4-20 MA COOLING SETPOINT	
		HSP	XX.X MA	4-20 MA HEATING SETPOINT	

Table 18 — Outputs Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
GEN.O	ENTER	FAN1	ON/OFF	FAN 1 RELAY	
		FAN2	ON/OFF	FAN 2 RELAY	
		FAN3	ON/OFF	FAN 3 RELAY	
		FAN4	ON/OFF	FAN 4 RELAY	
12.0		MLV	ON/OFF	MINIMUM LOAD VALVE	
		C.PMP	ON/OFF	COOLER PUMP RELAY	21
ĺ		C.HT	ON/OFF	COOLER HEATER	
l		CNDP	ON/OFF	CONDENSER PUMP RELAY	
		SMZ	X.X	LOAD/UNLOAD FACTOR	" ,
CIR.A	ENTER	CC.A1	ON/OFF	COMPRESSOR AT RELAY	
		CC.A2	ON/OFF	COMPRESSOR A2 RELAY	
		LD.A1	ON/OFF	LOADER A1 RELAY	
*		LD.A2	ON/OFF	LOADER A2 RELAY	
		OL.P.A	ON/OFF	OIL PUMP	
		MC.A1	ON/OFF	MOTOR COOLING A1 SOLENOID	
		MC.A2	ON/OFF	MOTOR COOLING A2 SOLENOID	10
		OL.H.A	ON/OFF	OIL HEATER	
Ī		OL.A1	ON/OFF	OIL SOLENOID A1	
		OL.A2	ON/OFF	OIL SOLENOID A2	
Ī		EXV.A	XXX %	EXV % OPEN	
		VH.PA	XXX %	VARIABLE HEAD PRESS %	
CIR.B	ENTER	CC.B1	ON/OFF	COMPRESSOR B1 RELAY	
		CC.B2	ON/OFF	COMPRESSOR B2 RELAY	
		LD.B1	ON/OFF	LOADER B1 RELAY	
		LD.B2	ON/OFF	LOADER B2 RELAY	0.
84 1		OL.P.B	ON/OFF	OIL PUMP	3
		MC.B1	ON/OFF	MOTOR COOLING B1 SOLENOID	
		MC.B2	ON/OFF	MOTOR COOLING B2 SOLENOID	
		OL.H.B	ON/OFF	OIL HEATER	181
		OL.B1	ON/OFF	OIL SOLENOID B1	
		OL.B2	ON/OFF	OIL SOLENOID B2	
		EXV.B	XXX %	EXV % OPEN	đi
		VH.PB	XXX %	VARIABLE HEAD PRESS %	******

Table 19 — Operating Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
MODE	ENTER	MD01	ON/OFF	CSM CONTROLLING CHILLER	9
		MD02	ON/OFF	WSM CONTROLLING CHILLER	
		MD03	ON/OFF	MASTER/SLAVE CONTROL	
		MD04	ON/OFF	LOW SOURCE PROTECTION	
		MD05	ON/OFF	. RAMP LOAD LIMITED	
		MD06	ON/OFF	TIMED OVERRIDE IN EFFECT	
ą.		MD07	ON/OFF	LOW COOLER SUCTION TEMPA	
R.		MD08	ON/OFF	LOW COOLER SUCTION TEMPB	1
		MD09	ON/OFF	SLOW CHANGE OVERRIDE	
	$\blacksquare$	MD10	ON/OFF	MINIMUM OFF TIME ACTIVE	
	$\blacksquare$	MD11	ON/OFF	LOW DISCHRGE SUPERHEAT A	
		MD12	ON/OFF	LOW DISCHRGE SUPERHEAT B	
		MD13	ON/OFF	DUAL SETPOINT	
		MD14	ON/OFF	TEMPERATURE RESET	
10		MD15	ON/OFF	DEMAND LIMIT IN EFFECT	
- 1	$\blacksquare$	MD16	ON/OFF	COOLER FREEZE PROTECTION	
		MD17	ON/OFF	LOW TMP COOL/HI TMP HEAT	
		MD18	ON/OFF	HI TMP COOL/LO TMP HEAT	
	$\blacksquare$	MD19	ON/OFF	MAKING ICE	
_		MD20	ON/OFF	STORING ICE	
L		MD21	ON/OFF	HIGH SCT CIRCUIT A	
		MD22	ON/OFF	HIGH SCT CIRCUIT B	
		MD23	ON/OFF	HIGH MOTOR CURRENT CIR. A	
_		MD24	ON/OFF	HIGH MOTOR CURRENT CIR. B	
		MD25	ON/OFF	CKT A OFF REF FLOW DELAY*	0
		MD26	ON/OFF	CKT B OFF REF FLOW DELAY*	
L		MD27	ON/OFF	CIRCUIT A — PUMPING OUT	SHUTDOWN IN PROGRESS
	<b>V</b>	MD28	ON/OFF	CIRCUIT B — PUMPOUT OUT	SHUTDOWN IN PROGRESS
3.		MD29	ON/OFF	UNIT OFF: NO WATER FLOW	

necycle restart pending 15-minute delay due to loss of refrigerant flow detected at start-up.

Table 20 — Run Status Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
. VIEW	ENTER	EWT	XXX.X °F	ENTERING FLUID TEMP	
		LWT	XXX.X °F	LEAVING FLUID TEMP	
		SETP	XXX.X °F	ACTIVE SETPOINT	
		СТРТ	XXX.X °F	CONTROL POINT	
	7	STAT	x	CONTROL MODE	SERVICE TEST OFF LOCAL OFF CCN OFF TIME OFF EMRGCY ON LOCAL ON CCN ON TIME
		occ	YES/NO	OCCUPIED	
		MIN.L	XX MIN	MINUTES LEFT FOR START	
	$\blacksquare$	MODE	YES/NO	OVERRIDE MODES IN EFFECT	
		CAP	XXX %	PERCENT TOTAL CAPACITY	
		DEM.L	XXX %	ACTIVE DEMAND LIMIT	
		ALRM	xxx	CURRENT ALARMS & ALERTS	
		TIME	XX.XX	TIME OF DAY	00.00-23.59
		MNTH	XX	MONTH OF YEAR	January, February, etc.
		DATE	xx	DAY OF MONTH	01-31
		YEAR	XX	YEAR	
RUN	ENTER	HRS.U	XXXX HRS	MACHINE OPERATING HOURS	
	. <b>\</b>	STR.U	xxxx	MACHINE STARTS	
HOUR	ENTER	HRS.A	XXXX HRS	CIRCUIT A RUN HOURS	
		HRS.B	XXXX HRS	CIRCUIT B RUN HOURS	
		HR.A1	XXXX HRS	COMPRESSOR A1 RUN HOURS	
		HR.A2	XXXX HRS	COMPRESSOR A2 RUN HOURS	
		HR.B1	XXXX HRS	COMPRESSOR B1 RUN HOURS	
	<b>\rightarrow</b>	HR.B2	XXXX HRS	COMPRESSOR B2 RUN HOURS	
STRT	ENTER	STR.A	xxxx	CIRCUIT A STARTS	
		ST.A1	xxxx	COMPRESSOR A1 STARTS	
		ST.A2	xxxx	COMPRESSOR A2 STARTS	
		STR.B	XXXX	CIRCUIT B STARTS	,
		ST.B1	xxxx	COMPRESSOR B1 STARTS	
		ST.B2	xxxx	COMPRESSOR B2 STARTS	

Table 20 — Run Status Mode and Sub-Mode Directory (cont)

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
VERS	ENTER	MBB		CESR-131344-xx-xx	xx-xx is Version number
		EXV		CESR-131172-xx-xx	xx-xx is Version number
		ЕММ		CESR-131174-xx-xx	xx-xx is Version number
		CP1		100233-1R1-xx-xx	xx-xx is Version number
2.0		CP2		100233-1R1-xx-xx	xx-xx is Version number
		SCB		CESR-131226-xx-xx	xx-xx is Version number
		NAVI		CESR-131227-xx-xx	xx-xx is Version number

# Table 21 — How to Adjust Navigator Backlight from Configuration Mode

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
DISP	ENTER	TEST	ON/OFF	TEST DISPLAY LEDS	
	ENTER		Enter Password 1111		Enter password as required using ENTER key after each number.
Į.		TEST	OFF		'OFF' will be flashing.
		TEST	ON		Change value to 'ON' ('ON' flashes).
	ЕМТЕЯ	TEST	ON	H	Display Test is Enabled. The alarm and all mode LED's light up. The Navigator will display all block segments.
# (I)				0.	Press arrow keys at the same time. The Navigator will display 'Adjust Brightness.'
-				-	Use the up arrow key to brighten the back- light and the down arrow key to dim the backlight. Press the ESCAPE key when fin- ished to exit the mode.

Table 22 — How to Adjust Navigator Contrast from Configuration Mode

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
DISP	ENTER	TEST	ON/OFF	TEST DISPLAY LEDS	
	ENTER		Enter Password 1111		Enter password as required using ENTER key after each number.
1		TEST	OFF		'OFF' will be flashing
		TEST	ON		Change value to 'ON' ('ON' flashes).
,	ENTER	TEST	ОИ		Display Test is Enabled. The alarm and all mode LED's light up. The Navigator will display all block segments.
	ENTER ESCAPE				Press Enter and Escape keys at the same time. The Navigator will display 'ADJUST CONTRAST' with a percentage indication.
		G.			Use the up arrow key to increase contrast and the down arrow key to decrease the contrast. Press the ESCAPE key when finished to exit the mode.

Table 23 — Time Clock Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
TIME	ENTER	нн.мм	xx.xx	HOUR AND MINUTE	Military (00:00 — 23:59)
DATE		MNTH	xx	MONTH OF YEAR	January, February, etc.
		DOM	xx	DAY OF MONTH	Range: 01-31
		DAY	х	DAY OF WEEK	Monday, Tuesday, etc.
		YEAR	xxxx	YEAR	
DST	ENTER	STR.M	XX	MONTH	Default: 4 Range: 1-12
		. STR.W	×	WEEK	Default: 1 Range: 1-5
		STR.D	х	DAY	Default: 7 Range: 1-7
		MIN.A	×x	MINUTES TO ADD	Default: 60 Range: 0-99
		STP.M	xx	MONTH	Default: 10 Range: 1-12
	2 🐷	STP.W	xx	WEEK	Default: 5 Range: 1-5
		STR.D	xx	DAY	Default: 7 Range: 1-7
Nav		MIN.5	xx	MINUTES TO SUBTRACT	Default: 60 Range: 0-99
SCHD	ENTER	MON.O	XX.XX	MONDAY OCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
	•	MON.U	XX.XX	MONDAY UNOCCUIPED TIME	Default: 00.00 Range: 00.00 to 23.59
		TUE.O	xx.xx	TUESDAY OCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
		TUE.U	XX.XX	TUESDAY UNOCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
*		WED.O	XX.XX	WEDNESDAY OCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
2.50		WED.U	XX.XX	WEDNESDAY UNOCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
		THU.O	xx.xx	THURSDAY OCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
	$\blacksquare$	THU.U	xx.xx	THURSDAY UNOCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
		FRI.O	xx.xx	FRIDAY OCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
		FRI.U	xx.xx	FRIDAY UNOCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
		SAT.O	xx.xx	SATURDAY OCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
Ī		SAT.U	xx.xx	SATURDAY UNOCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
		SUN.O	xx.xx	SUNDAY OCCUPIED TIME	Default: 00.00 Range: 00.00 to 23.59
		SUN.U	XX.XX	SUNDAY UNOCCUPIED TIME	Default: 00.00 to 23.59  Range: 00.00 to 23.59

Table 24A — Example of Configuring Dual Chiller Control (Master Chiller)

SUB-MODE	ITEM	KEYPAD ENTRY	DISPLAY	ITEM EXPANSION	COMMENT
OPT2	OPT2	ENTER			
	CTRL	ENTER .	SWITCH		VALUE FLASHES
	CTRL	ENTER	SWITCH	CONTROL METHOD	SEE NOTE 1
				q	•
	CCNA	ENTER	1.	W	DEFAULT 1
	CCNA	ENTER	.1	CCN ADDRESS	CHANGE IF REQUIRED
		$\blacksquare$			
	CCNB	ENTER	0		DEFAULT 0
	CCNB	ENTER	0	CCN BUS NUMBER	CHANGE IF REQUIRED
	CCNB	ESCAPE	OPT2	18	- 500 Mar 1990 Mar 19
		$\blacksquare$	RESET		PROCEDE TO SUBMODE RSET
RSET	RSET	ЕНТЕР			The same of the sa
	CRST	3	NO RESET	COOLING RESET TYPE	
					15 ITEMS
	LLEN	ENTER	DSBL	LEAD/LAG CHILLER ENABLE	SCROLLING STOPS
		ENTER	DSBL	d	VALUE FLASHES
			ENBL		SELECT ENBL
	LLEN	ЕМТЕЯ	ENBL	LEAD/LAG CHILLER ENABLE	CHANGE ACCEPTED
			MSSL		CISTICE / ICC
	MSSL	БИТЕЯ	MAST	MASTER/SLAVE SELECT	DEFAULT MAST
			SLVA	SLAVE ADDRESS	DELINOEI WHO!
	SLVA	ENTER	0		VALUE FLASHES
	10		2		SELECT 2
	SLVA	ENTER	2	SLAVE ADDRESS	CHANGE ACCEPTED
		<b>V</b>			OTBITCH FLO
	LLBL	ENTER	MASTER LEADS	LEAD/LAG BALANCE SELECT	VALUE FLASHES
			AUTOMATIC	IS/IS (II B) IS (II OE OEEEO)	SELECT AUTOMATIC
	LLBL	ENTER	AUTOMATIC	LEAD/LAG BALANCE SELECT	CHANGE ACCEPTED
		▼		ED IDIENG DADNIOE SEEEO	CHANGE ACCEPTED
	LLBD	ENTER	100		DEFAULT 168
	LLOD		168	LEAD/LAG BALANCE DELTA	DEFAULT 108
		ENTER			
	LLDY	ЕНТЕН	5	LAG START DELAY	(P
1		БИТЕЯ	. 5		VALUE FLASHES
			10		SELECT 10
	ITDA	ENTER	10	LAG START DELAY	CHANGE ACCEPTED
•	PARA	ENTER	NO	PARALLEL CONFIGURATION	DEFAULT NO
			YES		SELECT YES
	PARA	ENTER	YES	PARALLEL CONFIGURATION	SEE NOTE 2
		ESCAPE	RSET		MASTER COMPLETE

NOTES:

1. The desired control method should be configured for the Master only. The slave is always configured for switch control.

2. Yes = Parallel piping configuration. No = Series piping configuration. Master and Slave chillers must both be configured for the same piping configuration.

Table 24B — Example of Configuring Dual Chiller Control (Slave Chiller)

SUB-MODE	ITEM	KEYPAD ENTRY	DISPLAY	ITEM EXPANSION	COMMENT
OPT2	OPT2	ENTER			
	CTRL	ENTER	SWITCH	CONTROL METHOD	SEE NOTE 1
		ESCAPE	SWITCH	A	
		ESCAPE	CTRL		
	CTRL		CCNA		
	CCNA	ENTER	1	CCN ADDRESS	SCROLLING STOPS
		ENTER	1		VALUE FLASHES
			2		SELECT 2 (SEE NOTE 2)
	CCNA	ENTER	2	CCN ADDRESS	CHANGE ACCEPTED
		ESCAPE	CCNA		*
		▼	CCNB		
	CCNB	ENTER	0	CCN BUS NUMBER	DEFAULT 0 (SEE NOTE 3)
		ESCAPE	CCNB		
		ESCAPE	OPT2		
1			RSET		PROCEED TO SUBMODE RSET
RSET	RSET	ENTER	CRST	COOLING RESET TYPE	
		<b>V</b>	LLEN	LEAD/LAG CHILLER ENABLE	15 ITEMS
	LLEN	ENTEA	DSBL		SCROLLING STOPS
		ENTER	DSBL		VALUE FLASHES
	8		ENBL		SELECT ENBL
	·LLEN	EMTER	ENBL	LEAD/LAG CHILLER ENABLE	CHANGE ACCEPTED
ĺ		ESCAPE	LLEN	*	
			MSSL	MASTER/SLAVE SELECT	
	MSSL	ентея	MAST		SCROLLING STOPS
		ENTER	MAST		VALUE FLASHES
			SLVE		SELECT SLAVE
	MSSL	ENTER	SLVE	MASTER/SLAVE SELECT	CHANGE ACCEPTED
		ESCAPE	MSSL		
					5 ITEMS
	PARA	ENTER	NO	PARALLEL CONFIGURATION	
			YES		SELECT YES
	PARA	ENTER	YES	PARALLEL CONFIGURATION	SEE NOTE 5
		ESCAPE	RSET		SLAVE COMPLETE

NOTES:

1. Slave is always configured for switch control.
2. Slave CCN Address must be different than Master.
3. Slave CCN Bus Number must be the same as Master.
4. Slave does not require LLBL, LLBD or LLDY to be configured.
5. Yes = Parallel piping configuration. No = Series piping configuration.

Master and Slave chillers must both be configured for the same piping configuration.

Alarms/Alerts — Alarms and alerts are messages that one or more faults have been detected. The alarms and alerts indicate failures that cause the unit to shut down, terminate an option (such as reset) or result in the use of a default value such as a set point. Refer to the Troubleshooting section for more information.

Up to 25 alarms/alerts can be displayed in currently active alarms. Up to 50 alarms/alerts can be stored in the alarm history. See Tables 25 and 26 to view and clear alarms.

IMPORTANT: Do not clear the alarms without first reviewing the full list and investigating and correcting the cause of the alarms:

When an alarm or alert is stored in the display and the machine automatically resets, the alarm/alert is deleted. Codes for safeties which do not automatically reset are not deleted until the problem is corrected and the machine is reset. To clear manual reset alarms from the CCP modules, press the reset button located on the CCP board generating the alarm, for 5 seconds, (CCP1 for compressors A1 or B1, CCP2 for compressors A2 or B2). Next, follow the example in Table 26 to clear the alarm from the Main Base Board (MBB) history.

Alarm relay usage alerts and alarms are configurable in (CONFIGURATION MODE, SUB-MODE OPT2) to be both one or the other or off paragraph.

Run Hours and Starts — The HOUR and STRT submodes under the Run Status mode contain items for number of hours for each circuit and each compressor and the total number of starts for each compressor. All items are password protected, but can be changed if a replacement MBB is installed.

Press ENTER to make the current value flash. Use the arrow keys to configure the correct value and press the enter key again. Record the current values from the MBB before removing the module or downloading new software.

Temperature Reset — The control system is capable of handling leaving-fluid temperature reset based on return cooler fluid temperature. Because the change in temperature through the cooler is a measure of the building load, the return temperature reset is in effect an average building load reset method. The control system is also capable of temperature reset based on outdoor-air temperature (OAT), space temperature (SPT), or from an externally powered 4 to 20 mA signal. Accessory sensors must be used for OAT and SPT reset (HH79NZ023 for OAT and HH51BX006 for SPT). The Energy Management Module (EMM) must be used for temperature reset using a 4 to 20 mA signal.

To use the return reset, four variables must be configured. In the Configuration mode under the sub-mode RSET, items CRST, CRT1, CRT2, and DGRC must be set properly. See Tables 27 and 28 on page 37 for correct configuration.

To reset the return fluid temperature, the unit set point is reset from full load based on the chilled fluid return temperature. The example uses a reset value of 10 degrees at full reset. Full reset is at a 2-degree temperature difference across the cooler and no reset would be at a 10 F difference across the cooler. See Fig. 14-17 and Table 29.

Under normal operation, the chiller will maintain a constant leaving fluid temperature approximately equal to the chilled fluid set point. As the cooler load varies, the entering cooler fluid will change in proportion to the load as shown in Fig. 14. Usually the chiller size and leaving-fluid temperature set point are selected based on a full-load condition. At part load, the fluid temperature set point may be colder than required. If the leaving fluid temperature was allowed to increase at part load, the efficiency of the machine would increase.

Return temperature reset allows for the leaving temperature set point to be reset upward as a function of the return fluid temperature or, in effect, the building load.

Figure 14 is an example of no reset. Figures 15, 16, and 17 are examples of outdoor air, space and return water temperature resets.

Table 25 — Alarms Mode and Sub-Mode Directory

SUB-MODE	KEYPAD ENTRY	ITEM	ITEM EXPANSION	COMMENT
CRNT	ENTER	AXXX or TXXX	CURRENTLY ACTIVE ALARMS	Alarms are shown as AXXX Alerts are shown as TXXX.
RCRN	ENTER	YES/NO	RESET ALL CURRENT ALARMS	TANA
HIST	ENTER	AXXX or TXXX	ALARM HISTORY	Alarms are shown as AXXX. Alerts are shown as TXXX.

Table 26 — Example of Reading and Clearing Alarms

SUB-MODE	KEYPAD ENTRY	ITEM	ITEM EXPANSION	COMMENT
CRNT	ENTER	AXXX or TXXX	CURRENTLY ACTIVE ALARMS	ACTIVE ALARMS (AXXX) OR ALERTS (TXXX) DISPLAYED.*
CRNT	ESCAPE		2	The training state of the state
		NO		Use to clear active alarms/alerts
RCRN	ENTER	NO		NO Flashes
		YES		Select YES
	ENTER	NO		Alarms/alerts clear, YES changes to NO


<sup>\*</sup>Press ENTER and ESCAPE simultaneously to display expanded alarm description.

Table 27 — Configuring Temperature Reset

MODE	KEYPAD ENTRY	SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
CONFIGURATION	ENTER	DISP	ENTER	TEST	ON/OFF	TEST DISPLAY LEDS	100
		UNIT	ENTER	TYPE	х	UNIT TYPE	
2.		OPT1	ENTER	FLUD	х	COOLER FLUID	
		OPT2	ENTER	CTRL	х	CONTROL METHOD	
		RSET	entea	CRST	Х	COOLING RESET TYPE	0 = No Reset 1 = 4 to 20 mA Input (EMM required (Connect to EMM J6-2,5) 2 = Outdoor-Air Temperature (Connect to TB5-7,8) 3 = Return Fluid 4 = Space Temperature (Connect to TB5-5,6)
				CRT1	XXX.X F	NO COOL RESET TEMP	Default: 125 F (51.7 C) Range: 0° to125 F Set to 4.0 for CRST= 1 No Cool Reset ΔT for CRST=3
				CRT2	XXX.X F	FULL COOL RESET TEMP	Default: 0° F (-17.8 C) Range: 0° to 125 F Set to 20.0 for CRST=1 Full Cool Reset ΔT for CRST=3
	*			DGRC	XX.X ΔF	DEGREES COOL RESET	Default: 0° F (0° C) Range: -30 to 30 F (-16.7 to 16.7 C


Table 28 — Return Water Reset

SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
RSET	ENTER CRST 3	COOLING RESET TYPE	0 = no reset 1 = 4 to 20 mA input 2 = Outdoor air temp 3 = Return Fluid 4 = Space Temperature		
1,500 1,500		CRT1	10.0 F (5.5 C)	NO COOL RESET TEMP	Default: 125 F (51.7 C) Range: 0° to 125 F
		CRT2	2.0 F (1.1 C)	FULL COOL RESET TEMP	Default: 0° F (-17.8 C) Range: 0° to 125 F
		DGRC	5.0 ΔF (2.8 ΔC)	DEGREES COOL RESET	Default: 0°F (0° C) Range: -30 to 30 F (-16.7 to 16.7 C)




EWT — Entering Water (Fluid) Temperature LWT — Leaving Water (Fluid) Temperature

Fig. 14 — Cooling Return Water — No Reset




LWT — Leaving Water (Fluid) Temperature

Fig. 15 — Outdoor-Air Temperature Reset



LWT — Leaving Water (Fluid) Temperature

Fig. 16 — Space Temperature Reset



EWT — Entering Water (Fluid) Temperature
LWT — Leaving Water (Fluid) Temperature

Fig. 17 — Return Water Reset

**Demand Limit** — Demand Limit is a feature that allows the unit capacity to be limited during periods of peak energy usage. See Fig. 18. There are 3 types of demand limiting that can be configured. The first type is through 2-stage switch control, which will reduce the maximum capacity to 2 user-configurable

percentages. The second type is by 4 to 20 mA signal input which will reduce the maximum capacity linearly between 100% at a 4 mA input signal (no reduction) down to the user-configurable level at a 20 mA input signal. The third type uses the CCN Loadshed module and has the ability to limit the current operating capacity to maximum and further reduce the capacity if required.

NOTE: The 2-stage switch control and 4- to 20-mA input signal types of demand limiting require the Energy Management Module (EMM).

To use Demand Limit, select the type of demand limiting to use. Then configure the Demand Limit set points based on the type selected.

DEMAND LIMIT (2-Stage Switch Controlled) — To configure Demand Limit for 2-stage switch control set the Demand Limit Select (DMDC) to 1. Then configure the 2 Demand Limit Switch points (DLS1 and DLS2) to the desired capacity limit. See Table 29. Capacity steps are controlled by 2 relay switch inputs field wired to TB6.

For Demand Limit by 2-stage switch control, closing the first stage demand limit contact will put the unit on the first demand limit level. The unit will not exceed the percentage of capacity entered as Demand Limit Switch 1 set point. Closing contacts on the second demand limit switch prevents the unit from exceeding the capacity entered as Demand Limit Switch 2 set point. The demand limit stage that is set to the lowest demand takes priority if both demand limit inputs are closed. If the demand limit percentage does not match unit staging, the unit will limit capacity to the closest capacity stage.

To disable demand limit configure the DMDC to 0. See Table 29.

EXTERNALLY POWERED DEMAND LIMIT (4 to 20 mA Controlled) — To configure Demand Limit for 4 to 20 mA control set the Demand Limit Select (DMDC) to 2. Then configure the Demand Limit at 20 mA (DM20) to the maximum loadshed value desired. The control will reduce allowable capacity to this level for the 20 mA signal.

DEMAND LIMIT (CCN Loadshed Controlled) — To configure Demand Limit for CCN Loadshed control set the Demand Limit Select (DMDC) to 3. Then configure the Loadshed Group Number (SHNM), Loadshed Demand Delta (SHDL), and Maximum Loadshed Time (SHTM). See Table 29.

The Loadshed Group number is established by the CCN system designer. The *Comfort*Link™ Control will respond to a Redline command from the Loadshed control. When the Redline command is received, the current stage of capacity is set to the maximum stages available. Should the loadshed control send a Loadshed command, the *Comfort*Link Control will





Fig. 18 — 4 to 20 mA Demand Limiting

reduce the current stages by the value entered for Loadshed Demand delta. The Maximum Loadshed Time is the defines the maximum length of time that a loadshed condition is allowed to exist. The control will disable the Redline/Loadshed command if no Cancel command has been received within the configured maximum loadshed time limit.

Cooling Set Point (4 to 20 mA) — Unit operation is based on an external 4 to 20 mA signal input to the Energy Management Module (EMM). The signal is connected to TB6-3,5 (+,-). Figure 19 shows how the 4 to 20 mA signal is linearly calculated on an overall 10 F to 80 F for both Water and Medium Temperature Brine COOLER FLUID configurations. See Table 30 for configuration instructions.



EMM — Energy Management Module

Fig. 19 — Cooling Set Point (4 to 20 mA)

Table 29 — Configuring Demand Limit

MODE	KEYPAD ENTRY	SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
CONFIGURATION	ENTER	DISP	ENTER	TEST	ON/OFF	Test Display LEDs	
		UNIT	ENTER	TYPE	х	Unit Type	
9	$\blacksquare$	OPT1	ENTER	FLUD	х	Cooler Fluid	
		OPT2	ENTER	CTRL	х	Control Method	
		RSET	ENTER	CRST	х	Cooling Reset Type	
				CRT1	XXX.X °F	No Cool Reset Temperature	
				CRT2	XXX.X °F	Full Cool Reset Temperature	
				DGRC	XX.X ΔF	Degrees Cool Reset	
(w)				DMDC	х	Demand Limit Select	Default: 0 0 = None 1 = Switch 2 = 4 to 20 mA Input 3 = CCN Loadshed
				DM20	XXX%	Demand Limit at 20 mA	Default: 100% Range: 0 to 100
				SHNM	xxx	Loadshed Group Number	Default: 0 Range: 0 to 99
				SHDL	XXX%	Loadshed Demand Delta	Default: 0% Range: 0 to 60%
				SHTM	XXX MIN	Maximum Loadshed Time	Default: 60 min. Range: 0 to 120 min.
		Ē		DLS1	XXX %	Demand Limit Switch 1	Default: 80% Range: 0 to 100%
				DLS2	XXX%	Demand Limit Switch-2	Default: 50% Range: 0 to 100%

NOTE: Heating reset values skipped in this example.

Table 30 — Menu Configuration of 4 to 20 mA Cooling Set Point Control

MODE (RED LED)	KEYPAD ENTRY	SUB-MODE	KEYPAD ENTRY	ITEM	DISPLAY	ITEM EXPANSION	COMMENT
CONFIGURATION	ENTER	DISP					
		UNIT					
		OPT1				¥	
		OPT2					
		RSET				(K	
		SLCT	ENTER	CLSP	0	COOLING SETPOINT SELECT	
			ENTER	8	0		Scrolling Stops
8			ENTER		0		Flashing '0'
					4		Select '4'
			ENTER		4		Change Accepted

#### TROUBLESHOOTING

The 30GXN,R and 30HX screw chiller control has many features to aid in troubleshooting. By using the Navigator control, operating conditions of the chiller can be viewed while the chiller is running. The Service Test function allows for testing of all outputs and compressors. Verify that the chiller is properly configured, including options and/or accessories, using the Configuration mode. For checking specific items, refer to the Mode/Sub-Mode directory (Table 11).

Checking Display Codes — To determine how the machine has been programmed to operate, check the diagnostic information displayed in the Status function and the configuration information displayed in the Service function.

**Unit Shutoff** — To shut the unit off, move the Enable/Off/Remote Contact switch to the Off position. Both circuits will complete a pumpdown cycle and all compressors and solenoids will shut off. For extreme cases, move the Emergency On/Off switch to the Off position. All compressors, solenoids and other outputs will stop immediately.

**Complete Unit Stoppage** — Complete unit stoppage can be caused by any of the following conditions:

- · cooling load satisfied
- · remote on/off contacts open
- · programmed schedule
- emergency stop command from CCN
- · general power failure
- blown fuse in control power feed disconnect
- open control circuit fuse(s)
- Enable/Off/Remote Contact switch moved to Off position
- freeze protection trip
- low flow protection trip
- · open contacts in chilled water flow switch
- Open contacts in any auxiliary interlock. Terminals that
  are jumpered from factory are in series with control
  switch. Opening the circuit between these terminals
  places unit in Stop mode, similar to moving the control
  switch to Off position. Unit cannot start if these contacts
  are open. If they open while unit is running, the unit
  stops
- · cooler entering or leaving fluid thermistor failure
- low/high transducer supply voltage
- loss of communications between the Main Base Board (MBB) and either the EXV board, SCB board or either CCP module
- · low refrigerant pressure
- · off-to-on delay is in effect

#### **A** CAUTION

If a stoppage occurs more than once as a result of any of the above safety devices, determine and correct the cause before attempting another restart.

**Single Circuit Stoppage** — Single circuit stoppage can be caused by the following:

- · low oil pressure
- · open contacts in high pressure switch
- · low refrigerant pressure
- · thermistor failure
- · transducer failure
- · alarm condition from CCP module

Stoppage of one circuit by a safety device action does not affect other circuit. When a safety device trips, the circuit is

shut down immediately and EXV closes. Refer to Table 31 for typical stoppage faults and reset types.

#### **A** CAUTION

If a stoppage occurs more than once as a result of any of the preceding safety devices, determine and correct the cause before attempting another restart.

Restart Procedure — After the cause for stoppage has been corrected, restart is either automatic or manual, depending on the fault. Manual reset requires that the alarm(s) be reset via the Navigator. Select the RCRN item under the Alarms mode. Press [AMER], [AMERICAN again to reset all current alarms and alerts. A password entry may be required. Some typical fault conditions are described in Table 31. For a complete list of fault conditions, codes and reset type, see Table 32.

POWER FAILURE EXTERNAL TO THE UNIT — Unit restarts automatically when power is restored.

Alarms and Alerts — These are warnings of abnormal or fault conditions and may cause either one circuit or the whole unit to shut down. They are assigned code numbers and a detailed description of each alarm/alert code error including possible causes is shown in Table 32. The alarm descriptions are displayed on the Navigator under the 'CRNT' or 'HIST' sub-modes of the Alarms mode. The Main Base Board also recognizes and reports illegal configurations as shown in Table 32.

When an alarm or alert is activated configurable, the alarm relay output (MBB relay K7, terminals TB5-11,12) is energized. The alarms and alerts indicate failures that cause the unit to shut down, terminate an option (such as reset) or result in the use of a default value such as a set point. Refer to Table 32 for more information.

Up to 50 alarms/alerts can be stored at once. Use Alarm and Alert tables to view and clear alarms. *Comfort*Link<sup>TM</sup> Compressor Protection (CCP) module alarms require an additional step to reset alarms. To clear these alarms, first find and correct the cause of the alarm. Then press and hold the reset button on the CCP board for 5 seconds. This action will reset only the alarmed circuit or compressor, and clear the CCP. Next, reset the alarm(s) using the Navigator as shown in Table 26. For configuration header fault alarms from the CCP module, move the Enable/Off/Remote Contact switch to the Off position. Wait for all compressors to stop. Turn off the unit control power. Correct the configuration header problem and restore unit control power.

Table 31 — Typical Stoppage Faults and Reset Types

RESET TYPE
Manual reset
Auto reset first time, manual it repeated in same day
Manual reset
Unit restarts automatically when power is restored
Manual reset
Manual reset after 1 hour
Manual reset
Automatic reset

LEGEND

CSM — Chillervisor™ System Manager WSM — Water System Manager Compressor Alarm/Alert Circuit — Each compressor is directly controlled by a CCP module. Compressor faults (T051, T052, T055, T056) are reported as alerts. The specific

fault condition for a compressor alert is included as part of the alert description displayed on the Navigator. Press and simultaneously to display description.

### Table 32 — Alarm and Alert Codes

ALARM/ALERT CODE	ALERT	DESCRIPTION	WHY WAS THIS ALARM GENERATED?	ACTION TAKEN BY	RESET METHOD	PROBABLE CAUSE
T026	Alert	Compressor A1 Low Oil Pressure – 1	See Note 1 and Fig. 20 on page 49.	Comp A1 shut down	Manual	Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
7007		Compressor A1 Low Oil Pressure – 2	Point 2. See Note 1 and Fig. 20 on page 49.	Comp A1 shut down	Manual	Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
T027	Alert	Compressor A2 Low Oil Pressure – 1	Point 1. See Note 1 and Fig. 20 on page 49.	Comp A2 shut down	Manual	Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
s		Compressor A2 Low Oil Pressure – 2	Po-Ps < Oil Set Point 2. See Note 1 and Fig. 20 on page 49.	Comp A2 shut down	Manual	Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
T028	Alert	Compressor B1 Low Oil Pressure – 1	PO-Pe < Oil Set Point 1. See Note 1 and Fig. 20 on page 49.	Comp B1 shut down	Manual	Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
		Compressor B1 Low Oil Pressure – 2	Po-Ps < Oil Set Point 2. See Note 1 and Fig. 20 on page 49.	Comp B1 shut down		Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
Т029	Alert	Compressor B2 Low Oil Pressure – 1	Po-Pe < Oil Set Point 1. See Note 1 and Fig. 20 on page 49.	Comp B2 shut down		Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
		Compressor B2 Low Oil Pressure – 2	Po-Ps < Oil Set Point 2. See Note 1 and Fig. 20 on page 49.	Comp B2 shut down		Low Water Temperature, low refrigerant charge, plugged oil filter, closed oil valve, bad oil solenoid, compressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
A030		Compressor A1 Pre- Start Oil Pressure	Oil Pump did not build suffi- cient pressure during pre-lube cycle.	Compressor cannot start.	f	Low oil, oil pump failure, oil solenoid failure, oil transducer failure, check valve failed open, oil shutoff valve closed.
A031	8	Compressor A2 Pre- Start Oil Pressure	Oil Pump did not build suffi- cient pressure during pre-lube cycle.	Compressor cannot start.	Manual L	Low oil, oil pump failure, oil solenoid failure, oil transducer ailure, check valve failed open, oil shutoff valve closed.
A032		Compressor B1 Pre- Start Oil Pressure	cycle.	Compressor cannot start.	Manual L s	ow oil, oil pump failure, oil solenoid failure, oil transducer ailure, check valve failed open, oil shutoff valve closed.
A033			Oil Pump did not build suffi- cient pressure during pre-lube cycle.	Compressor cannot start.	s fa	ow oil, oil pump failure, oil olenoid failure, oil transducer ailure, check valve failed pen, oil shutoff valve closed.

Table 32 — Alarm and Alert Codes (cont)

ALARM/ALERT CODE	ALARM OR ALERT	DESCRIPTION	WHY WAS THIS ALARM GENERATED?	ACTION TAKEN BY CONTROL	RESET METHOD	PROBABLE CAUSE
A034	Alarm	Comp. A1 Max. Oil Delta P, check oil line	(Discharge press – Oil press) > 100 PSI for more than 5 seconds	Comp. A1 shut down	Manual	Plugged oil filter, closed oil valve, bad oil solenoid, com- pressor oil check valve stuck oil line check valve stuck, plugged oil strainer
A035	Alarm	Comp. A2 Max. Oil Delta P, check oil line	(Discharge press – Oil press) > 100 PSI for more than 5 seconds	Comp. A2 shut down	Manual	Plugged oil filter, closed oil valve, bad oil solenoid, com- pressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
A036	Alarm	Comp. B1 Max. Oil Delta P, check oil line	(Discharge press - Oil press) > 100 PSI for more than 5 seconds	Comp. B1 shut down	Manual	Plugged oil filter, closed oil valve, bad oil solenoid, com- pressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
A037	Alarm	Comp. B2 Max. Oil Delta P, check oil line	(Discharge press – Oil press) > 100 PSI for more than 5 seconds	Comp. B2 shut down	Manual	Plugged oil filter, closed oil valve, bad oil solenoid, com- pressor oil check valve stuck, oil line check valve stuck, plugged oil strainer
A038	Alarm	Comp. A1 Failed Oil Solenoid	Diff. Oil Pressure > 2.5 PSI during period after oil pump starts and before oil sole- noid opens	Comp. A1 not allowed to start	Manual	Faulty oil solenoid valve
A039	Alarm	Comp. A2 Failed Oil Solenoid	Diff. Oil Pressure > 2.5 PSI during period after oil pump starts and before oil sole- noid opens	Comp. A2 not allowed to start	Manual	Faulty oil solenoid valve
A040	Alarm	Comp. B1 Failed Oil Solenoid	Diff. Oil Pressure > 2.5 PSI during period after oil pump starts and before oil sole- noid opens	Comp. B1 not allowed to start	Manual	Faulty oil solenoid valve
A041	Alarm	Comp. B2 Failed Oil Solenoid	Diff. Oil Pressure > 2.5 PSI during period after oil pump starts and before oil sole- noid opens	Comp. B2 not allowed to start	Manual	Faulty oil solenoid valve

## Table 32 — Alarm and Alert Codes (cont)

ALARM/ALER CODE	T ALARM OR ALERT	DESCRIPTION	WHY WAS THIS ALARM GENERATED?	ACTION TAKEN B'	Y RESET METHOL	PROBABLE CAUSE
T051	Alert	Compressor A1 Failure – (See below		CONTROL	METHOL	5   11021121 01001
T052	Alert	Compressor A2 Failure – (See belov	7			
T055	Alert	Compressor B1 Failure – (See belov	See additional descriptions v)	below.		
T056	Alert	Compressor B2 Failure – (See below	7)			
		High Pressure Switch		Comp. shut down	Manual	Loss of condenser air/water
		Trip	HPS input to CCP module open	o surpriorial domin	ivianuar	flow. Operation beyond chiller capability. Liquid valve not open.
		No Motor Current	CCP reads less than 10% of MTA on all legs for >3.0 seconds	Comp. shut down	Manual	Power supply disconnected, blown fuse(s), wiring error, cor tactor not energized, faulty cur rent toroid, check toroid wiring.
Si.		Current Unbalance	CCP measures current imbalance between phases must be above C.UNB for 25 minutes	Circuit shut down	Manual	Loose terminals on power wires. Alert will be generated i measured imbalance exceeds set point.
		Single Phase Curren Loss	t CCP measures current imbalance between phases greater than 50% (running current <50% of MTA) or 30% (running current ≥ 50% of MTA) for 1 second.	Circuit shut down	Manual	Blown fuse, wiring error, loose terminals
		High Motor Current	CCP detects high current compared to MTA setting	Comp. shut down	Manual	Operation beyond chiller capa- bility, improperly punched con- figuration header, blown fuse
*		Ground Fault Trip	CCP detects ground current (4.0 ± 2.0 amps)	Comp. shut down	Manual	Motor winding(s) gone to ground, wiring error, loose plug connector.
		Contactor Failure	CCP detects min. 10% of MTA for 10 seconds after shutting off compressor contactor. Oil solenoid is energized.	All remaining com- pressors shut down, All loaders deener- gized. Min. load valve of affected circuit energized (if equipped)	Manual	Faulty contactor, contactor welded, wiring error.
		Current Phase Reversal	CCP detects phase reversal from toroid reading or from incoming power supply.	Circuit shut down	Manual	Terminal block power supply leads not in correct phase. Toroid wire harness crossed. Check compressor contactor.
£)		Motor Over Temperature	CCP detects motor winding temperature >245 F	Comp. shut down	Manual	Motor cooling (all) or Economizer (2 comp. circuits) sole- noid failure, low refrigerant charge. Faulty economizer TXV or poor bulb connection to motor cooling line.
* 1	L	Open Thermistor	CCP detects open circuit in motor temp thermistor	Comp. shut down	Manual	Wiring error or faulty thermistor*
		MTA Header Fault	CCP finds error with MTA value punched out in header.	Comp. shut down		Header pins on CCP board either all or none punched out, header not fully seated in CCP board.
		MTA Value Error	MTA value stored in MBB does not agree with MTA header value from CCP.	Comp. not allowed to start		Header pin(s) on CCP board not punched out correctly. See Appendix A. Incorrect size or vollage entered when MBB was downloaded.
		Shorted Thermistor	CCP detects short circuit in motor temp thermistor	Comp. shut down	Manual	Wiring error or faulty thermistor*
A060	1	Cooler Leaving Fluid Thermistor Failure – 1	Thermistor outside range of -40 to 240° F (-40 to 116° C)	Chiller shut down	Automatic	Thermistor failure, damaged cable/wire or wiring error.
	.  1	Cooler Leaving Fluid hermistor Failure – 2	LWT > EWT + 5° F for 15 minutes	Chiller shut down	Manual	Thermistor failure, damaged cable/wire, wiring error or water piping error.
A061	. Т	cooler Entering Fluid hermistor Failure		Uses 0.1×F/% Total Capacity as rise/ton	Automatic	Thermistor failure, damaged cable/wire or wiring error.
T062	ĮF	ondenser Leaving luid Thermistor ailure		None Chiller contin-	Automatic	Thermistor failure, damaged cable/wire or wiring error.
T063	F	ondenser Entering luid Thermistor ailure	Thermistor outside range of –40 to 240° F (–40 to 116° C)	None. Chiller contin- ues to run.		Thermistor failure, damaged cable/wire or wiring error.
T070	Alert C		Average of compressor A1 and A2 (if installed) sensors > 210° F for 30 seconds.	Circuit A shut down	C	Thermistor failure, damaged sable/wire, wiring error or notor cooling solenoid failure.

Table 32 — Alarm and Alert Codes (cont)

ALARM/ ALERT CODE	ALARM OR ALERT	DESCRIPTION	WHY WAS THIS ALARM GENERATED?	ACTION TAKEN BY CONTROL	RESET METHOD	PROBABLE CAUSE
T071	Alert	Cir. B Discharge Gas Thermistor Failure	Average of compressor B1 and B2 (if installed) sensors > 210° F for 30 seconds.	Circuit B shut down	Manual	Thermistor failure, damaged cable/wire, wiring error or motor cooling solenoid failure
T073	Alert	Outside Air Tempera- ture Thermistor Failure	Thermistor outside range of -40 to 240 F (-40 to 116 C)	Reset disabled. Runs under normal control/ set points.	Automatic	Thermistor failure, damaged cable/wire, wiring error or ser sor not installed.
T074	Alert	Space Temperature Thermistor Failure	Thermistor outside range of -40 to 240 F (-40 to 116 C)	Reset disabled. Runs under normal control/ set points.	Automatic	
T075	Alert	Compressor A1 Discharge Gas Thermistor Failure	Thermistor outside range of 40 to 240° F (-40 to 116° C)	Comp A1 shut down	Automatic	
T076	Alert	Compressor A2 Discharge Gas Thermistor Failure	Thermistor outside range of 40 to 240° F (-40 to 116° C)	Comp A2 shut down	Automatic	Thermistor failure, damaged cable/wire, wiring error or motor cooling solenoid failure
T077	Alert	Compressor B1 Discharge Gas Thermistor Failure	Thermistor outside range of 40 to 240° F (-40 to 116° C)	Comp B1 shut down	Automatic	Thermistor failure, damaged cable/wire, wiring error or motor cooling solenoid failure
Т078	Alert	Compressor B2 Discharge Gas Thermistor Failure	Thermistor outside range of -40 to 240° F (-40 to 116° C)	Comp B2 shut down	Automatic	Thermistor failure, damaged cable/wire, wiring error or motor cooling solenoid failure
T079	Alert	Lead/Lag Leaving Fluid Temperature Thermistor Failure	Thermistor outside range of -40 to 240 F (-40 to 116 C)	Breaks Dual Chiller link if set up for Paral- lel operation.	Automatic	Thermistor failure, damaged cable/wire, wiring error or sen sor not installed.
T090	Alert	Circuit A Discharge Pressure Transducer Failure	Voltage ratio more than 98.9% or less than 6%.	Circuit A shut down	Automatic	Transducer failure, poor con- nection to MBB, or wiring damage/error.
T091	Alert	Circuit B Discharge Pressure Transducer Failure	Voltage ratio more than 98.9% or less than 6%.	Circuit B shut down	Automatic	Transducer failure, poor con- nection to MBB, or wiring damage/error.
T092	Alert	Circuit A Suction Pressure Transducer Failure	Voltage ratio more than 99.9% or less than 0.5% for 50 seconds.	Circuit A shut down	Automatic	Transducer failure, poor con- nection to MBB, or wiring damage/error.
Т093	Alert	Circuit B Suction Pressure Transducer Failure	Voltage ratio more than 99.9% or less than 0.5% for 50 seconds.	Circuit B shut down	Automatic	Transducer failure, poor con- nection to MBB, or wiring damage/error.
T094	Alert	Comp A1 Oil Pres- sure Transducer Failure	Voltage ratio more than 98.9% or less than 6%.	Comp A1 shut down	Automatic	Transducer failure, poor con- nection to SCB, or wiring damage/error.
T095	Alert	Comp A2 Oil Pres- sure Transducer Failure	Voltage ratio more than 98.9% or less than 6%.	Comp A2 shut down	Automatic	Transducer failure, poor con- nection to SCB, or wiring damage/error.
T096	Alert	Comp B1 Oil Pres- sure Transducer Failure	Voltage ratio more than 98.9% or less than 6%.	Comp B1 shut down	Automatic	Transducer failure, poor con- nection to SCB, or wiring damage/error.
T097	Alert	Comp B2 Oil Pres- sure Transducer Failure	Voltage ratio more than 98.9% or less than 6%.	Comp B2 shut down	Automatic	Transducer failure, poor con- nection to SCB, or wiring damage/error.
T098	Alert	Circuit A Economizer Pressure Transducer Failure – 1	Voltage ratio more than 99.9% or less than 0.5% for 50 seconds.	Circuit A shut down	Automatic	Transducer failure, poor con- nection to SCB, or wiring damage/error.
		Circuit A Economizer Pressure Transducer Failure – 2	Economizer pressure is more than 12 psi (83 kPa) less than suction pressure.	Circuit A shut down	Manual	Suction and Economizer pressure connectors/wiring are swapped.
T099		Circuit B Economizer Pressure Transducer Failure – 1	Voltage ratio more than 99.9% or less than 0.5% for 50 seconds.	Circuit B shut down	Automatic	Transducer failure, poor con- nection to SCB, or wiring damage/error.
		Failure – 2	Economizer pressure is more than 12 psi (83 kPa) less than suction pressure.	Circuit B shut down	Manual	Suction and Economizer pres- sure connectors/wiring are swapped.
T110		Circuit A Loss of Charge	Discharge pressure reading < 10 psig for 30 seconds.	Circuit A shut down	Manual	Refrigerant leak or transducer failure.
T111	Alert	Circuit B Loss of	Discharge pressure reading < 10 psig for 30 seconds.	Circuit B shut down	Manual	Refrigerant leak or transducer failure.

Table 32 — Alarm and Alert Codes (cont)

ALARM/ ALERT CODE	ALARM OF ALERT	DESCRIPTION	WHY WAS THIS ALARM GENERATED?	ACTION TAKEN BY CONTROL	RESET METHOD	PROBABLE CAUSE
T120	Alert	Circuit A Low Saturated Suction Temperature	SST reads 6° F (3.3° C) or more below the brine freeze point for 3 minutes or 28° F below brine freeze point for 2 minutes.	Circuit A shut down	Manual†	Low refrigerant charge, plugged strainer, faulty expa sion valve, or low water flow.
T121	Alert	Circuit B Low Saturated Suction Temperature	SST reads 6° F (3.3° C) or more below the brine freeze point for 3 minutes or 28° F below brine freeze point for 2 minutes.	Circuit B shut down	Manual†	Low refrigerant charge, plugged strainer, faulty expa sion valve, or low water flow.
T122	Alert	Circuit A High Saturated Suction Temperature	After first 90 seconds, SST > 55 F (12.8 C) and EXV < 1% for 5 minutes.	Circuit A shut down	Manual	Faulty expansion valve or transducer.
T123	Alert	Circuit B High Saturated Suction Temperature	After first 90 seconds, SST > 55 F (12.8 C) and EXV < 1% for 5 minutes.	Circuit B shut down	Manual	Faulty expansion valve or transducer.
T124	Alert	Circuit A Low Oil Level/Flow	Level switch input open.	Circuit A shut down after 4th failure in 18 hours.	Manual	Low oil level, failed switch, wiring error, failed control module.
T125	Alert	Circuit B Low Oil Level/Flow	Level switch input open.	Circuit B shut down after 4th failure in 18 hours.	Manual	Low oil level, failed switch, wiring error, failed control module.
T126	Alert	Circuit A High Dis- charge Pressure	SCT > MCT_SP + 5° F (2.8° C)	Circuit A shut down.	Automatic**	Faulty transducer/high pres- sure switch, low/restricted condenser air/water flow††
T127	Alert	Circuit B High Dis- charge Pressure	SCT > MCT_SP + 5° F 2.8° C)	Circuit B shut down.	Automatic**	Faulty transducer/high pres- sure switch, low/restricted condenser air/water flow††
A128	Alarm	Circuit A Condenser Freeze Protection (alarm ignored for brine chillers)	For water cooled chillers only, if SCT < 34 F (1.1° C)	Chiller shut down. Turns condenser pump On if Chiller is Off.	Automatic	Failed/bad discharge pres- sure transducer, refrigerant leak, configured for water- cooled condenser.
A129	Alarm	Circuit B Condenser Freeze Protection (alarm ignored for brine chillers)	For water cooled chillers only, if SCT < 34 F (1.1° C)	Chiller shut down. Turns condenser pump On if Chiller is Off.	Automatic	Failed/bad discharge pres- sure transducer, refrigerant leak, configured for water- cooled condenser.
T135	Alert	Circuit A Failure to Pump Out	With EXV closed, SST did not drop 10° F (5.6° C) in 6 minutes, or SST is not 6° F (3.3° C) less than Brine Freeze, or SST is not less than 10 F (-12 C).	None	Manual	Faulty transducer or EXV.
T136	Alert	Circuit B Failure to Pump Out	With EXV closed, SST did not drop 10° F (5.6° C) in 6 minutes, or SST is not 6° F (3.3° C) less than Brine Freeze, or SST is not less than 10 F (-12 C).	None	Manual	Faulty transducer or EXV
T137		Circuit A Low Dis- charge Superheat	Superheat < 5° F (2.8° C) for 10 minutes.	Circuit A shut down		Faulty thermistor, transducer, EXV, or Economizer TXV. Motor cooling solenoid stuck open.
T138	-	Circuit B Low Dis- charge Superheat	Superheat < 5° F (2.8° C) for 10 minutes.	Circuit B shut down	Manual	Faulty thermistor, transducer, EXV, or Economizer TXV. Motor cooling solenoid stuck open.
T140		Compressor A1 – High Oil Filter Pres- sure Drop	Oil filter pressure drop (FD.A1) exceeds 25 psig 172 kPa) for water-cooled units or 30 psig (207 kPa) for air-cooled and split system units.	None	Manual	Filter change needed to pre- vent machine from shutting down.
T141	1	aign Oil Filter Pres- sure Drop	Oil filter pressure drop (FD.A2) exceeds 25 psig (172 kPa) for water-cooled units or 30 psig (207 kPa) for air-cooled and split system units.	None	1	Filter change needed to pre- vent machine from shutting down.

Table 32 — Alarm and Alert Codes (cont)

ALARM/ALERT CODE	ALARM OR ALERT	DESCRIPTION	WHY WAS THIS ALARM GENERATED?	ACTION TAKEN BY CONTROL	RESET METHOD	PROBABLE CAUSE
T142	Alert	Compressor B1 – High Oil Filter Pressure Drop	Oil filter pressure drop (FD.B1) exceeds 25 psig (172 kPa) for water-cooled units or 30 psig (207 kPa) for air-cooled and split system units.	None	Manual	Filter change needed to prevent machine from shutting down.
T143 ·	Alert	Compressor B2 – High Oil Filter Pressure Drop	Oil filter pressure drop (FD.B2) exceeds 25 psig (172 kPa) for water-cooled units or 30 psig (207 kPa) for air-cooled and split system units.	None	Manual	Filter change needed to prevent machine from shutting down.
A150	Alarm	Unit is in Emergency Stop	CCN command received to shut unit down	Chiller shut down	CCN/ Automatic	Network command
A151	Alarm	Illegal Configuration-x	Illegal Configuration has been entered. Correction needed.	Chiller cannot start.	Manual	Configuration error. See Table 33.
A152	Alarm	Circuit A&B Off for Alerts. Unit down.	Control has shut down both circuits due to alerts.	None	Automatic	Check individual alarms.
T153	Alert	Real Time Clock Hard- ware Failure	Time not advancing on board,	Defaults to occupied	Automatic	Time clock not initialized or board fail
A154	Alarm	Serial EEPROM Hard- ware Failure	Internal failure of the EEPROM.	Machine shuts down	Manual	Replace Main Base Board.
A155	Alarm	Serial EEPROM Stor- age Failure Error	Internal diagnostic has found an error on critical data.	Machine shuts down	Manual	Re-download the software of consider replacement of the Main Base Board.
A156	Alarm	Critical Serial EEPROM Storage Fail- ure Error	Internal diagnostic has found an error on critical data.	Machine shuts down	Manual	Replace Main Base Board.
A157	Alarm	A/D Hardware Failure	A/D converter on the MBB has failed.	Machine shuts down	Manual	Replace Main Base Board.
A159	Alarm	Loss of Condenser Flow	Flow switch not closed within 1 minute after pump is started or if flow switch opens during normal operation for > 10 sec.	Chiller shut down.	Manual	Low condenser water flow, failed condenser pump.
A172	Alarm	Loss of Communica- tion with EXV Module	MBB has lost communication with the EXV Module	Chiller shut down.	Automatic	Failed EXV Module, wiring error, loose connections, failed transformer, wrong address.
T173	Alert	Loss of Communica- tion with Energy Man- agement Module	MBB has lost communication with the Energy Management Module when this option is installed.	EMM options are disabled.	Automatic	Failed EMM, wiring error, loose connections, failed transformer wrong address, wrong configu- ration.
T174	Alert	4-20 mA Cool Setpoint Input Failure	If configured and input signal to EMM less than 2 mA or greater than 22 mA.	Function disabled. Normal set point used.	Automatic	Faulty signal generator, wiring error, loss of signal
T175		4-20 mA Heat Setpoint Input Failure	If configured and input signal to EMM less than 2 mA or greater than 22 mA.	Function disabled. Normal set point used.	Automatic	Faulty signal generator, wiring error, loss of signal
T176		4-20 mA Reset Input Out of Range	If configured and input signal to EMM less than 2 mA or greater than 22 mA.	Reset function dis- abled. Normal set point used.	Automatic	Faulty signal generator, wiring error loss of signal
T177	Alert	4-20 mA Demand Limit Input Out of Range	If configured and input signal to EMM less than 2 mA or greater than 22 mA.	Reset function dis- abled. Normal set point used.	Automatic	Faulty signal generator, wiring error, loss of signal
A178		Loss of Communica- tion with Screw Chiller Module	MBB has lost communication with the Screw Chiller Module	Chiller shut down.		Failed SCB Module, wiring error, loose connections, failed transformer, wrong address.
A180	11		MBB has lost communication with the Compressor Protection Module 1	Chiller shut down.	Automatic	Failed CCP Module, wiring error, loose connections, failed transformer, wrong address.
A181		ion with Compressor	MBB has lost communication with the Compressor Protection Module 2	Chiller shut down.	Automatic	Failed CCP Module, wiring error, loose connections, failed transformer, wrong address.

Table 32 — Alarm and Alert Codes (cont)

ALARM/ALERT CODE	ALARM OR ALERT	DESCRIPTION	WHY WAS THIS ALARM GENERATED?	ACTION TAKEN BY	RESET	PROBABLE CAUSE
T182	Alert	Compressor Protection Module 1 Internal Diagnostic	The ComfortLink™ Compres sor Protection Module has generated an internal diag- nostic alert.		Manual on CCP and MBB	Eliminate EMI sources around
T183	Alert	Compressor Protection Module 2 Inter- nal Diagnostic	The ComfortLink Compressor Protection Module has generated an internal diagnostic alert.	Affected compressors are shut down.	Manual on CCP and MBB	Eliminate EMI sources around the module, consider replacement of the CCP module if alerts continue.
T184	Alarm	Compressor Protection Module 1	CCP has experienced too many power cycles***	Chiller shut down	Manual	Loose connections, frequent power interruptions.
T185	Alarm	Compressor Protection Module 2	CCP has experienced too many power cycles***	Chiller shut down	Manual	Loose connections, frequent power interruptions.
2/A	Alarm	Cooler Pump Inter- lock Failed at Start-Up	Interlock did not close within 5 minutes after chiller was enabled	Chiller shut down. Pump turned off.	Manual	Failure of cooler pump, cooler pump interlock, or flow switch
A201	Alarm'	Cooler Pump Inter- lock Opened Unexpectedly	Interlock opened for at least 10 seconds during operation and does not close within 5 min.	Chiller shut down. Pump turned off.	Manual	Failure of cooler pump, cooler pump interlock, or flow switch
A202	Alarm	Cooler Pump Inter- lock Closed When Pump OFF	Interlock closed when pump relay is off	Cooler pump remains off. Unit prevented from starting.	Manual	Failure of cooler pump relay or interlock, welded contacts. Cooler pump enabled but mot controlling pump
T203	Alert	Loss of Communica- tion with the Slave Chiller	The master chiller (when configured) has lost communication with the slave chiller for 3 minutes.	Master chiller runs as a stand-alone chiller.	Automatic	Failed Slave MBB Module, wir- ing error, loose connections, wrong address, loss of control power on slave chiller.
T204	Alert	Loss of Communica- tion with the Master Chiller	The slave chiller (when configured) has lost communication with the master chiller for 3 minutes.	Slave chiller runs as a stand-alone chiller.	Automatic	Failed Master MBB Module, wiring error, loose connec- tions, wrong address, loss of control power on master chiller.
T205	Alert	Master and Slave Chiller with Same Address	The master chiller (when configured) has determined that its address is the same as the slave address.	Dual chiller control dis- abled.	Automatic	Master and Slave chiller must have different addresses.
T206		High Leaving Chilled Water Temperature	LCW read > LCW Delta Alarm limit and total capacity is 100% and current LCW > LCW reading 1 minute ago	None.		Building load greater than unit capacity, low water/brine flow, or compressor fault. Check for other alarms or alerts.
A207		Cooler Freeze Protec- tion	Cooler EWT or LWT less than freeze point. Freeze point is the brine freeze setpoint +2 F (1.1 C).	Chiller shut down. Leave Cooler pump on. Turn Cooler pump on if Chiller is off.	Automatic†	Faulty thermistor, low water flow
T210	ş.	Winterization Required	SCT<32 F in either circuit	None		Winterization must be per- formed to avoid cooler freeze- up. After winterization has been completed, configure W.DNE Winterization Performed (Con- figuration Mode, Sub-mode SERV) to YES to reset alert.
T950		Loss of Communica- tion with WSM		WSM forces removed. Runs under own control.	Automatic	Failed module, wiring error, failed transformer, loose con- nection plug, wrong address
A951		oss of Communica- ion with Chillervisor System Manager CSM)	been received by the MBB	CSM forces removed. Runs under own control.	Automatic	Wiring faulty or module failure
T998	500		of runtime, SST is less than 0° F (-18 C) and the rate of change is negative (in 5 second increments).	Circuit A compressor is shut down.	f f fi ti	Refrigerant restriction such as closed suction service valve, closed liquid line service valve, aulty liquid line solenoid valve, aulty liquid line solenoid valve, aulty EXV/Economizer operator, plugged refrigerant strainer, closed discharge line ralve.
Т999		low in Circuit B.		Circuit B compressor is shut down.	c fa fa ti	Refrigerant restriction such as losed suction service valve, losed liquid line service valve, aulty liquid line solenoid valve, aulty EXW/Economizer opera- on plugged refrigerant trainer, closed discharge line alve.

### **LEGEND AND NOTES FOR TABLE**

#### LEGEND

A/D	<ul> <li>Analog to Digital Converter</li> </ul>
CCN	Carrier Comfort Network
CCP	<ul> <li>ComfortLink™ Compressor Protection</li> </ul>
EMI	Electromagnetic Interference
EMM	- Energy Management Module
EWT	<ul> <li>Entering Water Temperature</li> </ul>
EXV	- Electronic Expansion Valve
HPS	High-Pressure Switch
LCW	<ul> <li>Leaving Chilled Water</li> </ul>
LWT	<ul> <li>Leaving Water Temperature</li> </ul>
MBB	Main Base Board
MCT_SP	- Maximum Condensing Temperature Set Point
MTA	- Compressor Must Trip Amps
SCB	<ul> <li>Screw Compressor Board</li> </ul>
SCT	<ul> <li>Saturated Condensing Temperature</li> </ul>
SST	<ul> <li>Saturated Suction Temperature</li> </ul>
TXV	<ul> <li>Thermostatic Expansion Valve</li> </ul>
WSM	- Water-System Manager

\*Compressors are equipped with 2 motor winding temperature thermistors. Verify first that the problem is not a wiring error before using backup thermistor.

†Manual reset after 1 hour from occurrence.
\*\*Reset automatic first time, manual if repeated on the same date. ††Note that the high-pressure switch should trip before this alert is generated. Check HPS operation if this alert is generated.
\*\*\*Maximum 5 power losses at CCP in one hour.

NOTES:

1. Low Oil Pressure Alert Criteria and Set Points
Where: P<sub>d</sub> = Discharge Pressure, P<sub>s</sub> = Suction Pressure.
P<sub>o</sub> = Oil Pressure and P<sub>e</sub> = Economizer Pressure Two oil set points are used by the control for the Low Oil Pressure

Oil Set Point 1 is defined as:

a. If  $P_s < 35$ , then Oil Set Point 1 = 10 psig. b. If  $P_s > 35$  and < 51, then Oil Set Point 1 = 12.5 psig. c. If  $P_s \ge 51$ , then Oil Set Point 1 = 15 psig.

Oil Set Point 2 (see Fig. 20) is defined as:

a. If  $(P_d - P_s) < 125$ , then Oil Set Point 2 = 0.235 x  $(P_d - P_s) + 0.588$ 

0.568
b. If  $(P_d - P_s) > 125$  and < 165, then Oil Set Point 2 = 2.0 x  $(P_d - P_s) - 220.0$ c. If  $(P_d - P_s) \ge 165$  then Oil Set Point 2 = 0.6364 x  $(P_d - P_s) + \frac{1}{500}$ 

(Po - Pe) is the Oil pressure differential displayed as items DO.A1 and DO.A2 (Pressures mode under sub-mode PRC.A) for Circuit A and DO.B1 and DO.B2 (Pressures mode under sub-mode PRC.B) for Circuit B.
 Alert criteria is based on operating time.
 a. On time less than 5 seconds oil pressure is ignored.
 b. On time between 5 and 120 seconds, the alert will be generated if the following condition is true for 3 consecutive read-inns:

(P<sub>0</sub> - P<sub>e</sub>) < [15 psig/120 sec.] x [Compressor Run Time in sec.] c. On time greater than 120 seconds the alarm will be generated if one of the following conditions is true:

(P<sub>0</sub> - P<sub>e</sub>) < Oil Set Point 1 for 15 seconds.

(P<sub>0</sub> - P<sub>s</sub>) < Oil Set Point 2 for 15 seconds.




Fig. 20 — Oil Pressure Set Point 2 Calculation

Table 33 — Illegal Configurations (Alarm A151)

CODE NUMBER	ILLEGAL CONFIGURATION DESCRIPTION	
1	Unit type outside range of 1-5	
2	Number of compressors in Circuit A outside range of 1-2	
3	Number of compressors in Circuit B outside range of 1-2	
4	Invalid FAN.S or HPCT Selection	
5	Air-cooled chiller with Low Temperature Brine fluid (FLUD = Low Brine)	
6	Water-cooled chiller configured for air-cooled head pressure control type (HPC	
7	Air-cooled chiller with condenser pump control enabled	
8	Air-cooled chiller with condenser fluid sensors enabled	

**EXV Troubleshooting Procedure** — Follow steps below to diagnose and correct EXV/Economizer problems.

Check EXV motor operation first. Switch the Enable/Off/Remote (EOR) Contact switch to the Off position. Press on the Navigator until 'Select a menu item' appears on the display. Use the arrow keys to select the Service Test mode. Press EXTER. The display will be:

> TEST OFF OUTS COMP

Press [PRE] (password entry may be required) and use to change 'OFF' to 'ON'. Switch the EOR switch to Enable. The Service Test mode is now enabled. Move the pointer down to the OUTS sub-mode and press [PRE]. Move the pointer to item EXV.A or EXV.B as needed. Press [PRE] and the valve position will flash. Use to select 100% valve position (hold for quick movement) and press [PRE].

You should be able to feel the actuator moving by placing your hand on the EXV. A sight glass is located on the valve body to verify that the sleeve is moving to expose/cover slots in the orifice. A hard knocking should be felt from the actuator when it reaches the top of its stroke (can be heard if surroundings are relatively quiet). Press again twice if necessary to confirm this. To close the valve, press again twice if necessary to confirm this. To close the valve, press and press and press and press street. The actuator should knock when it reaches the bottom of its stroke. If it is believed that the valve is not working properly, continue with the checkout procedure below:

Check the EXV output signals at appropriate terminals on the EXV module (see Fig. 21). Connect positive test lead to red wire (EXV-J6 terminal 3 for Circuit A, EXV-J7 terminal 3 for Circuit B). Set meter to approximately 20 vdc. Using the Service Test procedure above, move the valve output under test to 100%. DO NOT short meter leads together or pin 3 to any other pin as board damage will occur. During the next several seconds, carefully connect the negative test lead to pins 1,2,4 and 5 in succession (plug J6 for Circuit A, plug J7 for Circuit B). Digital voltmeters will average this signal and display approximately 6 vdc. If it remains constant at a voltage other than 6 VDC or shows 0 volts, remove the connector to the valve and recheck.

The EXV motor moves at 300 steps per second. Commanding the valve to either 0% or 100% will add 7500 steps to the move. For example, if the EXV is fully closed, selecting 100% would allow 75 seconds for the dc voltage to be checked (15,000/300 + 7500/300).

Press In and select 0% to close the valve. Check the 4 position DIP switch on the board (all switches should be set to On). If a problem still exists, replace the EXV module. If the reading is correct, the expansion valve and EXV wiring should be checked. Check the EXV terminal strip and interconnecting wiring.

- Check color coding and wire connections. Make sure they are connected to the correct terminals at the EXV driver and EXV plug and that the cables are not crossed.
- Check for continuity and tight connection at all pin terminals.

Check the resistance of the EXV motor windings. Remove the EXV module plug (J6 for Circuit A, J7 for Circuit B) and check the resistance of the two windings between pins 1 and 2 for one winding and pins 4 and 5 for the other winding (see Fig. 21). The resistance should be 75 ohms  $\pm$  7.5 ohms.

INSPECTING/OPENING ELECTRONIC EXPANSION VALVES

IMPORTANT: Obtain replacement O-ring before opening EXV. Do not reuse O-rings.

To check the physical operation of an EXV, the following steps must be performed.

- 1. Close the liquid line service valve of the circuit to be checked. Put the Enable/Off/Remote Contact switch in the Off position. Using the Navigator, enter the Service Test mode and change the sub-mode TEST from 'OFF' to 'ON'. Switch the EOR switch to the Enable position. Under the COMP sub-mode, enable the desired compressor (CC.xx) for the circuit. Let compressor run until gage on suction pressure port reads 10 psig. Press [ATE], and [ENTER] to turn the compressor off. The compressor will complete its pumpout routine and turn off. Immediately after the compressor shuts off, close the discharge valve.
- Remove any remaining refrigerant from the system low side using proper reclaiming techniques. Drain oil from cooler using Schrader port in cooler inlet line. Turn off the line voltage power supply to the compressors and control circuit power.
- 3. The expansion valve motor is hermetically sealed inside the top portion of the valve. Carefully unscrew the large retaining nut securing the motor portion to the body of the valve making sure the EXV plug is still connected. The EXV lead screw and sleeve will come off with the motor portion of the device.
- 4. Enter the appropriate EXV test step under the OUTS submode in the Service Test mode. Locate the desired item 'EXV.A' or 'EXV.B'. Press of to make the valve position of 0% flash. Press and hold until 100% is displayed and press observe the operation of the lead screw and sleeve. The motor should be turning the lead screw and sleeve counterclockwise, raising the sleeve closer to the motor. Lead screw movement should be smooth and uniform from fully closed to fully open position. Press to select 0% and press again to check open to closed operation. If the valve is properly connected to the processor and receiving correct signals, yet does not operate as described above, the sealed motor portion of the valve should be replaced.




Fig. 21 — EXV Cable Connections to EXV Module

BRAZED-PLATE ECONOMIZERS — Brazed-plate economizers are factory-installed in each circuit on 30GXN,R108, 118-350 and 30HXA,C161-271 models. A TXV is included to meter the flow of refrigerant to the economizer port of the compressor. Flow through the TXV is enabled only when the circuit is fully loaded for 30GXN,R models. The TXV bulb is secured to the side of the economizer outlet tube. See Fig. 22 for typical piping arrangement.

Brazed-plate heat exchangers cannot be repaired if they develop a leak. If a refrigerant leak is detected, the heat exchanger <u>must be</u> replaced. To replace a brazed-plate heat exchanger the following steps must be performed:

- Using proper techniques, move the refrigerant remaining in the circuit to the high side and close the discharge and liquid line ball valves. Reclaim any refrigerant remaining in the low side.
- 2. Un-solder the refrigerant-in and refrigerant-out connections.
- Remove the four 8mm (1/4-20 on 30HX units) nuts holding the heat exchanger to the brackets. Save the nuts and hardware.
- Check that the replacement heat exchanger is the same as the original heat exchanger.
- Insulate the new heat exchanger to match the original and attach to the mounting brackets with the hardware removed in Step 3.
- 6. Carefully braze the refrigerant lines to the connections on the heat exchanger. Lines should be soldered using silver as the soldering material with a minimum of 45% silver. Keep the temperature below 1472 F (800 C) under normal soldering conditions (no vacuum) to prevent the copper solder of the brazed plate heat exchanger from changing its structure. Failure to do so can result in internal or external leakage at the connections which cannot be repaired.
- Braze equalizer line in place if removed. Attach economizer and motor cooling solenoid coils to their bodies if removed.
- 8. Dehydrate and recharge the circuit. Check for leaks.

NOTE: The brazed-plate heat economizers are not serviceable.

If operating problems persist after economizer replacement, they may be due to a bad liquid level sensor, suction pressure transducer, discharge gas thermistor or intermittent connections between the processor board terminals and EXV plug. Recheck all wiring connections and voltage signals.

Other possible causes of improper refrigerant flow control could be restrictions in the liquid line. Check for plugged strainer(s) or restricted metering slots in the EXV (see Fig. 23). Formation of ice or frost on lower body of electronic expansion valve is one symptom of restricted metering slots. However, frost or ice formation is normally expected when leaving fluid temperature from the cooler is below 40 F (4.4 C). Clean or replace valve if necessary.

NOTE (non-economized units only): Frosting of valve is normal during compressor test steps and at initial start-up. Frost should dissipate after 5 to 10 minutes operation in a system that is operating properly. If valve is to be replaced, wrap valve with a wet cloth to prevent excessive heat from damaging internal components.





Fig. 22 — Brazed-Plate Economizer



**Torque Specifications** 

ITEM	ft-lb	n-m
Sight Glass	15-25	20-34
Seal Cap	18-22	24-30

Fig. 23 — Typical 30GXN,GXR,HX EXV

## SERVICE

Servicing Coolers and Condensers — When cooler heads and partition plates are removed, tube sheets are exposed showing the ends of tubes. The 30GXN,GXR,HX units use a flooded cooler design. Water flows inside the tubes. TUBE PLUGGING - A leaky tube in one circuit can be plugged until retubing can be done. The number of tubes plugged determines how soon the cooler must be retubed. All tubes in the 30GXN,R and 30HX coolers and 30HX condensers can be removed. Loss of unit capacity and efficiency as well as increased pump power will result from plugging tubes. Failed tubes should be replaced as soon as possible. Up to 10% of the total number of tubes can be plugged before retubing is necessary. Figure 24 shows an Elliott tube plug and a crosssectional view of a plug in place. The same components for plugging and rolling tubes can be used for all coolers and 30HXC condensers. See Table 34. If tube failure is in both circuits, using tube plugs will not correct problem. Contact your Carrier representative for assistance.

#### **A** CAUTION

Use extreme care when installing plugs to prevent damage to the tube sheet section between the holes.

RETUBING (See Table 35) — When retubing is to be done, obtain service of qualified personnel experienced in boiler maintenance and repair. Most standard procedures can be followed when retubing the 30GXN,R and 30HX heat exchangers. Care must be taken as the tubes are rolled in the center tube sheet and require special pulling tools. A 7% crush is recommended when rolling replacement tubes into the tubesheet. A 7% crush can be achieved by setting the torque on the gun at 48 to 50 in.-lb (5.4 to 5.6 N-m).

The following Elliott Co. tube rolling tools are required:

113123 Expander Assembly

213123 Mandrel 2115122 Rolls

2134123 Cage

Place one drop of Loctite No. 675 or equivalent on top of tube prior to rolling. This material is intended to "wick" into the area of the tube that is not rolled into the tube sheet, and prevent fluid from accumulating between the tube and the tube sheet. New tubes must also be rolled into the center tube sheet to prevent circuit-to-circuit refrigerant leakage.

Table 34 — Plugging Components


COMPONENTS FOR PLUGGING	PART NUMBER
For Tubes Brass Pin Brass Ring	853103-1* 853002-640* or -6571
For Holes without Tubes Brass Pin Brass Ring Roller Extension	853103-1A* 853002-738* S82-112/11
Loctite	No. 675**
Locquic	"N"**


<sup>\*</sup>Order directly from: Elliott Tube Company, Dayton, Ohio. †Measure tube ID before ordering.

Table 35 — Tube Diameters

ITEM	INCHES	MILLIMETERS
Tube sheet hole diameter:	0.756	19.20
Tube OD	0.750	19.05
Tube ID after rolling:	0.650	16.51
(includes expansion	to	to
due to clearance)	0.667	16.94

NOTE: Tubes replaced along heat exchanger head partitions must be flush with tube sheet.





PIN AND RING INSTALLED Fig. 24 — Tube Plugging

## TIGHTENING COOLER/CONDENSER HEAD BOLTS

O-Ring Preparation — When reassembling cooler and condenser heads, always check the condition of the O-ring(s) first. The O-ring should be replaced if there are any visible signs of deterioration, cuts or damage. Apply a thin film of grease to the O-ring before installation. This will aid in holding the O-ring into the groove while the head is installed. Torque all bolts to the following specification and in the sequence shown in Fig. 25.

- 1. Install all bolts finger tight.
- 2. Follow numbered sequence shown for head type being installed. This will apply even pressure to the O-ring.
- Apply torque in one-third steps until required torque is reached. Load all bolts to each one-third step before proceeding to the next one-third step.
- No less than one hour later, retighten all bolts to required torque values.
- 5. Restore water/brine flow and check for leaks. Fix leaks as necessary. Replace insulation (on cooler heads only).

### Inspecting/Cleaning Heat Exchangers

COOLERS — Inspect and clean the cooler tubes at the end of the first operating season. Because these tubes have internal ridges, a rotary-type tube cleaning system is necessary to fully clean the tubes. Tube condition in the cooler will determine the scheduled frequency for cleaning, and will indicate whether water treatment is adequate in the chilled water/brine circuit. Inspect the entering and leaving thermistors for signs of corrosion or scale. Replace the sensor if corroded or remove any scale if found.

<sup>\*\*</sup>Can be obtained locally.




Fig. 25 — Cooler and Condenser Head Recommended Bolt Torque Sequence

CONDENSERS (30HX Only) — Since this water circuit is usually an open-type system, the tubes may be subject to contamination and scale. Clean the condenser tubes with a rotary tube cleaning system at regular intervals, and more often if the water is contaminated. Inspect the entering and leaving condenser water thermistors (if installed) for signs of corrosion or scale. Replace the sensor if corroded or remove any scale if found.

Higher than normal condenser pressures, together with inability to reach full refrigeration load, usually indicate dirty tubes or air in the machine. If the refrigeration log indicates a rise above normal condenser pressures, check the condenser refrigerant temperature against the leaving condenser water temperature. If this reading is more than what the design difference is supposed to be, then the condenser tubes may be dirty, or water flow may be incorrect. Due to the pressure in the R-134a system, air usually will not enter the machine; the refrigerant will leak out.

During the tube cleaning process, use brushes specially designed to avoid scraping and scratching the tube wall. Contact your Carrier representative to obtain these brushes. Do not use wire brushes.

#### **A** CAUTION

Hard scale may require chemical treatment for its prevention or removal. Consult a water treatment specialist for proper treatment procedures.

Water Treatment — Untreated or improperly treated water may result in corrosion, scaling, erosion, or algae. The services of a qualified water treatment specialist should be obtained to develop and monitor a treatment program.

#### **A** CAUTION

Water must be within design flow limits, clean and treated to ensure proper machine performance and reduce the potential of tubing damage due to corrosion, scaling, erosion, and algae. Carrier assumes no responsibility for chiller or condenser damage resulting from untreated or improperly treated water.

#### Condenser Coils (30GXN,R only

COIL CLEANING — For standard aluminum, copper and pre-coated aluminum fin coils, clean the coils with a vacuum cleaner, fresh water, compressed air, or a bristle brush (not wire). Units installed in corrosive environments should have coil cleaning as part of a planned maintenance schedule. In this type of application, all accumulations of dirt should be cleaned off the coil.

#### **A** CAUTION

Do not use high-pressure water or air to clean coils — fin damage may result.

CLEANING E-COATED COILS — Follow the outlined procedure below for proper care, cleaning and maintenance of E-coated aluminum or copper fin coils:

<u>Coil Maintenance and Cleaning Recommendations</u> — Routine cleaning of coil surfaces is essential to maintain proper operation of the unit. Elimination of contamination and removal of harmful residues will greatly increase the life of the coil and extend the life of the unit.

Remove Surface Loaded Fibers — Surface loaded fibers or dirt should be removed with a vacuum cleaner. If a vacuum cleaner is not available, a soft brush may be used. In either case, the tool should be applied in the direction of the fins. Coil surfaces can be easily damaged (fin edges bent over) if the tool is applied across the fins.

NOTE: Use of a water stream, such as a garden hose, against a surface loaded coil will drive the fibers and dirt into the coil. This will make cleaning efforts more difficult. Surface loaded fibers must be completely removed prior to using low velocity clean water rinse.

<u>Periodic Clean Water Rinse</u> — A periodic clean water rinse is very beneficial for coils that are applied in coastal or industrial environments. However, it is very important that the water rinse is made with very low velocity water stream to avoid damaging the fin edges. Monthly cleaning as described below is recommended.

Routine Cleaning of Coil Surfaces — Monthly cleaning with Environmentally Sound Coil Cleaner is essential to extend the life of coils. It is recommended that all coils, including standard aluminum, pre-coated, copper/copper or E-coated coils are cleaned with the Environmentally Sound Coil Cleaner as described below. Coil cleaning should be part of the units regularly scheduled maintenance procedures to ensure long life of the coil. Failure to clean the coils may result in reduced durability in the environment.

Environmentally Sound Coil Cleaner is non-flammable, hypoallergenic, non-bacterial, USDA accepted biodegradable and 100% ecologically safe agent that will not harm the coil or surrounding components such as electrical wiring, painted metal surfaces or insulation. Use of non-recommended coil cleaners is strongly discouraged since coil and unit durability could be affected.

Environmentally Sound Coil Cleaner Application Equipment

2<sup>1</sup>/<sub>2</sub> Gallon Garden Sprayer

Water Rinse with Low Velocity Spray Nozzle

Environmentally Sound Coil Cleaner Application Instructions — Although Environmentally Sound Coil Cleaner is harmless to humans, animals, and marine life, proper eye protection such as safety glasses is recommended during mixing and application.

- Remove all surface loaded fibers and dirt with a vacuum cleaner as described above.
- Thoroughly wet finned surfaces with clean water and a low velocity garden hose being careful not to bend fins.
- Mix Environmentally Sound Coil Cleaner in a 2<sup>1</sup>/<sub>2</sub> gallon garden sprayer according to the instructions included with the Enzyme Cleaner. The optimum solution temperature is 100 F.

# NOTE: <u>DO NOT USE</u> water in excess of 130 F as the enzymatic activity will be destroyed.

- Thoroughly apply Environmentally Sound Coil Cleaner solution to all coil surfaces including finned area, tube sheets and coil headers.
- Hold garden sprayer nozzle close to finned areas and apply cleaner with a vertical, up-and-down motion. Avoid spraying in horizontal pattern to minimize potential for fin damage.
- 6. Ensure cleaner thoroughly penetrates deep into finned areas. Interior and exterior finned areas must be thoroughly cleaned. Finned surfaces should remain wet with cleaning solution for 10 minutes. Ensure surfaces are not allowed to dry before rinsing. Reapply cleaner as needed to ensure 10-minute saturation is achieved.

Thoroughly rinse all surfaces with low velocity clean water using downward rinsing motion of water spray nozzle. Protect fins from damage from the spray nozzle.

#### **A** CAUTION

Harsh Chemical and Acid Cleaners — Harsh chemical, household bleach or acid cleaners should not be used to clean outdoor or indoors coils of any kind. These cleaners can be very difficult to rinse out of the coil and can accelerate corrosion at the fin/tube interface where dissimilar materials are in contact. If there is dirt below the surface of the coil, use the Environmentally Sound Coil Cleaner as described above.

<u>High Velocity Water or Compressed Air</u> — High velocity water from a pressure washer, garden hose or compressed air <u>should never be used</u> to clean a coil. The force of the water or air jet will bend the fin edges and increase airside pressure drop. Reduced unit performance or nuisance unit shutdown may occur.

Condenser Fans (30GXN,R Only) — Each fan is supported by a formed wire mount bolted to a fan deck and covered with a wire guard. The exposed end of the fan motor shaft is protected from weather by grease. If the fan motor must be removed for service or replacement, be sure to regrease fan shaft and reinstall fan cover, retaining clips, and fan guard. For proper performance, the fans should be positioned as shown in Fig. 26 or 27. Tighten setscrews to  $14 \pm 1$  ft-lb  $(18 \pm 1.3 \text{ N-m})$ .

Check for proper rotation of the fan(s) once reinstalled (clockwise for high static and counterclockwise for standard viewed from above). If necessary to reverse, switch leads at contactor(s) in control box.




Fig. 26 — Condenser Fan Position (Standard Fan)




Fig. 27 — Condenser Fan Position (High-Static Fan)

## Refrigerant Charging/Adding Charge

IMPORTANT: These units are designed for use with R-134a only. DO NOT USE ANY OTHER REFRIGERANT in these units without first consulting your Carrier representative.

#### **A** CAUTION

When adding or removing charge, circulate water through the condenser (30HXC) and cooler at all times to prevent freezing. Freezing damage is considered abuse and may void the Carrier warranty.

#### **A** CAUTION

DO NOT OVERCHARGE system. Overcharging results in higher discharge pressure with higher cooling fluid consumption, possible compressor damage and higher power consumption.

Indication of low charge on a system:

NOTE: To check for low refrigerant charge on a 30HXC unit, several factors must be considered. A flashing liquid line sight glass (located in the EXV body) is not necessarily an indication of inadequate charge. There are many system conditions where a flashing sight glass occurs under normal operation. The EXV metering device is designed to work properly under these conditions.

- Make sure that the circuit is running at a full-load condition. To check whether circuit A is fully loaded, enter the Outputs mode from the Navigator and then sub-mode 'CIR.A' or 'CIR.B' depending on the circuit under investigation. The circuit is fully loaded if its compressor and loader relays all show 'On'.
- It may be necessary to use the Service Test feature to force the circuit into a full-load condition. If this is the case, see the instructions for using the Service Test feature in Table 13 of this manual.
- 3. With the circuit running at full load, verify that the cooler leaving fluid temperature is in the range of 38 to 46 F (3.3 to 7.8 C). Check temperature drop across liquid line strainer/drier. Maximum allowable temperature drop is 3° F (1.7° C). Strainer is cleanable if necessary and contains 1 standard drier core on all 30GX and 30HXA,C 161-271 models.
- At this condition, observe the refrigerant in the liquid line sight glass. If there is a clear sight glass, and no signs of flashing, then the circuit is adequately charged. Skip the remaining steps.
- 5. If the refrigerant appears to be flashing, the circuit is probably low on charge. Verify this by checking the EXV Percent Open. This information is located under the sub-mode 'CIR.A' or 'CIR.B' (Outputs mode) and is shown as items 'EXV.A' and 'EXV.B' Scroll through the Navigator until the desired item is located.
- If the EXV Percent Open is greater than 60%, and the liquid line sight glass is flashing, then the circuit is low on charge. Follow the procedure for adding charge for 30HXC units.

To add charge to the 30HXC systems:

 Make sure that the unit is running at full load, and that the cooler leaving fluid temperature is in the range of 42 to 46 F (5.6 to 7.8 C).

- At these operating conditions, check the liquid line sight glass. If there is a clear sight glass, then the unit has sufficient charge. If the sight glass is flashing, then check the EXV Percent Open. If this is greater than 60%, then begin adding charge.
  - NOTE: A flashing liquid line sight glass at operating conditions other than those mentioned above is not necessarily an indication of low refrigerant charge.
- Add 5 lb (2.3 kg) of liquid charge into the cooler using the fitting located on the tube entering the bottom of the cooler. This fitting is located between the Electronic Expansion Valve (EXV) and the cooler.
- 4. Observe the EXV Percent Open value. The EXV should begin closing as charge is being added. Allow the unit to stabilize. If the EXV Percent Open remains above 60%, and the sight glass continues flashing, add an additional 5 lb (2.3 kg) of liquid charge.
- Allow the unit to stabilize, and again check the EXV Percent Open. Continue adding 5 lb (2.3 kg) at a time of liquid refrigerant charge, and allow the unit to stabilize before checking the EXV position.
- 6. When the EXV Percent Open is in the range of 40 to 60%, check the liquid line sight glass. Slowly add enough additional liquid charge to ensure a clear sight glass. This should be done slowly to avoid overcharging the unit.
- Verify adequate charge by continuing to run at full load with 42 to 46 F (5.6 to 7.8 C) cooler leaving fluid temperature. Check that the refrigerant is not flashing in the liquid-line sight glass. The EXV Percent Open should be between 40 and 60%.

To add charge to the 30GX and 30HXA systems:

- Make sure that the circuit is running at a full load condition and all condenser fans are energized and running on the keypad, at the appropriate line on the display. To check whether circuit A is fully loaded, enter the Outputs mode from the Navigator and then sub-mode 'CIR.A' or 'CIR.B' depending on the circuit under investigation. The circuit is fully loaded if its compressor and loader relays all show 'On'.
- It may be necessary to use the Service Test feature to force the circuit into a full-load condition. If this is the case, see the instructions for using the Service Test feature in Table 13 of this manual.
- With the circuit running at full-load, verify that the cooler leaving fluid temperature is in the range of 38 to 48 F (5.6 to 7.8 C).
- 4. For 30HXA chillers, raise the compressor discharge to approximately 125 F (51.7 C) saturated condensing temperature (185 psig [1276 kPa]). For 30GXN,R chillers, raise the compressor discharge to approximately 130 F (54.4 C) saturated condensing temperature (198 psig [1366 kPa]). Measure the liquid temperature entering the EXV for 30HXA units. For 30GXN,R units, measure the liquid temperature after the tee where all liquid lines have joined (see Fig. 28 and 29). The liquid temperature should be approximately 107 F (41.7 C) for optimum charge. If the temperature is greater than 107 F (41.7 C) and the sight glass is flashing, the circuit is undercharged.
- Add 5 lb (2.3 kg) of liquid charge into the cooler using the fitting located on the tube entering the bottom of the cooler. This fitting is located between the Electronic Expansion Valve (EXV) and the cooler.
- Allow the system to stabilize and then recheck the liquid temperature. Repeat Step 5 as needed allowing the system to stabilize between each charge addition. Slowly add charge as the sight glass begins to clear to avoid overcharging.




Fig. 28 — Saturated Liquid Temperature Measurement (30GXN,R080-150 and 160)




Fig. 29 — Saturated Liquid Temperature Measurement (30GXN,R153, 163-350)

## Oil Charging/Low Oil Recharging

OIL SPECIFICATION — If oil is added, it must meet the following Carrier specifications:

This oil is available in the following quantities from your local Carrier representative (see Table 36).

Table 36 — Available Oil Quantities and Part Numbers

QUANTITY	TOTALINE PART NUMBER	RCD PART NUMBER
1 Quart	P903-1225	
1 Gallon	P903-1201	PP23BZ104-001
5 Gallons	P903-1205	PP23BZ104-005

Addition of oil charge to 30HX,GXN,GXR systems:

- If the 30HX,GXN,GXR unit shuts off repeatedly on Low Oil Level (Alert number 124 or 125), this may be an indication of inadequate oil charge. It could also mean simply that oil is in the process of being reclaimed from the low-side of the system.
- Begin by running the unit at full load for 1½ hours. Use the Manual Control feature of the software if the unit does not normally run at full load.
- 3. After running the unit for 1½ hours, allow the unit to restart and run normally. If the Low Oil Level alarms persist, continue following this procedure.
- 4. Close the liquid line service valve, and place a pressure gage on top of the cooler. Enable the Service Test feature using the Navigator and turn the EOR switch to Enable. Start the desired compressor by turning it On under the 'COMP' sub-mode. Select item 'CC.A1' for compressor A1, 'CC.B1' for compressor B1, etc.
- 5. Before starting the compressor, the unit will go through its normal pre-lube pump routine. If there is an insufficient level of oil in the oil separator, the compressor will not start, and a pre-start oil pressure alarm will be posted. Skip to Step 8.
- 6. If the compressor starts successfully, observe the cooler pressure gage. When this gage reads approximately 10 psig, turn the selected compressor Off from the Navigator and move the EOR switch to the Off position.
- Open the liquid line service valve and allow the unit to restart and run normally. If the Low Oil Level alarms persist, continue following this procedure.
- 8. If none of the previous steps were successful, the unit is low on oil charge. Add oil to the oil separator using the <sup>1</sup>/<sub>4</sub>-in. Schrader-type fitting on the discharge line entering the top of the oil separator (30HX units) or through the Schrader fitting on the top of the oil separator (30GXN,R units).

#### **A** CAUTION

Do not add oil at any other location as improper unit operation may result.

- 9. Make sure that the unit is not running when adding oil, as this will make the oil charging process easier. Because the system is under pressure even when the unit is not running, it will be necessary to use a suitable pump (hand pump or electric pump) to add oil to the system.
- 10. Using a suitable pump, add <sup>1</sup>/<sub>2</sub> gal. (1.89 L) of Castrol Icematic<sup>®</sup> SW-220 Polyolester oil (absolutely no substitutes are approved) to the system. Make sure that the oil level safety switch is NOT jumpered, and allow the unit to restart and run normally. Do not exceed maximum oil change. See Table 37.

Table 37 — Factory Oil Charges

UNIT SIZE	CIRCUIT A (gal)	CIRCUIT A (L)	CIRCUIT B (gal)	CIRCUIT B (L)
30GX080-178	5.0	18.9	5.0	18.9
30GX204-268	7.0	26.5	5.0	18.9
30GX281-350	7.0	26.5	7.0	26.5
30HXA076-186	5.0	18.9	5.0	18.9
30HXC076-186	4.5	17.0	4.5	17.0
30HXA206-271	8.0	30.2	5.0	18.9
30HXC206-271	7.5	28.4	5.0	18.9

11. If low oil level problems persist, add another 1.89 L (<sup>1</sup>/<sub>2</sub> gal.) of oil. Continue adding oil in 1.89 L (<sup>1</sup>/<sub>2</sub> gal.) increments until the problem is resolved. If it is necessary to add more than 5.75 L (1.5 gallons) of oil to the system, contact your Carrier representative.

Oil Filter Maintenance - Each compressor has its own internal oil filter and each circuit also has an in-line external filter. The internal oil filter pressure drop should be checked and filter changed (if necessary) after the initial 200 to 300 hours of compressor operation. Oil line pressure loss is monitored by the control and reported for each compressor as the oil filter pressure drop. This information can be found in the Pressures mode of the Navigator for each circuit. The 'PRC.A' sub-mode contains oil filter pressure differentials for each Circuit A compressor (items 'FD.A1' 'FD.A2'). Similarly, the PRC.B sub-mode contains oil filter pressure differentials for each circuit B compressor (items FD.B1, FD.B2). This pressure differential (discharge pressure minus oil pressure, both from pressure transducer inputs) is typically 15 to 20 psi (103 to 138 kPa) for a system with clean internal and external filters. To determine the oil pressure drop due to the oil lines and external filter only, connect a gage to the oil pressure bleed port. Compare this value to the discharge pressure read at the Navigator. If this value exceeds 10 psi (69 kPa), replace the external filter. The difference between the gauge pressure and compressor oil pressure read at the Navigator is the pressure drop through the internal oil filter. Replace the internal oil filter if the pressure drop is greater than 25 psi (173 kPa) for 30HXC and 30 psi (207 kPa) for 30GXN,R and 30HXA chillers.

REPLACING THE EXTERNAL OIL FILTER

### **A** CAUTION

Compressor oil is pressurized. Use proper safety precautions when relieving pressure.

Fully front seat (close) the angle valve on the filter and the ball valve at the compressor. Connect a charging hose to the oil pressure bleed port and drain the oil trapped between service valves. A quart (liter) of oil is typically what is removed during this process. Remove the charging hose.

Unscrew the nut from the other side of the filter and remove the old filter. Remove protective plastic caps from new filter and install. Draw a vacuum at the bleed port. Remove charging hose. Open angle valve enough to let oil flow. Check both fittings for leaks and repair if necessary. Backseat angle valve and open ball valve.

REPLACING THE INTERNAL OIL FILTER — Close the service valves at the compressor and drain the oil using the bleed port. If the oil pressure does not bleed off using this method it will be necessary to remove the entire circuit charge. Using a <sup>3</sup>/<sub>4</sub>-in. Allen wrench, remove the internal filter access cover (see Fig. 30). Remove the old filter. Replacement filters (one for each compressor) are factory supplied to cover the first changeout. After that, filters are field supplied. Lightly oil O-ring in the filter and install with filter open end first into the housing. Replace access cover and retorque to 75 ft-lb (101 N-m). Follow procedure in previous section for opening angle valve and purging lines. Check for leaks and repair if necessary.

Compressor Changeout Sequence — Compressor service requires metric tools and hardware. Change compressors according to the following procedure:

- Turn off all main and control circuit power supplying the machine.
- Close the discharge and liquid valve(s), suction valve (if equipped), and cooler inlet line service valve (if equipped), oil line shutoff valve, and minimum load

- shutoff valve (if equipped) for circuit to be changed. Disconnect the oil inlet line from the compressor. Disconnect oil filter with fitting at shutoff valve side and set filter and compressor inlet line assembly aside.
- Remove any remaining refrigerant in the compressor and refrigerant lines using proper reclaiming techniques. All of the refrigerant that is in the cooler must be removed if there is no suction service valve installed on the cooler.

IMPORTANT: Cooler and condenser pumps must be energized. Fluid must be flowing through heat exchangers whenever adding or removing charge.

- 4. Remove junction box cover of compressor to be changed. Check main power leads for marked numbers. If no numbers are visible on leads, mark leads with appropriate numbers to match those printed on the ends of the terminal lugs. This is extremely important as power leads MUST be installed on the exact terminals from which they were removed.
- 5. Disconnect main power leads from compressor terminal lugs. Mark remaining control circuit wires (connected together with wire nuts) for ease of reconnecting later. The following color scheme applies (verify with label diagram on panel):

Loader 1 2 Violet wires Loader 2 2 Pink wires

Motor Cooling Solenoid 1 Blue wire, 1 Brown wire \*
Oil Solenoid 1 Orange wire, 1 Brown wire\*

High-Pressure Switch 2 Red wires

\*One lead from the motor cooling and oil solenoids are connected together with a single brown wire.




Fig. 30 — Compressor Component Diagram


- 6. Remove loader (mark solenoids no. 1 and 2 for replacement) and oil solenoids and high-pressure switch from compressor. Using 2 wrenches, carefully remove the oil pressure transducer from the compressor. These will all be reconnected to the replacement compressor.
  - NOTE: Some oil will leak out of the transducer fitting when the transducer is removed. See Fig. 30.
- Mark motor temperature leads (2 blue wires) and remove from quick connect terminals in the junction box.

#### **A** CAUTION

The next steps involve compressor unbolting and removal. Compressor seals are made using O-rings. Use care when removing bolts and disconnecting flanges. The O-rings must NOT be re-used. New O-rings are provided with the replacement compressor. The 06N screw compressors weigh approximately 920 lb (417 kg). Be sure that an appropriate lifting cart or hoist is used to avoid injury. See Fig. 31 for lifting locations and center of gravity dimensions. Make sure compressor is properly rigged before unbolting.

- 8. Remove the 2 bolts securing the motor cooling/economizer line flange to the compressor.
- 9. Remove the four M14 bolts securing the discharge line flange to the compressor. Two of the bolts also secure the mounting bracket for the external oil filter. Support the oil line to prevent damage to the line while the compressor is being changed. For 30GX units, place temporary protection over coils to prevent fin and tube damage.
- Move lifting apparatus into place and attach to the 2 lifting rings on the compressor. Apply minimal tension to hold the compressor while the remaining bolts are removed.
- Remove the <sup>3</sup>/<sub>8</sub>-in. holddown bolt securing the foot at the discharge end of the compressor to the mounting bracket on the cooler. A foot bracket will be mounted to the replacement compressor.
- 12. Remove the 4 lockwashers and nuts securing the compressor to the suction flange of the cooler. The compressor is held in place using four M14 x 2 studs through the suction nozzle of the cooler. The studs have an E-12 external Torx drive head. If possible, remove studs; if studs hit the cooler insulation, leave them in place they will not interfere with compressor removal or installation. Save all the hardware as it will be needed to install the replacement compressor.


#### LIFTING LUGS BOTH OUTSIDE EDGES EQUIDISTANT FROM GEAR COVER END



NOTE: Locate strap from center of gravity lifting ring and support motor casing to provide 3-point level rigging.

Fig. 31 — Compressor Lifting Diagrams

- 13. After checking to ensure all lines, wires, conduits, etc. are free and out of the way, remove compressor from cooler. Apply a light film of O-ring grease to new O-ring and place back into groove in mounting flange of compressor. If the new compressor is the A1/A2 (30HX units), A2 (30GXN,R204-268 units) or B2 (30GXN,R281-350 units) compressor, remove the compressor junction box and rotate it 180 degrees. Tighten screws to 6.8 to 9.5 N-m (5 to 7 ft-lb). The A1 and A2 compressors are on the right side of the unit when facing the unit control box.
- 14. Remove suction cover plate and bolts from new compressor and set compressor on unit flange. Thread the studs all the way back into the compressor. Install the 4 lock washers and nuts finger-tight. Tighten bolts in a crossing pattern to a range of 81.4 to 135.6 N-m (60 to 100 ft-lb). Do NOT overtighten as damage may result to O-ring. Install and tighten holddown bolt in mounting foot.
- Remove motor cooling/economizer and discharge line cover plates from new compressor.
- 16. Apply a light film of O-ring grease to motor cooling/economizer and discharge line O-rings, place back into grooves and install flange bolts. Tighten discharge line bolts in a crossing pattern to a range of 81.4 to 135.6 N-m (60 to 100 ft-lb). Tighten motor cooling/economizer bolts to a range of 81.4 to 108.5 N-m (60 to 80 ft-lb). Do NOT overtighten as damage may result to O-rings.
- 17. Reconnect the oil filter to the shutoff valve and oil line to the compressor. Install oil line straight into fitting until ferrule seats against fitting. Thread packing nut onto fitting and tighten finger tight. Use a backup wrench to finish tightening the nut. Do not overtighten.
- Reinstall the loader and oil solenoids, high-pressure switch, and oil pressure transducer. Make sure the loader solenoids are installed on the correct number loader.
- 19. Reconnect conduits back into compressor junction box. Reconnect all wiring that was removed in Steps 4, 5, and 7. Temporarily install the reverse rotation low pressure switch that is supplied with the replacement compressor. Connect the switch to the second high pressure port using a standard <sup>1</sup>/<sub>4</sub>-in. service hose. The switch will not reset until 10 psig of pressure is present on the switch. Temporarily wire the reverse rotation low pressure switch in series with the compressor's high pressure switch as shown in Fig. 32.
- 20. Leak check compressor and refrigerant lines with nitrogen. Repair any leaks found. Remove nitrogen from system. Evacuate compressor and refrigerant lines. Refer to the Refrigerant Charging/Adding Charge and Oil Charging/Low Oil Recharging sections on pages 55 and 56 for recharging procedures.
- 21. Open all shutoff valves and leak check the circuit and all fittings and joints. Repair any leaks found.
- 22. Reset the reverse rotation low pressure switch.
- 23. Restore main and control power to the machine. Put the Enable/Off/Remote Contact switch in the Enable position. Using the Navigator under the Service Test mode, turn the TEST sub-mode 'On'. Under the OUTS sub-mode, test each compressor's oil and motor cooling solenoids (items 'MC.AÎ', 'OS.AÎ', etc.). Next, locate and test each loader solenoid under the COMP sub-mode (items 'LD.A1', etc.). It is important that the loaders are located properly (loader 1 on right hand side when viewed from side opposite control box on 30HXA,HXC units, on left hand side when reaching over compressor to far side on 30GXN,R units).



LEGEND

HPS — High-Pressure Switch RRS — Reverse Rotation Switch (HK01CB002)

#### Fig. 32 — Reverse Rotation Switch Wiring

- 24. Locate the appropriate compressor item ('CC.A1', etc.) under the COMP sub-mode and start the compressor. Press [FITTER], followed by (a) to change the value to On, and then enter again. Once the compressor has successfully started, energize both loaders one at a time. Let the circuit stabilize with both loaders energized. Refer to the Refrigerant Charging/Adding Charge and Oil Charging/ Low Oil Recharging sections of this document for recharging procedures and performance criteria.
- 25. Once proper rotation has been verified, disconnect and lock out the power to the chiller. The reverse rotation low pressure switch can now be removed from the compressor and high pressure switch circuit.

BURNOUT CLEAN-UP PROCEDURE - If a screw compressor motor burns out on a 30GX,HX chiller, a simple cleanup should be performed. The following procedure provides the minimum steps to be taken before restarting the circuit.

- 1. Remove the oil from the oil separator. This can be facilitated by connecting a hose to the port located on the service valve entering the external oil filter. Run the hose to a container(s) that can hold up to 5 to 6 gallons (19 to 20 L) of oil. Pressurize the circuit to force out most of the oil in the separator. To remove the remaining oil, the pre-lube pump can be run in the Service Test mode from the Navigator. Enable the desired pump (either item 'OL.P.A' or 'OL.P.B' in the OUTS sub-mode). To vent wear to the pump components, do not allow the prelube pump to operate "dry."
- 2. Remove the failed compressor following the Compressor Changeout Sequence procedure on page 57.
- Once the compressor is removed access the oil catch pan through the cooler-compressor mounting flange. Clean out any debris which may have collected in the oil catch
- Install a new compressor.
- 5. To dilute and remove any residual oil left in the separator, pump approximately 1/2 gallon (2 L) of compressor oil into the oil separator using the Schrader port located on top of the separator (30GXN,R) or on the discharge line (30HXA,HXC) and remove using the pre-lube pump described in Step 1.
- 6. Disconnect the hose from the external oil filter service valve.
- 7. Install a new filter drier core and compressor external oil filter. If desired, a burnout (activated carbon) core may be used, but should be replaced with a standard filter drier core during the next filter replacement.
- 8. Measure in the amount of Castrol SW 220 Polyolester oil as specified on the nameplate of the chiller.
- 9. Leak check, evacuate and recharge the machine as described in this manual with the amount of R-134a stated on the chiller nameplate.
- 10. Perform periodic acid checks on the circuit and change the filter drier core in the liquid line as necessary. Use the Carrier Standard Service Techniques Manual as a source of reference.

Moisture-Liquid Indicator - Clear flow of liquid refrigerant indicates sufficient charge in the system. Note, however, that bubbles in the sight glass do not necessarily indicate insufficient charge. Moisture in the system is measured in parts per million (ppm), changes of color of indicator are:

Green - moisture is below 80 ppm;

Yellow-green (chartreuse) — 80 to 225 ppm (caution);

Yellow (wet) — above 225 ppm.

Change filter drier at the first sign of moisture in the system.

IMPORTANT: Unit must in operation for at least 12 hours before moisture indicator can give an accurate reading. With the unit running, the indicating element must be in contact with liquid refrigerant to give true reading.

Filter Drier — Whenever moisture-liquid indicator shows presence of moisture, replace filter drier core. Refer to Carrier Standards Service Technique Manual, Chapter 1, Refrigerants, for details on servicing filter driers. Cleanable strainers have been installed in each circuit's liquid line to aid in removal of system contaminants and debris. There is one industry standard drier core in each strainer. See Fig. 33.

Liquid Line Service Valve — This valve is located ahead of the filter drier and provides a 1/4-in. Schrader connection (30GXN,R only) for field charging. In combination with compressor discharge service valve, each circuit can be pumped down into the high side for servicing.

Thermistors - To aid in verifying thermistor performance, resistances at various temperatures are listed for all thermistors (except motor thermistors) in Tables 38A-39B. See Table 40 for motor thermistor values.

LOCATION - General location of thermistor sensors and terminal connections in the control box are listed in Table 3.

THERMISTOR REPLACEMENT

#### **A** CAUTION

All thermistors are installed in wells and will slide out of the wells easily. The wells are under refrigerant pressure (cooler EWT and LWT are under waterside pressure) and do not need to be removed to replace a faulty thermistor.

To Replace Thermistors T1, T2, T3, T4, T5, or T6 (Entering, Leaving Water; Discharge Gas Temperature) — Disconnect appropriate connector from the Main Base Board (MBB) or Screw Compressor Board (SCB). Thermistors T1 and T2 are connected to MBB-J8 and thermistors T3 through T6 are connected to EXV-J5. These six thermistors use insulation displacement connectors. New thermistors should be spliced to existing wiring close to the connector unless new connectors are required. A special AMP crimping tool, part no. 58580-1, is needed if new connectors are used. Remove thermistor cable from harness. Remove and discard original thermistor from well. Insert new thermistor in well body to its full depth. Add a small amount of thermal conductive grease to thermistor probe and well. Thermistors are friction-fit thermistors and will slip back into well located at the cooler head (T1, T2) or at the top of each compressor discharge line (T3 through T6). Secure thermistor to well body with a wire tie to prevent thermistor from working its way out of the well. See Fig. 34.

<u>To Service Compressor Motor Thermistors</u> — Two thermistors are factory installed in each compressor. Connections for the thermistors are located in the compressor junction box. There are 3 terminals for the thermistors: S1, S2, and C. Motor temperature is measured by leads connected to one of the S terminals and the C terminal. If a compressor motor thermistor failure occurs, verify that there is a true short or open circuit at

these terminals. If one of the thermistors fails, disconnect and relocate the wire on one of the S terminals to the other S terminal (S1 to S2 or S2 to S1). The thermistors are not serviceable in the field. If both of the compressor motor thermistors fail, compressor replacement is required. See Table 40 for motor thermistor temperature and resistance values.





Fig. 33 — Filter Drier



60

Table 38A — 5K Thermistor Temperature (°F) vs Resistance/Voltage

	T		-				- 1	
TEMP (F)	VOLTAGE DROP (V)	RESISTANCE (Ohms)	TEN (F		RESISTANCE (Ohms)	TEMI (F)	VOLTAGE DROP (V)	RESISTANCE (Ohms)
-254322109817651432110987654321012345678901123145678901123456789013333356789011234567890123345678901233456789012334567890123345678901555555555555555555555555555555555555	3.699 3.689 3.689 3.689 3.668 3.657 3.668 3.658 3.6364 3.6361 3.583 3.576 3.5533 3.365 3.264 3.264 3.265 3.2663 3.2663 3.2764 2.972 2.9879 2.8879	98,010 94,707 91,522 88,449 85,486 85,827 79,871 77,212 74,648 72,175 69,790 65,272 63,133 61,070 59,081 57,162 55,311 53,526 51,804 50,143 48,541 46,996 42,679 41,339 40,047 38,800 37,596 32,176 31,202 30,260 29,351 28,473 32,176 31,202 30,260 29,351 28,477 32,1779 21,153 22,1779 21,153 22,427 21,779 21,153 20,547 19,960 19,393 18,843 18,311 17,796 17,297 16,814 14,214 13,826 13,449 13,084 12,387 12,053 11,730	55 66 66 66 66 66 67 77 77 77 77 77 77 77	1.956 1.930 1.905 1.905 1.879 1.879 1.829 1.804 7.1.779 1.754 1.729 1.705 1.681 1.632 1.606 1.585 1.562 1.598 1.516 1.493 1.470 1.448 1.426 1.494 1.381 1.340 1.319 1.298 1.278 1.217 1.198 1.179	7,686 7,686 7,668 7,468 7,277 7,091 6,735 6,594 6,238 6,081 5,781 5,697 5,361 5,497 5,361 5,497 5,361 4,876 4,875 4,622 4,511 4,400 3,906 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,914 4,000 3,916 4,000 3,916 4,000 3,917 1,917 1,917 1,917 1,917 1,917 1,917 1,917 1,917 1,918 1,860 1,750 1,617 1,618 1,617 1,618 1,617 1,618 1,617 1,618 1,619 1,419	143 144 145 146 147 148 149 150 151 152 153 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 1772 173 174 175 180 181 182 183 184 185 189 190 191 192 203 204 205 206 207 208 209 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225	0.511 0.502 0.494 0.485 0.477 0.469 0.461 0.453 0.445 0.438 0.430 0.416 0.402 0.395 0.381 0.375 0.362 0.356 0.350 0.344 0.339 0.333 0.327 0.317 0.311 0.296 0.282 0.277 0.272 0.268 0.289 0.255 0.251 0.247 0.243 0.299 0.255 0.251 0.247 0.243 0.299 0.255 0.251 0.247 0.213 0.210 0.206 0.201 0.217 0.213 0.210 0.206 0.201 0.217 0.213 0.210 0.206 0.207 0.194 0.191 0.188 0.195 0.153 0.161 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.165 0.163 0.164 0.144 0.144 0.144 0.144 0.144 0.144 0.144 0.144 0.144 0.144 0.138 0.135 0.133	1,190 1,165 1,141 1,118 1,095 1,072 1,050 1,029 1,050 1,029 1,050 1,029 1,007 986 965 945 9925 906 887 8887 8888 850 8315 798 782 765 734 779 765 690 663 650 663 663 6626 614 602 591 581 551 553 524 516 508 501 494 487 480 473 461 450 445 439 424 419 415 410 405 401 396 381 391 386 382 377 361 356 350 344 338 332 325 318 311 304 297 289 282

Table 38B — 5K Thermistor Temperature (°C) vs Resistance/Voltage

TEMP (C)	VOLTAGE DROP (V)	RESISTANCE (Ohms)		TEMP (C)	VOLTAGE DROP (V)	RESISTANCE (Ohms)		TEMP (C)	VOLTAGE DROP (V)	RESISTANCE (Ohms)
-32	3.705	100,260		15	1.982	7,855		62	0.506	1,158
-31	3.687	94,165		16	1.935	7,499		63	0.490	1,118
-30	3.668	88,480		17	1.889	7,161		64	0.475	1.079
-29	3.649	83,170		18	1.844	6,840		65	0.461	1,079
-28	3.629	78,125		19	1.799	6,536		66	0.447	1,006
-27	3.608	73,580		20	1.754	6,246		67	0.433	971
-26	3.586	69,250		21	1.710	5,971		68	0.420	938
-25	3.563	65,205		22	1.666	5.710		69	0.420	906
-24	3.539	61,420		23	1.623	5,461		70	0.395	876
-23	3.514	57,875	**	24	1.580	5,225		71	0.383	
-22	3.489	54,555		25	1.538	5,000		72	0.371	836
-21	3.462	51,450		26	1.497	4,786		73	0.360	805
-20	3.434	48,536		27	1.457	4,583		74		775
-19	3.406	45,807		28	1.417	4,389		75	0.349	747
-18	3.376	43,247		29	1.378	4,204		76	0.339	719
-17	3,345	40,845		30	1.340	4,028	98		0.329	693
-16	3.313	38,592		31	1.302	3,861		77 78	0.319	669
-15	3.281	38,476		32	1.265	3,701			0.309	645
-14	3.247	34,489		33	1.229	3,549		79	0.300	623
-13	3.212	32,621		34	1.194	3,404		80 81	0.291	602
-12	3,177	30.866	22	35	1.160	3,266		82	0.283	583
-11	3.140	29,216		36	1.126	3,134		83	0.274	564
-10	3.103	27,633		37	1.093	3,008		84	0.266	547
-9	3.065	26,202		38	1.061	2,888		85	0.258	531
-8	3.025	24,827		39	1.030	2,773		86	0.251	516
-7	2.985	23,532		40	0.999	2,663		87	0.244	502
-6	2.945	22,313		41	0.969	2,559		88	0.237	489
-5	2.903	21,163		42	0.940	2,459			0.230	477
-4	2.860	20,079		43	0.912	2,363		89	0.223	466
-3	2.817	19,058		44	0.885	2,272		90	0.217	456
-2	2.774	18,094		45	0.858	2,184		91	0.211	446
-1	2.730	17,184		46	0.832	2,101		92	0.204	436
0	2.685	16,325		47	0.807	2.021	*	93	0.199	427
1	2.639	15,515		48	0.782	1,944		94	0.193	419
2	2.593	14,749		49	0.758	1,871		95	0.188	410
3	2.547	14,026		50	0.735	1,801		96	0.182	402
4	2.500	13.342		51	0.713	1,734		97	0.177	393
5	2.454	12,696		52	0.691	1,734		98	0.172	385
6	2,407	12,085		53	0.669	1,609		99	0.168	376
7	2.360	11,506		54	0.649	1,550		100	0.163	367
8	2.312	10,959		55	0.629	1,550		101	0.158	357
9	2.265	10,441		56	0.610	1,439		102	0.154	346
10	2.217	9,949		57	0.591	1,387		103	0.150	335
11	2.170	9,485		58	0.573			104	0.146	324
12	2.123	9,044		59	0.555	1,337 1,290		105	0.142	312
13	2.076	8,627		60	0.538	1,290		106	0.138	299
14	2.029	8.231		61	0.538	1,244	-	107	0.134	285

Table 39A — 10K Thermistor Temperatures (°F) vs Resistance/Voltage Drop (For Thermistor T10)

	TEMP (F)	VOLTAGE DROP (V)	RESISTANCE (Ohms)	TEMP (F)	VOLTAGE DROP (V)	RESISTANCE (Ohms)	TEMP (F)	VOLTAGE DROP (V)	RESISTANCE (Ohms)
	-25 -24 -23	4.758 4.750 4.741	196,453 189,692 183,300	61 62 63	2.994 2.963 2.932	14,925 14,549 14,180	147 148 149	0.890 0.876 0.862	2,166 2,124 2,083
	-22 -21	4.733	177,000	64	2.901	13,824	150	0.848	2,043
	-20	4.724 4.715	171,079 165,238	65 66	2.870 2.839	13,478 13,139	151 152	0.835 0.821	2,003 1,966
	-19	4.705	159,717	67	2.808	12,814	153	0.808	1,928
	-18 -17	4.696 4.686	154,344 149,194	68 69	2.777 2.746	12,493 12,187	154 155	0.795 0.782	1,891
	-16	4.676	144,250	70	2.715	11,884	156	0.770	1,855 1,820
	-15 -14	4.665 4.655	139,443 134,891	71 72	2.684 2.653	11,593 11,308	157	0.758	1,786
	-13	4.644	130,402	73	2.622	11,031	158 159	0.745 0.733	1,752 1,719
	-12 -11	4.633 4.621	126,183 122,018	74 75	2.592 2.561	10,764 10,501	160	0.722	1,687
	-10	4.609	118,076	76	2.530	10,249	161 162	0.710 0.699	1,656 1,625
	-9 -8	4.597 4.585	114,236 110,549	77 78	2.500 2.470	10,000 9,762	163	0.687	1,594
	-7	4.572	107,006	79	2.439	9,526	164 165	0.676 0.666	1,565 1,536
	-6 -5	4.560 4.546	103,558 100,287	80 81	2.409 2.379	9,300 9,078	166	0.655	1,508
	-4	4.533	97,060	82	2.349	8,862	167 168	0.645 0.634	1,480 1,453
	-3 -2	4.519 4.505	94,020 91,019	83 84	2.319 2.290	8,653 8,448	169	0.624	1,426
	-1	4.490	88,171	85	2.260	8,251	170 171	0.614 0.604	1,400 1,375
	0	4.476 4.461	85,396 82,729	86 87	2.231	8,056	172	0.595	1,350
		4.445	80,162	88	2.202 2.173	7,869 7,685	173 174	0.585 0.576	1,326 1,302
	2 3 4	4.429 4.413	77,662 75,286	89	2.144	7,507	175	0.567	1,278
	5	4.397	72,940	90 91	2.115 2.087	7,333 7,165	176 177	0.558 0.549	1,255 1,233
	6	4.380 4.363	70,727 68,542	92 93	2.059	6,999	178	0.540	1,211
	7	4.346	66,465	94	2.030 2.003	6,838 6,683	179 180	0.532 0.523	1,190 1,169
	9 10	4.328 4.310	64,439 62,491	95 96	1.975 1.948	6,530	181	0.515	1,148
	11	4.292	60,612	97	1.921	6,383 6,238	182 183	0.507 0.499	1,128 1,108
	12 13	4.273 4.254	58,781 57,039	98 99	1.894	6,098	184	0.491	1,089
	14	4.235	55,319	100	1.867 1.841	5,961 5,827	185 186	0.483 0.476	1,070 1,052
	15 16	4.215 4.195	53,693 52,086	101 102	1.815 1.789	5,698	187	0.468	1,033
	17	4.174	50,557	103	1.763	5,571 5,449	188 189	0.461 0.454	1,016 998
	18 19	4.153 4.132	49,065 47,627	104 105	1,738 1,713	5,327	190	0.447	- 981
	20	4.111	46,240	106	1.688	5,210 5,095	191 192	0.440 0.433	964 947
	21 22	4.089 4.067	44,888 43,598	107 108	1.663 1.639	4,984 4,876	193	0.426	931
	23	4.044	42,324	109	1.615	4,769	194 195	0.419 0.413	915 900
	24 25	4.021 3.998	41,118 39,926	110 111	1.591 1.567	4,666 4,564	196	0.407	885
	26	3.975	38,790	112	1.544	4,467	197 198	0.400 0.394	870 855
	27 28	3.951 3.927	37,681 36,610	113 114	1.521 1.498	4,370 4,277	199	0.388	841
	29	3.903	35,577	115	1.475	4.185	200 201	0.382 0.376	827 814
	30 31	3.878 3.853	34,569 33,606	116 117	1.453 1.431	4,096 4.008	202	0.370	800
	32	3.828	32,654	118	1.409	3,923	203 204	0.365 0.359	787 774
	33 34	3.802 3.776	31,752 30,860	119 120	1.387 1.366	3,840	205	0.354	762
	35	3.750	30,009	121	1.345	3,759 3,681	206 207	0.349 0.343	749 737
	36 37	3.723 3.697	29,177 28,373	122 · 123	1.324 1.304	3,681 3,603	208	0.338	725
	38	3.670	28,373 27,597	124	1.284	3,529 3,455 3,383	209 210	0.333 0.328	714 702
	39 40	3.654 3.615	26,838 26,113	125 126	1.264 1.244	3,383 3,313	211	0.323	691
- 1	41	3.587	25,396 24,715	127	1.225	3,244 3,178	212 213	0.318 0.314	680 670
	42 43	3.559 3.531	24,715	128 129	1.206 1.187	3,178 3,112	214 215	0.309	659
	44	3.503	23,399	130	1.168	3,049	216	0.305	649 639
	45 46	3.474 3.445	24,042 23,399 22,770 22,161	131 132	1.150 1.132	3,049 2,986 2,926	217	0.296	629
	47	3.416	21.573	133	1.114	2,866	218 219	0.292 0.288	620 610
	48 49	3.387	20,998	134 135	1.096 1.079	2,809	220	0.284	601
	50	3.328	19,903	136	1.062	2,752 2,697	221	0.279 0.275	592 583
	51	3.298 3.268	19,386 18.874	137 138	1.045 1.028	2.643	223	0.272	574
	53	3.238	19,903 19,386 18,874 18,384	139	1.012	2,590 2,539	224	0.268 0.264	566 557
5	54	3.208 3.178	17,904 17,441	140 141	0.996 0.980	2,488 2,439 2,391			
5	56	3.147 3.117	16,991 16,552	142	0.965	2,391		\$	Œ
5	58	3.086	16,131	143 144	0.949 0.934	2,343 2,297			
	59 50	3.056 3.025	15,714 15,317	145 146	0.919 0.905	2,297 2,253 2,209			
		0.020	10,017	140	0.805	2,209			

Table 39B — 10K Thermistor Temperatures (°C) vs Resistance/Voltage Drop (For Thermistor T10)

TEMP	VOLTAGE	RESISTANCE	TEMP	VOLTAGE	- BHOLOWALLE	• • • • • • • • • • • • • • • • • • • •		
(C)	DROP (V)	(Ohms)	(C)	DROP (V)	RESISTANCE (Ohms)	TEMP (C)	VOLTAGE	RESISTANCE
-32	4.762	200,510	15	3.056	15,714	62	DROP (V)	(Ohms)
-31 -30	4.748	188,340 177,000	16	3.000	15,000	63	0.940	2,315
-30 -29	4.733	177,000	17	2.944	14,323	64	0.813	2,235
-28	4.716	166,342	18	2.889	13,681	65	0.862	2,157 2,083
-26 -27	4.700	156,404	19	2.833	13,071	66	0.837	2,083
-27 -26	4.682 4.663	147,134 138,482	20	2.777	12,493	67	0.813	2,011 1,943
-25	4.644	138,482	21	2.721	11,942	68	0.790	1,876
-24	4.624	130,402	22	2.666	11,418	69	0.767	1,813
-23	4.602	122,807	23	2.610	10,921	70	0.745	1,752
-22	4.580	115,710 109,075	24	2.555	10,449	71	0.724	1,732
-21	4.557	102,868	25	2.500	10,000	72	0.703	1 637
-20	4.533	97,060	26 27	2.445	9,571	73	0.683	1.582
-19	4.508	91,588	28	2.391	9,164	74	0.663	1.530
-18	4.482	86,463	29	2.337 2.284	8,776	75	0.645	1,693 1,693 1,637 1,582 1,530 1,480
-17	4.455	81,662	30	2.284	8,407	76	0.626	1,431
-16	4.426	77,162	31	2.178	8,056	77	0.608	1,385
-15	4.397	72,940	32	2.127	7,720	78	0.591	1,340
-14	4.367	77,162 72,940 68,957	33	2.075	7,401 7,096	79	0.574	1,431 1,385 1,340 1,297 1,255 1,215
-13	4.335	65,219	34	2.025	6,806	80	0.558	1,255
-12	4.303	61.711	35	1.975	6,530	81 82	0.542	1,215
-11	4.269	58,415 55,319	36	1.926	6,266	83	0.527	1,177
-10	4.235	55,319	37	1.878	6,014	84	0.512	1,140
-9	4.199	52,392	38	1.830	5,774	85	0.497 0.483	1,104
-8 -7	4.162	49,640	39	1.784	5,546	86	0.483	1,070
-6	4.124	47,052	40	1.738	5,327	87	0.457	1,037 1,005
_5	4.085 4.044	44,617	41	1.692	5,117	88	0.444	974
-4	4.003	42,324 40,153	42	1.648	4,918	89	0.431	944
-3	3.961	38,109	43	1.605	4,727	90	0.419	915
-2	3.917	36,182	44 45	1.562	4,544	91	0.408	889
-1	3.873	34,367	45	1.521	4,370	92	0.396	861
0	3.828	32,654	47	1.480 1.439	4,203	93	0.386	836
1	3.781	31.030	48	1.400	4,042	94	0.375	811
2	3.734	31,030 29,498	49	1.362	3,889 3,743	95	0.365	787
3	3.686	28.052	50	1.324	3,743	96	0.355	764
. 4	3.637	26.686	51	1.288	3,603 3,469	97 98	0.345	742
5 6	3.587	25,396 24,171	52	1.252	3,340	99	0.336	721
5	3,537	24,171	53	1.217	3.217	100	0.327 0.318	700
7 8	3.485	23,013 21,918	54	1.183	3.099	101	0.318	680
9	3.433	21,918	55	1.150	2,986	102	0.310	661 643
10	3.381	20,883	56	1.117	3,099 2,986 2,878	103	0.302	626
11	3.328 3.274	19,903	57	1.086	2,774	104	0.287	609
12	3.220	18,972 18,090	58	1.055	2,675	105	0.279	592
13	3.165	17,255	59	1.025	2,579	106	0.272	576
14	3.111	16,474	60 61	0.996	2,488	107	0.265	561
	V.TT	10,474	01	0.968	2,400			

Table 40 — Thermistor Temperature vs Resistance, Motor Temperature Thermistors

TEMP	TEMP	RESISTANCE
(F)	(C)	(Ohms)
-22 -13 -4 5 14 23 32 41 50 59 68 77 86 95 104 113 122 131 149 158 167 176 185 194 203 211 220 230 239 248	-30 -25 -25 -20 -15 -10 5 0 5 10 15 20 25 30 30 45 55 60 70 75 80 85 90 95 100 110 110 110 110 110 110	88,480.0 65,205.0 48,536.0 36,476.0 27,663.0 11,6325.0 12,696.0 9,949.5 7,855.5 6,246.0 5,000.0 4,028.4 3,265.7 2,663.2 2,184.2 1,801.2 1,493.1 1,243.9 1,041.4 875.8 739.7 627.6 534.9 457.7 393.3 339.3 293.8 255.3 222.6 194.8

NOTE: Motor temperature thermistor values must be verified using resistance. Voltage drop cannot be used.

Pressure Transducers — Discrete high and low pressure transducers are used for pressure sensing on all 30GXN,GXR,HX chillers. The discharge and oil pressure transducers are high pressure transducers, and the suction and economizer pressure transducers are low pressure transducers (white dot). No pressure transducer calibration is required. The transducers operate on a 5 vdc supply, which is generated by the Main Base Board (MBB) for suction and discharge pressure transducers and by the Screw Compressor Board (SCB) for the oil and economizer pressure transducers. See unit wiring labels for specific MBB and SCB pressure transducer power and signal connections. Refer to Fig. 35A-35C for pressure transducer locations.

TROUBLESHOOTING — If transducer is suspected of being faulty, first check supply voltage to transducer. Supply voltage should be 5 vdc  $\pm$  .2 v. If supply voltage is correct, compare pressure reading displayed on keypad and display module against pressure shown on a calibrated pressure gage. If the 2 pressure readings are not reasonably close, replace pressure transducer. Low pressure transducers suction and economizer-pressures should be within  $\pm$  2 psig. Discharge and oil pressures should be within  $\pm$  5 psig.

FLOW SENSOR — Figure 36 shows a typical view of the flow sensor as attached to a victaulic nozzle. It also shows the connector pin orientation of the sensor. If nuisance trips of the sensor are occurring, follow the steps below to correct the situation:

When power is supplied to the device, a warm-up period is initiated. During this period, the right-most green LED is lit and turned off as each LED to the left is successively lit until the left-most red LED is lit. The warm-up period may take up

to 30 seconds. When some flow is detected but not enough for machine operation, a red LED at the far left will be illuminated. With increasing flow, successive red LEDs illuminate. When the switch determines flow is present, the amber LED illuminates indicating the output has closed. This is not an indication of minimum flow. Increasing flow above the amber LED output indication illuminates the first green LED. Each successive green LED indicates greater flow. The switch closure does not indicate minimum flow for the machine. With one green LED lit, minor fluctuations in water flow may cause nuisance alarms. Additional green LEDs indicate higher flow rates, and can avoid the nuisance alarms. Refer to Fig. 37.

- Check to confirm that all strainers are clean, valves are open and pumps are running. For the case of VFD controlled pumps, ensure that the minimum speed setting has not been changed.
- Measure the pressure drop across the cooler and using Appendix E on pages 95-100, calculate the cooler flow and compare this to the system requirements.
- If the measured flow rate through the cooler agrees with the system requirements. At least 2 green LEDs should be lit
- 4. If the contacts do not close while two green LEDs are lit, verify operation of the flow switch relay. Without changing fluid flow through the cooler, check for power at the flow switch relay (FSR) coil. If power is not present, check continuity of flow sensor cable. If the sensor cable is not shorted or open when correct flow has been confirmed and the green sensor LEDs are lit, the sensor has failed and must be replaced.




Fig. 35A — 30HX Pressure Transducer Locations (2-Compressor Unit)

#### **LEGEND FOR FIG. 35A-35C**

DPT — Discharge Pressure Transducer EPT — Economizer Pressure Transducer

EXV — Electronic Expansion Valve
OPT — Oil Pressure Transducer
SPT — Suction Pressure Transducer




Fig. 35B — 30HX Pressure Transducer Locations (3-Compressor Unit)





Fig. 35C — 30GXN,R Pressure Transducer Locations (Top View)



1.61 [41]

2.83 [72]

M12 x 4 PIN MALE

2.36 [60]

1.38 [35]

3.25 [82.6]

24VAC BLU

EXTERNAL RELAY COIL

WIRING DIAGRAM

WIRING DIAGRAM

0.305 [7.75] [12]

\*And associated modular units.

Fig. 36 — 30GXN,R Flow Sensor




Fig. 37 — Chilled Water Flow Switch LED Display

**Safety Devices** — The 30GX,HX chillers contain many safety devices and protection logic built into the electronic control. Following is a description of the major safeties.

#### COMPRESSOR PROTECTION

Motor Overload — The compressor protection modules (CCP) protect each compressor against overcurrent. Do not bypass the current transducers or make any changes to the factory-installed and configured 8-pin headers. The configuration of these headers defines the Must Trip Amps (MTA) at which the CCP will turn the compressors off. Determine the cause for trouble and correct the problem before resetting the CCP. See Appendix A for setting of MTAs and configuration headers.

Each CCP board also reads the status of each compressor's high-pressure switch. All compressors have factory-installed high-pressure switches. See Table 41.

Table 41 — High-pressure Switch Settings

UNIT	SWITCH	SETTING
ONT	psig	kPa
30GX	303 ±7	2089 ±48
30HXA	275 ±7	1896 ±48
30HXC	191 ±7	1317 ±48

If the switch opens during operation, the compressor will be shut down. The CCP will reset automatically when the switch closes, however, a manual reset is required to restart the compressor.

OIL SEPARATOR HEATERS (30GX) — Each oil separator circuit has a heater mounted on the underside of the vessel. The heater is energized with control circuit power. Oil heaters are energized when the discharge gas temperature falls below 105 F (40.6 C). The heaters are deenergized when the discharge gas temperature rises above 110 F (43.3 C). The control will allow the chiller to attempt to start with the heaters energized and will keep the heaters on, even when running, until the discharge gas temperature reaches 110 F (43.3 C). Note that the oil heaters are deenergized if the oil level switch is open.

#### COOLER PROTECTION

Low Water Temperature — Microprocessor is programmed to shut the chiller down if the leaving fluid temperature drops below 34 F (1.1 C) for water or more than 8° F (4.4° C) below set point for brine units. When the fluid temperature rises 6° F (3.3° C) above the leaving fluid set point, the safety resets and the chiller restarts. Reset is automatic as long as this is the first occurrence of the day.

IMPORTANT: If the unit is installed in an area where ambient temperatures fall below 32 F (0° C), cooler heaters and inhibited ethylene glycol or other suitable solution must be used in the chilled fluid circuit.

Relief Devices — Fusible plugs are located in each circuit (30GXN,R only) between the condenser and the liquid line shutoff valve.

PRESSURE RELIEF VALVES — Valves are installed in each circuit and are located on all coolers. One relief valve is also installed on each 30HXC condenser. Both circuits' oil separators on 30GXN,R and 30HXA units have factory-installed relief valves as well. These valves are designed to relieve if an abnormal pressure condition arises. Relief valves on all coolers and 30HXC condensers relieve at 220 psi (1517 kPa). Relief valves on 30GXN,R and 30HXA oil separators relieve at 320 psi (2206 kPa). All 30HXA, HXC units with factory-installed suction service valves also have a relief valve in each compressor discharge line. These valves are designed to relieve at 350 psig (2413 kPa). These valves should not be capped. If a valve relieves, it should be replaced. If the valve is

not replaced, it may relieve at a lower pressure, or leak due to trapped dirt from the system which may prevent resealing.

Pressure relief valves located on cooler and condenser shells and 30HXA oil separator shells have  $^{3}/_{4}$ -in. NPT connections for relief. The 30GXN,R oil separators have  $^{1}/_{2}$ -in. male flare connections. Some local building codes require that relieved gases be removed. This connection allows conformance to this requirement.

#### **Control Modules**

#### **A** CAUTION

Turn controller power off before servicing controls. This ensures safety and prevents damage to controller.

MAIN BASE BOARD (MBB), SCREW COMPRESSOR BOARD (SCB), EXPANSION VALVE BOARD (EXV), ENERGY MANAGEMENT MODULE (EMM), COMFORTLINKTM COMPRESSOR PROTECTION BOARDS (CCP) AND THE NAVIGATOR — All of the ComfortLink modules perform continuous diagnostic evaluations of the condition of the hardware. Proper operation and communication of these modules is indicated by LEDs on the surface of each module (all except the Navigator that displays 'Communication Failure' when it occurs).

RED LED — All module red LEDs will blink in unison at a 1 to 2 second rate when communicating and functioning properly. Lighted continuously indicates a problem requiring replacement of module. Off continuously indicates power should be checked. If there is no input power, check fuses. If fuse is bad, check for shorted secondary of transformer, tripped circuit breaker or bad module. An LED blinking at a rate of twice per second indicates potential loss of program. The suspect board(s) should be downloaded using the SmartLoader program. If this is not successful, the module should be replaced.

GREEN LED — Each module has a green LED that should always be blinking when power is on. Each module's green LED will be blinking at different rates. This is a normal condition. If the green LED is not blinking, check the red LED. If the red LED is normal, verify that all communication connections (J3 for MBB, J3/J4 for SCB, EXV, EMM and J10/J11 for CCP1 and CCP2) are correct. If wiring is correct, check the Main Base Board instance jumper (should be set to '1'). The EXV, EMM and SCB module address switches should all be set to ON. For CCP1, switch 1 should be On and switches 2, 3 and 4 should be Off. For CCP2, switches 1,3 and 4 should be On and switch 2 should be Off. Remote terminal strip (TB3) connections are made to the Main Base Board at plug MBB-J5.

YELLOW LED — The Main Base Board (MBB) has a yellow LED. This light will blink whenever CCN (Carrier Comfort Network) communications are in progress. Only the MBB is designed to communication on the CCN bus. All other modules (including the Navigator) are designed to communicate only on the LEN bus.

The majority of the system operating intelligence resides in the MBB, however each individual module does have its own operating software. The machine operator communicates with the MBB through the Navigator. Communications between all modules is accomplished by a 3-wire sensor bus called the Local Equipment Network (LEN). These 3 wires run in parallel from module to module.

For all models, control modules are powered by 24 vac power sources protected by circuit breakers. Separate power sources are used for the CCP modules. Refer to the 24-v wiring schematic located on the chiller for detailed information. Refer to Table 42 for control troubleshooting information.

Table 42 — Compressor Control Troubleshooting

SYMPTOMS	CAUSE	REMEDY
COMPRESSOR DOES NOT RUN	Power line open Control fuse open High-Pressure Switch (HPS) tripped Loose terminal connection Improperly wired controls Low line voltage Compressor motor defective Seized compressor Pre-lubrication not successful	Check main disconnect. Check control circuit for ground or short. Replace fuse. Use Navigator to reset current alarms. Check connections from CCP to contactor Check wiring and rewire. Check line voltage. Determine location of voltage drop and remedy deficiency. Check motor winding for open or short. Replace compressor if necessary. Replace compressor. Check oil pump operation, oil pressure transducer, verify oil sole- noid valve operation.
COMPRESSOR CYCLES OFF ON LOW SATURATED SUCTION TEMPERATURE	Loss of charge Bad transducer Low refrigerant charge Failed expansion device Partially plugged or plugged strainer	Repair leak and recharge. Replace transducer. Add refrigerant. Repair/replace as needed. Remove and clean strainer.
COMPRESSOR SHUTS DOWN ON HIGH PRESSURE CONTROL	High-pressure switch erratic in action Compressor discharge valve partially closed Condenser fan(s) not operating (air cooled units) Condenser coil plugged or dirty (air cooled units) Condenser water valve not operating (water cooled units) Circuit overcharged	Replace switch. Open valve or replace if defective. Check wiring. Repair or replace motor(s) if defective. Clean coil. Check wiring. Repair or replace valve if defective. Clean condenser.
UNIT OPERATES LONG OR CONTINUOUSLY	Low refrigerant charge Control contacts fused Partially plugged or plugged strainer Defective insulation Service load exceeding design capacity Inefficient compressor	Add refrigerant. Replace control. Clean or replace. Replace or repair. Evaluate load requirements. Check loader solenoid valves. Replace if necessary.
SYSTEM NOISES	Piping vibration Expansion valve hissing Compressor noisy	Support piping as required. Add refrigerant. Check for plugged liquid line strainer. Replace compressor (worn bearings). Check for loose compressor bolts securing compressor to cooler.
COMPRESSOR LOSES OIL	Leak in system Mechanical damage to rotors	Find and repair leak. Replace compressor.
HOT LIQUID LINE	Shortage of refrigerant due to leak	Repair leak and recharge,
FROSTED LIQUID LINE	Shutoff valve partially closed or restricted	Open valve or remove restriction.
COMPRESSOR LOADERS NOT WORKING PROPERLY	Burned out coil Defective loader solenoid valve Miswired solenoid	Replace valve. Rewire correctly.

### Carrier Comfort Network (CCN) Interface -

The 30GX,HX chiller units can be connected to the CCN if desired. The communication bus wiring is a shielded, 3-conductor cable with drain wire and is supplied and installed in the field. The system elements are connected to the communication bus in a daisy chain arrangement. The positive pin of each system element communication connector must be wired to the positive pins of each system element. Wiring connections for CCN can be made at terminal block TB3. There are four terminals (including shield) located at TB3 for permanent CCN connection. For temporary CCN connection to the chiller, there is also an RJ-11 (6 position, 6 conductor) connector. The connector is for field connection of a laptop computer running Service Tool or ComfortVIEW<sup>TM</sup> software programs. Consult CCN Contractor's Manual for further information.

NOTE: Conductors and drain wire must be 20 AWG (American Wire Gage) minimum stranded, tinned copper. Individual conductors must be insulated with PVC, PVC/nylon, vinyl, Teflon, or polyethylene. An aluminum/polyester 100% foil shield and an outer jacket of PVC, PVC/nylon, chrome vinyl, or Teflon with a minimum operating temperature range of –20 C to 60 C is required. Wire manufactured by Alpha (2413 or 5463), American (A22503), Belden (8772), or Columbia (02525) meets the above mentioned requirements.

It is important when connecting to a CCN communication bus that a color coding scheme be used for the entire network to simplify the installation. It is recommended that red be used for the signal positive, black for the signal negative, and white for the signal ground. Use a similar scheme for cables containing different colored wires. At each system element, the shields of its communication bus cables must be tied together. If the communication bus is entirely within one building, the resulting continuous shield must be connected to a ground at one point only. If the communication bus cable exits from one building and enters another, the shields must be connected to grounds at the lightning suppressor in each building where the cable enters or exits the building (one point per building only).

IMPORTANT: A shorted CCN bus cable will prevent some routines from running and may prevent the unit from starting. If abnormal conditions occur, disconnect the CCN bus. If conditions return to normal, check the CCN connections and cable. Run new cable if necessary. A short in one section of the bus can cause problems with all system elements on the bus.

Replacing Defective Modules — The ComfortLink<sup>TM</sup> replacement modules are shown in Table 43. The unit model and serial numbers are printed on the unit nameplate located on an exterior corner post (30GX) or the corner of the control box (30HX). The basic software and unit configuration data is factory installed by Carrier in the replacement module. Therefore, when ordering any replacement module, specify the replacement part number (located on each module front or back), full unit model number and serial number. The replacement modules will be downloaded with the basic software. If the Main Base Board (MBB) has been replaced, verify that all configuration data is correct. Follow the Configuration mode table and verify that all items under sub-modes UNIT, OPT1 and OPT2 are correct. Any additional field installed accessories or options (sub-mode RSET,SLCT) should also be verified.

Table 43 — Replacement Module Part Number

MODULE	REPLACEMENT PART NUMBER (With Software)	REPLACEMENT PART NUMBER (Without Software)
Main Base Board (MBB)	30GX506748	HK50AA029
Expansion Valve Board (EXV)	30HX515217	HK50AA026
Screw Compressor Board (SCB)	30HX501316	HK50AA032
Navigator Display	HK50AA033	N/A
Energy Management Module (EMM)	30HX515218	HK50AA028
ComfortLink™ Compressor Protection Boards (CCP1, CCP2)	HN67LM103	N/A

Refer to the Start-Up Checklist for 30GXN,GXR,HX Liquid Chillers (completed at time of original start-up) found in the job folder. This information is needed later in this procedure. If the checklist does not exist, fill out the current information in the Configuration mode on a new checklist. Tailor the various options and configurations as needed for this particular installation.

#### **A** CAUTION

Electrical shock can cause personal injury. Disconnect all electrical power before servicing.

- 1. Check that all power to unit is off. Carefully disconnect all wires from the defective module by unplugging its connectors. Remove the screw securing the communication drain wire (CCP modules only). Save the screws.
- 2. Remove the defective module by removing its mounting screws with a Phillips screwdriver, and removing the module from the control box. Save the screws later use. For Navigator replacement, remove the screw securing the cable clamp near TB3.
- 3. Verify that the instance jumper (MBB) or address switches (all other modules) exactly match the settings of the defective module.
- 4. Package the defective module in the carton of the new module for return to Carrier.
- Mount the new module in the unit's control box using a Phillips screwdriver and the screws saved in Step 2.
- 6. Reinstall all module connectors and communication drain wire (CCP modules only). For Navigator replacement, make sure the plug is installed at TB3 in the LEN connector.
- 7. Carefully check all wiring connections before restoring power.
- Verify the Enable/Off/Remote Contact switch is in the OFF position.
- Restore control power. Verify that all module red LEDs blink in unison. Verify that all green LEDs are blinking and that the Navigator is communicating correctly.
- 10. Verify all configuration information, settings, setpoints and schedules. Return the Enable/Off/Remote Contact switch to normal operation position.

Winter Shutdown Preparation — At the end of each cooling season the fluid should be drained from the system. However, due to the cooler circuiting, some fluid will remain in the cooler after draining. To prevent freeze-up damage to the cooler tubes perform the following procedure.

1. If cooler heaters have been installed, deenergize the heaters to prevent damage and possible safety hazards

- when draining, or when there is no liquid in the system. Remove Fuse 1 to deenergize the heaters. Drain the fluid from the system.
- 2. Isolate the cooler from the rest of the system with water shut off valves.
- 3. Completely fill the cooler with an appropriate amount of inhibited ethylene glycol solution (or other suitable corrosion-inhibitive antifreeze) for 15° F (8.3° C) below the expected low ambient conditions (5 gallon [19 L] minimum).
- 4. Leave the cooler filled with the antifreeze solution for the winter, or drain if desired. Be sure to deenergize heaters (if installed) as explained in Step 1 to prevent damage. Use an approved method of disposal when removing the antifreeze solution.
- 5. Update item W.DNE Winterization Performed (Configuration Mode, Sub-mode SERV) to YES. Winterization is complete.

#### Maintenance

RECOMMENDED MAINTENANCE SCHEDULE — The following are only recommended guidelines. Job site conditions may dictate that maintenance schedules be performed more frequently than listed here.

ROUTINE (as conditions dictate)

30GX machines with E-coat condenser coils:

- Check condenser coils for debris, clean as necessary
- Periodic clean water rinse, especially in coastal and industrial applications.

#### MONTHLY

30GX machines with E-coat Condenser Coils:

- Check condenser coils for debris, clean as necessary
- Coil cleaning with Carrier approved coil cleaner.

#### **EVERY 3 MONTHS**

#### All machines:

- Check all refrigerant joints and valves for refrigerant leaks, repair as necessary.
- Check moisture indicating sight glass for possible refrigerant loss and presence of moisture.
- Check oil filter pressure drops, replace as necessary.
- Check chilled water flow switch operation.

#### 30GX machines:

- Check condenser coils for debris, clean as necessary.
- Check condenser fan operation.

#### YEARLY:

#### All machines:

- Check all electrical connections. Tighten as necessary.
- Check accuracy of all transducers for each circuit, replace as necessary.
- Check accuracy of thermistors, replace if greater than ± 2° F (1.2° C) variance from calibrated thermometer.
- Obtain and test an oil sample, change as necessary.
- Clean cooler tubes if appropriate.
- Check to be sure that the proper concentration of antifreeze is present in the chilled water loop.
- Check to be sure that the proper amount of inhibitor is present in the chilled water loop.
  Check all refrigerant strainers and filter driers for
- pressure drops, replace/clean as necessary
- Check chilled water strainers, clean as necessary

#### 30GX machines:

- Check cooler heater operation
- Check condenser fan blades to insure they are securely fastened to the motor shaft and their condition.

#### 30HXC machines:

- Check Condenser Water Regulating Valve operation, if equipped.
- Clean condenser tubes if appropriate.
- · Check condenser water strainers, clean as necessary

#### PRE-START-UP PROCEDURE

IMPORTANT: Before beginning Pre-Start-Up or Start-Up, complete the Start-Up Checklist for the 30GX,HX Liquid Chillers on pages CL-1 to CL-10. This Checklist assures proper start-up of the chiller, and provides a record of unit condition, application requirements, system information and operation at initial start-up. The checklist should be removed from the manual and kept with the job file for future reference.

IMPORTANT: DO NOT ATTEMPT TO START THE CHILLER UNTIL THE FOLLOWING CHECKS HAVE BEEN COMPLETED.

#### **A** CAUTION

DO NOT make any changes to the factory-installed compressor power wiring in the control box or at the compressor junction box. Doing so will cause permanent damage to the compressor and will require compressor replacement. Proper phasing has already been checked at the factory.

#### System Check

- Check all auxiliary components such as the chilled fluid circulating pump, air-handling equipment, or other equipment to which the chiller supplies liquid. Consult the manufacturer's instructions. If the unit has field-installed accessories, be sure all are properly installed and wired correctly. Refer to the unit wiring diagrams.
- 2. Check the cooler flow switch for proper operation (item 'FLOW', Inputs mode under sub-mode GEN.I). Ensure sensor contacts close when the pump is on and open when the pump is turned off. A flow switch is factory installed on all models with two or more pass coolers. For single pass cooler models, the flow switch is factory supplied for field installation with factory-supplied victaulic nozzles.
- Open the discharge and liquid valves in each circuit. Both shutoff valves are in-line ball type and are open when stem is parallel with the refrigerant flow.
- 4. If factory-installed suction service valves are installed, open the suction service valves in each circuit. Service valve is located below the compressor in the cooler suction connection flange. To operate the valve, first remove the cap. Use a back-up wrench on the packing gland to prevent loosening while removing cap. Loosen the jam nut. Rotating the valve handle clockwise will close valve and counterclockwise will open valve. When closing the valve, the linkage arm must swing past center of the actuator shaft cam to seat and prevent accidental opening of the valve. Tighten the jam nut. See Fig. 38 and 39.
- Before filling the system with fluid following a winter shutdown, check the chilled water loop for pressure. Higher than atmospheric pressure could be the result of a refrigerant leak in the cooler.
- Open the oil shutoff valves located by the oil pre-filter, and the ball valve to each compressor.
- Check the tightness of all electrical connections. Check incoming power supply for proper nameplate voltage.




Fig. 38 - Suction Valve Detail






Fig. 39 — Suction Valve Handle Details

- Check to ensure the unit is level per the installation instructions.
- 9. Check all field configuration data and set points.
- 10. Enter correct date, time, and operating schedule(s).
- 11. Verify operation of solenoids, pumps, valves, compressors, fans, etc. as listed in the Start-Up Checklist.
- Open condenser water valves. Check condenser water pump for proper operation (30HXC).

#### START-UP AND OPERATION

Actual Start-Up — Actual start-up should be done only under supervision of a qualified refrigeration mechanic and qualified Carrier Comfort Network personnel.

- 1. Set leaving fluid temperature. No cooling range adjustment is necessary.
- Start chilled fluid pump and condenser pump (30HXC) if not controlled by unit.
- Switch Enable/Off/Remote Contact switch to Enable or Remote Contact.
- 4. Provided there is a load on the chiller, allow the machine to operate and confirm that everything is functioning properly. Verify that the leaving fluid temperature agrees with the cooling set point (1 or 2), or if reset is being used, the modified set point. Chiller is controlling to the Control Point (item 'CTPT') displayed on the Navigator.


Operating Sequence — The chiller is started by switching the Enable/Off/Remote Contact switch to either Enable or Remote Contact position. If cooler pump control is enabled, the cooler pump is started. If condenser pump control (30HXC) is enabled, the condenser pump is started. On a command for cooling, the oil pump is turned on to start the pre-lubrication process. After 20 seconds, the oil solenoid is opened and the control reads the oil pressure from the transducer and determines if sufficient pressure has been built up. If there is not sufficient pressure, an alarm is generated after the second attempt and the compressor is not started.

Upon building pressure, the compressor is allowed to start (after 15 seconds). For across-the-line (XL) start chillers, the compressor starts and comes up to full speed within 1 to 3 seconds. For Wye-Delta start chillers, contactors 1M and S (starter

contactor assembly) are closed and the compressor is started in a Wye configuration. This method reduces the locked rotor current requirements by approximately 60% while maintaining enough torque to bring the compressor up to full speed.

#### **FIELD WIRING**

Field wiring is shown in Fig. 40-54.



<sup>\*</sup> Dependant on control circuit power supply voltage.




Fig. 41 — Remote Alarm Relay Accessory Wiring; All Models, 115 or 230 V\*




Fig. 42 — Chilled Water Pump Relay Wiring; All Models, 115 or 230 V\*




Fig. 43 — Optional Ground Fault Interrupter; Convenience Outlet Accessory Wiring

### MAIN BASE BOARD




Fig. 44A — 30GXN,R Minimum Load Valve Accessory Wiring, 115 or 230 V\*

#### MAIN BASE BOARD




Fig. 44B — 30HX Minimum Load Valve Accessory Wiring, 115 or 230 V\*




Fig. 45 — Condenser Pump Relay Wiring; 30HXC and Remote Condenser Fan/Liquid Line Solenoid Valve Wiring; 30HXA 115 or 230 V\*




Fig. 46 — Chilled Water Interlock and Flow Switch Input Wiring




Fig. 47 — Remote On/Off Switch Input Wiring




Fig. 48 — Condenser Flow Switch Interlock and Entering/Leaving Water Thermistor Wiring; 30HXC Units




Fig. 49 — Remote Dual Setpoint Wiring; All Units




Fig. 50 — Outdoor-Air Thermistor ( $5K\Omega$  at 77 F [25 C]) and Space Temperature Sensor ( $10K\Omega$  at 77 F [25 C]) All Units, Field Supplied





Fig. 51 — Motormaster® Option; 30GXN,R Units



NOTE: Install a 500  $\Omega$  resistor across output terminals to convert output signal to 2-10 vdc.

Fig. 52 — Field-Supplied Head Pressure Device Wiring; 30HX Units






Fig. 53 — Service Port Option or Accessory Wiring; 30GX Units



NOTE: Use signal converter for input types other than 4-20 mA.

Fig. 54 — Energy Management Module Option or Accessory Wiring; All Units



# APPENDIX A

UNIT 30GXN,R	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	PUNCHOUTS FOR COMP B2	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIP AMPS SETTING	COMP B2 MUST TRIP AMPS SETTING
	575-60	1,2,3,5,8	_	1,2,3,4,8	_	94		· 78	
	380-60	1,2,4,8		1,2,4,5,6,8		142	_	118	
	230-60	1,3,6	_	1,3,4,5	-	232	_	192	
080	208/230-60	1,4,6,7,8	_	1,3,5,6,8	-	258		214	
	460-60	1,2,4,5,6,7	1	1,2,3,5	_	116		96	_
	230-50	1,4,5,6		1,3,4,8		248		206	
	380/415-50	1,2,5,6,8	_	1,2,4,5,7	_	150	_	124	
	575-60	1,2,3,5,6,7	1	1,2,3,4,6,8	_	84	_	70	
	380-60	1,2,4,5	_	1,2,3,7	_	128	_	108	
	230-60	1,3,5,6,7	_	1,2	8	212		176	
083	208/230-60	1,3,7,8	= =	1,3,4,6,7	_	234		196	
	460-60	1,2,3,7,8	_	1,2,3,5,6		106		88	
	230-50	1,3,5	-	1,3,4,5,6,8		224		182	
	380/415-50	1,2,4,6,8	i—	1,2,3,8		134		110	
	575-60	1,2,4,5,6,7		1,2,3,4,8		116		78	
)	380-60	1,2	_	1,2,4,5,6,8		176		118	
1	230-60	1,5	-	1,3,4,5		288			
090	208/230-60	2,3,4,5,7,8		1,3,5,6,8		314		192	
	460-60	1,2,4	14	1,2,3,5		144		214	
	230-50	2,3,4,5,6,7		1,3,4,8		308		96	
	380/415-50	1,3,4,5,7,8		1,2,4,5,7				206	
	575-60	1,2,3,6		1,2,3,4,6,8		186		124	
	380-60	1,2,5,8		1,2,3,7		104		70	
	230-60	1,4,6,7		1,2		158		108	
093	208/230-60	1,5			=	260		176	
•••	460-60	1,2,4,6,7,8		1,3,4,6,7		288		196	
ŀ	230-50	1,4,7		1,2,3,5,6		130		88	
ł	380/415-50	1,2,6,7,8		1,3,4,5,6,8		268		182	
	575-60			1,2,3,8		162	`-	110	
ŀ	380-60	1,2,4,7 1,3,5,6,7	_	1,2,3,4,8		140		78	. –
}	230-60			1,2,4,5,6,8		212	_	118	_
106	208/230-60	2,3,5,7		1,3,4,5		348		192	
100	460-60	2,4,5		1,3,5,6,8		384		214	-
}-	230-50	1,2,8		1,2,3,5		174	-	96	<del></del>
-	380/415-50	2,4,5,6,7		1,3,4,8	_	372	-	206	
	575-60	1,3,5		1,2,4,5,7	_	224		124	
		1,2,4,5		1,2,3,5,6		128	_	88	
. #	380-60	1,3,4,6,7,8		1,2,4,6,7	-	194	_	132	
400	-230-60	2,3,4,5		1,3,5,7	-	320	-	220	_
108	208/230-60	2,3,6,7,8		1,4,5,6,7		354	-	244	
-	460-60	1,2,5	-	1,2,3,8		160	_	110	
-	230-50	2,3,4,6,7	-	1,3,6,7		324	_	228	
	380/415-50	1,3,4,7,8		1,2,4,7,8		202	_	138	
-	575-60	1,2,4,7		1,2,3,5,8	_	140	-	94	
-	380-60	1,3,5,6,7		1,2,4,8		212	_	142	
114	230-60	2,3,5,7	-	1,3,6	_	348		232	
L	208/230-60	2,4,5	-	1,4,6,7,8	-	384	_	258	
	460-60	1,2,8	_	1,2,4,5,6,7	-	174	_	116	
	575-60	1,2,4,5	_	1,2,3,6		128	_	104	
	380-60	1,3,4,6,7,8	-	1,2,5,8		194		158	
	230-60	2,3,4,5	-	1,4,6,8	_	320		262	
118	208/230-60	2,3,6,7,8	_	1,5	-	354		288	
	460-60	1,2,5	_	1,2,4,6,7,8		160		130	
	230-50	2,3,4,6,7	_						
	200-00	2,0,7,0,7		1,5,6,8		324		278	-

UNIT 30GXN,R	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	PUNCHOUTS FOR COMP B2	AMPS	COMP A2 MUST TRIP AMPS	COMP B1 MUST TRIP AMPS	COMP B2 MUST TRIP AMPS
	575-60	1,2,5,7,8		1,2,3,7		SETTING 154	SETTING	SETTING	SETTING
	380-60	1,3,7,8		1,2,6,7	_	234		108	
	230-60	2,4,6,7	_	1,4,7		388		164	
125	208/230-60	2,7		1,7,8		428		268	
	460-60	1,3,4,6,7,8		1,2,4,6,8		194		298	
	230-50	2,4,8		1,5,6,7				134	-
	380/415-50	1,3		1,2,6,8		398 240		276	
	575-60	1,2,5,7,8	-	1,2,3,6				166	_
	380-60	1,3,7,8		1,2,5,8		154		104	
	230-60	2,4,6,7		1,4,6,8		. 234		158	
128	208/230-60	2,7		1,5		388		262	_
	460-60	1,3,4,6,7,8	_	1,2,4,6,7,8		428		288	
	230-50	2,4,8		1,5,6,8		194	_	130	-
	380/415-50	1,3		1,2,6		398		278	
	575-60	1,2,5,7,8		1,2,4,5		240		168	-
	380-60	1,3,7,8		1,3,4,6,7,8	<del></del> -	154		128	
	230-60	2,4,6,7		2,3,4,5		234		194	_
135, 390B	208/230-60	2,7	_	2,3,6,7,8		388		320	
	460-60	1,3,4,6,7,8		1,2,5		428		354	
·	230-50	2,4,8				194		160	_
	380/415-50	1,3	_	2,3,4,6,7		398	( <del></del> )	324	-
	575-60	1,2,5,7,8	_	1,3,4,7,8		240	-	202	
	380-60	1,3,7,8	==-	1,2,4,5		154	-	128	-
	230-60	2,4,6,7		1,3,4,6,7,8		234		194	
138, 283B, 303B,	208/230-60	2,7	_=_	2,3,4,5		388	_	320	
373B	460-60	1,3,4,6,7,8	==+	2,3,6,7,8		428		354	-
	230-50	2,4,8	$-\equiv +$	1,2,5		194	-	160	_
	380/415-50	1,3		2,3,4,6,7		398	-	324	
	575-60	1,2,4,5		1,3,4,7,8	-	240		202	
	380-60	1,3,4,6,7,8		1,3,4,5,7		128	_	188	_
	230-60	2,3,4,5		1,5,8		194	-	286	
150, 370B	208/230-60	2,3,6,7,8		3,5,6		320		472	
	460-60	1,2,5		4,7,8		354		522	— .
i	230-50	2,3,5,7		1,3,7		160		236	<del></del>
i	380/415-50	1,3,5,6,7,8		2,5,6,7	-	348	-	404	
	575-60	1,3,4,5,7		1,4,5,6,8		210	_	246	
ł	380-60	1,5,4,5,7		1,2,4,5	-	188	-	128	
	230-60	3,5,6		1,3,4,6,7,8		286	-	194	
153, 283A, 328B,	208/230-60	4,7,8		2,3,4,5		472	_	320	
393B, 418B	460-60	1,3,7	-	2,3,6,7,8	_	522	_	354	_
ŀ	230-50	3,6,7		1,2,5	_	236	_	160	-
	380/415-50	1,6,8		2,3,5,7	_	484	_	348	-
	575-60	1,2,5,7,8		1,3,5,6,7,8		294	_	210	_
	380-60			1,3,4,5,7		154		188	
F	230-60	1,3,7,8 2,4,6,7	=-	1,5,8		234	_	286	
160, 415B	208/230-60	2,4,0,7		3,5,6		388.	-	472	
,	460-60	1,3,4,6,7,8		4,7,8		428		522	
H	230-50	2,4,8		1,3,7		194	-	236	
F	380/415-50	1,3	_=	3,6		398		488	
	575-60			1,6,8		240	-	294	
-	380-60	1,3,4,5,7 1,5,8		1,2,5,7,8		188		154	_
-	230-60			1,3,7,8		286		234	_
163, 303A	208/230-60	3,5,6		2,4,6,7	-	472	-	388	-
	460-60	4,7,8		2,7	-	522	-	428	
-	230-50	1,3,7		1,3,4,6,7,8		236	_	194	
-		3,6,7		2,4,8	_	484		398	
	380/415-50 575-60	1,6,8		1,3	_	294	_	240	
_		1,3,4,5,7		1,3,4,5,7		188 -	_	188	
174	380-60	1,5,8		1,5,8		286	_	286	
1/4	230-60	3,5,6		3,5,6	_	472		472	
	208/230-60	· 4,7,8		4,7,8		522	<del>-</del> -	522	
	460-60	1,3,7		1,3,7	_	236	_	236	

UNIT 30GXN,R	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	PUNCHOUTS FOR COMP B2	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIP AMPS SETTING	COMP B2 MUST TRIP AMPS SETTING
	575-60	1,3,4,5,7		1,3,4,5,7		188	- OLITING	188	SETTING
	380-60	1,5,8	_	1,5,8		286	_	286	
178, 328A, 353A,	230-60	3,5,6		3,5,6		472		472	
353B	208/230-60	4,7,8	_	4,7,8	_	522		522	
(2000 E.C.)	460-60	1,3,7	_	1,3,7	_	236		236	
	230-50	3,6,7		3,6,7		484		484	
	380/415-50	1,6,8		1,6,8		294	_	294	
	575-60	1,3,4,5,7	1,2,3,5,7,8	1,2,5,7,8	_	188	90	154	
	380-60	1,5,8	1,2,4,6	1,3,7,8	-	286	136	234	_
204	230-60	3,5,6	1,3,6,7	2,4,6,7	_	472	228	388	
	208/230-60	4,7,8	1,4,5,7	2,7	_	522	252	428	
	460-60	1,3,7	1,2,4,5,6,7,8	1,3,4,6,7,8	-	236	114	194	_
	575-60	1,2,5,7,8	1,2,5,7,8	1,2,4,5	_	154	154	128	_
	380-60	1,3,7,8	1,3,7,8	1,3,4,6,7,8	<del></del>	234	234	194	
0.000000	230-60	2,4,6,7	2,4,6,7	2,3,4,5	_	388	388	320	
208	208/230-60	2,7	2,7	2,3,6,7,8		428	428	354	_
ļ	460-60	1,3,4,6,7,8	1,3,4,6,7,8	1,2,5		194	194	160	_
	230-50	2,4,8	2,4,8	2,3,5,7	_	398	398	348	
	380/415-50	1,3	1,3	1,3,5,6,7,8	_	240	240	210	
	575-60	1,3,4,5,7	1,2,3,7	1,3,4,5,7		188	108	188	
	380-60	1,5,8	1,2,6,7	1,5,8	_	286	164	286	
225, 370A,	230-60	3,5,6	1,4,7	3,5,6	_	472	268	472	
450A/B, 475B	208/230-60	4,7,8	1,7,8	4,7,8	_	522	298	522	
	460-60	1,3,7	1,2,4,6,8	1,3,7	_	236	134	236	
1	230-50	3,6	1,5,6,7	3,6		488	276	488	
, y	380/415-50	1,6,8	1,2,6,8	1,6,8		294	166	294	
	575-60	1,3,4,5,7	1,2,5,7,8	1,2,4,5		188	154	128	
	380-60	1,5,8	1,3,7,8	1,3,4,6,7,8	-	286	234	194	
229 452 479	230-60	3,5,6	2,4,6,7	2,3,4,5	_	472	388	320	
228, 453A/B, 478B	208/230-60	4,7,8	2,7	2,3,6,7,8		522	428	354	
	460-60	1,3,7	1,3,4,6,7,8	1,2,5		236	194	160	
	230-50	3,6,7	2,4,8	2,3,5,7		484	398	348	
	380/415-50	1,6,8	1,3	1,3,5,6,7,8	_	294	240	210	
_	575-60	1,3,4,5,7	1,3,4,5,7	1,2,5,7,8	_	188	188	154	
249, 475A,	380-60	1,5,8	1,5,8	1,3,7,8		286	286	234	
500A/B	230-60	3,5,6	3,5,6	2,4,6,7		472	472	388	
11	208/230-60	4,7,8	4,7,8	2,7		522	522	428	
	460-60	1,3,7	1,3,7	1,3,4,6,7,8		236	236	194	
_	575-60	1,3,4,5,7	1,3,4,5,7	1,2,5,7,8	_	188	188	154	
_	380-60	1,5,8	1,5,8	1,3,7,8	_	286	286	234	
253, 373A, 393A, _	230-60	3,5,6	3,5,6	2,4,6,7		472	472	388	
478A, 503A, 503B	208/230-60	4,7,8	4,7,8	2,7	_	522	522	428	
2036	460-60	1,3,7	1,3,7	1,3,4,6,7,8		236	236	194	
_	230-50	3,6,7	3,6,7	2,4,8	_	484	484	398	
	380/415-50	1,6,8	1,6,8	1,3		294	294	240	
	575-60	1,3,4,5,7	1,3,4,5,7	1,3,4,5,7		188	188	188	
	380-60	1,5,8	1,5,8	1,5,8		286	286	286	
264, 390A,	230-60	3,5,6	3,5,6	3,5,6	_	472	472	472	
415A, 525A/B	208/230-60	4,7,8	4,7,8	4,7,8	_	522	522	522	
	460-60	1,3,7	1,3,7	1,3,7	-	236	236	236	
	230-50	3,6	3,6	3,6	-	488	488	488	
	380/415-50	1,6,8	1,6,8	1,6,8	-	294	294	294	
	575-60	1,3,4,5,7	1,3,4,5,7	1,3,4,5,7	-	188	188	188	- = -
	380-60	1,5,8	1,5,8	1,5,8	_	286	286	286	
	230-60	3,5,6	3,5,6	3,5,6		472	472	472	
CO AIOA COOA L		-1-1-					11.50	7/6	
268, 418A, 528A, 528B	208/230-60	4,7,8	4,7,8			522	522	522	
268, 418A, 528A, 528B	208/230-60 460-60			4,7,8 1,3,7	= -	522 236	522 236	522 236	
268, 418A, 528A, 528B	208/230-60	4,7,8	4,7,8	4,7,8		522 236 484	522 236 484	522 236 484	

UNIT 30GXN,R	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	PUNCHOUTS FOR COMP B2	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIP AMPS SETTING	COMP B2 MUST TRIF AMPS SETTING
	575-60	1,3,4,5,7	1,2,3,7	1,3,4,5,7	1,2,3,7	188	108	188	108
281	380-60	1,5,8	1,2,6,7	1,5,8	1,2,6,7	286	164	286	164
LUI	460-60	1,3,7	1,2,4,6,8	1,3,7	1,2,4,6,8	236	134	236	
	380/415-50	1,6,8	1,2,6,8	1,6,8	1,2,6,8	294	166	294	134
	575-60	1,3,4,5,7	1,2,4,5	1,3,4,5,7	1,2,4,5	188	128	188	166
380-60 460-60	380-60	1,5,8	1,3,4,6,7,8	1,5,8	1,3,4,6,7,8	286	194	286	128
	460-60	1,3,7	1,2,5	1,3,7	1,2,5	236	160		194
	380/415-50	1,6,8	1,3,4,7,8	1,6,8	1,3,4,7,8	294	-202	236	160
	575-60	1,3,4,5,7	1,2,5,7,8	1,3,4,5,7	1,2,5,7,8	188	154	294	202
325	380-60	1,5,8	1,3,7,8	1,5,8	1,3,7,8	286	234	188	154
323	460-60	1,3,7	1,3,4,6,7,8	1,3,7	1,3,4,6,7,8	236		286	234
	380/415-50	1,6,8	1,3	1,6,8	1,3		194	236	194
	575-60	1,3,4,5,7	1,3,4,5,7	1,3,4,5,7		294	240	294	240
	380-60	1,5,8	1,5,8		1,3,4,5,7	188	188	188	188
350	460-60	1,3,7	1,3,7	1,5,8	1,5,8	286	286	286	286
	380/415-50			1,3,7	1,3,7	236	236	236	236
	1 000/410-00	1,6,8	1,6,8	1,6,8	1,6,8	294	294	294	294

30GXN,R (Reduced Ambient Data [Position 10 in model no. equal to '-', 'E', 'S', or 'U'], Limited Models Only)

\*\*ComfortLink\*\* Compressor Protection Module Configuration Header Punch-Outs and Must Trip Amps

12,3,5,6   1,2,3,5,6   1,2,3,47,8   88   74   112   123   112   123   112   112   123   112   112   123   113   1112   112   123   124   112   112   124   125   124   124   124   124   124   126   124   126   124   126	UNIT 30GXN,R	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	PUNCHOUTS FOR COMP B2	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIP AMPS SETTING	COMP B2 MUST TRIP AMPS SETTING
128,080		575-60	1,2,3,5,6	_	1,2,3,4,7,8	_	88	_		
280-60		380-60	1,2,4,6,8		1,2,3	-				
2002/20-00		230-60	1,3,5,7	_	1,3,4,5,6	-	-			<del> </del>
480-80	080	208/230-60	1,4,5,6,7	_						1
239-90		460-60		-		_	10101010			
380415-50		230-50								<del> </del>
123,47,8		380/415-50								
083   124,56,7,8		_								
283   280   20   13,46.7     12.8     168										
13.4										
## ## ## ## ## ## ## ## ## ## ## ## ##	083									
230-90	()									
S00/415-50										
1.23										
390-60   1,2,6										
290-60										
100   200/20-00   2,3,4,5,6,7,8   1,3,4,7   306   2004								-	112	_
## 460-60	000								184	)
230-50	090					-	306	-	204	_
S80415-50							138	-	92	_
675-60 1,2,3,5				-		-	294		200	
380-60 1.2.4					1,2,4,5,6	-	178		120	
230-60 1,3		200000000000000000000000000000000000000			1,2,3,4,6,7,8	_	96	_	66	_
093				-	1,2,3,6,8		144	E-8	102	
108			1,3		1,2,6	-	240		168	_
460-60	093	208/230-60	1,4,7,8		1,3,4,5,7,8		266	_	186	
230-50		460-60	1,2,4,5,6	-	1,2,3,5,6,7		120			
380/415-50		230-50	1,4,5,6	_	1,2,7	_	248	_		
106		380/415-50	1,2,5,6,8	_	1,2,3,6		150	_		
106    1,3,5,67,8		575-60	1,2,4,7,8	_	1,2,3,4,7,8					
106  230-60		380-60	1,3,5,6,7,8	_	1,2,3					
106		230-60	2,3,5,6	_	1,3,4,5,6					
480-60	106	208/230-60	2,4,5,8	_						
230-50		460-60								
380/415-50		230-50								
108		380/415-50		_						
108										
108										
108										
114   146	108					1000				
230-50	700							·-		
114   380/415-50   1,3,4,5,7,8   -   1,2,4,5,8   -   186   -   126   -   1										_
114								7 <del>-</del> 5		
114   380-60										-
114								_		
18   208/230-60   2,4,5,8	11/				-					
118	134							_	220	-
118					1,4,5,6,7		382	_	244	i <del></del> /
118   380-60   1,3,4,5,6,7,8     1,2,4,8     178     142       230-60   2,3,4,5,7     1,3,7     316     236       208/230-60   2,3,4,6,8     1,4,6,7     326     260       460-60   1,2,5,6,7,8     1,2,4,5,6,8     146     118       230-50   2,3,4,5,7     1,4,5,7,8     316     250       380/415-50   1,3,4,5,7,8     1,2,5,6     186     152       575-60   1,2,5,7,8     1,2,3,7,8     154     106       380-60   1,3,7,8     1,2,6,7,8     234     162       230-60   2,4,6,7     1,4,6     388     264       125   208/230-60   2,7     1,6,8     428     294       460-60   1,3,4,6,7,8     1,2,4,6,7     194     132       230-50   2,4,8     1,4     398     272       380/415-50   1,3     1,2,6,7     194     132       230-50   2,4,8     1,4     398     272       380/415-50   1,3     1,2,6,7     194     132       230-50   2,4,8     1,4     398     272       380/415-50   1,3     1,2,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,2,4,6,7     194     132       230-50   2,4,8     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6     2,4,6,7     1,4,6							172	-	110	
118						_	118	-	94	
118					1,2,4,8	-	178		142	_
460-60       1,2,5,6,7,8       —       1,2,4,5,6,8       —       146       —       118       —         230-50       2,3,4,5,7       —       1,4,5,7,8       —       316       —       250       —         380/415-50       1,3,4,5,7,8       —       1,2,5,6       —       186       —       152       —         575-60       1,2,5,7,8       —       1,2,3,7,8       —       154       —       106       —         380-60       1,3,7,8       —       1,2,6,7,8       —       234       —       162       —         230-60       2,4,6,7       —       1,4,6       —       388       —       264       —         125       208/230-60       2,7       —       1,6,8       —       428       —       294       —         460-60       1,3,4,6,7,8       —       1,2,4,6,7       —       194       —       132       —         230-50       2,4,8       —       1,4       —       398       —       272       —         380/415-50       1,3       —       1,2,6,7       —       1,2,6,7       —       1,2,6,7       —       1,2,6,7       —       1,2,6,7				-		-	316		236	_
230-50	118				1,4,6,7	_	326		260	
230-50	1			_	1,2,4,5,6,8	-	146			
380/415-50     1,3,4,5,7,8     —     1,2,5,6     —     186     —     152     —       575-60     1,2,5,7,8     —     1,2,3,7,8     —     154     —     106     —       380-60     1,3,7,8     —     1,2,6,7,8     —     234     —     162     —       230-60     2,4,6,7     —     1,4,6     —     388     —     264     —       208/230-60     2,7     —     1,6,8     —     428     —     294     —       460-60     1,3,4,6,7,8     —     1,2,4,6,7     —     194     —     132     —       230-50     2,4,8     —     1,4     —     398     —     272     —       380/415-50     1,3     —     1,2,6,7     —     1,2,6,7     —     1,2,6,7     —     1,2,6,7     —     1,2,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7     —     1,2,4,6,7	14									
575-60     1,2,5,7,8     —     1,2,3,7,8     —     154     —     106     —       380-60     1,3,7,8     —     1,2,6,7,8     —     234     —     162     —       230-60     2,4,6,7     —     1,4,6     —     388     —     264     —       208/230-60     2,7     —     1,6,8     —     428     —     294     —       460-60     1,3,4,6,7,8     —     1,2,4,6,7     —     194     —     132     —       230-50     2,4,8     —     1,4     —     398     —     272     —       380/415-50     1,3     —     1,2,6,7     —     1,2,6,7     —     1,2,6,7     —     1,2,6,7     —     1,2,6,7     —     1,2,4		380/415-50		_						
125		575-60	1,2,5,7,8	_						ment and the second
230-60	[	380-60	1,3,7,8	-						
125	[	230-60	2,4,6,7							
460-60 1,3,4,6,7,8 — 1,2,4,6,7 — 194 — 132 — 230-50 2,4,8 — 1,4 — 398 — 272 — 380/415-50 13 — 1,3,6,7	125	208/230-60	2,7							
230-50 2,4,8 — 1,4 — 398 — 272 — 380/415-50 13 — 1,2,6,7	1									
380/415-50 13 12.67	İ									
		380/415-50	1,3		1,2,6,7		240		164	

30GXN,R (Reduced Ambient Data [Position 10 in model no. equal to '-', 'E', 'S', or 'U'], Limited Models Only)

ComfortLink™ Compressor Protection Module Configuration Header Punch-Outs and Must Trip Amps

UNIT 30GXN,R	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	PUNCHOUTS FOR COMP B2	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIP AMPS SETTING	COMP B2 MUST TRIP AMPS SETTING
	575-60	1,2,4,6	_	1,2,3,5,8	_	136	-	94	- OLITING
	380-60	1,3,4,7		1,2,4,8	_	204	_	142	
128	230-60	2,3,5,6,7,8	_	1,3,7		338		236	-
120	208/230-60	2,4,5,6,8		1,4,6,7	-	374		260	
	460-60	1,2,7,8		1,2,4,5,6,8	_	170		118	-
	230-50	2,3,6,7,8		1,4,5,7,8	_	354		250	_
	380/415-50	1,3,5,6,8		1,2,5,6		214	_	152	::
	575-60 380-60	1,2,4,6		1,2,4,5,6,8	-	136	-	118	_
	230-60	1,3,4,7		1,3,4,5,6,7,8		204		178	-
138, 283B, 303B,	208/230-60	2,3,5,6,7,8		2,3,4,5,7	_	338		316	_
373B	460-60	2,4,5,6,8		2,3,4,6,8	_	374		326	
	230-50	1,2,7,8		1,2,5,6,7,8		170		146	=
	380/415-50	2,3,6,7,8		2,3,4,5,7	_	354	_	316	_
	575-60	1,3,5,6,8		1,3,4,5,7,8	-	214		186	
	380-60	1,2,7,8		1,2,4,5,6,8	-	170		118	_
	230-60	1,4,6,7,8		1,3,4,5,6,7,8	_	258		178	
153, 283A, 328B,	208/230-60	2,7		2,3,4,5,7		428		316	-
393B, 418B	460-60	3,5,6		2,3,4,6,8		472	-	326	_
	230-50	1,3,5,6,8		1,2,5,6,7,8		214	3 <del></del> 3	146	
1	380/415-50	3,4,5,6 1,4,7,8		2,3,4,5,7		440	_	316	
	575-60	1,2,7,8		1,3,4,5,7,8		266		186	_
	380-60	1,4,6,7,8		1,2,4,6		170	-	136	-
	230-60	2,7		1,3,4,7		258	_	204	—
163, 303A	208/230-60	3,5,6		2,3,5,6,7,8		428		338	( <del></del> )
100,00071	460-60	1,3,5,6,8		2,4,5,6,8		472	-	374	-
	230-50	3,4,5,6		1,2,7,8		214	<del></del>	170	-
	380/415-50	1,4,7,8		2,3,6,7,8		440	-	354	
	575-60	1,2,7,8		1,3,5,6,8		266		214	-
	380-60	1,4,6,7,8		1,2,7,8		170	-	170	_
	230-60	2,7		1,4,6,7,8		258	-	258	_
178, 328A,	208/230-60	3,5,6		2,7	_	428		428	
353A/B	460-60	1,3,5,6,8		3,5,6 1,3,5,6,8		472		472	. =
1	230-50	3,4,5,6		3,4,5,6		214		214	
e	380/415-50	1,4,7,8		1,4,7,8		440		440	
	575-60	1,2,4,6	1,2,4,6	1,2,4,5,6,8		266		266	
Ī	380-60	1,3,4,7	1,3,4,7	1,3,4,5,6,7,8		136 204	136	118	
1	230-60	2,3,5,6,7,8	2,3,5,6,7,8	2,3,4,5,7		338	204	178	
208	208/230-60	2,4,5,6,8	2,4,5,6,8	2,3,4,6,8		374	338 374	316	
	460-60	1,2,7,8	1,2,7,8	1,2,5,6,7,8		170		326	
1	230-50	2,3,6,7,8	2,3,6,7,8	2,3,4,5,7		354	170 354	146	
	380/415-50	1,3,5,6,8	1,3,5,6,8	1,3,4,5,7,8		214		316	
	575-60	1,2,7,8	1,2,4,6	1,2,4,5,6,8	1993-90	170	136	186	
	380-60	1,4,6,7,8		1,3,4,5,6,7,8		258	204	118	
000 450470	230-60	2,7	2,3,5,6,7,8	2,3,4,5,7	_	428	338		
228, 453A/B, 478B	208/230-60	3,5,6	2,4,5,6,8	2,3,4,6,8	_	472	374	316	
	460-60	1,3,5,6,8	1,2,7,8	1,2,5,6,7,8		214	170	146	
	230-50	3,4,5,6	2,3,6,7,8	2,3,4,5,7		440	354	316	<del>-</del>
	380/415-50	1,4,7,8	1,3,5,6,8	1,3,4,5,7,8		266	214	186	
	575-60	1,2,7,8	1,2,7,8	1,2,4,6	_	170	170	136	
	380-60	1,4,6,7,8	1,4,6,7,8	1,3,4,7	_	258	258	204	
253, 373A, 393A,	230-60	2,7	2,7	2,3,5,6,7,8		428	428	338	
478A, 503A/B	208/230-60	3,5,6	3,5,6	2,4,5,6,8		472	472	374	
	460-60	1,3,5,6,8	1,3,5,6,8	1,2,7,8	I	214	214	170	
	230-50	3,4,5,6	3,4,5,6	2,3,6,7,8	_	440	440	354	
	380/415-50	1,4,7,8	1,4,7,8	1,3,5,6,8		266	266	214	
25	575-60	1,2,7,8	1,2,7,8	1,2,7,8		170	170	170	
	380-60	1,4,6,7,8	1,4,6,7,8	1,4,6,7,8	_	258	258	258	
268, 418A,	230-60	2,7	2,7	2,7	_	428	428	428	
528A/B	208/230-60	3,5,6	3,5,6	3,5,6	_	472	472	472	
	460-60	1,3,5,6,8	1,3,5,6,8	1,3,5,6,8		214	214	214	
	230-50	3,4,5,6	3,4,5,6	3,4,5,6		440	440	440	
	380/415-50								

30HXC Models

ComfortLink™ Compressor Protection Module Configuration Header Punch-Outs and Must Trip Amps

UNIT 30HXC	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIP AMPS SETTING
	575-3-60	1,2,3,4,5,6,8	_	1,2,3,4,5,6,8	54	_	54
	380-3-60	1,2,3,5,6,7,8	-	1,2,3,5,6,7,8	82	_	82
	230-3-60	1,2,4,6	-	1,2,4,6	136	_	136
076	208/230-3-60	1,2,5,6		1,2,5,6	152	<u> </u>	152
	460-3-60	1,2,3,4,6,7	-	1,2,3,4,6,7	68		68
	230-3-50	1,2,4,8	_	1,2,4,8	142		142
	380/415-3-50	1,2,3,5,6,8		1,2,3,5,6,8	86	-	86
	575-3-60	1,2,3,4,6,7,8		1,2,3,4,5,6,8	66	_	54
	380-3-60	1,2,3,6,7	<u> </u>	1,2,3,5,6,7,8	100		82
	230-3-60	1,2,6,8	_	1,2,4,6	166		136
086	208/230-3-60	1,3,4,5,6	_	1,2,5,6	184		152
	460-3-60	1,2,3,5,6,7,8	_	1,2,3,4,6,7	82	_	68
	230-3-50	1,2,8		1,2,4,8	174	_	142
#	380/415-3-50	1,2,3,6	-	1,2,3,5,6,8	104		86
	575-3-60	1,2,3,4	-	1,2,3,4,5,6,8	80	_	54
	380-3-60	1,2,4,5,7,8		1,2,3,5,6,7,8	122		82
	230-3-60	1,3,4,7,8	-	1,2,4,6	202		136
096	208/230-3-60	1,3,5		1,2,5,6	224		152
	460-3-60	1,2,3,6,8	_	1,2,3,4,6,7	102	_	68
	230-3-50	1,3,5,6,7,8		1,2,4,8	210		142
•	380/415-3-50	1,2,4,5,8		1,2,3,5,6,8	126		86
	575-3-60	1,2,3,6,7,8		1,2,3,4,5,6,8	98		54
	380-3-60	1,2,5,6,7		1,2,3,5,6,7,8	148		LICAGA.
	230-3-60	1,4,5,6,8		1,2,4,6	246		82
106	208/230-3-60	1,4	_	1,2,5,6	272		136
	460-3-60	1,2,4,5,7,8	_	1,2,3,4,6,7	122	-	152
	230-3-50	1,4,5,7		1,2,4,8	252		68
	380/415-3-50	1,2,5,6		1,2,3,5,6,8	152		142
	575-3-60	1,2,3,6,7,8		1,2,3,4,6,7,8	98	-	86
	380-3-60	1,2,5,6,7	_	1,2,3,6,7	148		66
	230-3-60	1,4,5,6,8		1,2,6,8	246		100
116	208/230-3-60	. 1,4		1,3,4,5,6	272		166
	460-3-60	1,2,4,5,7,8		1,2,3,5,6,7,8	122		184 .
	230-3-50	1,4,5,7	_	1,2,8	252		82
	380/415-3-50	1,2,5,6		1,2,3,6	152		174
	575-3-60	1,2,3,6,7,8	_	1,2,3,4	98		104
	380-3-60	1,2,5,6,7		1,2,4,5,7,8	148		80
	230-3-60	1,4,5,6,8		1,3,4,7,8	246		122
126	208/230-3-60	1,4		1,3,5	272		202
	460-3-60	1,2,4,5,7,8		1,2,3,6,8	122		224
	230-3-50	1,4,5,7		1,3,5,6,7,8	252		102
	380/415-3-50	1,2,5,6		1,2,4,5,8			210
	575-3-60	1,2,4,5,6,8		1,2,3,4	152 118		126
	380-3-60	1,3,4,5,6,7,8	_	1,2,4,5,7,8	178		80
	230-3-60	1,6,8		1,3,4,7,8	294		122
136	208/230-3-60	2,3,4,6,8		1,3,5	326		202
	460-3-60	1,2,5,6,7,8		1,2,3,6,8		_	224
	230-3-50	2,3,4,5,6,7,8			146	_	102
	380/415-3-50	1,3,4,5,6		1,3,5,6,7,8 1,2,4,5,8	306		210
	575-3-60	1,2,4,5,6,8		1,2,3,6,7,8	184		126
	380-3-60	1,3,4,5,6,7,8			118		98
	230-3-60	1,6,8		1,2,5,6,7	178		148
146	208/230-3-60	2,3,4,6,8		1,4,5,6,7	294		244
1.10	460-3-60	1,2,5,6,7,8		1,4	326	-	272
	230-3-50	2,3,4,5,6,7,8		1,2,4,5,7,8	146		122
	380/415-3-50	1,3,4,5,6		1,4,5,7	306	-	252
	000/110-0-00	טיניויייייייייייייייייייייייייייייייייי		1,2,5,6	184	-	152

30HXC Models

ComfortLink™ Compressor Protection Module Configuration Header Punch-Outs and Must Trip Amps

30HXC	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIF AMPS SETTING
	575-3-60	. 1,2,4,5	_	1,2,3,5,6	128	- OLITING	88
	380-3-60	1,3,4,6,7,8	11	1,2,4,6,8	194		134
	230-3-60	2,3,4,5		1,3,5,7	320		220
161	208/230-3-60	2,3,6,7	_	1,4,5,6,7	356		
	460-3-60	1,2,5	_	1,2,3,8	160		244
	230-3-50	2,3,4,7,8		1,3,6,7,8	330		110
	380/415-3-50	1,3,4,6		1,2,4,6	200		226
	575-3-60	1,2,3,7,8	_	1,2,4,5	106		136
	380-3-60	1,2,6,7,8		1,3,4,6,7,8	162		128
	230-3-60	1,4,7,8		2,3,4,5	266		194
171	208/230-3-60	1,6	_	2,3,6,7	296		320
	460-3-60	1,2,4,6,8		1,2,5			356
	230-3-50	1,4			134		160
	380/415-3-50	1,2,6,7		2,3,4,7,8	272		. 330
	575-3-60	1,2,4,5		1,3,4,6	164		200
	380-3-60	1,3,4,6,7,8		1,2,4,5	128	_	128
	230-3-60	2,3,4,5		1,3,4,6,7,8	194	-	194
186	208/230-3-60	2,3,6,7		2,3,4,5	320	-	320
100	460-3-60			2,3,6,7	356		356
0.00	230-3-50	1,2,5	-	1,2,5	160	_	160
	380/415-3-50	2,3,4,7,8		2,3,4,7,8	330	_	330
		1,3,4,6		1,3,4,6	200	_	200
	575-3-60	1,2,3,7,8	1,2,3,4,5,7	1,2,4,5	106	60	128
	380-3-60	1,2,6,7,8	1,2,3,5,7,8	1,3,4,6,7,8	162	90	194
000	230-3-60	1,4,7,8	1,2,5,6,8	2,3,4,5	266	150	320
206	208/230-3-60	1,6	1,2,6,8	2,3,6,7	296	166	356
	460-3-60	1,2,4,6,8	1,2,3,4,7,8	1,2,5	134	74	160
	230-3-50	1,4	1,2,5,7,8	2,3,4,7,8	272	154	330
	380/415-3-50	1,2,6,7	1,2,3,5,7	1,3,4,6	164	92	200
	575-3-60	1,2,4,5	1,2,3,5,6	1,2,4,5	128	88	128
	380-3-60	1,3,4,6,7,8	1,2,4,6,8	1,3,4,6,7,8	194	134	194
APPEARS.	230-3-60	2,3,4,5	1,3,5,7	2,3,4,5	320	220	320
246	208/230-3-60	2,3,6,7	1,4,5,6,7	2,3,6,7	356	244	356
	460-3-60	1,2,5	1,2,3,8	1,2,5	160	110	160
	230-3-50	2,3,4,7,8	1,3,6,7,8	2,3,4,7,8	330	226	330
	380/415-3-50	1,3,4,6	1,2,4,6	1,3,4,6	200	136	200
	575-3-60	1,2,4,5	1,2,3,7,8	1,2,4,5	128	106	128
	380-3-60	1,3,4,6,7,8	1,2,6,7,8	1,3,4,6,7,8	194	162	194
	230-3-60	2,3,4,5	1,4,7,8	2,3,4,5	320	266	320
261	208/230-3-60	2,3,6,7	1,6	2,3,6,7	356	296	356
	460-3-60	1,2,5	1,2,4,6,8	1,2,5	160	134	160
1	230-3-50	2,3,4,7,8	1,4	2,3,4,7,8	330	272	330
	380/415-3-50	1,3,4,6	1,2,6,7	1,3,4,6	200	164	
	575-3-60	1,2,4,5	1,2,4,5	1,2,4,5	128	128	200
	380-3-60	1,3,4,6,7,8	1,3,4,6,7,8	1,3,4,6,7,8	194	194	128
	230-3-60	2,3,4,5	2,3,4,5	2,3,4,5	320		194
271	208/230-3-60	2,3,6,7	2,3,6,7	2,3,6,7	356	320	320
}	460-3-60	1,2,5	1,2,5	1,2,5		356	356
· }	230-3-50	2,3,4,7,8	2,3,4,7,8	2,3,4,7,8	160 330	160 330	160
			6.0.4.7.0	1.34/3	(40)	חניני	330

30HXA Models

ComfortLink™ Compressor Protection Module Configuration Header Punch-Outs and Must Trip Amps

UNIT 30HXA	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRIP AMPS SETTING
	575-3-60	1,2,3,4		1,2,3,4	80	_	80
	380-3-60	1,2,4,5,7,8		1,2,4,5,7,8	122	_	122
	230-3-60	1,3,4,7,8		1,3,4,7,8	202		202
076	208/230-3-60	1,3,5	-	1,3,5	224	-	224
	460-3-60	1,2,3,6,7		1,2,3,6,7	100		100
	230-3-50	1,3,5,6,7,8		1,3,5,6,7,8	210		210
	380/415-3-50	1,2,4,5,8		1,2,4,5,8	126		126
	575-3-60	1,2,3,5	<del>-</del>	1,2,3,4	96		80
	380-3-60	1,2,5,6,7,8	_	1,2,4,5,7,8	146		122
	230-3-60	1,4,5,6,7,8	_	1,3,4,7,8	242		202
086	208/230-3-60	1,4,7		1,3,5	268		224
	460-3-60	1,2,4,5,6	_	1,2,3,6,7	120	_	100
	230-3-50	1,4,5,8	_	1,3,5,6,7,8	254		210
	380/415-3-50	1,2,5,7,8	200	1,2,4,5,8	154		126
	575-3-60	1,2,4,5,6,8		1,2,3,4	118		80
	380-3-60	1,3,4,5,6,7,8		1,2,4,5,7,8	178		
	230-3-60	1,6,8		1,3,4,7,8	294	-	122
096	208/230-3-60	2,3,4,6,8		1,3,4,7,6	326		202
	460-3-60	1,2,5,6,7,8					224
	230-3-50	2,3,4,5,6,7		1,2,3,6,7	146		100
	380/415-3-50	1,3,4,5,7,8		1,3,5,6,7,8	308	=	210
	575-3-60			1,2,4,5,8	186		126
	380-3-60	1,2,4,8		1,2,3,4	142		80
	230-3-60	1,3,5,6		1,2,4,5,7,8	216		122
106	208/230-3-60	2,3,6,8		1,3,4,7,8	.358		202
100		2,4,8		1,3,5	398		224
	460-3-60	1,3,4,5,6,7,8	——————————————————————————————————————	1,2,3,6,7	178		100
	230-3-50	2,4,5,6,8		1,3,5,6,7,8	374		210
15	380/415-3-50	1,3,6,7,8		1,2,4,5,8	226	_	126
	575-3-60	1,2,4,8	_	1,2,3,5	142	_	96
	380-3-60	1,3,5,6		1,2,5,6,7,8	216	_	146
***	230-3-60	2,3,6,8	_	1,4,5,6,7,8	358	-	242
116	208/230-3-60	2,4,8	_	1,4,7	398	_	268
	460-3-60	1,3,4,5,6,7,8		1,2,4,5,6	178	-	120
	230-3-50	2,4,5,6,8	-	1,4,5,8	374	_	254
	380/415-3-50	1,3,6,7,8	_	1,2,5,7,8	226		154
	575-3-60	1,2,4,8	-	1,2,4,5,6,8	142	_	118
	380-3-60	1,3,5,6	-	1,3,4,5,6,7,8	216	_	178
	230-3-60	2,3,6,8	-	1,6,8	358	_	294
126	208/230-3-60	2,4,8		2,3,4,6,8	398	_	326
	460-3-60	1,3,4,5,6,7,8	_	1,2,5,6,7,8	178	_	146
	230-3-50	2,4,5,6,8	-	2,3,4,5,6,7	374	_	308
	380/415-3-50	1,3,6,7,8		1,3,4,5,7,8	226		186
	575-3-60	1,2,8	_	1,2,4,5,6,8	174		118
	380-3-60	1,4,6		1,3,4,5,6,7,8	264		178
	230-3-60	3,4,5,6,7		1,6,8	436		294
136	208/230-3-60	3,6,7	_	2,3,4,6,8	484		326
	460-3-60	1,3,5,7,8	_	1,2,5,6,7,8	218		
	230-3-50	3,4,7	-	2,3,4,5,6,7	460		146 308
	380/415-3-50	1,5,6,8		1,3,4,5,7,8	278		
	575-3-60	1,2,8		1,2,4,8	174	-	186
i	380-3-60	1,4,6		1,3,5,6			142
	230-3-60	3,4,5,6,7			264		216
146	208/230-3-60	3,6,7		2,3,6,8	436		358
140	460-3-60			2,4,8	484		398
	230-3-50	1,3,5,7,8		1,3,4,5,6,7,8	218		178
		3,4,7		2,4,5,6,8	460.	_	374
	380/415-3-50	1,5,6,8		1,3,6,7,8	278	-	226

30HXA Models

ComfortLink™ Compressor Protection Module Configuration Header Punch-Outs and Must Trip Amps

UNIT 30HXA	VOLTS-Hz	PUNCHOUTS FOR COMP A1	PUNCHOUTS FOR COMP A2	PUNCHOUTS FOR COMP B1	COMP A1 MUST TRIP AMPS SETTING	COMP A2 MUST TRIP AMPS SETTING	COMP B1 MUST TRI AMP SETTING
	575-3-60	1,3,4,6,7	_	1,2,4,6,7	196		132
	380-3-60	1,7,8	_	1,3,4,6	298		200
	230-3-60	3,7,8	_	2,3,4,7,8	490		330
161	208/230-3-60	- 5		2,3,8	544		366
	460-3-60	1,4,5,6,8	_	1,2,6,8	246		166
	230-3-50	4,6,8		2,3,5,6,8	518		342
	380/415-3-50	2,3,4,5,6		1,3,4,8	312		206
	575-3-60	1,2,5	_	1,3,4,6,7	160		196
	380-3-60	1,4,5,6,7	_	1,7,8	244		298
	230-3-60	2,5,6,7,8	_	3,7,8	402		490
171	208/230-3-60	3,4,5,8	_	5	446		544
	460-3-60	1,3,4,7,8		1,4,5,6,8	202		246
	230-3-50	2,5	_	4,6,8	416		518
	380/415-3-50	1,4,5,7	-	2,3,4,5,6	252		312
	575-3-60	1,3,4,6,7	_	1,3,4,6,7	196		196
	380-3-60	1,7,8	-	1,7,8	298		298
	230-3-60	3,7,8	-	3,7,8	490		490
186	208/230-3-60	5	-	5	544		544
	460-3-60	1,4,5,6,8	_	1,4,5,6,8	246		246
	230-3-50	4,6,8		4,6,8	518		1/2/2015/
	380/415-3-50	2,3,4,5,6		2,3,4,5,6	312		518
	575-3-60	1,2,5	1,2,3,5,7,8	1,3,4,6,7	160	90	312
	380-3-60	1,4,5,6,7	1,2,4,6	1,7,8	244	136	196 298
	230-3-60	2,5,6,7,8	1,3,6,7,8	3,7,8	402	226	490
206	208/230-3-60	3,4,5,8	1,4,5,7	5	446	252	544
	460-3-60	1,3,4,7,8	1,2,4,5,6,7,8	1,4,5,6,8	202	114	246
12.1	230-3-50	2,5	1,3,7	4,6,8	416	236	518
	380/415-3-50	1,4,5,7	1,2,4,8	2,3,4,5,6	252	142	312
	575-3-60	1,3,4,6,7	1,2,4,6,7	1,3,4,6,7	196	132	196
	380-3-60	1,7,8	1,3,4,6	1,7,8	298	200	298
	230-3-60	3,7,8	2,3,4,7,8	3,7,8	490	330	490
246	208/230-3-60	5	2,3,8	5	544	366	544
	460-3-60	1,4,5,6,8	1,2,6,8	1,4,5,6,8	246	166	246
	230-3-50	4,6,8	2,3,5,6,8	4,6,8	518	342	518
	380/415-3-50	2,3,4,5,6	1,3,4,8	2,3,4,5,6	312	206	312
	575-3-60	1,3,4,6,7	1,2,5	1,3,4,6,7	196	160	196
	380-3-60	1,7,8	1,4,5,6,7	1,7,8	298	244	298
	230-3-60	3,7,8	2,5,6,7,8	3,7,8	490	402	490
261	208/230-3-60	5	3,4,5,8	5	544	446	544
	460-3-60	1,4,5,6,8	1,3,4,7,8	1,4,5,6,8	246	202	246
	230-3-50	4,6,8	2,5	4,6,8	518	416	518
	380/415-3-50	2,3,4,5,6	1,4,5,7	2,3,4,5,6	312	252	312
	575-3-60	1,3,4,6,7	1,3,4,6,7	1,3,4,6,7	196	196	196
	380-3-60	1,7,8	1,7,8	1,7,8	298	298	298
	230-3-60	3,7,8	3,7,8	3,7,8	490	490	490
271	208/230-3-60	5	5	5	544	544	544
	460-3-60	1,4,5,6,8	1,4,5,6,8	1,4,5,6,8	246	246	
	230-3-50	4,6,8	4,6,8	4,6,8	518	518	246
	380/415-3-50	2,3,4,5,6	2,3,4,5,6	2,3,4,5,6	312	312	518 312

#### **APPENDIX B**

Capacity Loading Sequence Example — The following tables show the loading sequence for a 30HX186 (50/50 split) and a 30HX161 (59/41 split) chiller. Each

compressor has 2 loaders. There is no difference in operation between "Staged" and "Equal" circuit loading on 2 compressor

STAGE	COMP A1	LOADER A1	LOADER A2	COMP B1	LOADER B1	LOADER B2	% TOTAL CAPACITY (50/50 Split)	% TOTAL CAPACITY (59/41 Split)
0	0	0	0	0	0	0	0.0	0.0
_ 1	1	0	0	. 0	0	0	20.0	23.5
2	1	1	0	0	0	0	35.0	41.1
3	1	1	1	0	0	0	50.0	58.8
4	1	1	0	1	1	0	70.0	70.0
5	1	1	0	1	1	1	85.0	
6	1	1	1	1	1	1	100.0	82.4 100.0

STAGE	COMP A1	LOADER A1	LOADER A2	COMP B1	LOADER B1	LOADER B2	% TOTAL CAPACITY (50/50 Split)	% TOTAL CAPACITY (59/41 Split)
0	0	0	0	0	s. 0	0	0.0	0.0
1	1	0	0	0	. 0	0	20.0	23.5
2	1	1 .	0	0	. 0	0	35.0	41.1
3	1	1	1	0	. 0	0	50.0	58.8
3A	1	0	0	1	0	0	40.0	40.0
3B	1	. 0	0	1	1	0	55.0	52.4
4	1	0	0	1	1	1	70.0	64.7
5	1	1	0	1	1	1	85.0	
6	11	1	1	1	1	i	100.0	82.4 100.0

#### LEGEND

0 — Off 1 — On

#### NOTES:

NOTES:

1. Stage 3A (and 3B for 59/41 split) is not used by the algorithm when increasing stages. Stage 3 (and 2 for a 59/41 split) is not used when decreasing stages.

2. The % Total Capacities above are calculated based on compressor nominal tons. For the case of the 59/41 split above, the 30HX uses compressors with flow rates of 250 and 174 cfm (from compressor model numbers 06N \_\_250 and 06N \_\_174), which represent nominal tons of 80 and 56 (respectively) at 60 Hz. A factor of 40% is used when no loaders are energized, and a factor of 70% is used when Loader 1 is energized. The capacity shown for Stage 3B above is calculated as follows:

% Total Capacity = [(0.40 x 80 + 0.70 x 56)/(80 + 56)] x 100%

#### **Nominal Tons**

COMPRESSOR PART NO.	60 Hz NOM. TONS	50 Hz NOM TONS	
06N123	39	_	
06N146	46	39	
06N174	56	46	
06N209	66	56	
06N250	80	66	
06N300	_	80	

The following tables show the loading sequence for 30HX206 (57/43 split) and 30HX271 (67/33 split) chillers. All compressors

have two loaders and the chillers are configured for equal circuit loading. See Note 2.

STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	% TOTAL CAPACITY (57/43 Split)	% TOTAL CAPACITY (67/33 Split)
0	0	0	0	0	0	0	0	0.0	0.0
11	1	0	0	0	0	0	0	14.3	13.3
2	11	1	0	0	0	0	0	25.0	23.3
3	1	1	1	0	0	0	0	35.7	33.3
4	1	1	0	0	1	1	0	55.2	46.7
5	1	1	0	0	1	1	1	68.2	56.7
6	1	1	1	0	1	1	1	78.9	66.7
7	1	1	0	1	1	1	1	83.0	
8	1	1	1	1	1	1	1	100.0	100.0

		CLOSE CONT	ROL LOADING	SEQUEN	CE (CIRCU	IT A LEAD CIF	RCUIT, 3-COMP	RESSOR UNIT)	
STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	% TOTAL CAPACITY (57/43 Split)	% TOTAL CAPACITY (67/33 Split
0	0	0	0	0	0	0	0	0.0	0.0
1	1	0	0	0	0	0	0	14.3	13.3
2	1	1	0	0	0	0	0.	25.0	23.3
3	1	1.	· 1	0	0	0	0	35.7	33.3
3A	1	0	0	0	1	0	0	31.6	26.7
4	1	0	0	0	1	1	0	44.5	36.7
5	1	0	0	0	1	1	1	57.5	46.7
6	1	1	0	0	1	1	1	68.2	56.7
7	1	1	1	0	1	1	1	78.9	66.7
·7A	1	0	0	1	1	1 .	1	65.9	60.0
8	1	1	0	1	1	1	1	83.0	80.0
9	1	1	1	1	1	1	1	100.0	100.0

#### LEGEND

0 — Off 1 — On

NOTES:

1. Stages 3A and 7A are not used by the algorithm when increasing stages. Stages 3 and 7 are not used when decreasing stages.

2. The loading sequence for 30GXN,R204-264 units is the same as those shown for the 30HX206,271 above.

The following tables show the loading sequence for 30HX206 (57/43 split) and 30HX271 (67/33 split) chillers. All compressors have two loaders and the chiller is configured for

staged circuit loading. Loaders A1 on compressors A1 and A2 are energized in parallel. The same is true for Loaders A2 on both compressors A1 and A2. See Note 3.

STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	% TOTAL CAPACITY (57/43 Split)	% TOTAL CAPACITY (67/33 Split)
0	0	0	0	0	0	0	0	0.0	0.0
1	1	0	0	0	0	0	0	14.3	13.3
2	1	1	0	0	. O	0	0	25.0	23.3
3	1	1	1	0	0	0 .	0	35.7	33.3
4	1	1	0	1	0	0	0	39.7	46.7
5	1	1	1	1	0	0	0	56.8	66.7
6	1	1	1	1	1	1	0	87.0	90.0
7	1	- 1	1	1	1	1	1	100.0	100.0

STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	% TOTAL CAPACITY (57/43 Split)	% TOTAL CAPACITY (67/33 Split)
0	0	0	0	0	0	0	0	0.0	0.0
11	1	0	.0	0	0	0	0	14.3 ·	13.3
2	1	1	-0	0	0	0	0	25.0	23.3
3	1	1	1	0	Q.	0	0	35.7	33.3
3A	1	0	0	1	0	0	0	22.7	26.7
4	1	1	0	1	.0	0	0	39.7	46.7
5	1	1	11	1	0	0	0	56.8	66.7
6	1	1	1	1	1	0	0	74.1	80.0
7	1 .	11	1	1	1	1	0	87.0	90.0
8	1	1	1	1	1	1	1	100.0	100.0

#### LEGEND

0 — Off 1 — On

#### NOTES:

 Stage 3A is not used by the algorithm when increasing stages. Stage 3 is not used by the algorithm when decreasing stages.

by the algorithm when decreasing stages.

2. The % Total Capacities above are calculated based on compressor nominal tons. For the case of the 57/43 split above, the 30HX uses compressors with flow rates of 209, 123, and 250 cfm (from compressor model numbers 06N\_209, 06N\_123, and 06N\_250), which represent nominal tons of 66, 39, and 80 (respectively) at 60 Hz. A factor of 40% is used when no loaders are energized, and a factor of 70% is used when Loader 1 is energized. The capacity shown for Stage 4 above is calculated as follows:

% Total Capacity=[(0.70 x 66 + 0.70 x 39 + 0.0 x 80)/(66 + 39 + 80)] x 100% = 39.7%

 The loading sequence for 30GXN,R204-264 units is the same as those shown for the 30HX206, 271 above.

The following tables show the loading sequence for a 30GXN,R350 chiller. Each compressor has 2 loaders and the chiller is configured for *equal circuit loading*. See Note 2.

STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	COMP B2	% TOTAL CAPACITY (50/50 Split)
	0	0	0	0.	0	0	0	0	0.0
_1	1	0	0	0	0	0	0	0	10.0
2	1	1	0	0	0	0	0	0	18.0
3	1	1	1	0	0	0	0	0	25.0
4	1	1	0	0	1	1	0	0	35.0
5	1	1	1	0	1	1	0	0	
6	1	1	1	0	1	1	1		43.0
7	1	1	0	1				0	50.0
8	1	1	0				1	0	60.0
9	1		•	-	-!-	1	0	1	70.0
10		-	!	1	1	11	0	1	85.0
10			. 1	1	1	1	1	1	100.0

STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	COMP B2	% TOTAL CAPACITY (50/50 Split)
	0	0	0	0	0	0 .	0	0	0.0
1	1	0	. 0	0	0	0 .	0	0	10.0
2	1	1	0 .	0	0	0	0	0	18.0
3	1	11	11	0	. 0	0	. 0	0	25.0
3A	1	0	0	0	1	0	0	0	20.0
4	11	0	0	0	1	1	0	0	28.0
5	1	1	0	0	1	1	9 0	0	35.0
6	1	1	1	0	1	1	0	0	
7	1	1	1	0	1	1	1	0	43.0
7A	1	0	0	1	1				50.0
8	1	1	0	1	1			0	45.0
9	1	1	0	+			1	0	60.0
10	1	1	1		1	1	0	1	70.0
11		- ;			1	1	0	1	85.0
	() <b>L</b> ()	1	1	1	1	1	1	1	100.0

#### LEGEND

0 — Off 1 — On

NOTES:

1. Stages 3A and 7A are not used by the algorithm when increasing stages. Stages 3 and 7 are not used by the algorithm when decreasing stages.

2. The loading sequence for 30GXN,R281-325 units is the same as those shown for the 30GXN,R350 above.

The following tables show the loading sequence for a 30GXN,R350 chiller. Each compressor has 2 loaders and the chillers are configured for *staged circuit loading*. See Note 2.

STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	COMP B2	% TOTAL CAPACITY (50/50 Split)
0	0	0	0	0	0	0	0	0	0.0
1	1	0	0	0	0	. 0	0	0	10.0
2	1	1	0	0 .	0	0	0	0	18.0
3	1	1	. 1	0	0	0	0	0	25.0
4	1	1	0	1	0	0	0	0	35.0
5	1	1	a <b>1</b>	1	0	0	0	0	50.0
6	1	1	1	1	1	1	.0	0	68.0
7	1	1	1	1	1	1	1	0	75.0
8	1	1	1	1	1	1	0	1	85.0
9	1	1	1	1	1	1	1	1	100.0

		LOSE CONTRO						T	
STAGE	COMP A1	LOADER A1	LOADER A2	COMP A2	COMP B1	LOADER B1	LOADER B2	COMP B2	% TOTAL CAPACITY (50/50 Split)
0	0	0	0	0	0	0	0	0	0.0
1	1	0	0	0	0	0	0	0	10.0
2	1	1	0	0	0	0	0	0	18.0
3	1	1	1	0	0	0	0	0	25.0
3A	1	0	0	1	0	0	0	0	20.0
4	1	1	0	1	0	0	0	0	35.0
5	1	1		1	. 0	0	0	0	50.0
6	1	1	1	1	1	0	0	0	60.0
7	1	1	1	1	1	1	0	0	68.0
8	1	1	1	1	1	1	1	0	75.0
8A	1	1	. 1	1	1	0	0	1	70.0
9	1	1	1	1	1	1	0	1	85.0
10	1	1	1	1	1	1	1	1	100.0

#### LEGEND

0 — Off 1 — On

NOTES:

1. Stages 3A and 8A are not used by the algorithm when increasing stages. Stages 3 and 8 are not used by the algorithm when decreasing stages.

2. The loading sequence for 30GXN,R281-325 units is the same as those shown for the 30GXN,R350 above.

## APPENDIX C

#### **Available Accessories**

ACCESSORY PART NUMBER		DESCRIPTION OF ACCESSORY	COMMENTS
30GX-90000		Condenser Grille Package	JOHN LIVIS
30GX-90000		Condenser Grille Package	
30GX-90000	3   30GXN,R118, 128, 138, 150, 160*	Condenser Grille Package	
30GX-90001	3 30GXN,R153, 174, 204, 225*	Condenser Grille Package	
30GX-90002		Condenser Grille Package	
30GX-900009	1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 - 1 -	Condenser Grille Package	
30GX-900010		Condenser Grille Package	3
30GX-90003	30GXN,R253, 268, 281-350	Condenser Grille Package	
30GX-900048	30GXN,R and 30HX (115 V Control)	Minimum Load Valve	
30GX-900049	30GXN,R and 30HX (230 V Control)		Both circuits
30GX-900015	30GXN,R080-350	Minimum Load Valve	Both circuits
30GX-900016		Sound Enclosure/Hail Guard/Wind Baffle	
30GX-900017		Sound Enclosure/Hail Guard/Wind Baffle	
30GX-900018	30GXN,R118, 128, 138, 150, 160*	Sound Enclosure/Hail Guard/Wind Baffle	
30GX-900019	30GXN,R153, 174, 204, 225*	Sound Enclosure/Hail Guard/Wind Baffle	One side per package
30GX-900020	174, 204, 220	Sound Enclosure/Hail Guard/Wind Baffle	One side per package
30GX-900030	30GXN,R208, 228*	Sound Enclosure/Hail Guard/Wind Baffle	One side per package
30GX-900039		Sound Enclosure/Hail Guard/Wind Baffle	One side per package
30GX-900023	1	Sound Enclosure/Hail Guard/Wind Baffle	One side per package
30GX-900035	000711,11000-220, 204	Vibration Isolation Pads	par parinage
30HX-900010	30GXN,R253, 268-350*	Vibration Isolation Pads	
30117-900010	30HX AII	Vibration Isolation Pads	
30GX-900027	30GXN,R118,128,138,150,153 (-1P)	Insulation Kit (14", 1-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900032	30GXN,R204-268 (+1P), 30HX206-271 (+1P)	Insulation Kit (18", 3-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900036	30GXN,R281-350 (+1P)	Insulation Kit (20", 3-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900038	30GXN,R281-350 (-1P)	Insulation Kit (20", 1-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900045	30GXN,R303A,390B,415B (STD)	Insulation Kit (16", 1-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900046	30GXN,R204-268 (-1P), 30GXN,R370A,373A,390A,393A,415A,418A, 450A/B, 453A/B,475A/B, 478A/B,500A/B,503A/B, 525A/B,528A/B (STD)	Insulation Kit (18", 1-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900047	30GXN,R283A/B,303B,328A/B, 353A/B,370B,373B,393B,418B (STD)	Insulation Kit (14", 1-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900067	30GXN,R108,125,135 (STD), 30GXN,R160,163,174,178, 30HX161-186 (+1P)	Insulation Kit (16", 3-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900068	30GXN,R118,128,138,150,153 (STD)	Insulation Kit (14", 2-Pass Cooler with Economizer)	Tubesheets and heads
30GX-900069	30GXN,R118,128,138,150,153 (+1P)	(Continuer)	Tubesheets and heads
30GX-900070	30GXN,R281-350 (STD)	Economizer)	Tubesheets and heads
30HX-900017	30GXN,R080,083,090,093 (+1P), 30HX076-096 (+1P)	Leonomizer)	Tubesheets and heads
30HX-900018	30HX116-146 (-1P)	Economizer)	Tubesheets and heads
30HX-900020	30GXN,R108,125,135 (+1P)	Economizer)	Tubesheets and heads
30HX-900021	30GXN,R160-178 (-1P), 30HX161-186 (-1P)	(Economizer)	Tubesheets and heads
30HX-900023	30HX206-271 (-1P)	Economizer)	Tubesheets and heads
30HX-900024	30GXN,R106,114 (+1P), 30HX106 (+1P)	Insulation Kit (16", 4-Pass Cooler, no Economizer)	Tubesheets and heads

<sup>\*</sup>And associated modular sizes.

#### LEGEND

(STD) — Chillers with standard number of cooler passes (-1P) — Chillers with minus one pass cooler option (+1P) — Chillers with plus one pass cooler option

#### **Available Accessories (cont)**

ACCESSORY PART NUMBER	UNITS	DESCRIPTION OF ACCESSORY	COMMENTS
30HX-900035	30GXN,R080,083,090,093, 30HX076-096 (STD) 30HX116-146 (+1P)	Insulation Kit (14", 3-Pass Cooler, no Economizer)	Tubesheets and head
30HX-900036	30GXN,R106,114 (STD) 30HX106 (STD)	Insulation Kit (16", 3-Pass Cooler, no Economizer)	Tubesheets and head
30HX-900037	30GXN,R080,083,090,093, 30HX076-096 (-1P), 30HX116-146 (STD)	Insulation Kit (14", 2-Pass Cooler, no Economizer)	Tubesheets and head
30HX-900038	30GXN,R108,125,135 (-1P), 30GXN,R160,163,174,178,30HX161-186 (STD)	Insulation Kit (16", 2-Pass Cooler, with Economizer)	Tubesheets and head
30HX-900039	30GXN,R204-268 (STD), 30HX206-271 (STD)	Insulation Kit (18", 2-Pass Cooler, with Economizer)	Tubesheets and head
30HX-900040	30GXN,R106,114 (-1P), 30HX106 (-1P)	Insulation Kit (16", 2-Pass Cooler, no Economizer)	Tubesheets and heads
30HX-900001	30HX116-271	Sound Enclosure Panels	†
30HX-900011	30HX076-106	Sound Enclosure Panels	
30HX-900004	30HX076-146	Victaulic Condenser Connections (18 in.)	
30HX-900005	30HX161-186	Victaulic Condenser Connections (20 in.)	
30HX-900015	30HX206-271	Victaulic Condenser Connections (22 in.)	
30HX-900032	30GXN,R and 30HX All	Energy Management Module	
30HX-900033	30HX (230 V, 460 V)	Control Transformer	
30HX-900034	034 30HX (575 V) Control Transformer		
30GX-900050	30GXN,R (230 V, 460 V)	Control Transformer (080-178*)	
30GX-900051	30GXN,R (575 V)	Control Transformer (080-178*)	
30GX-900052	30GXN,R (208 V)	Control Transformer (080-178*)	1/3
30GX-900055	30GXN,R (230 V, 460 V)	Control Transformer (204-350*)	
30GX-900056	30GXN,R (575 V)	Control Transformer (204-350*)	
30GX-900057	30GXN,R (208 V)	Control Transformer (204-350*)	
30GX-900058	30GXN,R220-528 Duplex	Duplex Trim Kit	
30GX-900071	30GXN,R080-150, 160*	Motormaster® V Control (575 V)	Single controller
30GX-900072	30GXN,R080-150, 160*	Motormaster V Control (208/230 V)	Single controller
30GX-900073	30GXN,R080-150,160*	Motormaster V Control (380/460 V)	Single controller
30GX-900074	30GXN,R153,163-350*	Motormaster V Control (575 V)	Two controllers
30GX-900075	30GXN,R153,163-350*	Motormaster V Control (208/230 V)	Two controllers
30GX-900076	30GXN,R153,163-350*	Motormaster V Control (380/460 V)	Two controllers
CEPL130322-02	30GXN,R and 30HX All	Chillervisor System Manager III	
CPNLDLK-01	30GXN,R and 30HX All	DataLink Control Panel	
CPNLDPT-01	30GXN,R and 30HX All	DataPort Control Panel	v
RLIDASY001A00	30GXN,R and 30HX All	Remote Enhanced Display	
30GT-911049	30GXN,R and 30HX All	GFI Convenience Outlet (60 Hz only)	
30GT-911057	30GXN,R All	Unit Control Display Window	
30GT-911063	30GXN,R All	Remote Service Port	

<sup>\*</sup>And associated modular sizes.

#### LEGEND

Chillers with standard number of cooler passes
 Chillers with minus one pass cooler option
 Chillers with plus one pass cooler option

#### APPENDIX D

Building Interface — The 30GXN,GXR,HX chiller can be interfaced with multi-vendor control systems through 3 levels of inter-operability using BacLink, DataPort<sup>TM</sup>, or DataLINK<sup>TM</sup> devices. BacLink functions as a gateway between a CCN and a BACnet system to facilitate the passing of data from the CCN to BACnet. The Carrier DataPort is an interface device that allows other HVAC control systems to "read only" values in system elements connected to a CCN communication bus. The Carrier

DataLINK device is an interface device that allows other HVAC control systems to read and change ("read/write") values in system elements connected to a CCN bus. Both DataPort and DataLINK devices request data from a specified CCN system element and translate this data into ASCII characters off network. Information from the 30GXN,GXR,HX chiller control to support interface are listed in the following tables.

#### **Object Definitions**

CCN Table	30GXN/G	XR/HXA/HXC Series 6 wi	th Software Ve	ersion 1.1 and la	ter		
Name	Description	Status	Units	Point	DataPort	DataLink	BAClink
	GENERAL PARAMETERS Control Mode	0 = Service Test 1 = OFF Local 2 = OFF CCN 3 = OFF Clock 4 = OFF Emergency 5 = ON Local 6 = ON CCN 7 = ON Clock		STAT	RO	RO	RO
A_UNIT	Octobed CCN Chiller Alarm State Active Demand Limit Override Modes In Effect Percent Total Capacity Active Setpoint Control Point Entering Fluid Temp Leaving Fluid Temp Emergency Stop Minutes Left for Start Heat/Cool Select	No/Yes Start/Stop Normal/Alert/Alarm 0 to 100 No/Yes 0 to 100 -20 to 70 (-28.8 to 21.1) -20 to 70 (-28.8 to 21.1) snnn.n snnn.n Enable/Emstop 00:00 to 15:00 Heat/Cool	%  °F (°C)  °F (°C)  °F (°C)  Minutes	OCC CHIL_S_S ALM DEM_LIM MODE CAP_T SP CTRL_PNT EWT LWT EMSTOP MIN_LEFT HEATCOOL	RO RO RO RO RO RO RO RO RO RO	RO RW RO RO RO RW RO RW RO RW	RO RW RO RW NA RO RW RO RW
CIRCADIO	CIRC. A DISCRETE OUTPUTS Compressor A1 Relay Compressor A2 Relay Loader A1 Relay Loader A2 Relay Minimum Load Valve Oil Heater Motor Cooling A1 Solenoid Motor Cooling A2 Solenoid Oil Pump Oil Solenoid A1 Oil Solenoid A2	Off/On		K_A1_RLY K_A2_RLY LOADR_A1 LOADR_A2 MLV OILA_HTR MTRCL_A1 MTRCL_A2 OILPMP_A OILSL_A1 OILSL_A1	RO RO RO RO RO RO RO RO RO	RW RO RO RO RO RO RO RO RO RO	RO RO NA NA NA NA NA NA
	CIRC. A DISCRETE INPUTS Compressor A1 Feedback Compressor A2 Feedback Oil Level Switch	Off/On Off/On Close/Open		K_A1_FBK K_A2_FBK OILA_SW	RO RO RO	RO RO RO	NA NA NA
CIRCA_AN	Saturated Condensing Tmp Saturated Suction Temp EXV% Open Variable Head Press Pct.	0 to 100 0 to 100 0 to 1200 nnn.n nnn.n snnn.n nnn.n snnn.n snnn.n	% % % Amps PSIG (KPA) PSIG (KPA) PSIG (KPA) °F (°C) °F (°C) °F (°C) °F (°C) °F (°C) % °F (°C) % %	CAPA_T CAPA_A A_CURR DP_A SP_A ECNP_A SH_A DISTMP_A DISTMPA1 DISTMPA2 TMP_SCTA TMP_SCTA TMP_SCTA TMP_SCTA EXV_A VHPA	RO RO RO RO RO RO RO RO RO RO RO	RO RO RO RO RO RO RO RO RO RO RO RO RO R	RO RO NA RO NA RO NA RO NA
	A1 Oil Pressure A1 Motor Temperature Comp A1 Running Current	nnn.n nnn.n nnn.n 0 to 600 0 to 100	PSIG (KPA) PSIG (KPA) °F (°C) Amps %	DOP_A1 OP_A1 TMTR_A1 A1_CURR A1_MTA	RO RO RO RO	RO RO RO RO	NA NA NA NA NA
	A2 Oil Pressure A2 Motor Temperature Comp A2 Running Current	nnn.n nnn.n nnn.n ) to 600 ) to 100	PSIG (KPA) PSIG (KPA) °F (°C) Amps %	DOP_A2 OP_A2 TMTR_A2 A2_CURR A2_MTA	RO RO RO RO	RO RO RO RO	NA NA NA NA NA

## Object Definitions (cont)

	30GXN/GX	R/HXA/HXC Series 6 with	Software Ve	rsion 1.1 and lat	er		
CCN Table Name	Description	Status	Units	Point	DataPort	DataLink	BAClink
CIRCEDIO	CIRC. B DISCRETE OUTPUTS Compressor B1 Relay Compressor B2 Relay Loader B1 Relay Loader B2 Relay Minimum Load Valve Oil Heater Motor Cooling B1 Solenoid Motor Cooling B2 Solenoid Oil Pump Oil Solenoid B1 Oil Solenoid B2	Off/On		K_B1_RLY K_B2_RLY LOADR_B1 LOADR_B2 MLV OILB_HTR MTRCL_B1 MTRCL_B2 OILPMP_B OILSL_B1 OILSL_B1	RO RO RO RO RO RO RO RO RO	RO RO RO RO RO RO RO RO RO	RO RO NA NA NA NA NA NA
×	CIRC. B DISCRETE INPUTS Compressor B1 Feedback Compressor B2 Feedback Oil Level Switch	Off/On Off/On Close/Open		K_B1_FBK K_B2_FBK OILB_SW	RO RO RO	RO RO RO	NA NA NA
CIRCB_AN	CIRCUIT B ANALOG VALUES Percent Total Capacity Percent Available Cap. Circuit Running Current Discharge Pressure Suction Pressure Economizer Pressure Discharge Superheat Temp Discharge Gas Temp Discharge Gas Temp - B1 Discharge Gas Temp - B2 Saturated Condensing Tmp Saturated Suction Temp EXV% Open Variable Head Press Pct.	0 to 100 0 to 100 0 to 1200 nnn.n nnn.n snnn.n nnn.n snnn.n nnn.n snnn.n snnn.n	%  %  Amps  PSIG (KPA)  PSIG (KPA)  PSIG (KPA)  *F (°C)   CAPB_T CAPB_A B_CURR DP_B SP_B ECNP_B SH_B DISTMP_B DISTMPB1 DISTMPB2 TMP_SCTB TMP_SCTB TMP_SSTB EXV_B VHPB	RO RO RO RO RO RO RO RO RO RO RO	RO R	RO RO NA RO RO NA RO NA	
	COMP B1 ANALOG VALUES B1 Oil Pressure Diff. B1 Oil Pressure B1 Motor Temperature Comp B1 Running Current Comp B1 % Must Trip Amps	nnn.n nnn.n nnn.n 0 to 600 0 to 100	PSIG (KPA) PSIG (KPA) °F (°C) Amps %	DOP_B1 OP_B1 TMTR_B1 B1_CURR B1_MTA	RO RO RO RO RO	RO RO RO RO	NA NA NA NA
92	COMP B2 ANALOG VALUES B2 Oil Pressure Diff. B2 Oil Pressure B2 Motor Temperature Comp B2 Running Current Comp B2 % Must Trip Amps	nnn.n nnn.n nnn.n 0 to 600 0 to 100	PSIG (KPA) PSIG (KPA) °F (°C) Amps %	DOP_B2 OP_B2 TMTR_B2 B2_CURR B2_MTA	RO RO RO RO RO	RO RO RO RO RO	NA NA NA NA
	FANS Fan 1 Relay * Fan 2 Relay † Fan 3 Relay Fan 4 Relay	Off/On Off/On Off/On Off/On	10 12 11	FAN_1 FAN_2 FAN_3 FAN_4	RO RO RO RO	RO RO RO RO	RO RO RO RO
OPTIONS	Cooler Leaving Fluid Condenser Entering Fluid Condenser Leaving Fluid	snnn.n snnn.n snnn.n snnn.n snnn.n	°F (°C) °F (°C) °F (°C) °F (°C) °F (°C)	COOL_EWT COOL_LWT COND_EWT COND_LWT DUAL_LWT	RO RO RO RO	RO RO RO RO	RO RO RO RO NA
	Outside Air Temperature	nn.n snnn.n snnn.n	mA °F (°C) °F (°C)	RST_MA OAT SPT	RO RO RO	RO RW RW	RO NA NA
	Demand Limit Switch 1 Demand Limit Switch 2 CCN Loadshed Signal	nn.n Off/On Off/On 0 = Normal 1 = Redline 2 = Loadshed	mA	LMT_MA DMD_SW1 DMD_SW2 DL_STAT	RO RO RO	RO RO RO RO	RO NA NA RO

#### APPENDIX D (cont) Object Definitions (cont)

30GXN/G)	R/HXA/HXC Series 6 with	n Software Ve	ersion 1.1 and late	er		
Description	Status	Units	Point	DataPort	DataLink	BAClink
PUMPS Cooler Pump Relay Condenser Pump Relay	Off/On Off/On		COOL_PMP COND_PMP	RO RO	RO RO	RO RO
Dual Setpoint Switch Cooler Flow Switch Condenser Flow Switch Ice Done Cooler Heater 4-20 mA Cooling Setpoint 4-20 mA Heating Setpoint Liq. Line Solenoid Valve	Off/On Off/On Off/On No/Yes Off/On nn.n open/Close	mA mA	DUAL_IN COOLFLOW CONDFLOW ICE COOL_HTR CSP_IN HSP_IN LLSV	RO RO RO RO RO RO RO	RO RO RO RO RO RO RO	NA NA NA NA NA NA
Dual Chiller Pct Total Cap Dual Chiller Tons Avail Dual Chiller Pct Avail Cap	nnn 0-100 nnn 0-100	Tons % Tons %	SIZE_DPX CAPT_DPX SIZEADPX CAPA_DPX	RO RO RO RO	RO RO RO RO	NA NA NA NA
Cooling Setpoint 1 Cooling Setpoint 2 ICE Setpoint	-20 to 70 (-28.8 to 21.1) -20 to 70 (-28.8 to 21.1) -20 to 32 (-28.8 to 0.0)	°F (°C) °F (°C) °F (°C)	CSP1 CSP2 CSP3	NA NA NA	RW RW RW	RW NA NA
Heating Setpoint 1 Heating Setpoint 2	80 to 140 (26.7 to 60.0) 80 to 140 (26.7 to 60.0)	°F (°C) °F (°C)	HSP1 HSP2	NA NA	RW RW	RW NA
Cooling Ramp Loading Heating Ramp Loading	0.2 to 2.0 (0.1 to 1.1) 0.2 to 2.0 (0.1 to 1.1)		CRAMP HRAMP	NA NA	RW RW	NA NA
Head Pressure Setpoint A Head Pressure Setpoint B	80 to 140 (26.7 to 60.0) 80 to 140 (26.7 to 60.0)	°F (°C) °F (°C)	HSP_A HSP_B	NA NA	RW RW .	NA NA
	0.1 to 20.0	°F (°C)	APRCH_SP	NA	RW	NA
Period 1 DOW (MTWTFSSH) Occupied Time Unoccupied Time Period 2 DOW (MTWTFSSH) Occupied Time Unoccupied Time Period 3 DOW (MTWTFSSH) Occupied Time Unoccupied Time Unoccupied Time Unoccupied Time Unoccupied Time Unoccupied Time Unoccupied Time Period 5 DOW (MTWTFSSH) Occupied Time Unoccupied Time Period 6 DOW (MTWTFSSH) Occupied Time Period 7 DOW (MTWTFSSH) Occupied Time Unoccupied Time Period 7 DOW (MTWTFSSH) Occupied Time Period 8 DOW (MTWTFSSH) Occupied Time Period 8 DOW (MTWTFSSH) Occupied Time	00000000 00:00	Hours	OVR-EXT DOW1 OCCTOD1 UNOCTOD1 DOW2 OCCTOD2 UNOCTOD2 UNOCTOD3 UNOCTOD3 UNOCTOD4 UNOCTOD4 UNOCTOD5 UNOCTOD5 UNOCTOD5 UNOCTOD5 UNOCTOD6 UNOCTOD6 UNOCTOD6 UNOCTOD7 UNOCTOD7 UNOCTOD7 UNOCTOD7	NA A A A A A A A A A A A A A A A A A A	RW RW RW RW RW RW RW RW RW RW RW RW RW R	RW R
	PUMPS Cooler Pump Relay Condenser Pump Relay MISCELLANEOUS Dual Setpoint Switch Cooler Flow Switch Cooler Flow Switch Condenser Flow Switch Ice Done Cooler Heater 4-20 mA Cooling Setpoint 4-20 mA Heating Setpoint 4-20 mA Heating Setpoint Liq. Line Solenoid Valve  Dual Chiller Size Dual Chiller Pct Total Cap Dual Chiller Pct Avail Dual Chiller Pct Avail Cooling Setpoint 1 Cooling Setpoint 2 ICE Setpoint HEATING Heating Setpoint 1 Heating Setpoint 2 ICE Setpoint B HEAD PRESSURE Head Pressure Setpoint A Head Pressure Setpoint B Approach Setpoint Timed Override Hours Period 1 DOW (MTWTFSSH) Occupied Time Unoccupied Time Period 5 DOW (MTWTFSSH) Occupied Time Unoccupied Time Period 5 DOW (MTWTFSSH) Occupied Time Period 5 DOW (MTWTFSSH) Occupied Time Period 7 DOW (MTWTFSSH) Occupied Time Period 8 DOW (MTWTFSSH) Occupied Time	PUMPS	Description	Description	PUMPS	Description


#### LEGEND

<sup>°</sup>C — Degrees Celsius
°F — Degrees Fahrenheit
NA — Not Available
RO — Read Only
RW — Read/Write

<sup>\*</sup>Circuit A Condenser Fan Output (30HXA only). †Circuit B Condenser Fan Output (30HXA only).


APPENDIX E

The following charts list pressure drops for coolers and condensers.




NOTE: Ft of water = 2.31 x psig.

30HX COOLER PRESSURE DROP — ENGLISH




30HX COOLER PRESSURE DROP - SI




Unit Size Range

NOTE: Ft of water = 2.31 x psig.

## 30HX CONDENSER PRESSURE DROP — ENGLISH




30HX CONDENSER PRESSURE DROP — SI




NOTE: Ft of water = 2.31 x psig.


30GXN,R080-178 COOLER PRESSURE DROP — ENGLISH




30GXN,R204-268 COOLER PRESSURE DROP — ENGLISH



30GXN,R080-178 COOLER PRESSURE DROP — SI




30GXN,R204-268 COOLER PRESSURE DROP — SI




30GXN,R281-350 COOLER PRESSURE DROP — ENGLISH


NOTE: Ft of water = 2.31 x psig.




30GXN,R281-350 COOLER PRESSURE DROP — SI




30GXN,R283, 303, 370, 390, 415 DUPLEX COOLER PRESSURE DROP — ENGLISH



30GXN,R328, 353, 373, 393, 418-528 DUPLEX COOLER PRESSURE DROP — ENGLISH




30GXN,R283, 303, 370, 390, 415 DUPLEX COOLER PRESSURE DROP — SI




30GXN,R328, 353, 373, 393, 418-528 DUPLEX COOLER PRESSURE DROP — SI


#### APPENDIX F





101




102










Typical System Components, 30HXC076-146, Without Economizer






Typical System Components, 30HXC206-271 Circuit A, With Economizer







Typical System Components, 30HXC206-271 Circuit B, With Economizer

108





Typical System Components, 30HXA076-146, Without Economizer





111





APPENDIX G
A\_UNIT (Unit Operation): Status Display

DESCRIPTION	STATUS	UNITS	POINT	FORCIBLE
Control Mode	0 = Service Test 1 = Off - Local 2 = Off - CCN 3 = Off - Clock 4 = Off Emergency 5 = On - Local 6 = On - CCN 7 = On - Clock		STAT	N
Occupied	Yes/No		OCC	N
CCN Chiller	Start/Stop		CHIL S S	Ÿ
Alarm State	0 = Normal 1 = Alarm 2 = Alert		ALM	N
Active Demand Limit	0 - 100	. %	DEM_LIM	Ÿ
Override Modes in Effect	Yes/No		MODE	N
Percent Total Capacity	0 - 100	%	CAP T	N
Active Setpoint	snnn.n	°F	SP	N
Control Point	snn.n	°F	CTRL PNT	Y
Entering Fluid Temp	snnn.n	°F	EWT	N
Leaving Fluid Temp	snnn.n	°F	LWT	N
mergency Stop	Enable/Emstop		EMSTOP	V
Minutes Left for Start	00:00-15:00	min	MIN LEFT	N
Heat Cool Select	Heat/Cool		HEATCOOL	N

# CIRCADIO (Circuit A Discrete Inputs/Outputs): Status Display

DESCRIPTION	STATUS	POINT	FORCIBLE
CIRC. A DISCRETE OUTPUTS			TOTOBLE
Compressor A1 Relay	On/Off	K A1 RLY	N
Compressor A2 Relay	On/Off	K A2 RLY	N
Loader A1 Relay	On/Off	LOADR A1	N N
Loader A2 Relay	On/Off	LOADR A2	N
Minimum Load Valve	On/Off	MLV	N
Oil Heater	On/Off	OILA HTR	N
Motor Cooling A1 Solenoid	On/Off	MTRCL A1	N
Motor Cooling A2 Solenoid	On/Off	MTRCL A2	N
Oil Pump	On/Off	OILPMP A	N
Oil Solenoid A1	On/Off	OILSL A1	N
Oil Solenoid A2	On/Off	OILSL_A2	N
CIRC. A DISCRETE INPUTS			
Compressor A1 Feedback	On/Off	K A1 FBK	N
Compressor A2 Feedback	On/Off	K A2 FBK	N
Oil Level Switch	Close/Open	OILA SW	N

# CIRCA\_AN (Circuit A Analog Parameters): Status Display

DESCRIPTION	STATUS	UNITS	POINT	FORCIBLE
CIRCUIT A ANALOG VALUES		Marie Control of the		1 01101000
Percent Total Capacity	0 - 100	%	CAPA T	l N
Percent Available Cap	0 - 100	%	CAPA A	N
Circuit Running Current	0 - 1200	AMPS	A CURR	N N
Discharge Pressure	nnn.n	PSIG	DP_A	N N
Suction Pressure	nnn.n	PSIG	SP_A	N
Economizer Pressure	nnn.n	PSIG	ECNP_A	N N
Discharge Superheat Temp	snnn.n	°F	SH A	N N
Discharge Gas Temp	nnn.n	°F	DISTMP A	N
Discharge Gas Temp - A1	nnn.n	°F	DISTMPA1	N
Discharge Gas Temp - A2	nnn.n	°F	DISTMPA2	N
Saturated Condensing Tmp	snnn.n	°F	TMP_SCTA	N
Saturated Suction Temp	snnn.n	°F	TMP SSTA	N
EXV % Open	0 - 100	%	EXV A	N
Variable Head Press. PCT	0 - 100	%	VHPA	N
COMP A1 ANALOG VALUES				
A1 Oil Pressure Diff.	nnn.n	PSIG	DOP_A1	N
A1 Oil Pressure	nnn.n	PSIG	OP_A1	N
A1 Motor Temperature	nnn.n	· °F	TMTR_A1	N
Comp A1 Running Current	0 - 600	AMPS	A1 CURR	N N
Comp A1 % Must Trip Amps	0 - 100	%	A1_MTA	N
COMP A2 ANALOG VALUES				
A2 Oil Pressure Diff.	nnn.n	PSIG	DOP_A2	NI NI
A2 Oil Pressure	nnn.n	PSIG	OP A2	N N
A2 Motor Temperature	non.n	°F	TMTR_A2	N N
Comp A2 Running Current	0 - 600	AMPS	A2 CURR	N
Comp A2 % Must Trip Amps	0 - 100	%	A2_CORR A2_MTA	N N

APPENDIX G (cont

# CIRCBDIO: (Circuit B Discrete Inputs/Outputs) Status Display

DESCRIPTION	STATUS	POINT	CODOIN! F
CIRC. B DISCRETE OUTPUTS		1 OINT	FORCIBLE
Compressor B1 Solenoid	On/Off	K_B1_RLY	
Compressor B2 Solenoid	On/Off	K_B2 RLY	N
Loader B1 Relay	On/Off	LOADR_B1	N
Loader B2 Relay	On/Off		N
Minimum Load Valve	On/Off	LOADR_B2	N
Oil Heater	On/Off	MLV	N
Motor Coolng B1 Solenoid	On/Off	OILB_HTR	N
Motor Coolng B2 Solenoid	On/Off	MTRCL_B1	N
Oil Pump	On/Off	MTRCL_B2	N
Oil Solenoid B1	On/Off	OILPMP_B	N
Oil Solenoid B2	On/Off	OILSL_B1	N
THE COLUMN DE	ONOII	OILSL_B2	N
CIRC. B DISCRETE INPUTS			
Compressor B1 Feedback	On/Off	V D1 FDV	
Compressor B2 Feedback	On/Off	K_B1_FBK	N
Oil Level Switch	Close/Open	K_B2_FBK	N
	Olose/Open	OILB_SW	N

# CIRCB\_AN: (Circuit B Analog Parameters) Status Display

DESCRIPTION	STATUS	UNITS	POINT	FORCIBLE
CIRCUIT B ANALOG VALUES			10	PONCIBLE
Percent Total Capacity	0 - 100	%	CAPB T	N
Percent Available Cap	0 - 100	%	CAPB A	N
Circuit Running Current	0 - 1200	AMPS	B CURR	N
Discharge Pressure	nnn.n	PSIG	DP B	
Suction Pressure	nnn.n	PSIG	SP B	N
Economizer Pressure	nnn.n	PSIG	ECNP B	N
Discharge Superheat Temp	snnn.n	°F	SH B	N
Discharge Gas Temp	nnn.n	°F	DISTMP B	N
Discharge Gas Temp - B1	nnn.n	°F	DISTMPB1	N
Discharge Gas Temp - B2	nnn.n	°F	DISTMPB2	N
Saturated Condensing Tmp	snnn.n	°F	TMP_SCTB	N
Saturated Suction Temp	snnn,n	°F	TMP_SSTB	N
EXV % Open	0 - 100	. %	EXV B	N
Variable Head Press. PCT	0 - 100	%	VHPB	N
		70	VHPB	N
COMP B1 ANALOG VALUES				
B1 Oil Pressure Diff.	nnn.n	PSIG	DOD DI	
B1 Oil Pressure	nnn.n	PSIG	DOP_B1	N
B1 Motor Temperature	nnn.n	°F	OP_B1	. N
Comp B1 Running Current	0 - 600	AMPS	TMTR_B1	N
Comp B1 % Must Trip Amps	0 - 100	%	B1_CURR	N
	0 100	70	B1_MTA	N
COMP B2 ANALOG VALUES				
B2 Oil Pressure Diff.	nnn.n	PSIG	DOD DO	
B2 Oil Pressure	nnn.n		DOP_B2	N
B2 Motor Temperature	, nnn.n	PSIG °F	OP_B2	N
Comp B2 Running Current	0 - 600		TMTR_B2	N
Comp B2 % Must Trip Amps	0 - 100	AMPS	B2_CURR	N
	0 - 100	%	B2_MTA	N

**OPTIONS: Status Display** 

DESCRIPTION	STATUS	UNITS	POINT	FORCIBLE
FANS				
Fan 1 Relay	On/Off		FAN_1	N
Fan 2 Relay	On/Off		FAN_2	N
Fan 3 Relay	On/Off		FAN_3	N
Fan 4 Relay	On/Off		FAN_4	N
UNIT ANALOG VALUES				
Cooler Entering Fluid	snnn.n	°F	COOL EWT	N
Cooler Leaving Fluid	snnn.n	°F	COOL_LWT	N
Condenser Entering Fluid	snnn.n	°F	COND EWT	N
Condenser Leaving Fluid	snnn.n	°F	COND_LWT	N
Lead/Lag Leaving Fluid	snnn.n	°F	DUAL_LWT	N
TEMPERATURE RESET				
4 - 20 ma Reset Signal	nn.n	ma	RST MA	N
Outdoor Air Temperature	snnn.n	°F	OAT	Y
Space Temperature	snnn.n	°F	SPT	Ý
DEMAND LIMIT				
4 - 20 ma Demand Signal	nn.n	ma	LMT MA	N
Demand Limit Switch 1	On/Off	IIIA	DMD SW1	N
Demand Limit Switch 2	On/Off		DMD_SW2	N
CCN Loadshed Signal	0 = Normal 1 = Redline . 2 = Loadshed		DL_STAT	N
PUMPS			34	
Cooler Pump Relay	On/Off		COOL PMP	N
Condenser Pump Relay	On/Off		COND_PMP	N
MISCELLANEOUS	-			
Dual Setpoint Switch	On/Off		DUAL_IN	N
Cooler Flow Switch	On/Off		COOLFLOW	N N
Condenser Flow Switch	On/Off		CONDFLOW	- N
Ice Done	Yes/No		ICE	N N
Cooler Heater	On/Off		COOL HTR	N N
4-20 ma Cooling Setpoint	nn.n	ma	CSP IN	
4-20 ma Heating Setpoint	nn.n	ma	HSP_IN	N
Liq. Line Solenoid Valve	Open/Close	IIId	LLSV	N N
Dual Chilles Clas				
Dual Chiller Size	nnn	Tons	SIZE_DPX	N
Dual Chiller Pct Total Cap	0-100	%	CAPT_DPX	N
Dual Chiller Tons Avail	nnn	Tons	SIZEADPX	N
Dual Chiller Pct Avail Cap	0-100	%	CAPA_DPX	N

#### 7-DAY\_OCC: Occupancy Configuration

DESCRIPTION	STATUS	POINT
Monday Occupied Time	00:00	MON_OCC
Monday Unoccupied Time	00:00	MON UNC
Tuesday Occupied Time	00:00	TUE OCC
Tuesday Unoccupied Time	00:00	TUE UNC
Wednesday Occupied Time	00:00	WED OCC
Wednesday Unoccupied Time	00:00	WED UNC
Thursday Occupied Time	00:00	THU OCC
Thursday Unoccupied Time	. 00:00	THU UNC
Friday Occupied Time	00:00	FRI OCC
Friday Unoccupied Time	00:00	FRI UNC
Saturday Occupied Time	00:00	SAT_OCC
Saturday Unoccupied Time	. 00:00	SAT_UNC
Sunday Occupied Time	00:00	SUN OCC
Sunday Unoccupied Time	00:00	SUN UNC

# ALARMDEF: Alarm Configuration

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
Alarm Routing Control	00000000	00000000	ONITO	
Equipment Priority	0 to 7	4		ALRM_CNT
Comm Failure Retry Time	1 to 240	10		EQP_TYPE
Re-alarm Time	1 to 255	30	min	RETRY_TM
Alarm System Name	XXXXXXXXX		min	RE-ALARM
, warm cystem name	*********	CHILLER		ALRM_NAM

# **BRODEFS: Broadcast Configuration**

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
CCN Time/Date Broadcast	Yes/No	No	Onno	
CCN OAT Broadcast	Yes/No	No		CCNBC
Global Schedule Broadcast	Yes/No	No		OATBC
Broadcast Acknowledger	Yes/No	No		GSBC
Daylight Savings Start:	TOOTTO	INO		CCNBCACK
Month	1 to 12	4		0715711
Week	1 to 5	4		STARTM
Day	1 to 7			STARTW
Minutes to Add	0 to 99	7		STARTD
Daylight Savings Stop	0 10 99	60	min	MINADD
Month	1 to 12	10		
Week	1 to 5			STOPM
Day		5		STOPW
	1 to 7	7		STOPD
Minutes to Subtract	0 to 99	60	min	MINSUB

#### **DISPLAY: Navigator Configuration**

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
Service Password	nnnn	1111	OHITO	PASSWORD
Password Enable	Enable/Disable	Enable		
Metric Display	Off/On	Off		PASS_EBL DISPUNIT
Language Selection	0 = ENGLISH 1 = FRANCAIS 2 = ESPANOL 3 = PORTUGUES	0		LANGUAGE

#### EXV\_CONF: Configuration

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
EXVA Stepper Type	0=1500 Step 1=15000 Step	1		EXVATYPE
EXVA Steps in Range	Type 0=1500 Type 1=15000	15000	STEPS	EXVARANG
EXVA Steps Per Second	Type 0=30 Type 1=300	300		EXVARATE
EXVA Fail Position in %		0	%	EXVAPOSE
EXVA Minimum Steps		0	STEPS	EXVAMINS
EXVA Maximum Steps	Type 0=1500 Type 1=15000	15000	STEPS	EXVAMAXS
EXVA Overrun Steps	Type 0=100 Type 1=1000	1000	STEPS	EXVAOVRS
EXVB Stepper Type	0=1500 Step 1=15000 Step	1		EXVBTYPE
EXVB Steps in Range	Type 0=1500 Type 1=15000	15000	STEPS	EXVBRANG
EXVB Steps Per Second	Type 0=30 Type 1=300	300		EXVBRATE
EXVB Fail Position in %		0	%	EXVBPOSF
EXVB Minimum Steps		0	STEPS	EXVBMINS
EXVB Maximum Steps	Type 0=1500 Type 1=15000	15000	STEPS	EXVBMAXS
EXVB Overrun Steps	Type 0=100 Type 1=1000	1000	STEPS	EXVBOVRS

#### OCCPC01S: Occupancy Configuration

DESCRIPTION	STATUS	UNITS	POINT
Timed Override Hours	0	hours	OVR-EXT
Period 1 DOW (MTWTFSSH)	00000000		DOW1
Occupied from	00:00		OCCTOD1
Occupied to	00:00		UNOCTOD1
Period 2 DOW (MTWTFSSH)	00000000		DOW2
Occupied from	00:00		OCCTOD2
Occupied to	00:00		UNOCTOD2
Period 3 DOW (MTWTFSSH)	00000000		DOW3
Occupled from	00:00		OCCTOD3
Occupied to	00:00		UNOCTOD3
Period 4 DOW (MTWTFSSH)	00000000		DOW4
Occupied from	00:00		OCCTOD4
Occupied to	00:00		UNOCTOD4
Period 5 DOW (MTWTFSSH)	00000000		DOW5
Occupied from	00:00		OCCTOD5
Occupied to	00:00		UNOCTOD5
Period 6 DOW (MTWTFSSH)	00000000		DOW6
Occupied from	00:00		OCCTOD6
Occupied to	00:00		UNOCTOD6
Period 7 DOW (MTWTFSSH)	00000000		DOW7
Occupied from	00:00		OCCTOD7
Occupied to	00:00		UNOCTOD7
Period 8 DOW (MTWTFSSH)	00000000		DOW8
Occupied from	00:00		OCCTOD8
Occupied to	00:00		UNOCTOD8

# OPTIONS1: Options Configuration

DESCRIPTION	STATUS	DEFAULT	POINT
Cooler Fluid	1 = Water 2 = Med. Brine 3 = Low Brine	1	FLUIDTYP
Min. Load Valve Select	No/Yes	No	MLV_FLG
Head Press. Control Type	0 = None 1 = Air Cooled 2 = Water Cooled 3 = Common Condenser 4 = Independent Condenser	0	HEAD_TYP
Var Head Pressure Select	0 = None 1 = 4-20 mA 2 = 0-20 mA 3 = 20-0 mA	0	VHPTYPE
Pressure Transducers	No/Yes	Yes	PRESS TY
Cooler Pump Control	Off/On	Off	CPC
Condenser Pump Interlock	Off/On	Off	CND LOCK
Condenser Pump Control	0 = Not Controlled 1 = On when STATE is On 2 = On when compressors are On	0	CNPC
Condenser Fluid Sensors	No/Yes	No	CD TEMP
EMM Module Installed	No/Yes	No	EMM BRD

# **OPTIONS2: Options Configuration**

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
Control Method	0 = Switch 1 = 7 day sched, 2 = Occupancy 3 = CCN	0	3,111,0	CONTROL
Loading Sequence Select	1 = Equal loading 2 = Staged loading	1		SEQ_TYPE
Lead/Lag Sequence Select	1 = Automatic 2 = Circuit A leads 3 = Circuit B leads	1		LEAD_TYP
Compressor Sequence	1 = Automatic 2 = Compressor 1 Leads 3 = Compressor 2 Leads	1		COMP_SEQ
Cooling Setpoint Select	0 = Single 1 = Dual, remote switch controlled 2 = Dual, 7 day clock controlled 3 = Dual, CCN occupancy controlled 4 = 4-20 mA input	0	¥e	CLSP_TYP
Heating Setpoint Select	0 = Single 1 = Dual, remote switch controlled 2 = Dual, 7 day clock controlled 3 = Dual, CCN occupancy controlled 4 = 4-20 mA input	0		HTSP_TYP
Ramp Load Select	Enable/Disable	Enable		RAMP EBL
Heat Cool Select	Cool	Cool		HEATCOOL
High LCW Alert Limit	2 to 60	60.0	ΔF	LCW LMT
Minutes off time	0 to 15	0	min	DELAY
Deadband Multiplier	1.0 to 4.0	2.0	11811	Z GAIN
Close Control Select	Disable/Enable	Disable		CLS CTRL
Ice Mode Enable	Disable/Enable	Disable		ICE CNFG
Current Unbalance SetPnt	10 to 25	10	%	CUR TRIP
Enable Noflow Detection	Disable/Enable	Enable	70	NOFLOWEN
Winterize Alert Config	Disable/Enable	Enable		WINTMSC
Alarm Relay Usage	0 = Alerts and Alarms 1 = Alarms Only 2 = Off	0		ALRMCNFG

#### **RESETCON: Options Configuration**

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
COOLING RESET				
Cooling Reset Type	0 = No Reset 1 = 4 to 20 mA Input 2 = External Temp — OAT 3 = Return Fluid 4 = External Temp — SPT	0		CRST_TYP
4-20 MA RESET				
4-20 — Degrees Reset	-30 to +30	0	Æ	C420_DEG
REMOTE RESET				
Remote — No Reset Temp	0 to 125	125	dF	CREM_NO
Remote — Full Reset Temp	0 to 125	0	dF	CREM_FUL
Remote — Degrees Reset	-30 to +30	0	45	CREM_DEG
RETURN TEMPERATURE RESET				
Return — No Reset Temp	0 to 30	10	Æ	CRTN_NO
Return — Full Reset Temp	0 to 10	0	۸F	CRTN_FUL
Return — Degrees Reset	-30 to +30	0	٧F	CRTN_DEG
HEATING RESET				
Heating Reset Type	0 = No Reset 1 = 4 to 20 mA Input 2 = External Temp — OAT 3 = Return Fluid 4 = External Temp — SPT	0		HRST_TYP
4-20 MA RESET				
4-20 — Degrees Reset	-30 to +30	. 0	샤	H420_DEG
REMOTE RESET				
Remote — No Reset Temp	0 to 125	50	dF	HREM_NO
Remote — Full Reset Temp	0 to 125	80	dF	HREM_FUL
Remote — Degrees Reset	-30 to +30	0	٩F	HREM_DEG
RETURN TEMPERATURE RESET				
Return — No Reset Temp	0 to 10	10	Æ	HRTN_NO
Return — Full Reset Temp	0 to 30	0	٠F	HRTN_FUL
Return — Degrees Reset	-30 to +30	0	NF.	HRTN DEG
DEMAND LIMIT				
Demand Limit Select	0 = None 1 = External Switch Input 2 = 4 to 20 mA Input 3 = Loadshed	0		DMD_CTRL
Demand Limit at 20 mA	0 to 100	100	%	DMT20MA
Loadshed Group Number	0 to 99	0	le constant	SHED_NUM
Loadshed Demand Delta	0 to 60	0	%	SHED_DEL
Maximum Loadshed Time	0 to 120	60	min .	SHED_TIM
Demand Limit Switch 1	0 to 100	80	%	DLSWSP1
Demand Limit Switch 2	0 to 100	50	%	DLSWSP2
LEAD/LAG				
Lead/Lag Chiller Enable	Disable/Enable	Disable		LL_ENA
Master/Slave Select	Slave/Master	Master		MS_SEL
Slave Address	0 to 239	2		SLV_ADDR
Lead/Lag Balance Select	0 = Master Leads 1 = Slave Leads 2 = Automatic	0		LL_BAL
_ead/Lag Balance Delta	40 to 400	168	hours	LL_BAL_D
ag Start Delay	0 to 30	5	min	LL DELAY
Parallel Configuration	Yes/No	No		PARALLEL

## SCHEDOVR: Schedule and Timed Override Configuration

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
Schedule Number	0 - 99	0		SCHEDNUM
Override Time Limit	0-4	0	hours	OTL
Timed Override Hours	0-4	0	hours	OVR EXT
Timed Override	Yes/No	No		TIMEOVER

#### **SETPOINT: Configuration**

DESCRIPTION	STATUS	DEFAULT	UNITS	DOINT
COOLING			OMITO	POINT
Cool Setpoint 1	-20 to 70	44.0	°F	0004
Cool Setpoint 2	-20 to 70	44.0	°F	CSP1
Ice Setpoint	-20 to 32	32.0	°F	CSP2 CSP3
HEATING				
Heat Setpoint 1	80 to 140	100.0	°F	HODA
Heat Setpoint 2	80 to 140	100.0	°F	HSP1 HSP2
RAMP LOADING				
Cooling Ramp Loading	0.2 to 2.0	1.0		ODALID
Heating Ramp Loading	0.2 to 2.0	1.0		CRAMP HRAMP
HEAD PRESSURE				
Head Pressure Setpoint A	80 to 140	113	°F	1105
Head Pressure Setpoint B	80 to 140	113		HSP_A
20.point 2	00 10 140	113	۰F	HSP_B
Approach Setpoint	0.1 to 20.0	3.0	°F	APRCH SP

# **UNIT: Base Unit Configuration**

DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
Unit Type	1 = Air Cooled 2 = Water Cooled 3 = Split System 4 = Heat Machine 5 = Air Cooled Heat Reclaim	1	·	UNIT_TYP
Unit Size	76 to 350	76	TONS	SIZE
Circuit A % Capacity	0 to 100	50	%	CIRCACAP
Number Circ A Compressor	1 to 2	1	,,,	NUMCA
Number Circ B Compressor	0 to 2	1		NUMCB
Discharge Super. Setpoint	10 to 40	22.0	°F	
EXV Circ. A Min Position	0 to 100	8.0	%	DSH_SP
EXV Circ. B Min Position	0 to 100	8.0	%	EXVAMINE
Fan Staging Select	1 to 8	1*	70	EXVBMINP
Compr. A1 Must Trip Amps	10 to 560	0†		FAN_TYPE
Compr. A2 Must Trip Amps	10 to 560	0†		CA1_MTA
Compr. B1 Must Trip Amps	10 to 560	0†		CA2_MTA
Compr. B2 Must Trip Amps	10 to 560	0 <del>1</del>		CB1_MTA
		- 0		CB2_MTA
Economized?	No/Yes	Yes		ECON SEL
Number of Evap: Passes	1 to 4	2		
Circuit with LWT Sensor	A/B	Ā		EVAPPASS
Con Table 7				LWTCKT

<sup>\*</sup>See Table 7. †See Appendix A.

#### **SERVICE: Configuration**

				2
DESCRIPTION	STATUS	DEFAULT	UNITS	POINT
PID GAINS			ONITO	POINT
Head Pressure P Gain	-20.0 to +20.0	1.0		HD PGAIN
Head Pressure I Gain	-20.0 to +20.0	0,1		HD IGAIN
Head Pressure D Gain	-20.0 to +20.0	-0.0		HD DGAIN
Water Valve Minimum Pos.	0 to 100	20	%	HD_MIN
MISCELLANEOUS				
Motor Temp Setpoint	120.0 to 240.0	200.0	°F	MTR T SP
Brine Freeze Point	-20.0 to 34.0	34.0	°F	BRN_FRZ
Max. Cond. Temp Setpoint	100 to Default		°F	MCT_SP
EXVA Start Position	0 to 40	20	%	EXVSPOSA
EXVB Start Position	0 to 40	20	%	EXVSPOSE
COMPRESSOR ENABLE				
Enable Compressor A1	Enable/Dsable	Enable		ENABLEA1
Enable Compressor A2	Enable/Dsable	Enable		ENABLEAT ENABLEA2
Enable Compressor B1	Enable/Dsable	Enable		ENABLEB1
Enable Compressor B2	Enable/Dsable	Enable		ENABLEB1

<sup>\*</sup> GXN,R, = 152 F, HXA = 145 F, HXC = 118 F

#### **ALARMS: Maintenance Display**

DESCRIPTION	STATUS	POINT
Active Alarm #1	Axxx or Txxx	ALARM01C
Active Alarm #2	Axxx or Txxx	ALARM02C
Active Alarm #3	Axxx or Txxx	ALARM03C
Active Alarm #4	Axxx or Txxx	ALARM04C
Active Alarm #5	Axxx or Txxx	ALARM05C
Active Alarm #6	Axxx or Txxx	ALARM06C
Active Alarm #7	Axxx or Txxx	ALARM07C
Active Alarm #8	Axxx or Txxx	ALARM08C
Active Alarm #9	Axxx or Txxx	ALARM09C
Active Alarm #10	Axxx or Txxx	ALARM10C
Active Alarm #11	Axxx or Txxx	ALARM11C
Active Alarm #12	Axxx or Txxx	ALARM12C
Active Alarm #13	Axxx or Txxx	ALARM13C
Active Alarm #14	Axxx or Txxx	ALARM14C
Active Alarm #15	Axxx or Txxx	ALARM15C
Active Alarm #16	Axxx or Txxx	ALARM16C
Active Alarm #17	Axxx or Txxx	ALARM17C
Active Alarm #18	Axxx or Txxx	ALARM18C
Active Alarm #19	Axxx or Txxx	ALARM19C
Active Alarm #20	Axxx or Txxx	ALARM20C
Active Alarm #21	Axxx or Txxx	ALARM21C
Active Alarm #22	Axxx or Txxx	ALARM22C
Active Alarm #23	Axxx or Txxx	ALARM23C
Active Alarm #24	Axxx or Txxx	ALARM24C
Active Alarm #25	Axxx or Txxx	ALARM25C

#### **CURRMODS: Maintenance Display**

DESCRIPTION	STATUS	POINT
CSM controlling Chiller	ON/OFF	MODE_1
WSM controlling Chiller	ON/OFF	MODE_2
Master/Slave control	ON/OFF	MODE_3
Low Source Protection	ON/OFF	MODE_4
Ramp Load Limited	ON/OFF	MODE_5
Timed Override in effect	ON/OFF	MODE_6
Low Cooler Suction TempA	ON/OFF	MODE_7
Low Cooler Suction TempB	ON/OFF	MODE 8
Slow Change Override	ON/OFF	MODE 9
Minimum OFF time active	ON/OFF	MODE_10
Low Discharge Superheat A	ON/OFF	MODE_11
Low Discharge Superheat B	ON/OFF	MODE_12
Dual Setpoint	ON/OFF	MODE_13
Temperature Reset	ON/OFF	MODE_14
Demand Limit in effect	ON/OFF	MODE_15
Cooler Freeze Prevention	ON/OFF	MODE_16
Lo Tmp Cool/Hi Tmp Heat	ON/OFF	MODE_17
Hi Tmp Cool/Lo Tmp Heat	ON/OFF	MODE_18
Making ICE	ON/OFF	MODE_19
Storing ICE	ON/OFF	MODE 20
High SCT Circuit A	ON/OFF	MODE_21
High SCT Circuit B	ON/OFF	MODE 22
High Motor Current Cir. A	ON/OFF	MODE 23
High Motor Current Cir. B	ON/OFF	MODE 24
CKT A Off Ref Flow Delay	ON/OFF	MODE 25
CKT B Off Ref Flow Delay	ON/OFF	MODE 26
Circuit A — Pumping out	ON/OFF	MODE_27
Circuit B — Pumpout out	ON/OFF	MODE 28
Unit Off: No Water Flow	ON/OFF	MODE 29

# **DUALCHIL: Maintenance Display**

DESCRIPTION	STATUS	UNITS	POINT
Dual Chiller Link Good?	103/140		DC LINK
Master Chiller Role	STAND ALONE, Lead Chiller, Lag Chiller		MC ROLE
Slave Chiller Role	STAND ALONE, Lead Chiller, Lag Chiller		SC ROLE
Lead Chiller Ctrl Point	snnn.n	dF	LEAD CP
Lag Chiller Ctrl Point	snnn,n	dF	LAG CP
Control Point	snn,n	dF	CTRL_PNT
Cool Entering Fluid-Slave	snnn,n	dF	COOLEWIS
Cool Leaving Fluid-Slave	snnn.n	dF	COOLLWIS
Cooler Entering Fluid	snrin.n	dF	COOL EWT
Cooler Leaving Fluid	snnn,n	dF	COOL LWT
Lead/Lag Leaving Fluid	snn.n	dF	
Percent Avail.Capacity	0-100	%	DUAL_LWT
Percent Avail.Cap.Slave	0-100		CAP_A
Lag Start Delay Time	hh:mm	%	CAP_A_S
Load/Unload Factor			LAGDELAY
Load/Unload Factor-Slave	snnn.n		SMZ
Lead SMZ Clear Commanded	snnn.n		SMZSLAVE
Lag- SMZ Clear Commanded	Yes/No		LEADSMZC
	Yes/No		LAG_SMZC
Lag Commanded Off?	Yes/No		LAG_OFF
Dual Chill Lead CapLimit	0-100	%	DCLDCAPL
Dual Chill Lag CapLImit	0-100	%	DCLGCAPL

# LOADFACT: Maintenance Display

DESCRIPTION	STATUS	UNITS	DOINE
CAPACITY CONTROL		ONIS	POINT
Load/Unload Factor	snn.n	0/.	0117
Control Point	snnn.n	/6 °E	SMZ
Leaving Fluid Temp	snn.n		CTRL_PNT
Calculated Z factor			LWT
Capacity Trans. State	n.n		Z_CALC
oupacity mans, state	n	6	CAP TRAN

# MISCDATA: Maintenance Display

DESCRIPTION	STATUS	UNITS	POINT
MISCELLANEOUS		011110	POINT
Options Temp 1, EXV AN2	snnn.n	°E	ODT THE
Options Temp 2, EXV AN1	snnn.n	°F	OPT_TMP1
Options Temp 3, SCB AN9	snnn.n	°F	OPT_TMP2 OPT_TMP3
Options Temp 4, SCB AN10	snnn.n	•E	OPT_TMP3
Options Current 1	nn.n	ma	OPT_CUR1
Options Current 2	nn.n	ma	OPT_CUR2
Pumpout Failure Count, A	nnn		The second secon
Pumpout Failure Count, B	nnn		PFAIL_A PFAIL B
HXC Brine Config Lock	No/Yes	_	BRN LOCK

# OCCDEFM: Occupancy Maintenance Display

DESCRIPTION	STATUS	POINT
Current Mode (1=Occup.)	0,1	MODE
Current Occup. Period #	0-8	PER-NO
Timed-Override in Effect	Yes/No	OVERLAST
Time-Override Duration	0-4 hours	OVR HRS
Current Occupied Time	hh:mm	STRTTIME
Current Unoccupled Time	hh:mm	ENDTIME
Next Occupied Day		NXTOCDAY
Next Occupied Time	hh:mm	NXTOCTIM
Next Unoccupied Day		NXTUNDAY
Next Unoccupied Time	hh:mm	NXTUNTIM
Previous Unoccupied Day	100,11011	PRVUNDAY
Previous Unoccupied Time	hh:mm	PRVUNTIM

#### **OILPRESS: Maintenance Display**

DESCRIPTION	STATUS	UNITS	POINT
A1 Oil Pressure	snnn.n	PSIG	OP_A1
A2 Oil Pressure	snnn.n	· PSIG	OP_A2
B1 Oil Pressure	snnn.n	PSIG	OP B1
B2 Oil Pressure	snnn.n	PSIG	OP_B2
A1 Oil Filter Diff. Press	nnn.n	PSI	FLTP A1
A2 Oil Filter Diff. Press	nnn.n	PSI	FLTP A2
B1 Oil Filter Diff. Press	nnn.n	PSI	FLTP B1
B2 Oil Filter Diff. Press	nnn.n	PSI	FLTP_B2
OIL PRESSURE SETPOINTS			
Calculated Oil Press A1	nn.n	PSI	OIL SPA1
Calculated Oil Press A2	nn.n	PSI	OIL SPA2
Calculated Oil Press B1	nn.n	PSI	OIL SPB1
Calculated Oil Press B2	nn.n ·	PSI	OIL_SPB2
MAX OPERATING PRESSURE			
Calculated MOP Circuit A	nn.n	°F	MOP_SPA
Calculated MOP Circuit B	nn.n	°F	MOP SPB

#### STRTABS: Maintenance Display

DESCRIPTION	STATUS	UNITS	POINT
Machine Operating Hours	nnnnn	hours	ABS HRM
Machine Starts	nnnnn		ADO_TITUM
Circuit A Run Hours	nnnnn	hours	ABS CYM
Compressor A1 Run Hours	nnnnn	hours	ABS_HRA1
Compressor A2 Run Hours	nnnnn	hours	ABS HRA2
Circuit B Run Hours	nnnnn	hours	ABS HRB
Compressor B1 Run Hours	nnnnn	hours	ABS_HRB1
Compressor B2 Run Hours	nnnnn	hours	ABS_HRB2
Circuit A Starts	nnnnn		ABS CYA
Compressor A1 Starts	nnnnn		ABS CYA1
Compressor A2 Starts	nnnnn		ABS CYA2
Circuit B Starts	nnnnn		ABS CYB
Compressor B1 Starts	nnnnn	-	ABS CYB1
Compressor B2 Starts	nnnnn		ABS CYB2

## STRTHOUR: Maintenance Display

DESCRIPTION	STATUS	UNITS	POINT
Machine Operating Hours	nnnnn	hours	HR_MACH
Machine Starts	nnnnn		CY_MACH
Circuit A Run Hours	nnnnn	hours	LID OID I
Compressor A1 Run Hours	nnnnn	hours	HR_CIRA
Compressor A2 Run Hours	100000000000000000000000000000000000000	hours	HR_A1
1. A 1996 A 1997 A	nnnnn	hours	HR_A2
Circuit B Run Hours	nnnnn	hours	HR CIRB
Compressor B1 Run Hours	nnnnn	hours	HR B1
Compressor B2 Run Hours	nnnnn	hours	HR_B2
Circuit A Starts	nnnnn		CY CIRA
Compressor A1 Starts	nnnnn	, , , , , , , , , , , , , , , , , , , ,	CY A1
Compressor A2 Starts	nnnnn		
Circuit B Starts			CY_A2
Control of the process of the control of the contro	nnnnn		CY_CIRB
Compressor B1 Starts	nnnnn		CY_B1
Compressor B2 Starts	nnnnn		CY_B2

#### **APPENDIX G (cont**

**TESTMODE: Maintenance Display** 

DESCRIPTION	STATUS	UNITS	POINT
Service Test Mode	On/Off		MAN_CTRL
Manual Control Override	On/Off		FAC_CTRL
Compressor A1 Relay	On/Off		S_A1_RLY
Compressor A2 Relay	On/Off		S_A2_RLY
Compressor B1 Relay	On/Off		S_B1_RLY
Compressor B2 Relay	On/Off		S B2 RLY
Loader A1 Relay	On/Off	190	S_LDR A1
Loader A2 Relay	On/Off		S LDR A2
Loader B1 Relay	On/Off		S LDR B1
Loader B2 Relay	On/Off		S_LDR B2
Oil Solenoid A1	On/Off		S_OSL A1
Oil Solenoid A2	On/Off		S OSL A2
Oil Solenoid B1	On/Off		S OSL B1
Oil Solenold B2	On/Off		S OSL B2
Motor Coolng A1 Solenoid	On/Off		S_MCS_A1
Motor Coolng A2 Solenoid	On/Off		S_MCS_A1
Motor Coolng B1 Solenoid	On/Off		S_MCS_B1
Motor Coolng B2 Solenoid	On/Off		S_MCS_B2
FAN 1 Relay	On/Off		S_FAN_1
FAN 2 Relay	On/Off		S_FAN_2
FAN 3 Relay	On/Off		S FAN 3
FAN 4 Relay	On/Off		S_FAN_4
Oil Heater	On/Off		
Oil Heater	On/Off		S_OHTR_A
Oil Pump	On/Off		S_OHTR_B
Oll Pump	On/Off		S_OPMP_A
Cooler Pump Relay	On/Off		S_OPMP_B
Condenser Pump Relay	On/Off		S_CL_PMP
Minimum Load Valve	On/Off		S_CN_PMP
Cooler Heater	On/Off		S_MLV
Remote Alarm Relay	On/Off		S_CHTR
EXV % OPEN	0-100	%	S_ALRM
EXV % OPEN	0-100	%	S_EXV_A
Var Head Press %	0-100	%	S_EXV_B
/ar Head Press %	0-100		S_VHPA
iq. Line Solenoid Valve	Open/Close	%	S_VHPB
	Open/Close		S_LLSV

### VERSIONS: Maintenance Display

DESCRIPTION	VERSION	STATUS
MBB	CESR131344-	nn-nn
EXV	CESR131172-	nn-nn
EMM	CESR131174-	nn-nn
SCB	CESR131226-	nn-nn
П ССР 1	100233-1R3-	nn-nn
TI CCP 2	100233-1R3-	nn-nn
NAVIGATOR	CESR130227-	nn-nn

#### **APPENDIX G (cont**

#### WINTLOG: Maintenance Display

DESCRIPTION	STATUS	POINT
Winterization Performed	No	WINTDONE
Date Winterized	. 00/00/00 00:00	WMSG00
Date Winterized	00/00/00 00:00	WMSG01
Date Winterized	00/00/00 00:00	WMSG02
Date Winterized	00/00/00 00:00	WMSG03
Date Winterized	00/00/00 00:00	WMSG04
Date Winterize Alerted	00/00/00 00:00	WALRT00
Date Winterize Alerted	00/00/00 00:00	WALRT01
Date Winterize Alerted	00/00/00 00:00	WALRT02
Date Winterize Alerted	00/00/00 00:00	WALRT03
Date Winterize Alerted	00/00/00 00:00	WALRT04
Date Winter Configured	00/00/00 00:00	WCONF00
Date Winter Unconfigured	00/00/00 00:00	WUCONF00
Date Winter Configured	00/00/00 00:00	WCONF01
Date Winter Unconfigured	00/00/00 00:00	WUCONF01
Date Winter Configured	00/00/00 00:00	WCONF02
Date Winter Unconfigured	00/00/00 00:00	WUCONF02

#### WSMDEFME: WSM Maintenance Display

DESCRIPTION	STATUS	POINT
WSM Active?	Yes/No	WSMSTAT
Chilled water temp	snn.n °F	CHWTEMP
Equipment status	On/Off	CHLRST
Commanded state	Enable/Disable/None	CHLRENA
CHW setpoint reset value	nn.n ^F	CHWRVAL
Current CHW setpoint	snn.n °F	CHWSTPT

APPENDIX H
30GXN,R Duplex Combinations

SIZE	MODULE A	MODULE B
283	153	138
303	163	138
328	178	153
353	178	178
370	225	150
373	253	138
390	264	135
393	253	153
415	264	160
418	268	153
450	225	225
453	228	228
475	249	225
478	253	228
500	249	
503	253	249
. 525	264	253
528		264
	268	268

#### APPENDIX I: MOTORMASTER® V OPERATION INSTRUCTION

Motormaster V (MMV) is a Variable Frequency Drive (VFD) that varies the condenser fan speed. The speed varies in proportion to a 4 to 20 mA signal produced by the *Comfort*Link<sup>TM</sup> controls. The MMV output speed is displayed in Hz.

#### Configuration

The MMV is configured for 1 of 12 operation modes based on the inputs to the control terminal block. 30GXN,R units use operating modes 5-8. In these configurations, the MMV follows a 4 to 20 mA speed reference signal present on terminals 25 (+) and 2 (-). One additional jumper is required to configure the drive for 50/60 Hz operation and input voltage. See Table 1 below for proper inputs. Once the drive is powered, it will change to the mode selected according to the inputs. No additional programming is required.

#### **Drive Programming**

#### **A** CAUTION

It is strongly recommended that the user NOT change any programming without consulting Carrier service personnel. Unit damage may occur from improper programming.

To enter password and change program values: Press Mode.

Upper right decimal point blinks.

Display reads "00".

To enter the PROGRAM mode to access the parameters, press the Mode button. This will activate the PASSWORD prompt (if the password has not been disabled). The display will read "00" and the upper right-hand decimal point will be blinking.

Use the and buttons to scroll to the password value (the factory default password is "111") and press the Mode button. Once the correct password value is entered, the display will read "P01," which indicates that the PROGRAM mode has been accessed at the beginning of the parameter menu (P01 is the first parameter).

NOTE: If the display flashes "Er", the password was incorrect, and the process to enter the password must be repeated.

Press Mode to display present parameter setting.

Upper right decimal point blinks.

Use and to scroll to the desired parameter number.

Use the and buttons to scroll to the desired parameter number.

Once the desired parameter number is found, press the Mode button to display the present parameter setting. The upper right-hand decimal point will begin blinking, indicating that the present parameter setting is being displayed, and that it can be changed by using the up and down buttons.

Use and to change setting.

Press Mode to store new setting.

Pressing the Mode will store the new setting and also exit the PROGRAM mode. To change another parameter, press the Mode key again to re-enter the PROGRAM mode (the parameter menu will be accessed at the parameter that was last viewed or changed before exiting). If the Mode key is pressed within two minutes of exiting the PROGRAM mode, the password is not required access the parameters. After two minutes, the password must be entered in order to access the parameters again.

To change password: first enter the current password then change parameter P44 to the desired password.

To reset factory defaults: change P48 to one of the 4 operating modes (5-8) and then cycle power.

Table 2 shows all program parameters for each of the 4 operating modes.

#### EPM chip:

This drive uses a removable EPM chip to store program parameters. It should not be removed with power applied to the VFD.

**Table 1: Configuration Tables** 

NOMINAL VOLTAGE	MODE	Hz	CONTROL INPUT (pins 25, 2)	START
208/230/460/575*	5	60	External control 4-20 mA	TB1-TB2
208/380	6	60	External control 4-20 mA	TB13A-TB2
230	7	50	External control 4-20 mA	TB13B-TB2
380/415	8	50	External control 4-20 mA	TB13C-TB2

<sup>\*208</sup> v can run in mode 5 or 6.

#### **APPENDIX I (cont**

Table 2: Program Parameters for the 4 Operating Modes:

PARAMETER NUMBER	DESCRIPTION		OPERATING MODES							
P01		Group 5	Group 6	Group 7	Group 8					
P02	Line Voltage: 01 = low line, 02 = high line	01	02	01	02					
P03	Carrier Freq: 01 = 4 kHz, 02 = 6 kHz, 03 = 8 kHz	01	01	01	01					
P04	Startup mode: flying restart	06	06	06	06					
P05	Stop mode: coast to stop	01	01	01	01					
P05	Standard Speed source: 04 = 4-20 ma, 05 = R22, 06 = R134a	04	04	04	04					
P08	TB-14 output: 01 = none	01	01	01	01					
P09	TB-30 output: 01 = none	01	01	01	01					
P10	TB-31 output: 01 = none	01	01	01	01 '					
	TB-13A function sel: 01 = none	01	01	01	01					
P11	TB-13B function sel: 01 = none	01	01	01	01					
P12	TB-13C function sel: 01 = none	01	01	01	01					
P13	TB-15 output: 01 = none	01	01	01	01					
P14	Control: 01 = Terminal strip	01	01	01	01					
P15	Serial link: 02 = enabled 9600,8,N,2 w/timer	02	02	02	02					
P16	Units editing: 02 = whole units	02	02	02	02					
P17	Rotation: 01 = forward only, 03 = reverse only	01	01	01	01					
P19	Acceleration time: 10 sec	10	10	10 .	10					
P20	Deceleration time: 10 sec	10	10	10	10					
P21	Dc brake time: 0	0	0	0						
P22	DC BRAKE VOLTAGE 0%	0	0		0					
P23	Min freq = 8 hz ~ 100 - 160 rpm	8	8	0	0					
P24	Max freq	60		8	8					
P25	Current limit:	125	60	50	50					
P26	Motor overload: 100	100	125	110	110					
	Base freq: 60 or 50 Hz		100	100	100					
	Fixed boost: 0.5 % at low frequencies	60	60	50	50					
	Accel boost: 0%	0.5	0.5	0.5	0.5					
	Slip compensation: 0%	0	0	0	0					
	Preset spd #1: 0	0	0	0	0					
	Preset and #2: 0	57	57	47	47					
	Preset spd #3: 0	0	0	0	0					
	Preset spd 4 default - R22 setpoint, TB12-2 open	0	0	0	0					
P35	Preset spd 5 default - R124a setpoint, TB12-2 open	18.0	18.0	18.0	18.0					
	Preset spd 5 default	12.6	12.6	12.6	12.6					
	Preset spd 6 default	0	0	0	0					
	Skip bandwidth	0	0	0	0					
		0	0	0	0					
	Speed scaling	0	0	0	0					
P40	Frequency scaling 50 or 60 Hz	60	60	50	50					
	oad scaling: default (not used so NA)	200	200	200	200					
_	Accel/decel #2: default (not used so NA)	60	60	60	60					
	Serial address	1	1	1	1					
	Password:111	111	111	111	111					
P45 S	Speed at min signal: 8 Hz used when PID disabled and 4-20ma input	8	8	8	8					
P46 S	Speed at max feedback: 60 or 50 Hz. Used when PID disabled and 4-20ma input	60	60	50	50					
	Clear history? 01 = maintain, (set to 00 to clear)	01	01	01	01					
	Program selection: Mode 1 - 12	05	06	07	08					
	PI Mode: 05 = reverse, 0-5V, 01 = no PID	01	01	01	01					
	/lin feedback = 0 (0V *10)	0	0	0	0					
	Max feedback = 50 (5V * 10)	50	50	50	50					
	Proportional gain = 4%	4	4	4	4					
P65 II	ntegral gain = .2	.2	.2	.2	.2					
P66 P	I accel/decel (setpoint change filter) = 5	5	5	5	5					
P67 N	fin alarm	0	0	0	0					
P68 N	fax alarm	0	0	0	0					

#### **Troubleshooting**

Troubleshooting the Motormaster® V control requires a combination of observing system operation and VFD display information. The MMV should follow the 4-20 mA signal from the *Comfort*Link<sup>TM</sup> controls.

The speed command from the ComfortLink controls can be monitored in 2 ways:

 Variables VH.PA, VH.PB in the "outputs" submenu of ComfortLink control — given as a percentage of 4 to 20 mA range. P56 in Motormaster V shows 4-20 mA input in percent of maximum input.

Due to the variable definitions of each controller, Table 3 shows a cross-reference:

Table 3: Controller Cross-Reference

CONTROL SIGNAL	VH.PA, VH.PB (ComfortLink)	4-20mA Input (P56, Motormaster V)	VFD Speed (P71, Motormaster V)
4 ma	0%	20%	8Hz
12 ma	50%	60%	26Hz
20 ma	100%	100%	60Hz

The MMV also provides real time monitoring of key inputs and outputs. The collective group is displayed through para-meters 50-56 and all values are read only.

- P50 FAULT HISTORY Last 8 faults
- P51: SOFTWARE version
- P52: DC BUS VOLTAGE in percent of nominal. Usually rated input voltage x 1.4.
- P53: MOTOR VOLTAGE in percent of rated output voltage
- P54: LOAD in percent of drives rated output current rating
- P55: VDC INPUT in percent of maximum input: 50 will indicate full scale which is 5 v
- P56: 4-20 mA INPUT in percent of maximum input: 20% = 4 mA, 100% = 20 mA

#### Fault codes

The drive is programmed to automatically restart after a fault and will attempt to restart three times after a fault (the drive will not restart after CF, cF, GF, F1, F2-F9, or F0 faults). If all three restart attempts are unsuccessful, the drive will trip into

FAULT LOCKOUT (LC), which requires a manual reset. See Tables 4 and 5.

To disable external control mode (5-8) and enter manual speed control mode:

Change P05 to '01-key pad'

Push and arrow key to set manual speed.

#### To provide manual start/stop control:

Remove start command jumper and install a switch between the appropriate start terminals.

#### Loss of CCN communications:

CCN communications with external control systems can be affected by high frequency electrical noise generated by Motormaster V control. Ensure unit is well grounded to eliminate ground currents along communication lines.

If communications are lost only while Motormaster V control is in operation, order a signal isolator/repeater (CEAS420876-2) and power supplies (CEAS221045-01, 2 required) for the CCN communication line.

#### Table 4: Fault Codes

FAULT CODE	DESCRIPTION	SOLUTION
AF	High Temperature Fault: Ambient temperature is too high; Cooling fan has failed (if equipped).	Check cooling fan operation
CF	Control Fault: A blank EPM, or an EPM with corrupted data has been installed.	Perform a factory reset using Parameter 48 — PROGRAM SELECTION. See Programming Notes (Step 6).
cF	Incompatibility Fault: An EPM with an incompatible parameter version has been installed.	Either remove the EPM or perform a factory reset (Parameter 48) to change the parameter version of the EPM to match the parameter version of the drive.
GF	Data Fault: User data and OEM defaults in the EPM are corrupted.	Restore factory defaults by toggling P48 to another mode. Then set P48 to desired mode to restore all defaults for that mode. See configuration section (Step 2). If that does not work, replace EPM.
HF	High DC Bus Voltage Fault: Line voltage is too high; Deceleration rate is too fast; Overhauling load.	Check line voltage — set P01 appropriately
JF	Serial Fault: The watchdog timer has timed out, indicating that the serial link has been lost.	Check serial connection (computer) Check settings for P15 Check settings in communication software to match P15
LF	Low DC Bus Voltage Fault: Line voltage is too low.	Check line voltage — set P01 appropriately
OF	Output Transistor Fault: Phase to phase or phase to ground short circuit on the output; Failed output transistor; Boost settings are too high; Acceleration rate is too fast.	Reduce boost or increase acceleration values. If unsuccessful, replace drive.
PF	Current Overload Fault: VFD is undersized for the application; Mechanical problem with the driven equipment.	Check line voltage — set P01 appropriately Check for dirty coils Check for motor bearing failure
SF	Single-phase Fault: Single-phase input power has been applied to a three-phase drive.	Check input power phasing
F1	EPM Fault: The EPM is missing or damaged.	
F2-F9, Fo	Internal Faults: The control board has sensed a problem.	Consult factory.
Drive display = '' even though drive should be running	Start contact is not closed.	Check auxiliary contact for proper operation and configuration. See configuration section (Step 5).
Drive display = 8.0 Hz even though fan should be running faster	Control signal is at 4 mA	Saturated condensing temperature is below setpoint in ComfortLink controls.
VFD flashes 57 (or 47) and LCS	Speed signal lost. Drive will operate at 57 (or 47) Hz until reset or loss of start command. Resetting requires cycling start command (or power).	In stand-alone mode: In external control mode (30GXN,R) check wiring from unit controls J8 for 4-20 mA signal. Drive runs at 57 Hz in modes 5,6 and 47 Hz in modes 7,8.
VFD flashes "LCS and"	Start contact is not closed.	Check auxiliary contact for proper operation and configuration. See configuration section (Step 5).
LC	Fault lockout — 3 or more unsuccessful starts	View PSD: Fault History to determine.

#### **Table 5: Status Indication**

FAULT CODE	FAULT NAME	DESCRIPTION
CL	CURRENT LIMIT	The output has exceeded the CURRENT LIMIT setting (Parameter 25) and the drive is reducing the output frequency to reduce the output current. If the drive remains in CURRENT LIMIT for too long, it can trip into a CURRENT OVERLOAD fault (PF).
Er	ERROR	Invalid data has been entered.
GE	GE	"GE" will be displayed if an attempt is made to change the OEM default settings when the drive is operating in the OEM mode (see Parameter 48).
LC	FAULT LOCKOUT	Failed three restart attempts. Requires a manual reset.
SP	START PENDING	This is displayed during the first 15 second interval between restart attempts.

# 30 Series Screw Liquid Chiller Maintenance Data Log

CHILLER MODEL NO.

CHILLER SERIAL NO.

	1	Motor	Temp.	L					<b>新田村</b>	をは、							1900年								経経経			CONTRACTOR OF THE PARTY OF THE			
acc	5 5	5	Oil Pressure													HANNE AND AND ADDRESS OF	語は機器	がはないので								経過機能					
COMPRESSOR			Pressure Diff.					は経過機能	的議論語								Action to the								製造製造						
	ľ	Discharge	Gas Temp.								<b>新新聞</b>																				
		_	o O	F4	A2	B1	B2	A1	Ş	18	B2	A1	A2	18	B2	A1	A2	81	82	F4	<b>K</b> 2	<u>m</u>	B2	A1	A2	B1	82	A1	A2	120	B2
	.1.	Cooled	Outside Air Temp																												
	pelc	Temp.	ln Out													i.															
CONDENSER	Water Cooled	-	_									_		-	-				<b>建</b>		-										4
CONDE	Ma	Pressure	<u>E</u>			-						_	_																		4
0		+	Cond.																				and the second								1
	Refrigerant		Pressure				STATE OF THE PERSON NAMED IN COLUMN						1						_		1		The contract of the contract o								
		Γ	o ti				1000000							-	1000000					-			1000								1
	er	Temp.	드				AT HERE			iller initi					Medical Control of the Control of th								SECTION TON					_			1
	Water	sure	ont			6	Willeston of the				-				Automotion in					*	_	_	AND SHAPE OF		ir ir						1
		Pressure	프				September 1								Checogone		100						27 (32.58q)								1
		λ.	S <sub>S</sub>				and the state of t								THE PURCHASION								5						T		
	erant	FCOD	Press.				Chicagolican				W.				Child and Street								20年前 100000000000000000000000000000000000								
	Refriger	Sat.	Suct.				技術の意味		THE CONTRACTOR						ESCHOOLS NAMED IN		18			1356											
		Suction	Pressure				<b>经报货金额</b>								ALIES STATES							¥6			distribution of		The state of the s		T		
7	Capacity -	P. C.				5	が対象を対象		STATE OF THE PARTY				39		おおはまると				8				THE RESERVE		400000000000000000000000000000000000000		1				
		Clican		4		М		4	THE STATE OF THE S	Ω		4		В		A		ω		4		М		A	1 22	m		<		В	
Dicialo	aminano e	Date/	Time								Market Market				THE REAL PROPERTY OF		のないので		The state of the s		T	T									

Copyright 2004 Carrier Corporation

PLANT

# CUT ALONG DOTTED LINE

#### START-UP CHECKLIST FOR 30GX,HX LIQUID CHILLER

. Project Infor	mation						
Job Name		<u>(</u>	19				market M
Address				ii			
				State _			
Installing Contra	actor						
Sales Office _		×		10			
Design Informa	ation						
	Capacity	EWT	LWT	Fluid Type	Flow Rate	P.D.	Ambient
Cooler							時間時
Condenser							
Equipment							
Model				Serial	( *2/	X	
Compressors							
A1) Model				Serial			
A2) Model			e	Serial		-	
B1) Model	•			Serial			
B2) Model					a .		
Condenser (30	OHXA only)					*	
	Circuit A				Circuit B		
Model				Model	# 	4	
Serial			0	Serial			
Model				Model			
Serial				Serial			

#### II. Preliminary Equipment Check (to be completed by installing contractor Is there any physical damage? □ No Description 1. Unit is installed level as per the installation instructions. ☐ Yes □ No 2. Power supply agrees with the unit nameplate. ☐ Yes □ No 3. Correct control voltage \_ ☐ Yes □ No 4. Electrical power wiring is installed properly. (Branch circuit fused or HACR breaker) ☐ Yes □ No 5. Unit is properly grounded. ☐ Yes □ No 6. Electrical circuit protection has been sized and installed properly. ☐ Yes □ No 7. All terminals are tight. ☐ Yes □ No All plug assemblies are tight. ☐ Yes □ No 9. All cables and thermistors have been inspected for crossed wires. ☐ Yes □ No 10. All thermistors are fully inserted into wells. ☐ Yes □ No 11. Mechanical room maintained above 50 F (10 C) (30HX only). ☐ Yes □ No 12. Relief valve vent piping installed per local codes. ☐ Yes □ No 13. Wind baffles installed (30GX, 09DX). ☐ Yes □ No NOTE: Required for unit operation where winds of 5 mph (2.2 m/s) or greater are anticipated at outdoor ambient temperatures below 32 F (0° C). Chilled Water System Check 1. All chilled water valves are open. ☐ Yes □ No 2. All piping is connected properly. ☐ Yes □ No 3. All air has been purged from the system. ☐ Yes □ No Chilled water pump is operating with the correct rotation. ☐ Yes □ No 5. Chilled water pump starter interlocked with chiller. ☐ Yes ☐ No Inlet piping to cooler includes a 20 mesh strainer. ☐ Yes □ No 7. Water loop volume greater than 3 gal/ton for air conditioning or 6 gal/ton for process cooling and low ambient operation. ☐ Yes □ No Proper loop freeze protection provided to \_\_\_\_\_ °F (°C). ☐ Yes □ No Antifreeze type\_ Concentration (If antifreeze solution is not utilized on 30GX machines and the minimum outdoor ambient is below 32 F (0° C) then items 9-12 have to be completed to provide cooler freeze protection to 0° F. Refer to Installation Instructions for proper cooler winterization procedure.) 9. Outdoor piping wrapped with electric heater tape. ☐ Yes □ No 10. Cooler heaters installed and operational (30GX Only). ☐ Yes □ No 11. Cooler heads and tube sheets are insulated. ☐ Yes □ No 12. Chilled water pump controlled by chiller. ☐ Yes □ No (Chilled water pump will start automatically to circulate water through

cooler during potential freezing conditions.)

	Condenser water System Check (30HXC Only)		
	All condenser water valves are open.	☐ Yes	□N
	2. All piping is connected properly.	☐ Yes	ПΝ
	3. All air has been purged from the system.	☐ Yes	$\square$ N
	4. Condenser water pump is operating with the correct rotation.	☐ Yes	ПΝ
	5. Condenser water pump controlled by chiller.	☐ Yes	□N
	6. Inlet piping to condenser includes a 20 mesh strainer.	☐ Yes	□ N
	7. Condenser water flow switch installed. (Required for 30HXC Brine.)	☐ Yes	
	8. Condenser water flow switch configured and operational.	☐ Yes	□ N
	Condenser water control valve installed.     (Separate control power required.)	☐ Yes	□ N
	Remote Condenser System Check (30HXA Only)		
	<ol> <li>All refrigerant piping is connected properly.</li> </ol>	☐ Yes	
	2. Equalizer line is installed from motor cooling line to back-pressure valve.	☐ Yes	□ No
	3. Liquid line filter driers installed.	☐ Yes	
	Liquid line solenoid valves installed.	☐ Yes	□No
	5. R-134a fan cycling pressure switches installed (09DK).	☐ Yes	□No
	6. Refrigerant piping and condenser have been leak checked and evacuated.	☐ Yes	□No
III.	Unit Start-Up		ň
	1. All liquid line valves are open.	☐ Yes	□ No
	2. All discharge valves are open.	☐ Yes	□No
	3. All suction service valves are open (if equipped).	☐ Yes	□ No
	4. All oil line valves are open.	☐ Yes	□ No
	5. Chilled water flow switch is operational.	☐ Yes	□ No
	6. Leak check unit. Locate, repair and report any refrigerant leaks.	☐ Yes	□ No
	7. Voltage is within unit nameplate range.	☐ Yes	□No
	8. Check voltage imbalance: A-B A-C B-C Average voltage = (A-B + A-C + B-C)/3  Maximum deviation from average voltage =		
	Voltage imbalance =% (max. deviation/average voltage) x 100		
	Voltage imbalance less than 2%.	☐ Yes	□No
	(DO NOT start chiller if voltage imbalance is greater than 2%. Contact local Utility for assistance.)		
	9. Verify cooler flow rate (maximum and minimum)  Pressure entering cooler psig (kpa)  Pressure leaving cooler psig (kpa)  Cooler pressure drop psig (kpa)  Psig x 2.31 ft/psi = ft of water	□ Yes	□ No
	Kpa x 0.334 m/psi = m of water	· · · · · · · · · · · · · · · · · · ·	
	Maximum cooler flow rate gpm (I/s) (See Cooler Pressure D  Minimum cooler flow rate gpm (I/s) (See Cooler Pressure D		

. Unit Start-Up (cont			2/	
<ol><li>Verify condenser flow rate.</li></ol>		☐ Yes	□No	
	psig (kpa)			
Pressure leaving condenser	psig (kpa)			
Condenser pressure drop	psig (kpa)			
	ft of water	×		
Application of the state of the	m of water			
Condenser flow rate	gpm (l/s) (See Co	ndenser Pressur	e Drop Curve)	
Start and operate machine. Complete the f	ollowing:			
1. Complete component test.		☐ Yes	□No	
2. Check refrigerant and oil charge. Record ch	narge information.	☐ Yes	□No	
3. Record compressor motor current.		☐ Yes	□No	
4. Record two sets of operational log readings	ò.	☐ Yes	□No	
5. Provide operating instructions to owner's pe		n time h		
Construction of the contract o	mon dono	77 time1		
Pofulacional Observa				
	cuit A Circ	cuit B		
Additional charge required	*			
Oil Charge		30		
Additional charge required				**
			-	
Comments:			2	
			(B)	
21 2-1-4	.0			
			8	
				0
Signatures:	D 80		e e	
Start-up Technician	Customer Represe	ntative		
Date	Date		*	

# Record Software Versions MODE — RUN STATUS

SUB-MODE	ITEM	DISPLAY	ITEM EXPANSION
VERS	MBB		CESR131344
†17	EXV		CESR131172
	EMM		CESR131174
	CP1		100233-1R3
	CP2		100233-1R3
	SCB		CESR131226
	NAVI		CESR131227

(Press and simultaneously to obtain software versions)

# Record Configuration Information MODE — CONFIGURATION

SUB-MODE			ITEM EXPANSION	ENTRY
DISP	TEST	ON/OFF	TEST DISPLAY LED'S	
	METR	ON/OFF	METRIC DISPLAY	
	LANG	х	LANGUAGE SELECTION	-
	PAS.E	ENBL/DSBL	PASSWORD ENABLE	
	PASS	XXXX	SERVICE PASSWORD	
UNIT	TYPE	х	UNIT TYPE	
	TONS	XXX	UNIT SIZE	
	CAP.A	xxx%	CIRCUIT A% CAPACITY	
	CMP.A	х	NUMBER CIRC A COMPRESSOR	
	CMP.B	Х	NUMBER CIRC B COMPRESSOR	
	DIS.S	XX.X	DISCHARGE SUPER SETPOINT	
	FAN.S	X	FAN STAGING SELECT	
	CM.A1	xxx AMPS	COMPR. A1 MUST TRIP AMPS	
	CM.A2	xxx AMPS	COMPR. A2 MUST TRIP AMPS	
	CM.B1	xxx AMPS	COMPR. B1 MUST TRIP AMPS	
	CM.B2	xxx AMPS	COMPR. B2 MUST TRIP AMPS	
OPT1	FLUD	X	COOLER FLUID	
	MLVS	YES/NO	MIN LOAD VALVE SELECT	
	HPCT	X	HEAD PRESSURE CONTROL TYPE	17
	VHPT	X	VAR HEAD PRESSURE SELECT	
	PRTS	YES/NO	PRESSURE TRANSDUCERS	
	CPC	ON/OFF	COOLER PUMP CONTROL	
	CNP.I	ON/OFF	CONDENSER PUMP INTERLOCK	
	CNPC	X	CONDENSER PUMP CONTROL	
	CWT.S	YES/NO	CONDENSER FLUID SENSORS	
	EMM	YES/NO	EMM MODULE INSTALLED	

# Record Configuration Information (cont) MODE — CONFIGURATION (cont)

SUB-MODE	ITEM	DISPLAY	ITEM EXPANSION	ENTRY
OPT2	CTRL	x	CONTROL METHOD	LIVIT
	CCNA	xxx	CCN ADDRESS	
	CCNB '	xxx	CCN BUS NUMBER	
	BAUD	X	CCN BAUD RATE	
	LOAD	x	LOADING SEQUENCE SELECT	
	LLCS	х	LEAD/LAG SEQUENCE SELECT	
	CP.SQ	х	COMPRESSOR SEQUENCE	
	LCWT	xx.x	HIGH LCW ALERT LIMIT	
	DELY	XX	MINUTES OFF TIME	
	CLS.C	ENBL/DSBL	CLOSE CONTROL SELECT	
	ICE.M	ENBL/DSBL	ICE MODE ENABLE	
	C.UNB	xx%	CURRENT UNBALANCE SETPOINT	
	NO.FL	ENBL/DSBL	NO REFRIGERANT FLOW ALRM ENABLE	
	W.MSG	ENBL/DSBL	WINTERIZE ALERT CONFIG	
2	ALR.C	x	ALARM RELAY USAGE	
RSET	CRST	x	COOLING RESET TYPE	
	CRT1	XXX.X	NO COOL RESET TEMP	
	CRT2	XXX.X	FULL COOL RESET TEMP	
	DGRC	XX.X	DEGREES COOL RESET	
	HRST	х	HEATING RESET TYPE	
	HRT1	XXX.X	NO HEAT RESET TEMP	1
	HRT2	XXX.X	FULL HEAT RESET TEMP	
	DGRH	xx.x	DEGREES HEAT RESET	11
W.	DMDC	X	DEMAND LIMIT SELECT	
	DM20	xxx%	DEMAND LIMIT AT 20 MA	
	SHNM	XXX	LOADSHED GROUP NUMBER	
	SHDL	xxx%	LOADSHED DEMAND DELTA	
	SHTM	XXX	MAXIMUM LOADSHED TIME	
	DLS1	xxx%	DEMAND LIMIT SWITCH 1	
	DLS2	xxx%	DEMAND LIMIT SWITCH 2	
	LLEN	ENBL/DSBL	LEAD/LAG CHILLER ENABLE	
	MSSL	SLVE/MAST	MASTER/SLAVE SELECT	
	SLVA	XXX	SLAVE ADDRESS	
	LLBL	X	LEAD/LAG BALANCE SELECT	
	LLBD	xxx	LEAD/LAG BALANCE DELTA	
741	LLDY	xxx	LAG START DELAY	
	PARA	YES/NO	PARALLEL CONFIGURATION	
SLCT	CLSP	х	COOLING SETPOINT SELECT	
	HTSP	x	HEATING SETPOINT SELECT	
	RL.S	ENBL/DSBL	RAMP LOAD SELECT	
	CRMP .	x.x	COOLING RAMP LOADING	
	HRMP	x.x	HEATING RAMP LOADING	
	HCSW	COOL/HEAT	HEAT COOL SELECT	
	Z.GN	x.x	DEADBAND MULTIPLIER	
*	BRN.L	YES/NO	HXC BRINE CONFIG LOCK	

# Record Configuration Information MODE — CONFIGURATION (cont)

SUB-MODE	ITEM	DISPLAY	ITEM EXPANSION	ENTRY
SERV	H.PGN	xx.x	HEAD PRESSURE P GAIN	
	H.IGN	XX.X	HEAD PRESSURE I GAIN	
	H.DGN	xx.x	HEAD PRESSURE D GAIN	
	H.MIN	xxx.x	WATER VALVE MINIMUM POS	
	MT.SP	xxx.x	MOTOR TEMP SETPOINT	
	BR.FZ	xxx.x	BRINE FREEZE POINT	
	MC.SP	xxx.x	MAX. COND. TEMP SETPOINT	
	EX.S.A	xx.xx	EXVA START POSITION	
	EX.S.B	XX.X	EXVB START POSITION	
	EN.A1	ENBL/DSBL	ENABLE COMPRESSOR A1	
× 1	EN.A2	ENBL/DSBL	ENABLE COMPRESSOR A2	
	EN.B1	ENBL/DSBL	ENABLE COMPRESSOR B1	
ì	EN.B2	ENBL/DSBL	ENABLE COMPRESSOR B2	
	W.DNE	YES/NO	WINTERIZATION PERFORMED	
	ECON	YES/NO	ECONOMIZED	
	EVPS	х	NUMBER OF EVAP. PASSES	
	LWTC	A/B	CIRCUIT WITH LWT SENSOR	
	AP.SP	XXX.X	APPROACH SETPOINT	
BCST	TD.B.C	ON/OFF	CCN TIME/DATE BROADCAST	8
Ī	OAT.B	ON/OFF	CCN OAT BROADCAST	
İ	GS.B.C	ON/OFF	GLOBAL SCHEDULE BROADCAST	
İ	BC.AK	ON/OFF	BROADCAST ACKNOWLEDGER	

#### MODE — SETPOINT

SUB-MODE	ITEM	DISPLAY	ITEM EXPANSION	ENTRY
COOL	CSP.1	xxx.x	COOLING SETPOINT 1	
20'	CSP.2	xxx.x	COOLING SETPOINT 2	2
	CSP.3	XXX.X	ICE SETPOINT	
HEAT	HSP.1	XXX.X	HEATING SETPOINT 1	
	HSP.2	XXX.X	HEATING SETPOINT 2	
HEAD	HD.P.A	xxx.x	HEAD PRESSURE SETPOINT A	
	HD.P.B	xxx.x	HEAD PRESSURE SETPOINT B	

# Component Test — Complete the following tests to make sure all peripheral components are operational before the compressors are started.

#### MODE - SERVICE TEST

To Enable Service Test Mode, move Enable/Off/Remote Contact Switch to OFF. Configure TEST to ON. Move Switch to ENABLE.

SUB-MODE	ITEM	DISPLAY	ITEM EXPANSION	ENTRY
TEST		ON/OFF	SERVICE TEST MODE	COMPLETE
OUTS	EXV.A	xxx %	EXV % OPEN	OOMI LETE
	VH.PA	xxx %	VAR HEAD PRESS %	
	OL.P.A	ON/OFF	OIL PUMP	
	MC.A1	ON/OFF	MOTOR COOLING SOLENOID A1	
	MC.A2	ON/OFF	MOTOR COOLING SOLENOID A2	
	OS.A1	ON/OFF	OIL SOLENOID A1	
	OS.A2	ON/OFF	OIL SOLENOID A2	
	EXV.B	xxx %	EXV % OPEN	
	VH.PB	xxx %	VAR HEAD PRESS %	
	OL.P.B	ON/OFF	OIL PUMP	
	MC.B1	ON/OFF	MOTOR COOLING SOLENOID B1	
	MC.B2	ON/OFF	MOTOR COOLING SOLENOID B2	
	OS.B1	ON/OFF	OIL SOLENOID B1	
	OS.B2	ON/OFF	OIL SOLENOID B2	
	FAN1	ON/OFF	FAN 1 RELAY	
8	FAN2	ON/OFF	FAN 2 RELAY	
65	FAN3	ON/OFF	FAN 3 RELAY	
	FAN4	ON/OFF	FAN 4 RELAY	
	CLR.P	ON/OFF	COOLER PUMP RELAY	
	CLR.H	ON/OFF	COOLER HEATER	
	CND.P	ON/OFF	CONDENSER PUMP RELAY	
	RMT.A	ON/OFF	REMOTE ALARM RELAY	
COMP	CC.A1	ON/OFF	COMPRESSOR A1 RELAY	
	CC.A2	ON/OFF	COMPRESSOR A2 RELAY	
31	LD.A1	ON/OFF	LOADER A1 RELAY	
ſ	LD.A2	ON/OFF	LOADER A2 RELAY	
Ī	MLV	ON/OFF	MINIMUM LOAD VALVE	
	OL.H.A	ON/OFF	OIL HEATER	
	CC.B1	ON/OFF	COMPRESSOR B1 RELAY	7
	CC.B2	ON/OFF	COMPRESSOR B2 RELAY	
	LD.B1	ON/OFF	LOADER B1 RELAY	
	LD.B2	ON/OFF	LOADER B2 RELAY	
	OL.H.B	ON/OFF	OIL HEATER	

Fan Motor 12 Fan Motor 13 Fan Motor 14 Fan Motor 15 Fan Motor 16

ALL UNITS				
Record the following inform condition.	nation from th	e Pressures an	d Temperatures Modes v	vhen machine is in a stable operation
COOLER ENTERING FLU	מוו			
				_ s s
COOLER LEAVING FLUID				<del>_</del> .
OUTSIDE AIR TEMPERAT	URE			-
SPACE TEMPERATURE				<u>-</u> -
CONDENSER ENTERING				<u> </u>
CONDENSER LEAVING F				_
LEAD/LAG LEAVING FLUI	D			
	127		CIRCUIT A	CIRCUIT B
SATURATED CONDENSIN	IG TEMP		STATE OF THE STATE	
SATURATED SUCTION TE	EMP .			
DISCHARGE SUPERHEAT	ΓTEMP (Cor	np 1/Comp 2)		
MOTOR TEMPERATURE (				
DISCHARGE PRESSURE				
SUCTION PRESSURE				
ECONOMIZER PRESSUR	E			
OIL PRESSURE (Comp 1/0	Comp 2)			
OIL PRESSURE DIFF. (Cor		2)		
OIL FILTER DIFF. (Comp 1/				**
CALCULATED OIL PRESS	(Comp 1/Co	mp 2)		
				9
Compressor Running Cur	rent — All re	adings taken at	full load.	
_	L1	L2	L3	
Compressor A1	£			
Compressor A2	-	( <del></del>	5P	
Compressor B1	-	( <del></del>		
Compressor B2			-	
Condenser Fan Motor Cur	rent			
	L1	L2	L3	*
Fan Motor 1			LO	
Fan Motor 2		-	-	
Fan Motor 3	-			
Fan Motor 4	× <del></del>			
Fan Motor 5	-			
Fan Motor 6			·	
Fan Motor 7	·		3	
Fan Motor 8		-		
Fan Motor 9	-	-		
		· · · · · · · · · · · · · · · · · · ·	<del></del> -	
Fan Motor 10				
LOUINGIOL LI				




# Product Data

#### 30HXA,HXC076-27 Condenserless and Water-Cooled Liquid Chillers 50/60 Hz

75 to 265 Tons (264 to 931 kW

# ComfortLink



Water-cooled and condenserless chillers designed from the ground up to meet the needs of today and tomorrow:

- Unit fits through a standard door with no disassembly required
- Chlorine-free HFC-134a refrigerant
- Dual independent refrigerant circuits
- Smooth compression using twin screw compressors
- ARI certified efficiencies to 0.53 kW/ton

#### Features/Benefits

Quality design and construction make th 30HXC (Water-Cooled) and 30HXA (Condenserless) units the preferred choic

#### Easy installation

The 30HX chiller has a compact design that fits through a standard door opening and requires minimal indoor space. The 30HX chiller is delivered as a complete package for easy installation. There are no extra controls, clocks, starters, or other items to install.

The 30HX unit also provides a single location electrical power entrance (using the accessory field-installed control power transformer) and quick, easy piping (using victaulic-type clampon couplings).

The 30HX 208/230-v, 230-v, 460-v and 575-v units are designed in accordance with UL (Underwriters' Laboratory, U.S.A.) and UL, Canada (Underwriters' Laboratory, Canada) standards to minimize electrical inspection time.



A quick start-up is assured once installation is complete, since each 30HX unit is manufactured at an ISO 9001:2000 listed manufacturing facility to guarantee quality. In addition, all 30HXC units are tested under load at the factory to provide reliable start-up. NOTE: Units shipped with optional nitrogen charge are tested for proper operation of the electrical components but are not run-tested at the factory.

#### Easy operation

The 30HX units have a quiet, lowvibration design featuring screw compressors.

Efficiency levels of the 30HX units meet or exceed energy efficiency requirements of ASHRAE (American Society of Heating, Refrigeration and Air Conditioning Engineers) 90.1-2001 and CSA (Canadian Standards Association) for both full-load and part-load operation, thus saving on operating costs through lower electrical costs. All 30HX units are also rated in accordance with ARI (Air Conditioning and Refrigeration Institute, U.S.A.) standards. The 60 Hz 30HXC units are ARI certified.


The 30HX controls are fully automatic. The leaving-fluid temperature is directly controlled to within .5° F (.3° C), and the entering-fluid temperature is continuously monitored to detect load and flow changes.

Dual, independent refrigerant circuits provide reliable, dependable cooling, and the 30HX units use medium-pressure HFC-134a refrigerant to

minimize stress on the compressors and ensure a long life.

From a service standpoint, the 30HX units offer the following features:

- Use of HFC-134a refrigerant, which has no planned phase-out in its future
- Mechanically cleanable cooler and condenser (30HXC units)
- Twin-screw compressors, which require no routine service or maintenance
- Easily accessed service information includes suction and discharge pressure and temperature using standard Navigator™ display module
- All parts are available through Totaline parts stores.




#### **Table of contents**



Features/Benefits	
Model Number Nomenclature	3
ARI Capacity Ratings	1 =
Physical Data	4,5
Options and Accessories	
Dimensions	
Dimensions	
Application Data	
Selection Procedure	
Performance Data	
Typical Piping and Wiring	57.58
Electrical Data	59-70
Controls	
Guide Specifications	72-74

# Model number nomenclatur



LEGEND
FIOPS — Factory-Installed Options

#### **Quality Assurance**



## **ARI** capacity ratings



#### 30HXC WATER-COOLED CHILLER ARI RATINGS (60 Hz ONLY)

UNIT SIZE 30HXC	CAPACITY		INPUT POWER	COOLE	R FLOW	PRES: DR	SURE	CONDE		CONDE PRESS DRO	URE	FULL-LOAD EFFICIENCY	IPLV†
	Tons	Output kW	(kW)	GPM	L/s	Ft of Water	kPa	GPM	L/S	Ft of Water	kPa	(kW/Ton)	(kW/Ton)
076	75.4	265.2	53.7	181.0	11.4	12.6	37.7	226.2	14.3	8.0	23.9	0.712	0.512
086	83.1	292.3	60.4	199.4	12.6	15.1	44.9	249.3	15.7	9.6	28.6	0.727	0.512
096	94.0	330.5	67.0	225.5	14.2	14.9	44.6	281.9	17.8	9.9	29.4	0.713	0.523
106	104.3	366.8	75.3	250.3	15.8	13.4	40.1	312.9	19.7	12.0	35.7	0.722	0.513
116	113.6	399.4	79.9	272.6	17.2	11.7	34.9	340.7	21.5	15.3	45.5	0.703	0.509
126	123.0	432.6	86.8	295.2	18.6	13.5	40.3	369.0	23.3	17.7	52.7	0.706	0.509
136	136.5	479.9	97.0	327.5	20.7	12.8	38.3	409.4	25.8	16.7	49.9	0.711	0.509
146	145.9	513.2	105.1	350.2	22.1	14.5	43.3	437.8	27.6	19.0	56.5	0.720	
161	156.5	550.6	111.7	375.7	23.7	12.0	35.7	469.6	29.6	19.4	57.9	0.714	0.533
171	165.9	585.3	118.2	398.1	25.1	13.3	39.6	497.6	31.4	15.9	47.4	0.712	A 100 A 100
186	177.2	623.1	126.7	426.2	26.8	12.1	36.2	531.6	33.5	18.0	53.7	0.715	0.538
206	211.6	744.0	146.4	507.7	32.0	12.8	38.2	634.7	40.0	19.0	56.7		0.562
246	248.6	874.1	172.4	596.5	37.6	14.1	42.1	745.7	47.0	20.1		0.692	0.510
261	257.2	904.6	180.5	617.3	38.9	15.0	44.8	771.6	48.7		59.9	0.693	0.522
271	267.4	940.3	189.5	641.7	40.5	16.1	48.0	802.1		21.4	63.9	0.702	0.523
	LEOENS					10.1	40.0	002.1	50.6	23.0	68.7	0.709	0.525

LEGEND

IPLV — Integrated Part-Load Value

\*Air Conditioning and Refrigeration Institute (U.S.A.). †IPLV shown is the lower of Sequence A or Sequence B unloading.

Rated (60 Hz only) in accordance with ARI Standard 550/590-98 at standard rating conditions.

Standard rating conditions are as follows:

Cooler Conditions:
Leaving Water Temperature: 44 F (6.7 C)
Flow: 2.4 gpm per

Flow:
Condenser Conditions:
Entering Water temperature: 85 F (29.4 C)
3.0 gpm per ton (0.054 L/s per kW)

Fouling Factor (Cooler):

0.00010 hr x sq ft x F per Btuh (0.000018 m² x K per W)

Fouling Factor (Condenser):

0.00025 hr x sq ft x F per Btuh (0.000044 m² x K per W)

IPLV is a single number part-load efficiency value calculated from the system full-load efficiency values and corrected for a typical building air-conditioning application.
 All data in this table is rated (60 Hz only) in accordance with ARI Standard 550/590-98 as represented in the ECOLOGIC™ Chiller Selection Program (E-Cat) version 2.80.
 Contact Carrier for custom ratings.



Rated in accordance with ARI Standard 550/590-98.

60 Hz only





#### 30HXA CONDENSERLESS CHILLER RATINGS (60 Hz ONLY)

UNIT SIZE	CAPACITY		INPUT POWER			PRESS DRO	SURE	FULL-LOAD EFFICIENCY
30HXA	Tons	Output kW	(kW)	GРM	L/s	Ft of Water	kPa	(kW/Ton)
076	67.7	237.9	76.2	162.4	10.2	10.4	31.1	1,127
086	76.0	267.2	84.5	182.3	11.5	12.8	38.2	1,112
096	85.8	301.9	95.1	206.0	13.0	12.6	37.7	1.108
106	96.9	340.9	106.9	232.7	14.7	11.8	35.1	1.103
116	104.9	368.9	115.0	251.8	15.9	10.1	30.3	1.097
126	113.9	400.6	125.3	273.4	17.2	11.8	35.1	1,101
136	127.0	446.5	138.5	304.7	19.2	11.3	33.7	1.091
146	137.2	482.5	150.0	329.3	20.8	13.0	38.7	1.094
161	147.3	518.1	159.9	353.6	22.3	10.7	32.0	1.086
171	159.0	559.3	173.8	381.7	24.1	12.3	36.7	1.093
186	174.3	612.8	192.7	418.2	26.4	11.8	35.1	1.106
206	198.5	698.2	216.4	476.5	30.1	11.4	34.1	
246	231.9	815.4	252.4	556.5	35.1	12.5	37.2	1.090
261	244.1	858.6	267.5	585.9	37.0	13.7		1.089
271	257.9	907.0	283.9	619.0	39.1	15.1	40.8 45.0	1.101

NOTES:

Rated (60 Hz only) in accordance with ARI Standard 550/590-98 at standard rating conditions.
 Standard rating conditions are as follows:

Cooler Conditions:

Leaving Water Temperature: Flow:

44 F (6.7 C) 2.4 gpm per ton (0.043 L/s per kW)

Saturated Discharge Temperature:

125 F (52 C)

Fouling Factor (Cooler):
0.00010 hr x sq ft x F per Btuh (0.000018 m² x K per W)
All data in this table is rated (60 Hz only) in accordance with ARI
Standard 550/590-98 as represented in the ECOLOGIC™ Chiller
Selection Program (E-Cat) version 2.80.
Contact Carrier for custom ratings.



#### 09DK CONDENSER RATINGS (60 Hz ONLY)

UNIT SIZE 09DK	НР	TONS	ВТИН	ВТИН/НЕ
044	3.0	56.2	674,400	224,800
054	4.0	65.8	789,600	197,400
074	6.0	95.4	1,144,800	190,800
084	6.0	103.5	1,242,000	207,000
094	6.0	116.3	1,395,600	232,600

NOTE: Rated in accordance with ARI standard 460-2000 at standard NOTE: Rated in accordance with Ani Standard rating conditions.

1. 125 F (52 C) Condensing Temperature
2. R-22 Test Fluid
3. 190 F (88 C) Entering Gas Temperature
4. 15° F (8.3° C) Subcooling
5. 95 F (35 C) Entering Dry Bulb Temperature



# Physical data



#### **ENGLISH**

UNIT SIZE 30HX	076	086	096	106	116	126	136	146
UNIT OPERATING WEIGHT (Ib)						1	100	140
Water-Cooled (HXC)	5700	5723	5855	6177	6415	6465	6688	6718
Condenserless (HXA)	4717	4744	4835	5151	5163	5205	5309	5333
COMPRESSORS				Semi-Herme	tic, Twin Sci			5555
Quantity Nominal Capacity per Compressor (tons)	2	2	2	2	2	1 2	1 2	1 2
Economizer	39/39	46/39	56/39	66/39	66/46	66/56	80/56	80/66
No. Capacity Steps	No	No	No	No	No	No	No	No
Standard	6	6	6					
Optional (maximum)	8	1 8	8	6 8	6 8	6	6	6
Minimum Step Capacity (%)				, °	0	8	8	8
Standard	20	20	20	20	20	20	20	20
Optional	10	10	10	10	10	10	10	10
REFRIGERANT				R-	134a		10	10
Charge* (lb) Circuit A/Circuit B	75/75	76/75	94/70	I 110/70	1 112/89	112/89	1 124/89	119/100
COOLER	4		Shell and		nhanced Co		124/03	119/100
Part No. 10HX400-	401	401	1 402	1 408	I 406	1 406	I 405	1 405
Net Fluid Volume (gal)	. 17.0	17.0	19.0	22.6	21.4	21.4	24.0	24.0
Maximum Refrigerant Pressure (psig)	220	220	220	220	220	220	220	220
Maximum Water-Side Pressure (psig) Water Connections	300	300	300	300	300	300	300	300
Inlet and Outlet (in.) (Standard Pass)	4	1 .	1 .					
Drain (in. NPT) (Standard Pass)	3/8	3/8	4	5	5	5	5	5
Relief Valve	/8	78	3/8	3/8	3/8	3/8	3/8	3/8
Connection (in. NPTF)	3/4	3/4	3/4	3/4	3/4	3/	2,	
Flow Capacity (lb air/min)	31.7	31.7	31.7	31.7	31.7	3/ <sub>4</sub> 31.7	3/ <sub>4</sub> 31.7	3/4
Relief Setting (psig)	220	220	220	220	220	220	220	31.7 220
Standard Number of Passes	3	3	3	3	2	2	2	2
30HXA OIL SEPARATOR								
Part No. 09RX400- Maximum Refrigerant Pressure (psig)	217	217	216	216	215	215	215	215
Refrigerant Connections (in.)	320	320	320	320	320	320	320	320
Discharge Circuit A/B	21/8/21/8	21/8/21/8	21/8/21/8	01//01/	044.544			The Mark
Liquid Circuit A/B	11/8/11/8	11/8/11/8	11/8/11/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8
Relief Valve	1	1 1/81/8	1 78/1 78	11/8/11/8	11/8/11/8	11/8/11/8	11/8/11/8	11/8/11/8
Connection (in. SAE Flare)	5/8	5/8	·5/8	5/8.	5/8.	5/8	5/8	E/
Flow Capacity (Ib air/min)	21.6	21.6	21.6	21.6	21.6	21.6	21.6	<sup>5</sup> / <sub>8</sub> 21.6
Relief Setting (psig)	320	320	320	320	320	320	320	320
CONDENSER (HXC)	1923200 m	and the second	Shell and	Tube with Er	hanced Cop			0.0
Part No. 09RX400- Net Fluid Volume (gal)	257	257	258	258	259	l 259	1 260	260
Maximum Refrigerant Pressure (psig)	16.8	16.8	18.3	18.3	23.9	23.9	27.5	27.5
Maximum Water-Side Pressure (psig)	220 300	220	220	220	220	220	220	220
Water Connections (In.)	300	300	300	300	300	300	300	300
Inlet and Outlet (Standard Pass)	Victaulic Type Connection							
Drain (NPT) (Standard Pass)	3/8	5 3/8	5 3/8	5 3/8	5	5	5	5
Relief Valve		78	-78	~/8	3/8	3/8	3/8	3/8
Connection (in. NPTF)	3/4	- 3/4	3/4	3/4	3/4	3/4	3/.	3/
Flow Capacity (Ib air/min)	31.7	31.7	31.7	31.7	31.7	31.7	3/ <sub>4</sub> 31.7	<sup>3</sup> / <sub>4</sub> 31.7
Relief Setting (psig) Standard Number of Passes	220	220	220	220	220	220	220	220
	2	2	2	2	2	2	2	2
DISCHARGE LINE† Relief Valve								
	3,	a,			1			
Connection (in. SAE Flare) Flow Capacity (Ib air/min)	<sup>3</sup> / <sub>8</sub> 6.3	3/8	3/8	3/8	3/8	3/8	3/8	3/8
Setting (psig)	350	6.3 350	6.3 350	6.3	6.3	6.3	6.3	6.3
LEGEND	000	330	35U	350	350	350	350	350 -

#### LEGEND

NPTF — National Pipe Thread Female SAE — Society of Automotive Engineers

<sup>\*</sup>Charges listed are for 30HXC units. The 30HXA units are shipped with a holding charge only. To determine the refrigerant charge requirements for 30HXA units see the System Refrigerant Charge for Start-Up table in the Application Data on page 28.

†Only on units with factory-installed suction service valves.



#### **ENGLISH** (cont)

UNIT SIZE 30HX	161	171	1 400	200	2000	7			
UNIT OPERATING WEIGHT (Ib)	101	171	186	206	246	261	271		
Water-Cooled (HXC)	7452	7660	7854	10.581	40.000				
Condenserless (HXA)	5752	5777	5946	7,485	10,969 7,621	10,992 7,621	11,029		
COMPRESSORS		Semi-Hermetic, Twin Screw							
Quantity	2	2	1 2	I 3	I 3	1 3	1 3		
Nominal Capacity per Compressor (tons) Economizer	80/56	66/80	80/80	66/39/80	80/56/80	80/66/80	80/80/80		
No. Capacity Steps	Yes	Yes	Yes	Yes	Yes	Yes	Yes		
Standard	6	6	6				0.50		
Optional (maximum)	8	8	8	8	8	8	8		
Minimum Step Capacity (%)	60.000	_	Ŭ	1	1 11	11	11		
Standard Optional	20	20	20	13	13	13	13		
REFRIGERANT	10	10	10	7	7	7	7		
Charge* (lb) Circuit A/Circuit B	157/110	4404440	74-6	R-134a					
COOLER TYPE	15//110	119/140	135/135	220/135	220/135	220/135	220/135		
Part No. 10HX400-	601		Shell and Tube	with Enhance		es			
Net Fluid Volume (gal)	28.5	611 28.5	621 33.4	631	632	632	632		
Maximum Refrigerant Pressure (psig)	220	220	220	43.1 220	47.2 220	47.2	47.2		
Maximum Water-Side Pressure (psig)	300	300	300	300	300	220 300	220		
Water Connections Inlet and Outlet (in.) (Standard Pass)	_	1		"	500	300	300		
Drain (NPT) (Standard Pass)	5 3/8	5	5	6	6	6	6		
Relief Valve	9/8	3/8	3/8	3/8	3/8	3/8	3/8		
Connection (in. NPTF)	3/4	3/4	3/4	3/4	3/4	21			
Flow Capacity (Ib air/min)	31.7	31.7	31.7	31.7	31.7	<sup>3</sup> / <sub>4</sub> 31.7	3/4		
Relief Setting (psig) Standard Number of Passes	220	220	220	220	220	220	31.7 220		
30HXA OIL SEPARATOR	2	2	2	2	2	2	2		
Part No. 09RX400-	215								
Maximum Refrigerant Pressure (psig)	320	214 320	214	213	213	213	213		
Refrigerant Connections (in.)	320	320	320	320	320	320	320		
Discharge Circuit A/B	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	01/ /01/		
Liquid Circuit A/B Relief Valve	13/8/13/8	13/8/13/8	13/8/13/8	15/8/13/8	15/8/13/8	15/8/13/8	2 <sup>1</sup> / <sub>8</sub> /2 <sup>1</sup> / <sub>8</sub> 1 <sup>5</sup> / <sub>8</sub> /1 <sup>3</sup> / <sub>8</sub>		
Connection (in. SAE Flare)	5/8	51		22			178178		
Flow Capacity (Ib air/min)	21.6	<sup>5</sup> / <sub>8</sub> 21.6	5/ <sub>8</sub> 21,6	5/8	5/8	5/8	5/8		
Relief Setting (psig)	320	320	320	21.6 320	21.6 320	21.6	21.6		
CONDENSER (HXC)				with Enhanced		320	320		
Part No. 09RX400-	261	262	1 262	l 263 I	Copper Tubes 264 I		221		
Net Fluid Volume (gal)	30.6	37.6	37.6	47.6	55.1	264 55.1	264 55.1		
Maximum Refrigerant Pressure (psig) Maximum Water-Side Pressure (psig)	220	220	220	220	220	220	220		
Water Connections (in.)	300	300	300	300	300	300	300		
Inlet and Outlet (Standard Pass)	Victaulic Type Connection								
Drain (NPT) (Standard Pass)	3/8	3/8	3/ <sub>8</sub>	8 3/8	8 3/8	8	8		
Relief Valve				′°	-78	3/8	3/8		
Connection (in. NPTF) Flow Capacity (lb air/min)	3/4	3/4	3/4	3/4	3/4	3/4	3/4		
Relief Setting (psig)	31.7 220	31.7 220	31.7	31.7	31.7	31.7	31.7		
Standard Number of Passes	2	220	220	220	220	220	220		
			-		2	2	2		
ISCHARGE LINE†									
Relief Valve	ii ii								
Relief Valve Connection (in. SAE Flare)	3/8	3/8	<sup>3</sup> /8	3/8	3/8	3/0	3/-		
Relief Valve	<sup>3</sup> / <sub>8</sub> 6.3 350	<sup>3</sup> / <sub>8</sub> 6.3 350	<sup>3/</sup> 8 6.3 350	<sup>3</sup> / <sub>8</sub> 6.3 350	<sup>3</sup> / <sub>8</sub> 6.3	<sup>3</sup> / <sub>8</sub> 6.3	<sup>3</sup> / <sub>8</sub> 6.3		

#### LEGEND

NPTF -- National Pipe Thread Female SAE -- Society of Automotive Engineers

<sup>\*</sup>Charges listed are for 30HXC units. The 30HXA units are shipped with a holding charge only. To determine the refrigerant charge requirements for 30HXA units see the System Refrigerant Charge for Start-Up table in the Application Data on page 28.
†Only on units with factory-installed suction service valves.

# Physical data (cont



SI

·										
UNIT SIZE 30HX	076	086	096	106	116	126	136	146		
UNIT OPERATING WEIGHT (kg)	0500		02-902-00-774		29424-0-10-27					
Water-Cooled (HXC) Condenseriess (HXA)	2586 2140	2597 2152	2657	2803	2911	2933	3034	3048		
COMPRESSORS	2140	2102	2194	2337	2342	2362	2408	2420		
Quantity	2	Semi-Hermelic, Twin Screw								
Nominal Capacity per Compressor (kW)	137/137	162/137	197/137	232/137	232/137	232/197	281/197	281/232		
Economizer	No	No	No	No	No	No	No	No		
No. Capacity Steps Standard	6	6						78		
Optional (maximum)	8	8	6 8	6 8	6 8	6 8	6	6		
Minimum Step Capacity (%)				"	۰ ،	0	8	8		
Standard Optional	20	20	20	20	20	20	20	20		
	10	10	10	10	10	10	10	10		
REFRIGERANT Charge* (kg) Circuit A/Circuit B	34.1/34.1	1 04 5/04 4	1 40 7/04 0	R-	134a	2 _ 2 _ 3	_			
COOLER	34.1/34.1	34.5/34.1	42.7/31.8	49.9/31.8	50.8/40.4	50.8/40.4	56.3/40.4	54.0/45.4		
Part No. 10HX400-	401	l 401	I 402	Tube with E   408	nhanced Co					
Net Fluid Volume (L)	64.3	64.3	71.9	85.5	406 81.0	406 81.0	405 90.8	405 90.8		
Maximum Refrigerant Pressure (kPa)	1517	1517	1517	1517	1517	1517	1517	1517		
Maximum Water-Side Pressure (kPa) Water Connections	2068	2068	2068	2068	2068	2068	2068	2068		
Inlet and Outlet (in.) (Standard Pass)	4	4	4	5		_	_	200		
Drain (NPT) (Standard Pass)	3/8	3/8	3/8	3/8	5 3/8	5 3/8	5 3/8	5 <sup>3</sup> /8		
Relief Valve				13%			78	78		
Connection (in. NPTF) Flow Capacity (kg air/min)	3/ <sub>4</sub> 14.38	3/4	3/4	3/4	3/4	3/4	3/4	3/4		
Relief Setting (kPa)	1517	14.38 1517	14.38 1517	14.38 1517	14.38	14.38	14.38	14.38		
Standard Number of Passes	3	3	3	3	1517 2	1517	1517 2	1517 2		
30HXA OIL SEPARATOR						-				
Part No. 09RX400-	217	217	216	216	215	215	215	215		
Maximum Refrigerant Pressure (kPa) Refrigerant Connections (in.)	2205	2205	2205	2205	2205	2205	2205	2205		
Discharge A/B	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	01//01/	01/ /01/	011 1011		
Liquid A/B	11/8/21/8	11/8/11/8	11/8/11/8	11/8/11/8	11/8/11/8	21/ <sub>8</sub> /21/ <sub>8</sub> 11/ <sub>8</sub> /11/ <sub>8</sub>	21/ <sub>8</sub> /21/ <sub>8</sub> 11/ <sub>8</sub> /11/ <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> /2 <sup>1</sup> / <sub>8</sub> 1 <sup>1</sup> / <sub>8</sub> /1 <sup>1</sup> / <sub>8</sub>		
Relief Valve					N. NONE 2017-10-61	1 70 1 78	178178	178178		
Connection (in. SAE Flare) Flow Capacity (kg air/min)	5/ <sub>8</sub> 9.80	5/ <sub>8</sub> . 9.80	5/8	5/8	5/8	5/8	5/8	5/8		
Relief Setting (kPa)	2206	2206	9.80 2206	9.80 2206	9.80 2206	9.80 · 2206	9.80	9.80		
CONDENSER (HXC)		2200		50.000.000	hanced Cop		2206	2206		
Part No. 09RX400-	257	257	258	258	259 1	259 I	260 I	260		
Net Fluid Volume (L)	63.6	63.6	69.3	69.3	90.5	90.5	104.1	104.1		
Maximum Refrigerant Pressure (kPa) Maximum Water-Side Pressure (kPa)	1517 2068	1517 2068	1517	1517	1517	1517	1517	1517		
Water Connections (in.)	2000	2008	2068	2068	2068	2068	2068	2068		
Inlet and Outlet (Standard Pass)	5	5	5	7 Ictaulic Type	Connection 5   5   5   5					
Drain (NPT) (Standard Pass)	3/8	3/8	3/8	3/8	3/8	3/8	3/8	3/8		
Relief Valve Connection (in. NPTF)	3/4	3/	3/		**		144,550			
Flow Capacity (kg air/min)	14.38	3/ <sub>4</sub> 14.38	3/ <sub>4</sub> 14.38	3/ <sub>4</sub> 14.38	3/ <sub>4</sub> 14.38	3/4	3/4	3/4		
Relief Setting (kPa)	1517	1517	1517	1517	1517	14.38 1517	14.38 1517	14.38 1517		
Standard Number of Passes	2	2	2	2	2	2	2	2		
DISCHARGE LINE† Relief Valve								-		
Connection (in, SAE Flare)	3/8	3/8	3/-	3,	٠, ا		. 1			
Flow Capacity (kg air/min)	2.9	2.9	3/ <sub>8</sub> 2.9	3/ <sub>8</sub> 2.9	3/ <sub>8</sub> 2.9	3/ <sub>8</sub> 2.9	3/8	3/8		
Relief Pressure (kPa)	2413	2413	2413	2413	2413	2413	2.9 2413	2.9 2413		
LEGEND										

#### LEGEND

NPTF — National Pipe Thread Female SAE — Society of Automotive Engineers

<sup>\*</sup>Charges listed are for 30HXC units. The 30HXA units are shipped with a holding charge only. To determine the refrigerant charge requirements for 30HXA units see the System Refrigerant Charge for Start-Up table in the Application Data on page 28.
†Only on units with factory-installed suction service valves.



#### SI (cont)

UNIT SIZE 30HX	161	171	186	206	246	261	.271
UNIT OPERATING WEIGHT (kg)						201	.211
Water-Cooled (HXC)	3381	3475	3564	4799	4976	4986	5000
Condenserless (HXA)	2610	2621	2698	3395	3457	3457	5003 3457
COMPRESSORS						3437	3457
Quantity	2	1 2	I 2	ni-Hermetic, Twi		e 21	
Nominal Capacity per Compressor (kW)	281/197	232/281	281/281	3 232/137/281	3	3	3
Economizer	Yes	Yes	Yes	Yes	281/197/281 Yes	281/232/281	281/281/281
No. Capacity Steps		100	103	162	tes	Yes	Yes
Standard	6	6	6	8	8	8	
Optional (maximum)	8	8	8	1 11	11	11	8
Minimum Step Capacity (%)				1	1	111	11
Standard	20	- 20	20	13	13	13	13
Optional	10	10	10	7	7	7	7
REFRIGERANT	Α			R-134a			· · · · · · · · · · · · · · · · · · ·
Charge* (kg) Circuit A/Circuit B	71.3/49.9	54.0/63.6	61.3/61.3	I 90.8/61.3	I 99.9/61.3	I 99.9/61.3	99.9/61.3
COOLER				e with Enhance		99.9/01.3	99.9/61.3
Part No. 10HX400-	601	l 611	621	l 631	ea Copper Tube		
Net Fluid Volume (L)	107.9	107.9	126.4	163.2	632 178.7	632	632
Maximum Refrigerant Pressure (kPa)	1517	1517	1517	1517	1517	178.8 1517	178.7
Maximum Water-Side Pressure (kPa)	2068	2068	2068	2068	2068	2068	1517 2068
Water Connections				2000	2000	2000	2008
Inlet and Outlet (in.) (Standard Pass)	5	5	5	6	6	6	6
Drain (NPT) (Standard Pass)	3/8	3/8	3/8	3/8	3/8	3/8	3/8
Relief Valve			- 2		5.4	/°	78
Connection (in. NPTF)	3/4	3/4	3/4	3/4	3/4	3/4	3/4
Flow Capacity (kg air/min) Relief Setting (kPa)	14.28	14.38	14.38	14.38	14.38	14.38	14.38
Standard Number of Passes	1517 2	1517	1517	1517	1517	1517	1517
	- 4	2	2	2	. 2	2	2
30HXA OIL SEPARATOR	2823						
Part No. 09RX400	215	214	214	213 ·	213	213	213
Maximum Refrigerant Pressure (kPa)	2205	2205	2205	2205	2205	2205	2205
Refrigerant Connections (in.) Discharge A/B	01//01/	044 1044		0.000	10000 COMPANY		2200
Liquid A/B	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8	21/8/21/8
Relief Valve	13/8/13/8	13/8/13/8	13/8/13/8	15/8/13/8	15/8/13/8	15/8/13/8	15/8/13/8
Connection (in. SAE Flare)	5/8	5/8	5/8	E/		727	
Flow Capacity (kg air/min)	9.80	9.80	9.80	<sup>5</sup> / <sub>8</sub> 9.80	5/8	5/8	5/8
Relief Setting (kPa)	2206	2206	2206	2206	9.80 2206	9.80	9.80
CONDENSER (HXC)						2206	2206
Part No. 09RX400-	261	262	onen and lube	with Enhance			
Net Fluid Volume (L)	115.8	142.3	262 142.3	263	264	264	264
Maximum Refrigerant Pressure (kPa)	1517	1517	1517	177.9 1517	208.6	208.6	208.6
Maximum Water-Side Pressure (kPa)	2068	2068	2068	2068	1517 2068	1517	1517
Water Connections (in.)	1			ulic Type Conn		2068	2068
Inlet and Outlet (Standard Pass)	6	6 1	6 1	8 1	8 1	8 1	
Drain (NPT) (Standard Pass)	3/8	3/8	3/8	3/8	3/8	3/8	8 <sup>3</sup> / <sub>8</sub>
Relief Valve				, , ,	′°	-78	~/8
Connection (in. NPTF)	3/4	3/4	3/4	3/4	3/4	3/4	3/4
Flow Capacity (kg air/min)	14.38	14.38	14.38	14.38	14.38	14.38	14.38
Relief Setting (kPa) Standard Number of Passes	1517	1517	1517	1517	1517	1517	1517
Grandard Mulliper of Passes		2	2	2	2	2	2
MOOHABORIUM	2						
DISCHARGE LINE†	2	-	-				
Relief Valve			22				<del></del>
Relief Valve Connection (in. SAE Flare)	3/8	3/8	3/8	3/8	3/8		
Relief Valve			22			3/ <sub>8</sub> 2.9	<sup>3</sup> / <sub>8</sub> 2.9

#### LEGEND

NPTF — National Pipe Thread Female SAE — Society of Automotive Engineers

<sup>\*</sup>Charges listed are for 30HXC units. The 30HXA units are shipped with a holding charge only. To determine the refrigerant charge requirements for 30HXA units see the System Refrigerant Charge for Start-Up table in the Application Data on page 28.
†Only on units with factory-installed suction service valves.

# Options and accessories

ITEM	FACTORY- INSTALLED OPTION	FIELD- INSTALLED ACCESSORY
Wye-Delta Start	Х	
Brine	X	
Minus-One-Pass Cooler Head	X	-
Plus-One-Pass Cooler Head	X	
Control Power Transformer		Х
Minimum Load Control	Х	X
Sound Reduction Enclosure		Х
Vibration Isolation		X
Temperature Reset Sensor		X
Chillervisor™ System Manager III		X
Cooler Head Insulation		X
Suction Service Valves	X	
Energy Management Module	X	Х

#### Factory-installed options

Wye-delta start — Generally, Wye-delta start is not required when using multiple compressors since the starting current is generally less than with one larger compressor using Wye-delta start. Wye-delta start is standard on 208/230 v, 60 Hz, 230 v, 60 Hz, and 230 v, 50 Hz units. It is available as a factory-installed option for all other unit voltages.

Brine — The brine option permits supply liquid temperatures to be set below 40 F (4.4 C). Refrigeration circuit components, such as the expansion device, are modified at the factory to correct for the lower refrigeration flow rates. Special installation requirements apply to brine units. See Cooler and Water-Cooled Condenser Freeze Protection section, page 23.

Minus-One-Pass cooler — This factory-installed option reduces pressure drop for high flow applications and/or provides same end inlet and outlet for 076-106 sizes, or opposite end inlet and outlet on 116-271 sizes.

**Plus-One-Pass cooler** — This factory-installed option improves low temperature brine performance. See Carrier 30HX electronic catalog for performance data.

Minimum load control — This option allows additional capacity reduction for unit operation below the minimum step of unloading (down to 10% of full load capacity). Minimum load control is also available as a field-installed accessory.

Suction service valves — Standard refrigerant discharge isolation and liquid valves enable service personnel to store the refrigerant charge in the cooler or condenser during servicing. This factory-installed option allows further isolation of the compressor from the cooler vessel.

Energy Management Module (EMM) — The EMM is used for 4 to 20 mA leaving fluid temperature reset, cooling point reset, 4 to 20 mA demand limit and two-step demand limit. Temperature reset lets the unit reset the leaving fluid temperature to a higher temperature during low load conditions. Temperature reset can also be accomplished based on return fluid, outdoor air or space temperature. (The EMM option is not required when using



entering-water, outdoor-air, or space temperature for temperature reset. These types of reset are available with the main board. However, an accessory thermistor is required for outdoor air and/or space temperature reset.) Demand limiting allows the unit capacity to be limited during periods of peak energy usage. Demand limit requires an external 4 to 20 mA signal or a 2-step remote pair of dry contacts. Both the 4 to 20 mA and 2-step demand limit percentage values are adjustable. EMM is also available as a field-installed accessory.

#### Field-installed accessories

**Control power transformer** — The transformer is sized to supply the needs of the control circuit, sourcing power from the main unit power connection.

Minimum load control — This accessory allows additional capacity reduction for unit operation below the minimum step of unloading (down to 10% of full load capacity). Minimum load control is also available as a factory-installed option.

**Sound reduction enclosure** — This kit contains a sound enclosure that covers the entire unit to reduce sound levels.

**Vibration isolation** — Neoprene isolators are field installed to reduce vibration transmission from the compressor through the floor and into the conditioned space.

**Temperature reset sensor** — This accessory sensor provides temperature reset capability from either the occupied space or outdoor-air temperature.

NOTE: Temperature reset capability using return temperature is standard.

Chillervisor System Manager III — This control can be used to regulate up to eight 30HXA or 30HXC chillers.


Cooler head insulation — This accessory is designed with flexible, <sup>3</sup>/<sub>4</sub> in. (19 mm) PVC foam (closed-cell) to insulate the cooler heads to minimize heat loss and head sweating.

Energy Management Module (EMM) is used for 4 to 20 mA leaving fluid temperature reset, cooling point reset, 4 to 20 mA demand limit and two-step demand limit. Temperature reset lets the unit reset the leaving fluid temperature to a higher temperature during low load conditions. Temperature reset can also be accomplished based on return fluid, outdoor air or space temperature. (The EMM option is not required when using entering-water, outdoorair, or space temperature for temperature reset. These types of reset are available with the main board. However, an accessory thermistor is required for outdoor air and/or space temperature reset.) Demand limiting allows the unit capacity to be limited during periods of peak energy usage. Demand limit requires an external 4 to 20 mA signal or a 2-step remote pair of dry contacts. Both the 4 to 20 mA and 2-step demand limit percentage values are adjustable. EMM is also available as a factory-installed option.


Consult factory for other available options not listed here.

# **Dimensions**














































# **Dimensions (cont**



## WEIGHT DISTRIBUTION AT MOUNTING PLATES



WEIGHT DISTRIBUTION AT EACH MOUNTING PLATE



NOTE: Dimensions shown in inches (mm).  $30 HX \ FOOT$ 

## 30HXC UNITS - lb (kg)

UNIT 30HXC		MOUNTING PLATE NO.								
ONIT CONKO	1	2	3	4	5	6				
076	738 (335)	943 (428)	595 (270)	1110 (503)	1418 (643)	896 (406)				
086	738 (335)	947 (430).	597 (271)	1112 (504)	1427 (647)	902 (409)				
096	686 (311)	968 (439)	693 (314)	1027 (466)	1447 (656)	1034 (469)				
106	730 (331)	1028 (466)	744 (337)	1073 (487)	1510 (685)	1092 (495)				
116	728 (330)	1114 (505)	777 (352)	1053 (478)	1615 (733)	1127 (511)				
126	738 (335)	1127 (511)	780 (354)	1061 (481)	1628 (738)	1131 (513)				
136	758 (344)	1176 (533)	811 (368)	1083 (491)	1689 (766)	1171 (531)				
146	763 (346)	1182 (536)	815 (370)	1085 (492)	1697 (770)	1172 (532)				
161	817 (371)	1272 (577)	908 (412)	1219 (553)	1890 (857)	1346 (610)				
171	936 (425)	1318 (598)	840 (381)	1379 (626)	1946 (883)	1241 (563)				
186	962 (436)	1361 (617)	860 (390)	1410 (640)	1996 (905)	1265 (574)				
206	948 (430)	2406 (1091)	1243 (564)	1201 (545)	3133 (1421)	1650 (748)				
246	985 (447)	2515 (1141)	1306 (592)	1154 (523)	3276 (1486)	1733 (786)				
261	985 (447)	2520 (1143)	1311 (595)	1154 (523)	3283 (1489)	1733 (789)				
271	985 (447)	2529 (1147)	1318 (598)	1154 (523)	3294 (1494)	1749 (793)				

## 30HXA UNITS — lb (kg)

UNIT 30HXA		*	MOUNTING	PLATE NO.								
OIIII OUIIAA	1	2	3	4	5	6						
076	555 (252)	793 (360)	418 (190)	926 (420)	1326 (601)	699 (317)						
086	555 (252)	798 (362)	418 (190)	928 (421)	1340 (608)	705 (320)						
096	509 (231)	808 (367)	493 (224)	848 (385)	1350 (612)	827 (375)						
106	555 (252)	869 (394)	541 (245)	896 (406)	1410 (640)	880 (399)						
116	530 (240)	895 (406)	540 (245)	855 (388)	1456 (660)	887 (402)						
126	540 (245)	905 (410)	541 (245)	864 (392)	1468 (666)	887 (402)						
136	548 (249)	926 (420)	555 (252)	873 (396)	1498 (679)	908 (412)						
146	551 (250)	930 (422)	555 (252)	883 (400)	1506 (683)	908 (412)						
161	560 (254)	965 (438)	598 (271)	954 (433)	1650 (748)	1025 (465)						
171	627 (284)	968 (439)	534 (242)	1072 (486)	1658 (752)	918 (416)						
186	648 (294)	1004 (455)	552 (250)	1110 (504)	1703 (772)	939 (426)						
206	671 (304)	1702 (772)	879 (399)	850 (385)	2216 (1005)	1167 (529)						
246	681 (309)	1748 (793)	911 (413)	797 (362)	2276 (1032)	1209 (548)						
261	681 (309)	1748 (793)	911 (413)	797 (362)	2276 (1032)	1209 (548)						
271	681 (309)	1748 (793)	911 (413)	797 (362)	2276 (1032)	1209 (548)						

NOTE: See pages 11-18 for center of gravity details.

## **Application data**

#### Unit location

Unit should be level (particularly in its major lengthwise dimension) to assure proper oil return.

The unit should be located indoors in an area of temperature greater than 50 F (10 C).

Good acoustic design practice should be followed, i.e., unit should not be located adjacent to sound-sensitive areas unless appropriate consideration has been made.

### Cooler fluid temperature

- Maximum leaving water (fluid) temperature (LWT) is 60 F (21 C). Unit can start and pull down with up to 95 F (35 C) entering water (fluid) temperature due to MOP (maximum operating pressure) feature of the expansion valve. For sustained operation, it is recommended that entering fluid temperature not exceed 70 F (21.1 C).
- 2. Minimum LWT is 40 F (4.4 C) for standard units. The brine option is required for operation with leaving fluid temperatures in the range of 39 to 12 F (4 to -9 C). For ratings below 40 F (4.4 C) LWT, contact your local Carrier representative.
- 3. Minimum entering water (fluid) temperature (EWT) is 45 F (7.2 C). Maximum EWT is 70 F (21.1 C).

### Leaving-fluid temperature reset

The accessory reset sensor can be applied to the chiller to provide reset of in LWT constant fluid flow systems. Reset reduces compressor power usage at part load when design LWT is not necessary. Humidity control should be considered, since higher coil temperatures resulting from reset will reduce latent heat capacity. Three reset applications are offered:

From return-fluid temperature — Increases LWT set point as return (or entering) fluid temperature decreases (indicating load decrease). Reset from return fluid may be used in any application where return fluid provides accurate load indication. Limitation of return-fluid reset is that the LWT may only be reset to value of design return-fluid temperature. No additional hardware is required.

From outdoor-air temperature — Increases LWT as outdoor ambient temperature decreases (indicating load decrease). This reset should be applied only where outdoor ambient temperature is an accurate indication of load. A field-supplied thermistor is required.

From occupied space temperature — Increases LWT as space temperature decreases (indicating load decrease). This reset should be applied only where space temperature is an accurate indication of load. A field-supplied thermistor is required.

Temperature can also be reset using a 4 to 20 mA signal from the control system. This type of reset requires the Energy Management Module Accessory.

### Condenser fluid temperature

 Maximum leaving condenser fluid temperature is 105 F (40.5 C) on all 30HXC units.



2. Standard 30HXC units will start at entering condenser fluid temperatures above 55 F (12.8 C). In general, however, continuous machine operation with entering condenser fluid temperatures below 70 F (21.1 C) is not recommended. When the entering condenser fluid temperature is expected to drop below 70 F (21.1 C), it is recommended that some form of condenser flow control be used to optimize performance. Tower pump, bypass valves, or flow regulating valves may be controlled by a 4 to 20 mA output from the 30HXC control (60-second open to close time recommended for actuator).

# Cooler and water-cooled condenser temperature rise

Ratings and performance data in this publication are for a cooling temperature rise of 10° F (5.6° C). Units may be operated at a different temperature rise, provided flow limits are not exceeded and corrections to capacity, etc., are made. For minimum flow rates, see the Minimum Flow Rates table. High flow rate is limited by pressure drop that can be tolerated.

Minimum cooler flow — Flow (maximum cooler temperature rise) is shown in the Minimum Flow Rates table. Minimum flow rate must be maintained to prevent fouling. When gpm (L/s) required is lower (or rise is higher), follow recommendations below:

- Multiple smaller chillers can be applied in series, each providing a portion of the design temperature rise.
- Chilled fluid can be recirculated to raise flow rate. However, mixed temperature entering cooler must be maintained at a minimum of at least 5° F (2.8° C) above the leaving chilled fluid temperature.
- Special plus one-pass cooler can be used. Contact your Carrier representative for further information.

Maximum cooler flow (> 5 gpm/ton or <  $5^{\circ}$  F rise [>  $0.09 \text{ L/s} \cdot \text{kW}$  or <  $2.7^{\circ}$  C rise]) — Maximum flow results in practical maximum pressure drop through cooler. Special minus-one-pass cooler can be used to reduce pressure drop. Contact your Carrier representative.

Return fluid can bypass the cooler to keep pressure drop through cooler within acceptable limits. This permits a higher  $\Delta T$  with lower fluid flow through cooler and mixing after the cooler. Contact your Carrier representative if pressure drop appears excessive.

Variable cooler flow rates — These variable rates may be applied to standard 30HX series chillers. However, the unit will attempt to maintain a constant leaving chilled-fluid temperature. In such cases, minimum fluid loop volume must be in excess of 3 gal per ton (3.2 L per kW) and flow rate must change in steps of less than 10% per minute. Apply 6 gal per ton (6.5 L per kW) fluid loop volume minimum if flow rate changes more rapidly.

**Minimum water-cooled condenser flow** — This value (maximum rise) is shown in Minimum Flow Rates table. Ensure leaving-fluid temperature does not exceed 105 F (40.5 C).

## **Application data (cont**


#### MINIMUM FLOW RATES

DEVICE SIZE COOLER RATE*	COOLE TEMP DIFFEREN	
30HX No. of Passes Type GPM L/s	F	С
2 Minus 1 136.0 8.6	13	7.4
076 3 Standard 90.0 5.7		_
4 Plus 1 68.0 4.3		
2 Minus 1 149.0 9.4		7.4
086 3 Standard 100.0 6.3		
4 Plus 1 75.0 4.7		
2 Minus 1 169.0 10.7		
096 3 Standard 113.0 7.1		_
4 Plus 1 85.0 5.3		
2 Minus 1 188.0 11.8		
106 3 Standard 125.0 7.9		_
4 Plus 1 94.0 5.9		
1 Minus 1 272.0 17.2		
116 2 Standard 136.0 8,6		_
3 Plus 1 91.0 5.7		
1 Minus 1 295.0 18.6		_
126 2 Standard 147.0 9.3		_
3 Plus 1 98.0 6.2		-
1 Minus 1 327.0 20.7		
136 2 Standard 164.0 10.3		
3 Plus 1 109.0 6.9		$\overline{}$
1 Minus 1 350.0 22.1		
COOLER 146 2 Standard 175.0 11.0		_
3 Plus 1 117.0 7.4		_
		_
		_
		C 7.4 11.1 14.8 7.4 11.1 14.8 7.4 11.1 14.8 7.4 11.1 14.8 5.6 11.1 16.7
	200	-
		_
		_
		_
		-
		_
		_
		-0.07
		_
3.70		-
10.0		
		_
10.0		_
10.0		_
		_
	-+-	_
116,126 2 — 170 10.7 - 136,146 2 — 195 12.3 -		_
		-
CONDENSER 161 2 — 235 14.8 -		
171,186 2 — 255 16.1 -		_
171,186 2 — 255 16.1 - 206 2 — 273 17.2 -		
171,186 2 — 255 16.1 - 206 2 — 273 17.2 - 246 2 — 333 21.0 -		
171,186 2 — 255 16.1 - 206 2 — 273 17.2 -		

<sup>\*</sup>Based on 20 F (11.1 C) temperature difference at ARI conditions. NOTES:

To obtain proper temperature control, loop fluid volume must be at least 3 gal/ton (3.23 L/kW) of chiller nominal capacity for air conditioning and at least 6 gal/ton (6.5 L/kW) for process applications.





### Oversizing chillers

Oversizing chillers by more than 15% at design conditions must be avoided as the system operating efficiency will be adversely affected (resulting in greater and/or excessive electrical demand and cycling of compressors). When future expansion of equipment is anticipated, install a single chiller to meet present load requirements, and install a second chiller to meet the additional load demand.

It is also recommended that the installation of 2 smaller chillers be considered where operation at minimum load is critical. The operation of 2 small chillers at higher loading is preferred to operating a single chiller at or near its minimum recommended value.

The minimum load control accessory should not be used as a means to allow oversizing chillers. Minimum load control should be given consideration where substantial operating time is anticipated below the minimum unloading step.

#### Parallel chillers

Where chiller capacities greater than can be supplied by a single 30HX chiller are required, or where stand-by capability is desired, chillers may be installed in parallel. Units may be of the same or different sizes. However, cooler and condenser flow rates must be balanced to ensure proper flow to each chiller. The standard 30HX ComfortLink<sup>™</sup> control can be configured to provide lead/lag control for two chillers. The accessory Chillervisor<sup>™</sup> System Manager III control may be used for proper leaving chilled fluid temperature control and to ensure proper staging sequence of up to 8 chillers. Refer to the accessory Chillervisor System Manager III installation instructions for further details.

#### Series chillers

Chillers in series may be used for capacities greater than those supplied by a single 30HX chiller. Using the Minus-One-Pass Cooler Head option, fluid pressure drop across the cooler can be held to reasonable levels. The leaving fluid temperature sensors need not be relocated. However, the cooler minimum entering fluid temperature limitations should be considered for the chillers located downstream of other chillers. The standard 30HX control can control two 30HX chillers in series. Condensers should be piped in parallel to maximize capacity and efficiency. This should also minimize condenser pressure drop and saturated condensing temperatures. However, if condensers are piped in series, ensure that the leaving fluid temperature does not exceed 105 F (40.5 C).

<sup>1.</sup> The 30HX units will start with loop temperatures up to 95 F (35 C).
2. Minimum flow rate shown is based on ARI Ratings and is for reference only.
20 F (11.1 C) is the maximum cooler temperature differential that will determine actual minimum flow rate.



### **Energy management**

Demand limiting and load shedding are popular techniques used to reduce peak electric demands typically experienced during hot summer days when air conditioning loads are highest. When utility electricity demands exceed a certain level, electrical loads are turned off to keep the peak demands below a prescribed maximum limit. Compressor unloading reduces electrical demand while allowing the chiller to operate under part-load capacity and to maintain partial chilled fluid cooling.

Electrical demand can be limited through demand limit input to chiller control which unloads the chiller to a predetermined percentage of the load. One stage of unloading can be initiated by a remote signal to significantly reduce the chiller power consumption. This power reduction applies to the full load power at nominal conditions. The demand limit control should not be cycled less than 10 minutes on and 5 minutes off.

### **Duty cycling**

Duty cycling will cycle an electrical load at regular intervals, regardless of electrical demand. This reduces the electrical demand by "fooling" demand measuring devices. Duty cycling of the entire compressor is **NOT** recommended since motor windings and bearings will be damaged by constant cycling.

### Wye-delta start

Wye-delta start is standard on 30HX 208/230-v, 60-Hz units and 230-v, 50-Hz units and optional on all other 30HX units. This feature is not always required on 30HX units due to the use of multiple compressors that allow small electrical load increments, but is available if required. Maximum instantaneous current flow (see ICF in Electrical Data tables on pages 59-62) should be used in determining need.

### Vibration isolation

External vibration isolators are available as field-installed accessories.


#### Strainers

A strainer with a minimum screen size of 20 mesh must be installed in both the cooler and condenser fluid lines, within 10 ft (3 m) of the inlets to both the cooler and condenser. For 30HXA units, this requirement applies only to the cooler.

### Chilled fluid loop volume

The chilled fluid loop volume in circulation must equal or exceed 3 gal per nominal ton of cooling (3.2 L per kW) for temperature stability and accuracy in normal air conditioning applications. For example, a 30HXC096 with a nominal capacity of 94.0 tons would require 282 gal (1067.4 L) in circulation in the system loop.

For process jobs where accuracy is vital, or for operation at ambient temperatures below 32 F (0° C) with low unit loading conditions, there should be from 6 to 10 gal per ton (6.5 to 10.8 L per kW). To achieve this volume, it is often necessary to install a tank in the loop. Tank should be baffled to ensure there is no stratification, and that water (or brine) entering the tank is adequately mixed with liquid in the tank. See Tank Installation drawing.



### Fouling factor

The factor used to calculate tabulated ratings for the cooler is  $0.00010~\rm{ft^2} \cdot hr \cdot F/Btu~(0.000018~m^2 \cdot K/W)$ , and for the condenser is  $0.00025~\rm{ft^2} \cdot hr \cdot F/Btu~(0.00044~m^2 \cdot K/W)$ . As fouling factor is increased, unit capacity decreases and compressor power increases. To determine selections at other fouling factors, use the chiller program in the electronic catalog.

# Cooler and water-cooled condenser freeze protection

If chiller refrigerant or fluid lines are in an area where ambient conditions fall below 32 F (0° C), it is recommended that an antifreeze solution be added to protect the unit and fluid piping to a temperature 12° F (6.7° C) below the lowest anticipated temperature. For corrections to performance, refer to the chiller program in the electronic catalog.

Use only antifreeze solutions approved for heat exchanger duty. Use of automotive antifreezes is not recommended because of the fouling that can occur once their relatively short-lived inhibitors break down.

If the system will not be used during freezing weather conditions and the chiller and fluid piping are not protected with an antifreeze solution, it is recommended that the chiller and outdoor piping be drained.

Refer to Cooler Fluid Temperature section, page 21, for leaving fluid temperature for brine units. When leaving chilled fluid temperatures will be lower than 40 F  $(4.4\ C)$ , an appropriate antifreeze solution must be used in the cooler. In addition, the following special installation instructions will apply:

- In addition to the factory-mounted chilled water flow switch, a field-supplied condenser water flow switch must be installed.
- 2. The chiller must control both the chilled water pump and the condenser pump. The cooler pump must operate for a minimum of 10 minutes after the chiller has shut down and the condenser pump must operate for a minimum of 30 minutes after the chiller has shut down. In the event of a loss of condenser water flow, the flow of chilled fluid to the evaporator must be stopped or the isolation valve must be closed. This is necessary to reduce the possibility of condenser freeze-up.

# **Application data (cont**

3. Condenser head pressure control valves must not reduce condenser flow below 0.75 gallons per ton (0.4 L/s per kW) or the lowest detectable flow level of the condenser water flow switch. For further information, refer to the 30HX Installation Instructions or contact your Carrier representative.

### 30HXA remote condenser requirements

- 1. Do not manifold independent refrigerant circuits into a single condenser circuit.
- Ensure each refrigerant circuit has its own head pressure control.
- Condensing pressure control must be provided on condensers used with 30HXA to maintain a minimum 75 F (24 C) saturated discharge temperature at light loads.
- 4. Condenser must provide 15° F (8.3° C) subcooling, a maximum of 40° F (22.2° C) difference between saturated condensing temperature and outdoor ambient temperature (to prevent overload at high ambient temperatures), and a minimum of 20° F (11.1° C) difference (to assure subcooling).
- Minimum saturated discharge temperature (SDT) is 90 F (32.2 C). Maximum SDT is 135 F (57.2 C) at full load.
- 6. Condenser should not be located more than 15 ft (4.6 m) below chiller to maintain subcooling.
- 7. Design discharge and liquid piping according to Carrier System Design Manual. Piping must be sized for HFC-134a. Refer to the ASHRAE Refrigeration Handbook for R-134a sizing tables. Also see 30HX Installation instructions and the Typical 30HXA Refrigerant Piping to Remote Condenser diagrams on page 29.
- Maximum interconnecting refrigerant line length is 200 ft (61 m) actual.
- 9. Liquid line solenoid valves are required.
- If accessory sound enclosure is installed, run lines along the floor so the sound enclosure can be notched to clear lines.

Refrigerant pipe sizing for 30HXA with Carrier 09D condenser combinations — For refrigerant pipe sizing of the 30HXA follow these directions:

#### Discharge line:


- For applications at conditions of 40 F (4.4 C) or higher, use the Refrigerant Line Sizes for 30HXA Chiller/09DK Condenser Combinations tables on pages 25 and 26.
  - For applications using brine, other condensers, or LWT below 40 F (4.4 C), size lines using the ASHRAE Refrigeration Handbook, or other suitable design guide.
- Install horizontal lines level or pitched slightly toward the base of discharge riser and the condenser (in the direction of flow).
- If chiller is below the condenser, loop the discharge line to at least one inch (25.4 mm) above the top of condenser.



- 4. A double discharge riser (as shown in Refrigerant Line Sizes, Double Discharge Riser Pipe Sizes table on page 26) is required if any of the following conditions exist:
  - a. Unit is equipped with minimum load control.
  - b. Chiller is located below condenser.
  - c. Discharge line size is in shaded area in Refrigerant Line Sizes, Recommended Refrigerant Pipe Sizes table on page 25.
- 5. Minimize line length and restrictions to minimize pressure drop and refrigerant charge.
- If accessory sound enclosure is applied, run lines along the floor so sound enclosure may be notched to clear lines.
- 7. Lines should not be buried underground.

### Liquid line:

- For applications at conditions of 40 F (4.4 C) or higher LWT, use the Refrigerant Line Sizes for 30HXA Chiller/09DK Condenser Combinations tables on pages 25 and 26.
  - For applications using brine, other condensers, or LWT below 40 F (4.4 C), size lines using the ASHRAE Refrigeration Handbook, or other suitable design guide.
- 2. If chiller is above condenser, maximum vertical separation is 15 ft (4.6 m).
- Minimize line length and restrictions to minimize pressure drop and refrigerant charge.
- Field-supplied liquid line solenoid valves are required.
   The solenoid valves must be located close to the chiller.
- If sound enclosure is applied, run lines along floor so sound enclosure may be notched to clear lines.
- 6. In-line receivers are NOT recommended due to their negative effect on system subcooling. Where the use of a receiver is desired for service purposes, the receiver should be piped in parallel with the main liquid line and equipped with shut-off valves to isolate it during unit operation. See sketch below.
- Filter driers (field supplied) are required.



### Relief valve vent lines

- Vent per local code requirements.
- 2. Each chiller has a minimum of 4 refrigerant relief valves: 2 on the cooler, 2 on the condenser (30HXC) or oil separator (30HXA). Units with factory-installed suction service valves also have one relief valve on each compressor discharge line. See Dimensions section on pages 11-18 for specific locations.
- If sound enclosure is applied, run lines along floor so sound enclosure may be notched to clear lines.



## REFRIGERANT LINE SIZES FOR 30HXA CHILLER/09DK CONDENSER COMBINATIONS

RECOMMENDED REFRIGERANT PIPE SIZES (in. OD)

			TOTAL LEN	GTH OF INTERCO	NNECTING PIPI	NG — FT (M)		
30HXA UNIT SIZE	CKT	0-50	0-15)	50-100	(15-30)	100-200 (30-60)		
OIZL		Liquid Line*	Discharge Line†	Liquid Line*	Discharge Line†	Liquid Line*	Discharge Line†	
076	A B	11/8 11/8	21/8 21/8	1 <sup>1</sup> / <sub>8</sub> 1 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	
086	A B	1 1/8 1 1/8	2 <sup>1</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub> 1 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	13/8	21/8	
096	A B	1 1/8 1 1/8	21/8 21/8	1 <sup>3</sup> / <sub>8</sub> 1 <sup>1</sup> / <sub>8</sub>	21/8	1 <sup>3</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	
106	A B	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	13/ <sub>8</sub> 11/ <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub>	2 <sup>1/</sup> <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	
116	A B	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub> 1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	
126	A B	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	25/8	1 <sup>3</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	
136	A B	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	15/8 13/8	2 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>	
146	A B	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	25/8	1 <sup>5</sup> / <sub>8</sub>	25/8 31/8	
161	A B	1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>	
171	A B	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	15/8 15/8	2 <sup>5</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	15/ <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>	
186	A B	1 <sup>3</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	15/8 15/8	2 <sup>5</sup> / <sub>8</sub> . 2 <sup>5</sup> / <sub>8</sub> .	21/8	31/ <sub>6</sub>	
206	A B	1 <sup>5</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	15/8 15/8	3 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	31/a 31/a 31/a	
246	A B	2 <sup>1</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 1 <sup>5</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	31/6	
261	A B	2 <sup>1</sup> / <sub>8</sub> 1 <sup>3</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 1 <sup>5</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub>	
271	A B	2 <sup>1</sup> / <sub>8</sub> .	3 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub> 1 <sup>5</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub> 2 <sup>5</sup> / <sub>8</sub> 2 <sup>1</sup> / <sub>8</sub>	31/8 31/8 31/8	

LEGEND

### OD — Outside Diameter

\*Field-supplied liquid line solenoid valve is required.
†Double discharge riser is required on ALL units which have minimum load control installed.



Values indicate double discharge riser required on STANDARD unit. See Double Discharge Riser Pipe Sizes table on page 26.

### NOTES:

- Refrigerant and Double Discharge Riser Pipe Sizes tables are based on equal chiller and 09DK condenser sizes i.e., 30HXA096 with 09DK094.
- SOHXA096 WIN 09DK094.
   For other system combinations, size lines per ASHRAE (American Society of Heating, Refrigerating, and Air Conditioning Engineers) or other R-134a line sizing guide.
   Refrigerant and Double Discharge Riser Pipe Sizes tables are based on cooler leaving water temperatures of 40 F (4.4 C) or above.
- Pipe diameter calculation is based on actual line length plus a 50% allowance for fittings.

# **Application data (cont**




# REFRIGERANT LINE SIZES FOR 30HXA CHILLER/09DK CONDENSER COMBINATIONS (cont) DOUBLE DISCHARGE RISER PIPE SIZES (in. OD)

	*	RISER "A"		RISER "B"						
30HXA UNIT SIZE	CKT	т	Total Length of Interconnecting Piping — FT (M)*							
		0-200 (0-60)	0-50 (0-15)	50-100 (15-30)	100-200 (30-60)					
076	A	1 <sup>1</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>					
	B	1 <sup>1</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>					
086	A	11/8	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>					
	B	11/8	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>					
096	A	11/8	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>					
	B	11/8	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>					
106	A	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>					
	B	1 <sup>3</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub>	1 <sup>3</sup> / <sub>8</sub>					
116	A	1 <sup>5</sup> / <sub>8</sub> .	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>					
	B	1 <sup>3</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>					
126	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	21/8					
	B	1 <sup>3</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	21/8					
136	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
	B	1 <sup>3</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>					
146	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
	B	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>					
161	. А	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
	- В	1 <sup>5</sup> / <sub>8</sub>	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>					
171	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	· 21/8	2 <sup>5</sup> / <sub>8</sub>					
	B	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	21/8	2 <sup>5</sup> / <sub>8</sub>					
186	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
	B	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
206	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
	B	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
246	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
	B	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
261	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub>					
	B	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>5</sup> / <sub>8</sub>					
271	A	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	3 <sup>1</sup> / <sub>8</sub>	31/8					
	B	1 <sup>5</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	2 <sup>1</sup> / <sub>8</sub>	25/8					

#### LEGEND

A — Riser Without Trap
B — Riser With Trap
OD — Outside Diameter

NOTE: Horizontal line sections should be sized according to the Total Length of Interconnecting Piping columns on the Recommended Refrigerant Pipe Sizes table on page 25.



<sup>\*</sup>Total Length of Interconnecting Piping refers to actual length, not total equivalent length.



For chillers using brine or those matched with other condensers, the lines must be sized manually using design guides such as ASHRAE, or curves in the 30HXA installation instructions. In many 30HXA sizes, the individual refrigerant circuits have unequal capacities. The Circuit Cooling Capacity table below lists the percentage capacity of each circuit for line sizing purposes. The Circuit Unloading Capacity table below indicates the minimum unloading capacities per circuit as well as a sample calculation of the minimum circuit tonnage for riser design. The example below lists circuit capacity calculations based on the Circuit Cooling and Circuit Unloading Capacity tables.

### CIRCUIT COOLING CAPACITY

30HXA UNIT SIZE	PERCENT OF TOT	AL UNIT CAPACITY	
SUITA UNIT SIZE	Circuit A %	Circuit B %	
076	50	50	
086	55	45	
096	59	41	
106	64	36	
116	60	40	
126	55	45	
136	59	41	
146	55	45	
161	59	41	
171	47	53	
186	50	50	
206	54	46	
246	61	39	
261	63	37	
271	64	36	

### CIRCUIT UNLOADING CAPACITY

30HXA UNIT	MINIMUM CIRCUIT CAPACITY — PERCENT OF FULL LOAD			
OUTINA OTTT	Standard Unit	With Minimum Load Control		
All Sizes, All Circuits	40%	20%		

### **Example Calculation of Circuit Capacities:**

Select (Standard) 30HXA086 Chiller

From Electronic catalog (E-cat) selection or balance diagram:

Total Unit Capacity = 74 tons (from unit selection at design conditions)

### Using the Circuit Cooling Capacity table:

Ckt "A" design capacity =  $74 \times 0.55 = 40.7$  tons

### Using the Circuit Unloading Capacity table:

Ckt "A" minimum capacity =  $40.7 \times 0.40 = 16.3$  tons

Ckt "B" design capacity =  $74 \times 0.45$  = 33.3 tons

Ckt "B" minimum capacity =  $33.3 \times 0.40 = 13.3 \text{ tons}$ 

System refrigerant charge — The 30HXA units are shipped from the factory with a small holding charge of R-134a refrigerant. The approximate refrigerant charge required for starting the 30HXA system is listed in the table on next page. This initial charge will allow starting of the unit. Additional refrigerant may be required to accommodate liquid line storage. See the liquid line refrigerant storage capacity table below for liquid line storage information.

### LIQUID LINE REFRIGERANT STORAGE CAPACITY

PIPING SIZE (in.)	REFRIGERANT (Ib) PER FT OF TUBING LENGTH	REFRIGERANT (kg) PER M OF TUBING LENGTH		
11/8	0.41	0.61		
13/8	0.63	0.94		
1 <sup>5</sup> / <sub>8</sub>	0.89	1.33		
21/8	1.52	2.26		
25/8	2.32	3.45		

# **Application data (cont**



### SYSTEM REFRIGERANT CHARGE FOR START-UP

зонха	REFRIGERANT CIRCUIT	CH	OLER ARGE	AIR-COOLED CONDENSER TYPE, SIZE (Qty)*	CON	DENSER IARGE	RECOMMENDED REFRIGERANT PIPE SIZES		PIPING HARGE	REFRI	TAL GERANT ARGE
		Lb	Kg	SIZE (Qty)	Lb	Kg	(in. OD)†	Lb	Kg	Lb	Kg
076	. A	48	22	09DK 084 (1)	62	28	11/8	10		120	55
	В	48	22	1,1	62	28	11/8	10	5	120	55
086	A	61	28	09DK 084 (1)	62	28	11/8	10	5	133	61
	B A	52 75	24		62	28	11/8	10	5	124	57
096	A	56	34 25	09DK 094 (1)	68	31	11/8	10	5	153	70
	A	88	40		68	31	11/8	. 10	5	134	61
- 1	^ B	56	25	09DK 074 (1) and 09DK 044 (1)	82	37	13/8	16	7	186	84
106	A	88	40	0051(047(1)	62	28	13/8	16	7	134	60
- 1	В	56	25	09AZ 102FE (1)	24	11	13/8	16	7	128	58
	A	84	38	000110001111111111111111111111111111111	18	8	13/8	16	7	90	40
ŀ	В	61	28	09DK 074 (1) and 09DK 054 (1)	82	37	13/8	16	7	182	82
116	- A	84	38	0001(004(1)	56	25	13/8	16	7	133	60
.	В	61	28	09AZ 112FE (1)	42	19	13/8	16	7	142	64
	A	90	41		42 82	19	13/8	16	7	119	54
	В	71	32	09DK 074 (2)	82	37	13/8	16	7	188	85
126	A	90	41	200240	24	37 11	13/8	16	7	169	76
	В	71	32	09AZ 122FE (1)	24	11	13/8	16	7	130	59
	A	99	45	normalistic con	82	37	1 <sup>3</sup> / <sub>8</sub>	16	7	112	50
400	В	71	32	09DK 074 (2)	82	37	13/8	16	7	197	89
136	Α	99	45	004740055 (4)	57	26	13/8	16	7	169	76
	В	71	32	09AZ 132FE (1)	42	19	13/8	16	7	172	78
	Α	95	43	00DK 004 (0)	124	56	13/8	16	7	130	58
146	В	80	36	09DK 084 (2) 09AZ 142FE (1)	124	56	13/8	16	7	235 220	106
140	Α	95	43		57	26	13/8	16	7	168	99
	В	.80	36		57	26	13/ <sub>8</sub>	16	7	153	69
	A	120	54	00014 004 (0)	124	56	13/8	16	7	260	117
161	В	88	40	09DK 084 (2)	124	56	13/8	16	7	228	103
	Α	120	54	09AZ 162FE (1)	68	31	13/8	16	7	204	92
	В	88	40	09AZ 102FE (1)	68	31	13/8	16	7	172	78
_	A	95	43	09DK 084 (2)	124	56	13/8	16	7	235	106
171	В	112	51	0001(00+(2)	124	56	13/8	16	7	252	114
_	A	95	43	09AZ 172FE (1)	68	31	13/8	16	7	179	81
	В	112	51	33. 3. 112. 2 (1)	68	31	13/8	16	7	196	89
_	. A	108	49	09DK 084 (2)	124	56	13/8	16	7	248	112
186	В	108	49		124	56	13/8	16	7	248	112
-	A B	108	49	09AZ 182FE (1)	68	31	13/8	16	7	192	87
	A	108	49		68	31	13/8	16	7	192	87
-	B	160	73	09DK 084 (2) and 09DK 094 (1)	272	123	15/8	22	10	454	206
206	A	108			124	56	13/8	16	7	248	112
-	В	108	73	09AZ 101FA (1) and	49	22	15/8	22	10	231	105
	A	176	80	09AZ 91FA (1)	37	17	13/8	16	7	161	73
00000	В	108	49	09DK 094 (3)	272	123	21/8	38	17	486	220
246	A	176	80	2017 17171 111	136	62	13/8	16	7	260	118
	В	108	49	09AZ 151FA (1) and 09AZ 91FA (1)	113	51	21/8	38	17	327	148
	A	176	80	50, 251171(1)	37 272	17	13/8	16	7	161	73
	В	108	49	09DK 094 (3)	136	123 62	21/8	38	17	486	220
261	A	176	80	0047 17154 (1)	136	62	13/8	16	7	260	118
	В	108	49	09AZ 171FA (1) and 09AZ 91FA (1)	37	17	21/8	38	17	350	159
	A	176	80		272	123	13/8	16	7	161	73
	В	108	49	09DK 094 (3)	136	62	21/8	38	17	486	220
271 —	A	176	80	09A7 181EA (1) and	136	62	1 <sup>3</sup> / <sub>8</sub>	16 38	7	260 350	118
				09AZ 181FA (1) and 09AZ 91FA (1)							

<sup>\*</sup>Refer to Carrier's electronic catalog for 09AZ/30HX rating data.
†Based on 25 ft (7.6 m) liquid line.


NOTE: Multiply the liquid line length (in feet) by the factor shown on page 27 for the refrigerant/ft of the tubing. Add base unit charge to liquid line charge to determine approximate refrigerant charge.



## TYPICAL 30HXA REFRIGERANT PIPING TO REMOTE CONDENSER (076-096 SIZES SHOWN)

#### NOTES:

- Piping shown is for general point-of-connection only and is not intended to show details for a specific installation. Certified field wiring and dimensional drawings are available upon request. The 30HXA units should be installed using certified drawings.
   Refer to Carrier System Design Manual for details regarding piping techniques.
   Piping and pressure relief devices are field supplied.
- Relief valve vent piping per local codes.
- If unit is equipped with accessory sound enclosure, run lines down to floor and notch bottom of enclosure to clear lines.




## TYPICAL 30HXA REFRIGERANT PIPING TO REMOTE CONDENSER(S) (206-271 SIZES SHOWN)

#### NOTES:

- 1. Piping shown is for general point-of-connection only and is not intended to show details for a specific installation. Certified field wiring and dimensional drawings are available upon request. The 30HXA units should be installed using certified drawings.

  2. Refer to Carrier System Design Manual for details regarding piping techniques.
- Piping and pressure relief devices are field supplied. Relief valve vent piping per local codes.
- If unit is equipped with accessory sound enclosure, run lines down to floor and notch bottom of enclosure to clear lines.



# Selection procedure with xample



Carrier's electronic catalog chiller selection program provides quick, easy selection of Carrier chillers. The program considers specific temperature and flow requirements and other factors, such as fouling and altitude correction. It can also select an air-cooled condenser for the condenserless 30HXA unit to match the required conditions. To select a 30HXA unit, use the electronic catalog or contact your Carrier representative. To select a 30HXC chiller, use the electronic catalog or follow one of the procedures below.

### ENGLISH (60 Hz)

I Determine 30HXC unit size and operating conditions required to meet given capacity at given conditions.

#### Given:

Capacity
Leaving Chilled Water Temp (LCWT)
Cooler Water Temp Rise
Condenser Entering Water Temp
Condenser Water Temp Rise 10° F
Cooling Fouling Factor
Condenser Fouling Factor
NOTE: For other than 10° F temperature rise, data cor-

NOTE: For other than 10°F temperature rise, data corrections must be made using the chiller program in the electronic catalog. On some units, a change of controls is also necessary.

II From Cooling Capacities table on page 31 and pressure drop curves on pages 55 and 56, determine operating data for selected unit.

Unit	C186
Capacity	9 tons
Compressor Motor Power Input	.5 kW
Cooler Water Flow	2 gpm
Cooler Pressure Drop 12.1 ft of	water
Condenser Water Flow 507.7	7 gpm
Condenser Pressure Drop 16.7 ft of	water

### SI (50 Hz)

I Determine 30HXC unit size and operating conditions required to meet given capacity at given conditions.

#### Given:

trols is also necessary.

Capacity 617 kW
Leaving Chilled Water Temp (LCWT) 7 C
Cooler Water Temp Rise
Condenser Entering Water Temp
Condenser Water Temp Rise 5.6° C
Cooling Fouling Factor
Condenser Fouling Factor
NOTE: For other than 5.6° C temperature rise, data corrections must be made using the chiller program in
the electronic catalog. On some units, a change of con-

II From Cooling Capacities table on page 41 and pressure drop curves on pages 55 and 56, determine operating data for selected unit.

Tarang and for science diffe.	
Unit	
Capacity	
Compressor Motor Power Input	
Cooler Water Flow	
Cooler Pressure Drop	
Condenser Water Flow	
Condenser Pressure Drop	

## Performance data



All performance data is based on:

- 1. Cooler water temperature rise of 10° F (5.6° C).
- 2. Cooler fouling factor of 0.00010 ft $^2$  hr F/Btu (0.000018 m $^2$  k/W).



- 3. Condenser fouling factor of 0.00025 ft<sup>2</sup> hr F/Btu (0.000044 m<sup>2</sup> k/W).
- 4. 10° F (5.6° C) subcooling.
- 5. Refrigerant 134a.

### **30HXC COOLING CAPACITIES**

60 Hz, ENGLISH

		_		80.0				NSER EN 85.0	TERING	WATER	RTEMP	RATURE	(F)		100		
LCWT	UNIT	-	1	Cooler	Loand	-	T-		T -	-		90.0		_		95.0	
(F)	30HXC	Сар.	KW	Flow Rate (Gpm)	Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)
40.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261 271	71.5 78.9 89.1 99.0 107.7 116.6 129.3 138.3 147.6 156.4 167.2 199.4 234.3 242.6 252.3	56.3 62.5 70.2 74.6 81.0 90.7 98.3	171.2 188.8 213.4 237.0 257.7 279.1 309.4 331.0 353.3 374.4 400.1 477.4 560.9 580.6 603.9	203.8 225.5 254.1 282.7 306.4 331.9 368.6 395.1 441.3 446.5 477.8 566.3 665.8 690.4 719.3	68.5 75.6 85.4 94.7 103.2 111.8 124.1 132.5 144.9 154.0 164.6 195.8 230.3 238.6 248.3	52.9 59.4 66.0 74.3 79.1 86.0 95.8 103.8 113.5 120.1 129.2 148.0 175.0 182.8 191.9	163.9 180.9 204.5 226.7 247.0 267.6 297.1 317.2 346.8 368.6 394.1 468.8 551.4 571.3 594.5	198.4 219.7 247.6 275.2 298.7 323.8 359.6 385.0 420.9 447.0 478.4 565.5 665.7 690.7 719.8	65.6 72.6 82.0 90.9 98.8 107.3 119.4 127.7 143.1 152.4 162.9 193.0 226.6 235.4 245.2	62.7	157.0 173.8 196.3 217.6 236.5 256.8 285.8 305.6 342.5 364.8 390.1 462.1 542.5 587.1	193.5 214.8 241.9 269.0 291.2 316.4 351.9 377.5 423.4 450.2 481.8 567.5 667.0 693.3 723.3		66.5 74.1 83.8 89.1 97.0 107.3 117.0 135.5 142.6 153.1 175.4 208.2 216.9	151.5 167.9 189.8 210.5 228.7 248.3 276.9 296.2 340.8 362.9 388.5 457.6 539.4 561.0	190.2 211.4 238.3 265.3 287.1 311.8 347.2 372.8 429.5 456.3 488.7 572.5 675.8 703.1
42.0	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	74.9 82.6 93.4 103.7 112.7 122.1 135.4 144.8 153.3 162.3 173.5 207.0 243.3 251.7 261.8	50.5 56.8 63.0 70.7 75.1 81.5 91.4 99.0 104.0 110.1 118.8 136.5 160.0 167.3 176.2	179.5 197.9 223.6 248.3 270.1 292.5 324.3 346.9 367.2 388.8 415.5 496.0 582.8 603.1 627.1	212.4 234.8 264.6 294.3 319.0 345.5 383.8 411.3 434.8 460.5 492.8 584.8 686.9 711.9 741.7	71.7 79.1 89.4 99.2 108.1 117.1 129.9 138.8 150.5 159.7 170.7 203.4 239.1 247.5 257.4	53.4 60.0 66.7 75.0 79.8 86.7 96.6 104.8 119.7 128.8 147.8 174.4 181.9 191.3	171.8 189.6 214.3 237.7 259.0 280.5 311.1 332.6 360.5 382.7 408.8 487.3 572.8 593.0 616.7	206.6 228.7 257.7 286.6 311.0 337.0 374.1 400.8 492.7 583.7 686.6 711.6 741.3	68.6 75.8 85.7 94.8 103.4 112.2 124.7 133.2 147.8 157.6 168.2 199.9 235.0 243.7 253.6	56.3 63.3 70.4 91.8 101.8 110.7 123.1 130.0 139.5 160.5 189.5 189.5 189.5 197.4 207.3	164.3 181.5 205.2 227.1 247.7 268.7 298.6 319.2 354.1 377.5 403.0 478.9 562.9 583.9	201.1 222.8 251.2 278.8 302.8 328.7 365.1 391.4 434.5 462.3 494.0 583.8 686.8 712.8	65.9 73.0 82.6 91.5 99.5 107.9 120.4 128.8 146.8 156.3 167.3 232.4 241.6	227.5 59.5 67.0 74.6 85.1 90.2 98.1 107.9 117.5 134.8 152.3 174.7 207.3 215.3	584.6 157.9 175.0 197.8 219.2 238.3 258.6 288.5 308.5 351.7 374.5 400.7 472.6 556.7 578.8	733.7 196.9 218.8 246.5 274.8 297.2 322.7 359.1 385.3 439.8 467.2 500.3 692.4 719.7
44.0	246 261	78.4 86.4 97.6 108.4 -117.9 127.6 141.6 151.4 159.0 168.2 179.8 214.7 252.0 260.8 271.2	51.1 57.4 63.7 71.3 75.8 82.3 92.2 99.8 103.6 110.5 118.4 136.9 160.0 167.6 175.8	187.9 207.1 234.1 259.9 282.6 306.0 339.5 363.0 381.1 403.3 431.0 514.8 604.2 625.1 650.0	221.1 244.4 275.4 306.1 331.8 359.4 359.3 427.7 448.4 475.0 507.8 603.7 708.1 734.0	75.1 82.8 93.6 103.9 113.2 122.5 136.0 145.4 156.3 165.6 211.2 248.2 256.8	53.9 60.7 67.3 75.7 80.4 87.3 97.4 105.6 113.0 119.7 128.5 147.6 173.7 181.8 190.8	180.1 198.6 224.5 249.2 271.3 293.8 326.0 348.6 374.7 397.1 424.2 506.2 594.9 615.6 640.0	215.2 238.0 268.3 298.4 323.6 350.5 389.4 417.2 448.2 474.9 507.7 602.3 708.0 734.0	71.8 79.3 89.6 99.3 108.3 117.4 130.4 139.2 153.4 163.0 174.2 207.3 243.9 252.6	56.9 64.0 71.1 80.1 85.2 92.6 102.8 111.5 123.0 129.9 139.3 160.5 189.1 197.5 207.0	607.5 172.1 190.1 214.9 238.1 259.7 281.5 312.7 333.7 367.7 390.8 417.6 496.9 584.6 605.5 629.9	707.9 734.3	249.0	226.1 60.0 67.4 75.0 87.2 90.1 108.5 119.3 139.3 141.5 151.5 174.6 205.7 214.4 224.8	603.0 164.7 182.3 206.0 228.2 248.3 269.7 300.4 321.1 362.9 386.5 413.1 489.5 574.8 597.0 621.7	750.9 203.8 226.3 254.9 285.0 307.2 333.7 371.3 398.9 451.6 603.6 709.2 737.1 768.6

LEGEND



## 30HXC COOLING CAPACITIES (cont)

60 Hz, ENGLISH (cont)

	r	1			· ·			IIZ, EIV									
2		-		80.0		т —			TERING	WATER	TEMPE	RATURE	(F)				
LCWT	UNIT	-	_	Cooler	Cond			85.0	Ι		_	90.0				95.0	
(F)	30НХС	Cap.	MY	Flow Rate (Gpm)	Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)
45.0	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	80.1 88.3 99.8 110.8 120.5 130.5 144.7 154.8 161.8 171.2 182.9 218.6 256.4 265.3 275.8	57.8 64.2 71.6 76.2 82.7 92.9 100.3 103.6 110.6	192.1 211.8 239.3 265.7 288.9 312.9 347.0 371.1 388.1 410.6 438.6 524.3 614.9 636.1 661.3	225.5 249.2 280.9 312.1 338.4 366.5 407.2 436.1 455.2 482.3 515.3 613.1 718.8 745.1 775.5	76.9 84.7 95.8 106.3 115.8 125.4 139.1 148.8 159.2 168.7 180.2 215.1 252.8 261.5 271.9	54.2 60.9 67.6 76.0 80.6 87.8 106.0 112.8 119.7 128.3 147.8 173.3 181.6 190.4	184.3 203.2 229.7 255.0 277.6 300.6 333.6 356.7 381.8 404.5 432.0 515.8 606.1 627.1 651.9	219.5 242.8 273.7 304.3 330.1 357.5 397.2 425.6 455.1 482.3 515.4 612.0 718.8 745.2 775.7	73.5 81.1 91.7 101.6 110.9 120.2 133.4 142.4 156.3 166.0 177.3 211.2 248.4 257.1 267.4	57.2 64.3 71.5 80.4 85.5 92.9 103.3 112.0 122.9 130.0 139.2 160.5 188.8 197.4 206.7	176.2 194.5 219.8 243.7 265.9 288.1 319.8 341.5 374.7 398.0 425.2 506.4 595.6 616.5 641.2	213.5 236.4 266.4 296.1 321.6 348.7 387.1 414.5 454.7 482.6 515.8 611.1 718.7 745.1 775.9	70.2 77.6 87.8 97.1 105.9 115.0 128.0 136.8 153.7 163.9 175.0 207.7 244.0 253.2	67.7 75.3 86.5 90.4 98.4 108.9 120.7 135.6 141.5 151.0 174.6 205.4 214.2	168.3 186.2 210.4 232.9 254.1 275.8 306.9 328.0 368.6 393.0 419.5 498.1 585.1 607.0	207.6 230.3 259.6 289.3 313.1 340.0 378.0 406.7 457.0 485.3 518.1 612.2 719.2 746.9
46.0	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	81.9 90.3 102.0 113.2 123.1 133.3 147.9 158.2 164.7 174.2 186.0 222.5 260.9 269.8 280.5	51.9 58.2 64.7 72.1 76.7 83.2 93.6 100.8 110.7 118.6 137.1 160.3 168.5 176.4	196.4 216.6 244.6 271.6 295.3 319.8 354.7 379.4 395.0 417.9 446.2 533.8 625.7 647.2 672.8	230.0 254.2 286.5 318.3 345.0 373.7 415.3 444.6 462.2 489.6 523.0 622.7 729.6 756.4 787.0	78.7 86.7 98.0 108.7 118.4 128.2 142.3 152.1 162.2 171.8 183.4 219.0 257.4 266.3 276.8	54.3 61.2 67.9 76.2 80.9 87.8 98.2 106.3 112.6 119.6 128.0 148.1 172.7 181.2 189.9	188.7 208.0 235.1 260.8 284.0 307.6 341.3 364.9 389.0 412.0 440.0 525.4 617.4 638.7 663.8	224.0 247.7 279.2 310.3 336.6 364.6 405.0 433.9 462.1 489.7 523.1 621.7 729.7 756.5 787.2	75.2 83.0 93.8 104.0 113.4 122.9 136.4 145.7 159.2 169.0 180.4 215.1 252.9 261.8 272.1	57.5 64.6 71.8 80.8 85.9 93.3 103.7 112.5 122.7 130.1 139.0 160.5 188.5 197.2	180.3 199.0 224.9 249.5 272.1 294.8 327.2 349.6 381.8 405.3 432.8 516.0 606.7 627.9	217.8 241.0 271.6 302.1 328.0 355.5 394.7 422.7 461.7 490.0 523.2 620.6 729.5 756.3	263.3 71.8 79.3 89.7 99.2 108.4 117.6 130.8 139.7 156.3 166.6 177.8 211.3 248.5	224.1 60.6 68.0 75.7 85.3 90.8 98.7 109.4 120.7 134.3 141.4 150.8 174.4 205.1 214.3	631.5 172.2 190.3 215.3 238.0 259.9 282.0 313.8 335.1 374.9 399.6 426.5 506.9 596.0 618.0	777.8 211.7 234.7 264.6 293.6 319.2 346.5 385.1 413.8 462.4 491.8 524.8 620.7 729.9 757.9
48.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	85.5 94.2 106.4 118.1 128.5 139.1 154.3 165.0 170.4 180.2 192.3 229.3 269.9 279.0 289.9	52.6 59.1 65.6 73.1 77.6 84.2 94.9 102.1 104.0 111.1 119.0 137.1 160.3 168.9 176.7	205.2 226.1 255.4 283.5 308.4 333.9 370.3 396.0 408.9 432.4 461.6 550.3 647.6 669.6 669.8	239.2 264.3 297.8 330.7 358.6 388.3 431.6 462.0 476.1 504.2 538.4 638.9 751.3 778.8	82.2 90.7 102.5 113.7 123.8 134.0 148.8 159.0 168.1 177.9 190.0 227.0 266.5 275.7	55.0 61.8 68.5 76.8 81.6 88.7 98.9 107.2 112.1 119.8 127.5 148.2 172.8 181.4 189.4	197.4 217.6 245.9 272.8 297.0 321.5 357.1 381.6 403.5 426.9 4455.9 544.8 639.6 661.6 687.6	233.0 257.6 290.3 322.6 350.0 379.0 421.2 451.0 476.2 504.5 538.6 641.0 751.7 779.2	78.7 86.8 98.1 108.9 118.7 128.5 142.7 152.5 165.2 175.1 186.9 223.1 262.3 271.4	58.1 65.3 72.5 81.5 86.5 93.9 104.6 113.4 129.8 138.6 159.9 187.8 196.9 205.8	652.7 188.9 208.2 235.5 261.3 284.8 308.4 342.5 366.1 396.5 420.2 448.6 535.5 629.5 651.2 676.8	751.7 779.3	266.9	61.2 68.8 76.5 86.1 91.6 99.5 110.4 119.8 133.3 141.1 150.5 174.0 204.6 214.1 223.6	180.3 199.1 225.2 249.4 272.4 295.3 328.2 350.2 388.9 413.4 441.6 525.5 618.4 640.4 665.9	789.0 220.2 243.9 275.1 305.5 332.1 360.1 400.2 428.2 475.7 505.3 539.7 638.9 751.9 750.0 811.7

### LEGEND



## 30HXC COOLING CAPACITIES (cont)

60 Hz, ENGLISH (cont)

	505000000			80.0					TERING	WATER	TEMPE	RATURE	(F)				
LCWT	UNIT	-			T			85.0				90.0				95.0	
(F)	SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)
50.0	076 086 096 106 116 126 136 146 161 171 186 206 246 246	89.0 98.2 110.9 123.1 133.7 144.6 160.9 171.9 176.2 185.5 198.6 236.1 277.4 287.1 298.9	53.1 59.9 66.3 73.8 78.2 84.8 96.0 103.2 104.0 111.1 119.0 136.8 159.4 168.4 176.3	213.7 235.8 265.6 320.9 347.2 386.4 412.8 423.0 445.4 476.9 566.9 666.0 689.4 717.6	248.0 274.3 309.0 343.2 371.4 401.9 448.3 479.3 490.1 517.0 553.6 655.1 768.9 798.1 831.3	85.9 94.6 106.9 118.6 129.2 139.9 155.3 166.0 174.0 184.1 196.4 235.1 275.6 285.0 296.1	55.8 62.7 69.6 77.7 82.6 89.5 100.5 108.3 112.4 119.7 127.9 148.2 173.3 182.1	206.1 227.2 256.7 284.9 310.2 335.8 372.8 398.5 417.7 442.0 471.7 564.5 661.8 684.3 711.0	242.3 267.8 301.8 335.2 363.6 393.8 437.9 468.6 490.5 519.4 660.5 774.1 802.2	82.3 90.7 102.6 113.8 124.1 134.4 149.2 159.5 171.3 181.4 193.6 231.3 271.8 281.1	58.5 65.9 73.1 82.1 87.0 94.5 105.5 114.3 122.0 129.5 138.3 160.2 186.9 196.1	197.7 217.9 246.4 273.4 298.0 322.7 358.4 383.0 411.2 435.5 464.9 555.4 652.7 675.0	235.7 260.6 293.9 326.6 354.6 384.1 426.9 457.2 490.4 519.6 554.7 659.5 774.2 802.4	78.6 86.7 98.1 108.8 118.8 128.7 142.9 152.6 168.0 178.4 190.4 227.1 267.1 276.3	69.5 77.2 86.9 92.3 100.3 111.4 120.9 133.0 140.9 150.2 173.7 204.0 213.5	188.8 208.3 235.5 261.2 285.2 309.0 343.2 366.5 403.5 428.3 457.2 545.2 641.2 663.3	229.0 253.5 285.8 317.8 345.4 374.3 415.7 445.1 490.0 520.0 555.0 658.4 774.2 802.4
55.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261 271	93.0 103.7 116.8 130.0 141.9 154.8 170.5 184.3 184.2 194.5 206.4 245.4 287.8 297.7 309.7	53.6 60.7 67.0 74.5 78.8 85.6 97.0 104.3 110.2 118.0 135.7 157.2 166.5 174.4	223.4 249.3 280.6 312.5 341.0 372.2 409.8 443.0 442.8 467.5 496.0 589.8 691.7 715.6 744.4	257.8 288.2 323.6 360.2 391.5 427.1 472.1 509.9 508.8 538.2 571.7 676.9 792.6 822.4	90.6 100.8 113.9 126.4 138.8 151.6 166.8 179.9 184.3 194.7 206.3 245.6 289.1 299.4 310.9	56.8 64.1 71.1 79.2 84.2 91.6 102.8 110.9 112.7 120.1 128.3 148.4 172.9 182.3 190.5	217.7 242.3 273.9 303.7 333.6 364.4 400.9 432.5 442.9 468.1 495.9 590.2 694.9 719.6 747.3	834.2 254.3 283.6 319.6 354.7 387.9 423.4 467.1 503.9 515.5 578.5 685.9 806.5 837.1 870.1	292.1 87.0 96.9 109.6 121.6 133.6 144.4 160.7 173.4 181.9 192.6 203.8 243.0 286.1 295.8 307.2	205.1 59.4 66.9 74.3 83.1 88.6 96.1 107.5 116.2 121.6 129.3 137.7 160.1 187.1 196.4	701.2 209.2 233.0 263.4 292.2 321.2 347.1 386.2 416.8 437.1 463.0 489.9 584.1 687.6 710.8	834.5 247.6 276.3 311.5 345.9 378.5 409.4 455.8 492.0 515.8 546.7 579.0 687.8 808.8 838.0	287.1 83.2 92.8 103.6 116.4 128.2 138.5 154.2 164.5 178.8 189.6 200.6 238.9 281.7 291.3	223.0 62.6 70.6 78.1 88.1 93.5 101.7 113.1 122.5 132.5 140.2 149.7 173.0 202.8 212.6	689.3 200.0 223.0 249.0 279.7 308.0 332.9 370.7 395.3 429.8 455.8 482.2 574.1 677.1 700.2	834.5 240.7 268.7 299.7 366.9 368.8 9444.2 474.8 515.8 546.9 579.3 686.5 809.0 838.3
60.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	93.0 103.8 116.9 130.1 142.0 153.6 170.7 184.5 183.1 193.5 206.5 245.6 288.0 297.9	53.6 60.7 67.0 74.5 78.8 85.6 97.0 104.3 103.0 110.4 118.0 135.7 157.7 166.5 174.4	223.8 249.8 281.1 313.0 341.6 369.5 410.6 443.8 440.6 496.8 590.7 692.7 716.6 745.5	258.0 288.5 323.9 360.5 391.9 424.1 472.5 510.4 506.3 536.0 572.0 677.3 793.0 822.8	90.7 100.9 112.7 126.5 139.0 150.2 167.0 178.1 182.8 193.7 206.5 245.7 289.3 299.6	56.8 64.1 70.8 79.2 84.3 91.5 102.8 110.6 120.2 128.3 148.4 172.9 182.3 190.5	218.2 242.8 271.1 304.4 334.3 361.2 401.7 428.5 439.7 466.0 496.7 591.1 696.0 720.6 748.6	254.6 283.9 316.5 355.1 388.3 419.9 467.6 499.4 512.0 543.1 579.0 686.3 806.9 837.5	87.1 97.0 108.4 121.7 132.1 144.6 160.9 171.7 180.4 191.3 204.0 243.2 286.3 296.0	59.4 66.9 74.0 83.1 96.2 107.5 115.7 129.2 137.7 160.1 187.1 196.4 204.9	738.4 209.6 233.4 260.7 292.7 317.9 347.9 387.1 413.0 433.9 460.3 490.8 585.1 688.8 712.1 739.7	871.0 247.8 276.5 308.3 346.3 346.3 456.3 487.6 512.1 543.5 579.5 688.3 809.4 838.6 871.7	302.6 83.3 92.9 103.7 115.6 126.7 138.7 152.5 164.7 177.3 188.3 200.8 239.0 278.8 291.6 302.9	62.6 70.6 78.1 87.9 93.4 101.7 112.8 122.5 132.6 140.3 149.7 173.0 203.1 212.5 222.0	727.2 200.4 223.4 249.5 278.0 304.7 333.6 366.8 396.1 426.5 452.9 483.0 575.0 670.7 701.4 728.5	871.5 240.9 269.0 300.0 334.8 365.1 399.4 439.7 475.3 512.2 543.7 579.8 687.0 802.1 838.9 872.1

### LEGEND



### 30HXC COOLING CAPACITIES (cont) 60 Hz, SI

				1 12	CON	DENSER E	NTERING	WATER TE	MPERAT	URE (C)			
LCWT	UNIT		- 1	25				30				35	
LCWT (C)	UNIT SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)
4.0	076 086 096 106 116 126 136 146 161 171 171 206 246 261 271	253.3 279.3 315.5 350.4 380.9 412.5 457.2 489.2 516.5 547.2 584.8 697.8 819.9 848.6 882.7	48.2 54.2 60.1 67.5 71.7 77.8 87.4 94.6 99.2 105.5 113.6 130.3 152.7 168.4	10.9 12.0 13.5 15.0 16.3 17.7 19.6 21.0 22.2 23.5 25.1 29.9 35.2 36.4 37.9	12.8 14.2 16.0 17.8 19.3 20.9 23.2 24.9 26.2 27.8 29.8 35.3 41.5 43.0	234.3 258.8 292.4 323.9 352.8 382.6 425.0 454.2 500.1 532.8 569.1 676.3 795.2 824.6 858.2	53.2 59.8 66.5 74.8 79.7 86.7 96.5 104.7 115.5 122.4 131.4 150.8 178.2 186.1 195.3	10.1 11.1 12.5 13.9 15.1 16.4 18.2 19.5 21.5 22.9 24.4 29.0 34.1 35.4 36.8	12.2 13.6 15.3 17.0 18.4 20.0 22.2 23.8 26.2 27.9 29.8 35.2 41.5 44.9	219.0 242.8 274.3 304.3 330.6 359.0 400.3 428.3 494.5 526.6 563.8 663.7 782.7 814.2 848.5	58.9 66.3 73.8 83.6 88.9 96.8 107.0 116.7 135.8 142.9 153.4 175.8 208.6 217.4	9.4 10.4 11.8 13.1 14.2 15.4 17.2 18.4 21.2 22.6 24.2 28.5 33.6 34.9	11.8 13.1 14.8 16.5 17.9 19.4 23.2 26.8 28.5 30.5 35.7 42.2 43.9 45.8
5.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	264.0 291.1 328.3 365.2 396.9 429.7 476.5 509.7 534.4 565.5 604.6 721.6 847.2 877.0 912.2	48.6 54.7 60.6 67.9 72.2 78.5 88.0 95.3 98.8 105.2 113.2 130.2 152.7 159.8 167.9	11.3 12.5 14.1 15.7 17.0 18.4 20.5 21.9 22.9 24.3 26.0 31.0 36.4 37.6 39.2	13.3 14.7 16.6 18.5 20.0 21.7 24.1 25.8 27.0 28.6 30.6 36.3 42.6 44.2 46.0	244.2 269.7 304.8 337.9 368.2 399.0 442.8 472.9 517.4 549.8 587.8 699.3 822.6 852.1 886.5	53.7 60.4 67.1 75.5 80.4 87.3 97.2 105.4 115.3 121.8 131.1 150.2 177.7 185.4 194.8	10.5 11.6 13.1 14.5 15.8 17.1 19.0 20.3 22.2 23.6 25.2 30.0 35.3 36.6 38.1	12.7 14.1 15.8 17.6 19.1 20.7 23.0 24.6 27.0 28.6 30.6 36.2 42.6 44.2 46.1	227.2 251.8 284.5 315.4 342.8 372.1 415.1 443.9 508.5 541.4 579.4 683.0 804.8 836.9 872.0	59.3 66.7 74.3 84.1 89.4 97.3 107.6 117.3 135.2 142.1 152.8 174.9 207.6 216.1 226.9	9.8 10.8 12.2 13.5 14.7 16.0 17.8 19.1 21.8 23.2 24.9 29.3 34.5 35.9 37.4	12.2 13.6 15.3 17.0 18.4 20.0 22.3 23.9 27.4 29.1 31.2 36.5 43.1 44.8 46.8
6.0	076 086 096 116 116 126 136 146 161 171 186 206 246 261	274.8 303.0 342.1 380.0 413.0 447.2 495.8 530.4 551.9 584.0 624.0 745.8 874.5 904.8 940.9	49.3 55.3 61.5 68.6 73.0 79.1 89.2 96.2 98.9 105.3 113.3 130.4 153.0 160.3 168.5	11.8 13.0 14.7 16.3 17.7 19.2 21.8 23.7 25.1 26.8 32.0 37.6 38.9 40.4	13.8 15.3 17.2 19.1 20.7 22.4 24.9 26.7 27.8 29.4 31.4 37.4 43.8 45.4 47.3	254.6 281.0 317.5 352.4 383.9 415.9 461.3 493.0 535.3 568.2 607.0 723.5 850.6 880.4 915.5	54.2 60.9 67.7 76.2 81.0 88.0 98.0 106.3 115.1 121.7 130.8 150.2 177.1 184.9 194.2	10.9 12.1 13.6 15.1 16.5 17.9 19.8 21.2 23.0 24.4 26.1 31.1 36.5 37.8 39.3	13.2 14.6 16.4 18.3 19.8 21.5 23.8 25.5 27.7 29.4 31.4 37.3 43.8 45.4 47.3	235.6 261.1 295.0 326.9 355.4 385.7 430.3 460.1 522.7 556.5 595.3 703.4 827.4 860.1 895.9	59.7 67.2 74.8 86.5 90.5 98.2 108.1 117.8 134.7 141.7 152.0 174.7 207.0 215.0 225.6	10.1 11.2 12.7 14.0 15.3 16.6 18.5 19.8 22.5 23.9 25.6 30.2 35.5 36.9 38.5	12.6 14.0 15.8 17.6 19.0 20.6 22.9 24.6 28.0 29.7 31.8 37.4 44.1 45.8 47.8

LEGEND



### **30HXC COOLING CAPACITIES (cont)**

60 Hz, SI (cont)

					CON	DENSER E	NTERING	WATER TE	MPERAT	JRE (C)			
LCWT	UNIT			25	,			30				35	
(C)	UNIT SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)
7.0	076 086 096 106 116 126 136 146 161 171 171 186 206 246 261	285.8 315.0 355.7 395.0 429.4 465.0 515.5 551.5 569.5 602.5 643.4 767.9 902.1 933.1	50.0 56.1 62.3 69.4 73.8 80.0 90.3 97.2 99.1 105.7 113.6 130.7 153.1 160.9 168.8	12.3 13.5 15.3 17.0 18.5 20.0 22.2 23.7 24.5 25.9 27.7 33.0 38.8 40.1 41.7	14.3 15.8 17.8 19.8 21.5 23.3 25.8 27.7 28.5 30.2 32.3 38.3 45.0 46.7 48.6	265.5 292.7 330.9 367.3 400.0 433.2 480.7 514.0 553.9 587.0 627.0 748.2 879.4 910.0 946.0	54.7 61.5 68.3 76.8 81.5 88.5 98.8 107.1 114.9 121.7 130.5 150.1 176.5 184.8 193.8	11.4 12.6 14.2 15.8 17.2 18.6 20.7 22.1 23.8 25.2 26.9 32.2 37.8 39.1 40.7	13.7 15.1 17.0 18.9 20.5 22.2 24.7 26.5 28.5 30.2 32.3 38.3 45.0 46.7 48.6	244.7 270.7 305.9 338.8 369.2 400.9 446.1 477.0 537.3 572.7 611.5 725.6 852.2 884.3 920.3	60.1 67.6 75.2 86.9 90.3 98.3 108.7 120.3 136.0 141.5 151.2 174.6 205.5 214.3 224.4	10.5 11.6 13.1 14.6 15.9 17.2 20.5 23.1 24.6 26.3 31.2 36.6 38.0 39.6	13.0 14.4 16.2 18.1 19.6 21.3 23.6 25.4 28.7 30.4 32.5 38.4 45.1 46.8 48.8
8.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	297.0 327.4 369.8 410.5 446.2 482.7 535.7 573.0 587.4 620.0 663.1 788.8 927.6 961.0 999.8	50.5 56.9 63.0 70.2 74.5 80.8 91.4 98.2 99.2 106.1 113.8 130.7 152.7 161.1 168.9	12.8 14.1 15.9 17.7 19.2 20.8 23.0 24.6 25.3 26.7 28.5 33.9 39.9 41.3 43.0	14.8 16.4 18.5 20.5 22.2 24.0 26.8 28.6 29.3 31.0 33.1 39.2 46.1 47.9 49.9	276.7 305.0 344.8 382.6 416.7 451.2 500.7 535.4 572.5 606.4 647.6 773.3 908.8 940.1 977.1	55.1 62.0 68.8 77.3 82.0 89.4 107.7 114.5 121.7 130.1 150.4 175.7 184.3 193.0	11.9 13.1 14.8 16.5 17.9 19.4 21.5 23.0 24.6 26.1 27.8 33.3 39.1 40.4 42.0	14.2 15.7 17.6 19.6 21.3 23.1 25.6 27.4 29.3 31.1 33.2 39.4 46.3 48.0 49.9	254.9 281.6 318.5 352.2 384.6 417.2 464.2 495.5 553.3 589.7 629.4 748.2 880.2 912.6 949.1	60.7 68.2 75.9 85.5 90.9 98.9 109.6 120.4 133.5 141.4 150.7 174.3 205.0 214.3 224.0	39.6 11.0 12.1 13.7 15.1 16.5 17.9 20.0 21.3 23.8 25.4 27.1 32.2 37.8 39.2 40.8	13.5 14.9 16.8 18.7 20.3 22.0 24.5 26.3 29.3 31.2 33.3 39.3 46.3 48.1 50.0
9.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	307.1 339.3 382.7 425.6 461.5 499.3 554.9 593.6 604.3 636.5 681.5 810.0 950.1 950.1 950.1 950.1 950.1	50.9 57.5 63.6 70.8 74.9 81.2 99.0 99.0 105.9 113.6 130.3 151.7 160.4 168.1	13.2 14.6 16.5 18.3 19.9 21.5 23.9 25.5 26.0 27.4 29.3 34.8 40.9 42.3 44.1	15.3 16.9 19.0 21.2 22.9 24.8 27.6 29.6 30.0 31.7 33.9 40.1 47.0 48.8 50.9	288.1 317.5 358.9 398.2 433.7 469.5 521.4 557.2 591.4 625.9 668.5 798.6 937.9 970.2 1008.4	55.6 62.5 69.3 77.7 82.6 89.7 100.0 108.4 114.0 121.6 129.6 150.5 175.5 184.0 192.0	12.4 13.7 15.4 17.1 18.7 20.2 22.4 24.0 25.4 26.9 28.8 34.4 40.3 41.7 43.4	14.7 16.2 18.3 20.3 22.0 23.9 26.5 28.4 30.1 31.9 34.1 40.5 47.5 49.3 51.2	265.4 293.1 331.5 367.1 401.0 434.6 483.1 515.4 571.9 607.9 649.4 772.8 909.5 941.7 979.1	61.3 68.9 76.6 86.2 91.7 99.6 110.5 119.9 133.3 141.1 150.5 174.0 204.6 214.0 223.6	11.4 12.6 14.3 15.8 17.3 18.7 20.8 22.2 24.6 26.2 27.9 33.2 39.1 40.5 42.1	13.9 15.4 17.4 19.3 21.0 22.8 25.3 27.1 30.1 31.9 34.1 40.4 47.5 49.3 51.3

LEGEND



## 30HXC COOLING CAPACITIES (cont)

60 Hz, SI (cont)

					CON	DENSER E	NTERING	WATER TE	MPERAT	JRE (C)			
LCWT	UNIT		T	25				30				35	
LCWT (C)	SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Сар.	input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)
10.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	316.8 350.6 394.6 439.6 476.2 515.7 572.0 613.8 618.4 652.7 697.0 830.5 971.5 1005.3	51.2 57.9 63.9 71.1 75.1 81.5 92.6 99.6 98.4 105.5 113.0 129.5 150.3 159.3	13.6 15.1 17.0 18.9 20.5 22.2 24.6 26.4 26.6 28.1 30.0 35.7 41.8 43.3 45.0	15.7 17.4 19.6 21.8 23.5 25.5 28.4 30.5 30.6 32.4 34.6 41.0 47.9 49.7 51.8	299.5 330.2 373.1 414.1 450.9 488.1 541.9 579.2 610.2 645.5 689.2 824.3 966.9 999.8 1038.9	56.3 63.2 70.2 78.4 83.4 90.5 101.3 109.5 114.0 121.6 129.6 150.5 175.9 184.7 192.9	12.9 14.2 16.1 17.8 19.4 21.0 23.3 24.9 26.3 27.8 29.7 35.5 41.6 43.0	15.2 16.8 18.9 21.0 22.8 24.7 27.5 29.4 30.9 32.7 35.0 41.6 48.8 50.6 52.6	276.5 305.0 345.0 382.5 417.7 452.5 502.6 536.8 590.9 627.4 669.6 798.6 939.2 971.6	61.8 69.5 77.2 87.0 92.3 100.4 111.4 120.9 133.0 140.9 150.2 173.7 204.0 213.5 223.0	11.9 13.1 14.8 16.5 18.0 19.5 21.6 23.1 25.4 27.0 28.8 34.4 41.8	14.4 16.0 18.0 20.0 21.8 23.6 26.2 28.1 30.9 32.8 35.0 41.5 48.8 50.6
13.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	333.2 371.6 414.1 462.7 503.0 549.3 604.3 653.5 644.6 680.9 721.9 867.6 1005.8 1035.5 1085.7	51.5 58.5 64.3 71.3 75.3 81.8 93.2 99.9 96.7 104.1 111.6 128.6 148.1 157.4 164.3	14.4 16.0 17.8 19.9 21.7 23.7 26.0 28.2 27.8 29.3 31.1 37.4 43.3 44.6 46.8	16.4 18.4 20.4 22.8 24.7 27.0 29.8 32.2 31.7 33.5 42.6 49.3 51.0 53.4	318.8 351.4 396.1 441.4 482.5 523.1 580.0 626.2 644.8 683.3 722.7 868.0 1012.4 1040.5 1092.2	57.5 64.7 71.7 80.0 85.1 92.4 103.7 114.5 122.1 130.3 150.8 176.1 185.1 193.4	13.7 15.1 17.1 19.0 20.8 22.5 25.0 27.0 27.8 29.4 31.1 37.4 43.6 44.8 47.1	16.1 17.8 20.0 22.3 24.3 26.3 29.2 31.5 32.4 36.4 43.5 50.8 52.4	295.3 322.0 367.5 404.1 444.8 486.7 540.2 577.9 627.2 666.1 704.3 840.0 986.6 1014.1	62.7 70.4 78.3 87.9 93.3 101.6 113.0 122.5 140.3 149.7 173.0 203.0 212.8	43.5 12.7 13.9 15.8 17.4 19.2 21.0 23.3 24.9 27.0 28.7 30.3 36.2 42.5 43.7	52.6 15.3 16.7 19.0 21.0 23.0 25.1 27.9 29.9 32.4 36.5 43.3 50.8 52.4 55.0
16.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	330.1 368.2 414.4 461.4 503.5 549.5 604.9 653.8 644.7 680.8 725.8 861.0 1007.7 1041.2 1083.0	51.4 58.4 64.3 71.3 75.2 81.7 93.2 100.0 96.7 104.2 111.4 128.7 148.2 157.0 164.5	14.2 15.9 17.9 19.9 21.7 23.7 26.1 28.2 27.8 29.4 31.3 37.1 43.5 44.9 46.7	16.3 18.2 20.4 22.8 24.7 27.0 29.8 32.2 31.7 33.5 35.8 42.3 49.4 51.2 53.3	315.2 315.2 350.8 396.5 439.8 483.2 522.1 580.7 626.6 645.0 682.8 728.0 861.3 1014.1 1048.1	57.3 64.6 71.7 79.9 85.1 92.4 103.7 111.9 114.5 122.0 130.3 150.9 176.0 185.2 193.4	13.6 15.1 17.1 19.0 20.8 22.5 25.0 27.0 27.8 29.4 31.4 37.1 43.7 45.2 46.9	54.9 15.9 17.7 20.0 22.2 24.3 26.3 29.2 31.5 32.4 34.4 36.7 43.2 50.9 52.7 54.8	1065.4 291.7 325.2 363.2 408.0 449.3 485.7 540.9 576.7 627.4 665.4 703.9 837.8 988.3 1022.1 1061.6	222.0 62.6 70.5 78.1 88.0 93.5 101.6 113.0 122.4 132.5 140.3 149.7 173.1 202.9 212.6 222.1	45.9 12.6 14.0 15.7 17.6 19.4 20.9 23.3 24.9 27.1 28.7 30.4 36.1 42.6 44.1 45.8	55.0 15.1 16.9 18.8 21.2 23.2 25.1 27.9 29.9 32.5 34.4 36.5 43.2 50.9 52.7 54.8

LEGEND



## 30HXC COOLING CAPACITIES (cont)

50 Hz, ENGLISH

		_	9				ū	O HZ, E	NGLISH	v.c							
						, (		NSER EN	TERING	WATER	TEMPE	RATURE	(F)	10.71			
LCWT	UNIT			80.0				85.0				90.0				95.0	
(F)	SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)
40.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	70.1 78.5 89.4 98.1 107.8 117.7 130.4 138.1 147.7 156.0 167.2 199.4 234.4 242.1 252.3	55.9 62.7 69.4 74.6	167.8 187.9 214.1 234.8 258.1 281.7 312.2 330.6 353.6 373.3 400.1 477.4 561.2 579.6 603.9	199.6 224.4 255.0 280.0 306.8 335.1 371.8 394.5 421.5 445.3 477.8 566.4 666.1 689.2 719.2	67.1 75.5 86.1 93.8 103.6 113.1 125.5 132.3 145.0 153.5 164.6 196.1 230.4 238.2 248.3	66.7	160.6 180.7 206.2 224.6 247.9 270.7 300.5 316.8 347.1 367.5 394.1 469.4 551.7 570.2 594.5	194.3 219.3 249.8 272.6 299.8 327.6 363.7 384.4 421.1 445.7 478.4 566.3 666.0 689.4	64.3 72.5 82.9 90.1 99.2 108.5 120.8 127.7 143.2 151.9 162.9 193.5 226.7 235.0	70.6 78.0 84.0 92.4 102.3 109.8 123.7 130.3 140.3 161.6 190.1	153.8 173.6 198.4 215.8 237.5 259.7 289.3 305.6 342.8 363.7 390.1 463.3 542.8 562.5	189.5 214.5 244.5 266.8 292.4 320.1 356.2 377.4 423.6 448.9 481.8 569.0 667.2 691.9	62.0 70.0 80.0 87.4 96.1 105.0 117.0 124.0 142.5 151.2 162.3 191.9 225.5 233.9	66.3 74.9 83.3 89.6 98.4 108.5 117.0 135.5 142.1 153.1 176.1 208.1 216.2	148.4 167.6 191.6 209.3 230.0 251.3 280.1 296.8 341.1 361.9 388.5 459.4 539.7 560.0	186.3 211.0 240.6 263.8 288.7 315.7 351.2 373.4 429.7 454.9 488.7 574.8 676.1 701.7
42.0	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	73.4 82.0 93.4 102.7 112.7 122.9 136.3 144.6 153.4 161.9 173.5 206.9 243.4 251.3 261.8	49.2 56.3 63.0 69.9 75.0 82.2 92.0 98.7 103.9 110.2 118.8 136.6 159.9 167.4 176.1	175.9 196.5 223.7 246.0 269.9 294.5 326.4 346.5 367.4 387.8 415.5 495.7 583.1 602.0 627.1	208.0 233.0 264.7 291.5 318.7 348.0 386.3 410.6 459.4 492.7 584.6 687.2 710.9 741.7	70.3 78.9 90.1 98.3 108.4 118.3 131.3 138.7 150.6 159.3 170.7 203.6 239.2 247.1 257.4	52.1 59.8 67.2 74.2 80.0 87.8 97.6 104.4 113.2 119.6 128.8 148.1 174.3 181.9	168.3 189.0 215.7 235.6 259.7 283.5 314.4 332.2 360.8 381.6 408.8 487.7 573.1 591.9 616.7	719.8 202.3 228.0 259.5 283.9 311.9 340.7 378.1 400.2 434.5 492.7 584.3 686.8 710.5 741.3	245.2 67.2 75.7 86.5 93.9 103.9 113.5 126.2 133.1 148.0 157.1 168.2 200.3 235.1 243.3 253.6	208.3 55.0 63.2 71.2 78.4 84.8 93.2 103.1 110.4 123.0 129.9 139.5 160.9 189.4 197.3 207.2	587.1 161.0 181.4 207.3 225.0 248.8 271.9 302.3 318.9 354.4 376.4 403.0 479.9 563.2 582.8 607.5	723.3 197.0 222.6 253.7 276.1 304.2 332.7 369.7 391.0 434.7 461.2 494.0 585.1 687.0 711.7	244.2 64.6 73.0 83.4 90.9 99.9 109.2 121.8 128.9 146.9 155.9 167.3 198.0 232.6 241.2	227.5 58.2 66.9 75.5 84.4 90.6 99.5 109.2 117.5 134.8 141.6 152.3 207.3 207.3	584.6 154.7 174.8 199.8 217.7 239.4 261.6 291.9 308.8 352.0 373.4 400.7 474.3 557.3 577.8	733.6 192.8 218.5 249.1 272.9 298.7 326.6 363.3 385.6 440.1 465.9 500.3 509.0 692.9 718.5
44.0	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	76.8 85.6 97.4 107.4 117.6 128.2 151.2 159.1 167.8 179.8 214.5 252.2 260.3 271.2	49.9 56.6 63.5 70.5 75.5 82.9 92.5 99.5 103.5 110.3 118.4 136.7 159.9 167.5 175.8	184.2 205.1 233.6 257.5 281.9 307.4 341.0 362.5 381.4 402.1 431.0 514.1 604.5 624.0 650.0	216.5 241.8 274.8 303.2 330.9 361.2 401.1 427.1 448.6 473.7 507.8 602.9 708.4 732.7	73.6 82.5 94.0 103.0 113.3 123.7 137.2 145.2 176.9 211.2 248.3 256.4 267.0	52.6 60.2 67.6 74.8 80.4 88.3 98.3 105.3 105.3 113.0 119.4 128.5 147.5 173.7 181.5 190.8	176.5 197.7 225.3 246.9 271.7 296.6 328.8 348.2 375.0 396.0 424.2 506.4 595.2 614.5 640.0	210.7 236.8 269.3 295.6 324.0 354.0 392.8 416.6 448.4 473.6 507.7 602.4 708.3 732.7	70.4 79.2 90.4 98.4 108.8 118.7 131.9 139.0 153.5 162.5 174.2 207.6 244.0 252.1	55.6 63.7 71.8 79.2 85.5 93.9 104.0 111.2 122.9 129.5 139.3 160.5 189.1 197.1	168.7 189.8 216.7 235.9 260.7 284.6 316.2 333.3 367.9 389.6 417.6 497.7 584.9 604.4	742.8 204.9 231.3 263.6 287.5 316.4 345.8 384.0 405.7 448.0 508.4 602.4 708.2 732.9 764.8		226.1 58.6 67.3 75.9 86.5 90.4 99.4 109.8 119.1 136.4 140.9 151.4 174.8 205.6 213.8 224.8	603.0 161.3 182.1 208.2 226.3 249.4 272.8 304.1 321.2 364.1 385.4 413.1 490.9 575.1 595.9 621.7	750.9 199.6 226.0 257.7 282.6 308.5 337.7 375.8 398.9 453.1 477.4 512.0 605.2 709.5 735.6 768.5

### LEGEND



## 30HXC COOLING CAPACITIES (cont)

50 Hz, ENGLISH (cont)

					6)		CONDE	NSER EN	TERING	WATER	TEMPE	RATURE	(F)				
LCWT	UNIT			80.0				85.0				90.0		T		95.0	
(F)	SIZE 30HXC	Cap.	Input kW	Rate (Gpm)	Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm
45.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	78.5 87.4 99.5 109.8 120.1 131.0 145.3 154.6 161.9 170.7 182.9 218.3 256.6 264.8 275.8	56.8 64.0 70.8 75.8 83.1 93.2	188.3 209.5 238.6 268.0 314.0 348.4 370.7 388.3 409.4 438.6 523.5 615.2 635.0 661.3	220.9 246.3 280.0 309.2 337.1 367.9 408.8 435.5 455.5 480.9 515.3 612.1 719.1 743.8 775.5	75.3 84.2 96.0 105.3 115.8 126.4 140.2 148.6 159.3 168.2 215.1 252.9 261.1 271.9	52.8 60.3 67.8 75.1 80.5 98.6 105.6 112.8 119.2 128.3 147.6 173.2 181.1	180.7 202.0 230.2 252.6 277.8 303.1 336.2 356.3 382.1 403.4 432.0 515.8 606.4 626.0 651.9	215.0 241.2 274.3 301.4 330.1 360.7 400.2 424.9 455.4 480.8 515.4 611.8 719.1 743.8 775.7	72.0 80.9 92.4 100.7 111.3 121.4 134.8 142.3 156.4 165.5 177.3 211.5 248.5 256.6 267.4	55.8 64.0 72.1 79.6 85.7 94.2 104.4 111.7 122.8 129.4 139.2 160.4 188.8 196.8 206.7	172.6 194.1 221.6 241.5 266.8 291.2 323.4 341.1 375.0 396.8 425.2 507.1 595.9 615.4 641.2	209.0 235.7 268.6 293.3 322.7 352.6 391.4 413.8 454.9 481.1 515.8 611.7 718.9 743.6	68.8 77.6 88.7 96.3 106.4 116.4 129.6 136.8 154.3 163.4 175.0 208.3 244.1 252.7	67.5 76.2 85.7 90.7 99.8 110.3 120.4 136.2 140.7 151.0 174.6 205.3 213.5	164.9 186.1 212.6 230.9 255.2 279.0 310.7 327.9 369.9 391.9 419.5 585.4 606.0	203. 230. 262. 286. 314. 344. 382. 406. 458. 518. 613. 719. 745.4
46.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261 271	80.3 89.2 101.6 112.2 122.6 133.7 148.3 158.0 164.8 173.7 186.0 222.2 261.0 269.3 280.5	50.6 57.2 64.4 71.3 76.2 83.5 93.8 100.5 103.8 110.3 118.6 136.6 160.3 168.1	192.5 214.0 243.6 269.1 294.2 320.7 355.8 378.9 395.2 416.7 446.2 532.9 626.1 646.0 672.8	225.3 251.0 285.3 315.3 343.5 374.8 416.6 443.9 462.4 488.1 523.0 621.4 729.9 754.9 787.0	77.1 86.1 98.1 107.8 118.4 129.1 143.3 152.0 162.3 171.3 183.4 219.0 257.5 265.8 276.8	53.0 60.5 67.9 75.4 80.6 88.6 98.8 106.0 112.5 119.0 128.0 147.7 172.7 180.7 189.9	184.5 206.5 235.3 258.5 283.9 309.7 343.6 364.5 389.3 410.8 440.0 525.3 617.7 637.6 663.8	219.4 245.7 279.3 307.4 336.3 367.3 407.8 433.3 462.3 488.1 523.1 621.3 730.0 787.2	73.7 82.7 94.4 103.1 113.8 124.2 137.8 145.6 159.3 168.5 180.4 215.4 253.1 261.3 272.1	56.1 64.2 72.4 79.9 86.0 94.5 104.8 112.1 122.6 129.4 139.0 160.2 188.4 196.5 206.3	176.7 198.5 226.5 247.2 272.9 297.8 330.6 349.2 382.1 404.2 432.8 516.6 607.0 626.7	775.8 213.3 240.2 273.6 299.2 328.9 359.3 398.9 422.1 461.9 488.3 523.2 621.0 729.8 754.7	263.3 70.4 79.3 90.6 98.3 108.9 119.0 132.4 139.6 156.6 166.1 177.8 211.8 248.6 257.2	224.1 59.2 67.8 76.6 84.4 91.0 100.2 110.7 120.4 134.6 140.5 150.8 174.2 205.0 213.4	631.5 168.8 190.2 217.4 235.8 261.1 285.3 317.6 334.9 375.7 398.5 426.5 506.3 616.9	777.8 207.4 234.4 267.3 290.8 320.5 350.7 389.8 413.3 463.4 490.1 524.8 621.9 730.2 756.2 789.0
48.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	83.8 93.0 105.8 117.0 127.8 139.3 154.6 164.8 170.5 179.7 192.3 228.7 270.0 278.5	51.3 58.0 65.2 72.3 76.9 84.3 95.0 101.8 110.6 118.9 136.5 160.3 168.4 176.7	201.1 223.1 254.0 280.9 306.8 334.4 371.1 395.5 409.2 461.6 548.8 648.0 668.4 695.8	234.3 260.5 296.1 327.6 356.5 388.9 432.5 461.3 476.4 502.7 538.4 637.1 751.6 777.3	80.6 89.8 102.3 112.6 123.5 134.6 149.5 158.8 168.2 177.4 190.0 226.6 226.6 2275.2 286.5	53.7 60.8 68.3 76.0 81.1 89.3 99.3 106.8 112.1 119.1 127.5 147.7 172.7 180.7 189.3	193.4 215.4 245.5 270.3 296.3 323.1 358.7 381.1 403.7 425.7 455.9 544.3 639.9 660.4	228.2 254.8 289.8 319.6 348.9 381.0 423.2 450.4 476.4 502.9 538.6 640.2 752.0 777.6	77.2 86.4 98.5 107.9 118.9 129.7 144.0 152.4 165.3 174.6 186.9 223.3 262.4 270.9	56.6 64.7 72.8 80.6 86.4 95.1 105.6 113.1 122.3 129.0 138.6 159.6 187.7 196.1 205.8	629.8 650.0	787.0 222.0 249.4 283.8 311.3 341.5 373.1 414.2 439.1 476.3 502.8 538.7 639.7 752.0 639.7 775.6 810.6		59.8 68.4 77.2 85.2 91.7 100.9 111.7 119.4 133.2 140.1 150.5 173.8 204.5 213.1 223.6	642.8 176.7 198.8 227.2 247.1 273.4 298.6 331.9 349.7 389.1 412.2 441.6 526.5 618.7 639.2	789.0 215.7 243.4 277.5 302.6 333.2 364.3 404.7 427.5 475.9 503.5 503.5 639.8 752.1 778.2

LEGEND



## 30HXC COOLING CAPACITIES (cont)

50 Hz, ENGLISH (cont)

				00.0		(		ISER EN	TERING	WATER	TEMPE	RATURE	(F)			-	
LCWT	UNIT		1	0.08				85.0				90.0			- 1	95.0	
(F)	SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cond Flow Rate (Gpm)
50.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	87.2 96.7 110.1 121.9 132.8 144.6 161.1 171.7 176.3 184.9 198.6 235.3 277.5 286.6 298.9	51.9 58.6 65.8 73.0 77.4 84.9 95.9 102.9 104.0 110.6 119.0 136.1 159.4 167.9 176.3	209.3 232.2 264.4 292.8 318.9 347.2 386.7 412.3 443.3 444.0 476.9 564.9 666.4 688.1 717.6	242.8 270.0 306.8 339.9 368.9 402.0 448.6 478.6 490.3 515.3 553.6 652.8 769.3 796.5 831.3	84.1 93.5 106.5 117.6 128.7 140.3 155.8 165.8 174.1 183.5 196.4 234.8 275.8 284.5 296.1	54.5 61.6 69.3 76.9 82.0 89.9 100.7 108.0 112.3 119.1 127.9 147.7 173.2 181.5 190.2	202.0 224.6 255.8 282.3 309.0 336.9 374.0 398.0 418.0 440.7 471.7 563.7 662.2 683.1 711.0	237.3 264.4 300.6 332.0 362.1 395.1 439.2 467.9 490.7 517.8 554.4 659.3 774.4 800.6 834.1	80.7 90.1 102.7 112.8 124.1 135.3 150.2 159.3 171.4 180.9 193.6 231.3 272.0 280.6 292.1	57.1 65.1 73.1 81.2 86.7 95.4 106.2 113.9 122.0 128.7 138.2 159.8 186.8 195.4	193.8 216.4 246.7 270.9 297.9 325.0 360.8 382.5 411.5 434.3 464.9 555.4 653.0 673.8 701.2	230.9 258.6 294.1 323.6 354.3 387.0 429.7 517.9 554.6 659.3 774.5 800.8 834.4	77.1 86.5 98.8 107.8 119.1 130.0 144.4 152.4 168.2 177.9 190.4 227.4 267.2 275.8 287.1	60.3 69.0 77.8 86.0 92.4 101.7 112.6 120.5 132.9 140.0 150.2 173.5 203.9 212.6 222.9	185.0 207.7 237.2 258.8 286.0 312.2 346.8 366.0 403.7 427.1 457.2 546.0 641.5 662.2 689.3	224.3 252.6 287.9 314.8 346.2 378.4 420.1 444.5 554.9 659.1 774.4 800.7 834.5
55.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	91.0 102.0 115.9 128.8 140.9 154.7 170.6 184.1 184.4 192.8 206.4 244.4 287.9 297.1 309.7	52.3 59.3 66.5 73.7 77.8 85.5 97.0 104.0 102.8 110.0 118.0 135.0 157.1 166.1 174.4	218.8 245.2 278.6 309.5 338.6 371.9 410.1 442.4 443.1 463.5 496.0 587.4 692.1 714.2 744.4	252.4 283.2 321.2 356.8 388.5 426.7 472.3 509.1 509.1 534.0 793.0 820.8 856.3	88.8 99.4 113.2 125.2 137.9 150.0 167.0 179.7 184.4 194.2 206.3 245.0 289.3 310.9	55.5 62.8 70.5 78.3 83.4 91.5 102.7 110.5 112.6 119.6 128.3 147.8 172.9 181.8 190.4	213.4 239.0 272.2 301.0 331.6 360.5 401.3 431.9 443.2 466.7 495.9 588.8 695.3 718.2 747.3	249.2 279.4 317.6 351.4 385.3 419.4 467.5 503.1 515.8 543.7 578.5 684.2 806.8 835.3 870.1	85.3 95.9 109.3 120.5 133.1 144.8 161.3 173.2 182.0 192.1 203.8 242.9 286.2 295.2 307.2	58.0 65.8 74.1 82.2 87.9 96.4 107.7 115.8 121.5 128.7 137.7 159.7 187.1 195.7	205.0 230.5 262.8 289.5 320.0 348.1 387.6 416.3 437.5 461.7 489.9 583.8 688.0 709.6	242.6 273.1 310.7 342.7 376.9 410.5 457.3 491.3 516.1 545.0 579.0 687.2 809.1 836.3	81.6 92.2 105.2 114.4 128.1 139.4 155.3 164.3 179.0 187.6 200.6 239.1 281.9 290.8	61.1 69.8 78.5 87.0 93.2 102.5 113.8 122.1 132.4 139.5 149.6 172.8 202.8 211.7	196.1 221.7 252.9 275.0 307.9 335.1 373.3 394.8 430.1 450.8 482.2 574.6 677.5 698.9	235.7 267.0 303.9 331.4 368.5 401.7 447.2 474.1 516.1 541.4 579.3 686.9 809.3 836.5 871.5
60.0	076 086 096 106 116 126 136 146 161 171 186 206 246 246 261 271	91.1 102.1 116.0 128.9 141.0 153.5 170.8 184.2 183.3 193.0 206.5 244.5 288.1 297.3 309.9	52.3 59.3 66.5 73.7 77.8 85.5 97.0 104.0 102.9 110.0 118.0 134.9 157.1 166.1 174.3	219.2 245.6 279.1 310.1 339.2 369.2 410.9 443.2 440.9 464.2 496.8 588.2 693.1 745.5	252.6 283.4 321.5 357.1 388.9 423.8 472.8 509.6 506.6 534.4 572.0 674.3 793.4 821.2	88.9 99.5 113.4 125.4 138.1 150.2 167.2 177.9 182.9 206.5 245.1 289.5 299.0	55.5 62.8 70.6 78.3 83.4 91.5 102.8 110.2 112.6 119.7 128.3 147.8 172.9 181.7 190.5	213.9 239.5 272.7 301.5 332.3 361.2 402.1 428.0 440.1 464.7 496.7 589.7 696.3 719.3 748.6	249.4 279.7 317.9 351.8 385.7 419.9 468.0 498.6 512.3 541.4 579.0 684.5 807.3 835.8	85.4 96.0 108.2 119.7 131.6 145.0 161.5 171.5 180.5 190.8 204.0 243.1 286.5 295.5	58.0 65.8 73.8 82.0 96.5 107.8 115.4 121.3 128.6 137.7 159.7 187.1 195.7 204.9	738.4 205.4 231.0 260.2 287.9 316.7 348.8 388.4 412.4 434.3 459.0 490.8 584.7 689.1 710.8 739.7	871.0 242.8 273.3 307.7 340.7 340.7 410.9 457.8 486.8 579.5 687.6 809.7 836.9 871.7	302.6 81.7 92.3 104.1 114.6 126.6 139.6 153.5 164.5 177.4 187.8 200.8 239.2 279.0 291.1 302.9	222.0 61.1 69.8 78.4 87.0 93.1 102.6 113.6 122.5 139.5 149.6 172.7 203.1 211.7 222.0	727.2 196.5 222.1 250.4 275.6 304.6 335.8 369.4 395.6 426.8 451.7 483.0 575.5 671.1 700.1 728.5	871.5 236.0 267.3 301.1 331.8 364.8 402.1 442.8 474.6 512.5 541.9 579.8 687.3 802.4 837.1 872.1

### LEGEND



## 30HXC COOLING CAPACITIES (cont)

50 Hz, SI

	T						112, 31						
120				25	COI	DENSER	ENTERING	WATER TE	EMPERATU	RE (C)			
LCWT	UNIT	-	T		T .			30				35	
(C)	SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)
4.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	248.2 277.4 315.8 347.2 380.9 415.6 460.4 488.6 516.9 545.6 584.8 697.4 820.3 847.1 882.6	47.0 53.6 60.2 66.7 71.5 78.5 88.0 94.3 99.1 105.1 113.6 130.3 152.7 159.8 168.4	10.6 11.9 13.5 14.9 16.3 17.8 19.7 21.0 22.2 23.4 25.1 29.9 35.2 36.3 37.9	12.6 14.1 16.0 17.6 19.3 21.1 23.4 24.8 26.2 27.7 29.8 35.3 41.5 42.9	229.6 258.6 295.2 320.9 354.4 387.2 430.2 453.8 500.4 569.1 677.5 795.6 823.2 858.2	52.0 59.6 67.2 74.0 80.0 88.0 97.6 104.4 115.4 122.0 131.4 151.0 178.1 185.5	9.8 11.1 12.7 13.8 15.2 16.6 18.5 19.5 21.5 22.8 24.4 29.1 34.1 35.3 36.8	12.0 13.5 15.4 16.8 18.5 20.2 22.5 23.8 26.2 27.8 29.8 35.3 41.5 43.0 44.9	214.4 242.2 276.8 302.6 363.4 404.8 429.2 494.8 525.1 563.8 666.5 783.2 812.7	57.7 66.0 74.6 83.2 89.3 98.2 108.2 116.8 135.7 142.2 153.3 176.4 208.5 216.6	9.2 10.4 11.9 13.0 14.3 15.6 17.4 18.4 21.2 22.5 24.2 28.6 33.9	11.6 13.1 15.0 16.4 18.0 19.6 21.8 23.2 26.8 28.4 30.5 35.9 42.2 43.8
5.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261 271	258.7 288.4 328.3 361.8 396.1 432.0 479.0 509.1 534.8 604.6 720.7 847.7 875.4 912.2	47.4 54.0 60.5 67.2 72.0 79.0 88.4 95.0 98.7 105.3 113.2 130.4 152.6 159.8 167.9	11.1 12.4 14.1 15.5 17.0 18.5 20.6 21.9 23.0 24.2 26.0 30.9 36.4 37.6 39.2	13.1 14.6 16.6 18.3 20.0 21.8 24.2 25.7 27.0 28.5 30.6 36.3 42.7 44.1 46.0	239.3 269.2 307.4 334.8 369.6 403.4 447.9 472.3 517.8 548.2 587.8 700.2 823.0 850.5 886.5	59.3 52.4 60.2 67.8 74.7 80.6 88.6 98.4 105.1 115.3 121.6 131.1 150.7 177.6 185.2 194.8	10.3 11.6 13.2 14.4 15.9 17.3 19.2 20.3 22.2 23.5 25.2 30.1 35.3 36.5 38.1	12.4 14.0 16.0 17.4 19.2 21.0 23.3 24.6 27.0 28.5 30.6 36.3 42.6 44.1 46.1	848.5 222.5 251.4 287.3 313.5 344.7 376.6 419.9 444.6 508.8 539.8 579.4 685.5 805.3 835.4 872.0	58.0 66.6 75.2 83.5 89.8 98.6 108.8 117.3 135.1 141.9 152.8 175.8 207.5 215.7 226.9	36.4 9.6 10.8 12.3 13.5 14.8 16.2 18.0 19.1 21.8 23.2 24.9 29.4 34.6 35.9 37.4	45.8 11.9 13.5 15.4 16.9 18.5 20.2 22.5 23.9 27.4 29.0 31.2 36.7 43.1 44.8 46.8
6.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	269.3 299.6 341.0 376.5 411.6 448.7 497.6 529.8 552.3 582.4 624.0 744.6 874.9 903.2 940.9	48.2 54.5 61.2 67.8 72.6 79.5 89.4 95.9 98.8 105.3 113.3 152.9 160.3 168.5	11.6 12.9 14.6 16.2 17.7 19.3 21.4 22.8 23.7 25.0 26.8 32.0 37.6 38.8 40.4	13.5 15.1- 17.2 18.9 20.7 22.5 25.0 26.7 27.8 29.3 31.4 37.3 43.8 45.4 47.3	249.5 280.2 319.8 349.2 385.1 420.2 466.2 492.5 535.7 566.6 607.0 724.2 851.0 878.8 915.5	52.9 60.7 68.2 75.3 81.2 89.1 99.0 105.9 115.0 121.5 130.8 150.4 177.1 184.8 194.2	10.7 12.0 13.7 15.0 16.5 18.0 20.0 21.2 23.0 24.3 26.1 31.1 36.6 37.7 39.3	12.9 14.5 16.5 18.1 19.9 21.7 24.1 25.5 27.7 29.3 31.4 37.3 43.8 45.3 47.3	230.8 230.8 260.7 298.1 324.5 357.0 390.0 435.5 460.4 523.3 554.9 595.3 705.6 828.3 858.5	58.4 67.1 75.7 85.9 90.8 99.4 109.5 117.7 134.7 141.3 152.0 175.1 207.0 214.6	9,9 11,2 12,8 13,9 15,3 16,8 18,7 19,8 22,5 23,8 25,6 30,3 35,6 36,9	12.3 14.0 15.9 17.5 19.1 20.8 23.2 24.6 28.0 29.7 31.8 37.5 44.1 45.7

LEGEND



## 30HXC COOLING CAPACITIES (cont)

50 Hz, SI (cont)

					COI	NDENSER I	ENTERING	WATER TE	MPERATU	RE (C)		2	
LCWT	UNIT			25				30		1		35	
LCWT (C)	SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)
7.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	280.1 311.0 354.0 391.5 427.5 465.9 516.8 550.9 600.8 643.4 766.1 902.6 931.4	48.8 55.2 62.0 68.7 73.3 80.3 90.4 96.9 99.1 105.5 113.6 130.3 153.0 160.7 168.8	12.0 13.4 15.2 16.8 18.4 20.0 22.2 23.7 24.5 25.8 27.7 32.9 38.8 40.0 41.7	14.0 15.6 17.7 19.6 21.4 23.3 25.9 27.6 28.5 30.1 32.3 38.2 45.0 46.6 48.6	260.2 291.5 332.3 364.0 400.7 437.3 485.1 513.4 554.3 585.3 627.0 748.5 879.8 908.4 946.0	53.4 61.0 68.6 75.9 81.6 89.6 99.7 106.7 114.8 121.3 130.5 150.0 176.5 184.4	11.2 12.5 14.3 15.6 17.2 18.8 20.8 22.1 23.8 25.2 26.9 32.2 37.8 39.0	13.4 15.0 17.1 18.8 20.6 22.5 24.9 26.4 28.5 30.1 32.3 38.3 45.1 46.6	239.7 270.6 309.1 336.0 370.8 405.5 451.7 477.0 539.3 571.0 611.5 727.6 852.6	58.8 67.4 76.1 86.1 90.6 99.7 110.1 120.1 136.4 140.8 151.2 174.7 205.4 213.6	10.3 11.6 13.3 14.4 15.9 17.4 19.4 20.5 23.2 24.5 26.3 31.3 36.6 37.9	12.7 14.4 16.4 18.0 19.7 21.5 23.9 25.4 28.8 30.3 32.5 38.5 45.1 46.7
8.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261 271	291.0 322.8 367.4 406.7 443.7 483.1 536.5 572.3 587.9 618.0 663.1 786.3 928.1 959.2 999.8	49.3 55.7 62.6 69.4 73.8 80.9 91.4 97.9 99.2 105.6 113.8 130.1 152.6 160.7 168.9	12.5 13.9 15.8 17.5 19.1 20.8 23.1 24.6 25.3 26.6 25.3 33.8 39.9 41.2 43.0	14.5 16.1 18.3 20.3 22.1 24.1 26.8 29.3 30.9 33.1 39.1 47.8 49.9	271.2 303.0 345.3 379.1 416.7 454.6 504.3 534.8 572.9 604.7 647.6 773.2 909.2 938.4 977.1	53.7 61.3 68.9 76.4 81.8 89.9 100.1 107.4 114.4 121.0 130.1 150.0 175.6 183.7 193.0	40.7 11.7 13.0 14.8 16.3 17.9 19.5 21.7 23.0 24.6 26.0 27.8 33.2 39.1 40.4 42.0	48.6 13.9 15.5 17.7 19.4 21.3 23.2 25.8 27.4 29.3 31.0 33.2 39.4 46.3 47.9 49.9	920.3 249.8 281.3 321.5 348.9 386.3 422.1 469.7 495.0 553.8 588.0 629.4 750.0 880.7 910.9 949.1	59.3 67.9 76.7 84.6 91.2 100.3 110.9 120.1 133.5 140.4 150.7 174.1 205.0 213.4 224.0	39.6 10.7 12.1 13.8 15.0 16.6 18.2 20.2 21.3 23.8 25.3 27.1 32.2 37.9 39.2 40.8	48.8 13.2 14.9 17.0 18.5 20.4 22.3 24.8 26.2 29.3 31.1 33.3 39.4 46.3 47.9 50.0
9.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	300.8 334.1 379.9 421.6 458.4 499.1 555.4 592.8 604.7 634.5 681.5 806.9 950.6 950.6 950.6 1023.9	49.7 56.2 63.1 70.0 74.1 81.2 92.1 98.7 99.0 105.5 113.6 129.6 151.6 160.0 168.1	12.9 14.4 16.3 18.1 19.7 21.5 23.9 25.5 26.0 27.3 29.3 34.7 40.9 42.2 44.1	15.0 16.7 18.9 21.0 22.7 24.8 27.6 29.5 30.0 31.6 33.9 40.0 47.1 48.7 50.9	282.4 314.7 358.6 394.6 432.9 472.1 556.6 591.8 624.1 668.5 798.1 938.3 938.3 1008.4	54.2 61.6 69.1 76.9 82.1 90.4 100.5 108.0 114.0 121.0 129.5 150.1 175.4 183.3 192.0	12.1 13.5 15.4 17.0 18.6 20.3 22.5 23.9 25.5 26.9 28.8 34.3 40.4 41.7 43.4	14.4 16.1 18.3 20.1 22.0 24.0 26.7 28.4 30.1 31.8 34.1 40.5 47.5 47.5	260.2 292.6 334.3 363.7 402.5 439.5 514.8 572.3 606.1 649.4 774.3 909.9 940.0 979.1	59.8 68.5 77.3 85.3 91.8 101.0 111.8 119.5 133.2 140.1 150.5 173.8 204.5 213.0 223.6	11.2 12.6 14.4 15.6 17.3 18.9 21.0 22.1 24.6 26.1 27.9 33.3 39.1 40.4 42.1	13.7 15.4 17.6 19.1 23.1 25.6 27.1 30.1 31.8 34.1 40.5 47.6 49.2 51.3

### LEGEND



### **30HXC COOLING CAPACITIES (cont)**

50 Hz, SI (cont)

			44		COI	DENSER	ENTERING	WATER TE	MPERATU	RE (C)			
LCWT	UNIT			25				30				35	
(C)	SIZE 30HXC	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cond Flow Rate (L/s)
10.0	076 086 096 106 116 126 136 146 161 171 186 206 246 261	310.3 344.9 391.7 435.4 472.8 515.3 572.4 613.0 618.9 650.8 697.0 826.8 972.0 1003.4 1046.2	50.0 56.5 63.4 70.3 74.2 81.4 92.5 99.3 98.3 105.2 113.0 128.8 150.3 158.8 166.9	13.4 14.8 16.9 18.7 20.4 22.2 24.6 26.4 26.6 28.0 30.0 35.6 41.8 43.2 45.0	15.4 17.1 19.4 21.6 23.4 25.5 28.4 30.4 30.6 32.3 34.6 40.8 47.9 49.6 51.8	293.6 326.6 372.1 410.3 449.4 489.9 544.0 578.5 610.7 643.7 689.2 823.3 967.4 998.0 1038.9	55.0 62.1 70.0 77.6 82.8 90.9 101.6 109.1 114.0 121.0 129.6 150.0 175.8 184.1 192.8	12.6 14.1 16.0 17.7 19.3 21.1 23.4 24.9 26.3 27.7 29.7 35.4 41.6 43.0 44.7	14.9 16.6 18.9 20.8 22.7 24.8 27.6 29.4 30.9 32.6 35.0 41.6 48.8 50.5 52.6	271.0 304.2 347.5 379.0 418.9 457.2 507.9 536.1 591.4 625.6 669.6 699.7 939.6 969.9	60.3 69.0 77.8 86.0 92.4 101.7 112.6 120.5 133.0 140.0 150.2 173.5 203.9 212.6 223.0	11.7 13.1 15.0 16.3 18.0 19.7 21.9 23.1 25.5 26.9 28.8 34.4 40.4 41.7 43.5	14.1 15.9 18.1 19.8 21.8 23.9 26.5 28.0 30.9 32.7 35.0 41.5 48.8 50.5 52.6
13.0	076 086 096 106 116 126 136 146 161 171 186 206 261 271	326.3 362.7 411.1 458.4 499.4 548.8 604.8 652.6 645.1 678.9 721.9 863.2 1006.3 1033.5 1085.7	50.2 57.0 63.8 70.5 74.4 81.7 93.1 99.6 96.6 103.8 111.6 127.9 148.0 157.0 164.3	14.1 15.6 17.7 19.7 21.5 23.6 26.1 28.1 27.8 29.3 31.1 37.2 43.4 44.5 46.8	16.1 17.9 20.3 22.6 24.5 26.9 29.8 32.1 31.7 33.4 35.6 42.3 49.3 50.9 53.4	312.5 346.7 394.1 437.4 479.8 523.5 580.8 619.9 645.3 681.4 722.7 866.1 1012.9 1044.3 1092.2	56.2 63.4 71.2 79.1 84.3 92.5 103.6 111.2 114.4 121.6 130.3 150.3 176.0 184.6 193.4	13.5 14.9 17.0 18.8 20.7 22.6 25.0 26.7 27.8 29.4 31.1 37.3 43.6 45.0 47.1	15.7 17.5 19.9 22.1 24.1 26.3 29.2 31.2 32.5 34.3 36.4 43.4 50.8 52.5 54.9	289.5 320.4 368.7 400.4 445.0 490.1 543.8 577.2 627.7 664.2 704.3 840.7 987.1 1012.3 1065.4	69.7 78.5 86.9 93.1 102.6 113.7 122.1 132.4 139.5 149.7 172.7 202.9 212.0 222.0	43.5 12.5 13.8 15.9 17.3 19.2 21.1 23.4 24.9 27.0 28.6 30.3 36.2 42.5 43.6 45.9	52.6 15.0 16.7 19.1 20.8 23.0 25.3 28.1 29.9 32.5 34.3 36.5 43.3 50.8 52.3
16.0	076 086 096 106 116 126 136 146 161 171 186 206 246 271 271	323.3 362.2 411.5 457.1 500.0 549.0 605.3 652.9 645.2 678.9 725.8 856.8 1008.3 1039.3 1083.0 1034.8 1087.7	50.2 57.0 63.8 70.5 74.3 81.6 93.1 99.6 96.7 103.9 111.4 128.0 148.1 156.7 164.5 147.1	13.9 15.6 17.7 19.7 21.6 23.7 26.1 28.2 27.8 27.8 31.3 36.9 44.8 46.7 44.8	16.0 17.9 20.3 22.5 24.5 26.9 29.8 32.1 31.7 33.4 49.4 51.1 53.3 90.9	308.9 346.3 394.4 435.8 480.5 581.7 625.8 645.5 680.8 728.0 1014.6 1046.2 1088.6 1041.5	56.0 63.4 71.2 79.1 84.3 92.5 103.7 111.5 114.4 121.5 130.3 175.9 184.6 193.4 173.3	13.3 14.9 17.0 18.8 20.7 22.5 25.1 27.0 27.8 29.4 31.4 37.1 43.8 45.1 46.9 44.9	15.6 17.5 19.9 22.0 24.1 26.3 29.3 31.5 32.5 32.5 34.3 36.7 43.2 50.9 52.6 54.8 93.4	286.0 323.5 369.0 404.4 449.3 489.0 544.7 576.0 627.9 663.6 703.9 838.5 988.9 1020.2 1061.6 1026.5	61.0 69.8 78.5 87.0 93.2 102.5 113.8 122.0 132.4 139.5 149.7 172.8 202.8 211.8 222.1 198.7	12.3 14.0 15.9 17.4 19.4 21.1 23.5 24.8 27.1 28.6 30.4 36.2 42.6 44.0 45.8 44.2 46.5	14.8 16.8 19.1 21.0 23.2 25.3 28.1 29.8 32.5 34.3 36.5 43.2 50.9 52.6 54.8 94.2

LEGEND



### **30HXA Ratings**

All performance data is based on:

- 1. Cooler water temperature rise of 10° F (5.6° C).
- Cooler fouling factor of 0.00010 ft<sup>2</sup> hr F/Btu (0.000018 m<sup>2</sup> k/W).
- 3. 10° F (5.6° C) subcooling.
- 4. Refrigerant 134a.

5. Combining 30HXA units with remote condensers that have subcooling greater than the 10° F (5.6° C) subcooling on which the ratings are based will increase system capacity. Combining 30HXA units with remote condensers that have less than the 10° F (5.6° C) subcooling on which the ratings are based will decrease system capacity. To adjust capacity, multiply capacity ratings by 0.96; then adjust this result upward by 0.4% for each degree F (0.7% for each degree C) of available subcooling.

### **COMBINATION RATINGS**

60 Hz, ENGLISH

	SCHOOL STATE	100	ж					CC	ONDENS	ER ENT	ERING A	IR TEMP	ERATU	RE (F)				
LCWT	UNIT	AIR-CO CONDE	OLED		85	Louis	-	95			105			115			125	
(F) 	ЗОНХА	Unit	(Qty)	Сар.	Input kW	Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)
40	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	084 084 074 (1) and 074 (1) and 074 (1) and 074 084 084 084 084 084 (2) and 094 094	054 (1) (2) (2) (2) (2) (2)	67.4 73.9 82.7 94.9 101.8 112.2 121.9 135.5 140.6 150.8 163.8 192.2 223.3 234.1 246.1	69.3 78.6 89.2 99.0 107.4 115.2 130.2 137.8 145.8 161.0 182.4 189.9 225.8 242.2 260.7	161.4 177.0 198.1 227.2 243.7 268.5 291.8 324.4 336.5 361.0 392.1 460.2 534.6 560.3 589.2	62.4 68.3 76.5 88.0 94.3 104.2 113.0 126.2 134.3 143.9 154.8 184.9 214.7 224.3 234.6	73.5 83.3 94.3 104.8 113.7 122.1 137.5 145.5 159.4 175.5 198.6 208.0 246.4 264.2 283.8	149.3 163.5 183.1 210.6 225.7 249.5 270.6 302.1 321.5 344.5 370.5 442.5 514.1 536.8 561.6	56.9 62.3 69.7 80.5 86.5 95.7 103.8 116.2 127.5 136.7 147.7 176.0 203.0 212.4 223.0	77.8 88.6 101.0 111.4 121.0 129.8 146.7 154.2 174.4 191.8 216.5 227.7 269.1 288.2 309.0	136.3 149.1 166.9 192.8 207.0 229.1 248.4 278.1 305.2 327.2 353.6 421.4 485.8 508.6 533.8	51.3 56.4 63.4 73.2 78.7 87.2 94.9 106.2 121.0 129.6 139.9 166.5 192.9 201.9 211.8	83.7 95.6 108.7 120.0 130.7 140.1 158.2 166.2 192.3 212.2 239.9 250.7 295.9 317.8 341.6	122.8 134.9 151.7 175.3 188.3 208.9 227.1 254.3 289.6 310.2 334.9 398.6 461.9 483.3	46.7 51.0 57.4 66.6 71.4 79.2 86.3 96.9 109.8 120.4 124.6 157.3 182.1	91.3 103.4 116.9 129.9 140.7 151.5 170.5 179.5 213.7 236.7 266.6 278.9 329.4 353.4	111.7 122.2 137.5 159.5 170.8 189.7 206.6 232.0 262.9 288.3 298.3 376.5 436.0 456.3
42	126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 (2) and 094 094	(1) (1) (1) (1) (2) (2) (2) (2) (2) (2) (2) (2) (2) (2	70.1 76.7 86.0 98.5 105.6 116.4 126.6 140.7 145.2 156.1 169.3 198.6 230.5 241.8	70.8 80.3 91.2 101.1 109.6 117.5 132.8 140.5 148.3 163.3 185.6 192.8 229.4 245.8 265.1	167.8 183.8 206.0 236.0 253.1 278.9 303.3 337.1 347.7 373.9 405.6 475.7 552.3 579.2 608.7	65.0 71.0 79.5 91.6 98.2 108.5 117.6 131.4 139.0 149.0 160.4 191.3 222.3 232.8 243.4	75.1 85.1 96.5 106.9 115.9 124.6 140.2 148.4 162.1 178.4 202.1 211.1 250.3 268.0 288.2	155.8 170.2 190.4 219.5 235.4 259.9 281.6 314.7 333.0 357.0 384.2 458.3 532.5 557.6 583.1	59.4 64.9 72.6 84.0 90.1 99.7 108.0 121.0 132.1 141.4 152.9 182.7 210.4 219.9 230.6	79.4 90.4 102.8 113.3 123.0 132.0 149.2 156.7 177.0 194.8 219.7 231.1 273.4 292.9 314.3	142.3 155.5 174.0 201.2 215.8 238.8 258.7 289.9 316.4 338.8 366.3 437.7 504.1 526.7	53.6 58.7 66.0 76.4 82.0 90.8 98.6 110.5 125.2 134.2 144.9 172.5 199.8 209.0	85.0 97.0 110.4 121.7 132.4 142.1 160.6 168.5 195.0 214.7 243.4 254.3 299.4 321.6	507.1 128.5 140.6 158.0 183.0 196.4 217.5 236.3 264.7 299.8 321.4 347.1 413.2 478.6 500.6	199.9 48.6 53.1 59.0 69.4 74.3 82.6 88.8 101.0 111.6 122.5 124.7 162.9 188.6 197.4	92.3 104.7 118.2 131.5 142.7 153.4 172.2 181.8 214.4 237.7 266.4 281.3 332.7 357.2	478.5 116.5 127.3 141.3 166.2 178.1 197.9 212.7 241.8 267.3 293.4 298.8 390.2 451.9 472.8
44	086 096 116 126 136 146 161 171 186 206 246 261	084 084 074 (1) and ( 074 (1) and ( 074 074 084 084 084 084 (2) and ( 094 094	(1) (1) (1) (1) (2) (2) (2) (2) (2) (2) (2) (2) (2) (2	72.9 79.6 89.2 102.3 109.7 120.9 131.4 146.0 149.8 161.0 174.7 205.1 237.9 249.6	72.5 82.2 93.4 103.3 111.9 119.9 135.8 150.9 166.1 189.2 195.6 233.0 249.7 269.4	174.7 190.9 213.8 245.3 262.9 289.9 314.9 350.0 359.2 386.0 418.9 491.7 570.4 598.3	67.5 73.9 82.6 95.2 102.1 112.8 122.1 136.6 143.8 154.5 166.3 197.9 229.9 241.0	76.8 86.9 98.6 109.2 118.4 127.1 143.3 151.3 164.8 181.5 205.8 214.1 254.3 272.5 292.9	161.9 177.1 198.0 228.3 244.8 270.4 292.8 327.5 344.8 370.3 398.6 474.5 551.1 577.7	61.9 67.6 75.7 87.4 93.8 103.9 112.4 126.1 136.8 146.3 158.0 189.4 218.2 227.7	81.1 92.0 104.7 115.4 125.0 134.4 152.1 159.5 179.9 198.2 223.9 234.6 277.9 297.9 319.8	523.0 545.9	219.2 56.1 61.2 68.7 79.6 85.2 94.5 102.7 115.1 129.5 138.7 149.8 178.6 206.7 226.8	86.4 98.4 112.1 123.5 134.4 144.2 163.0 170.9 197.9 217.6 247.1 257.9 304.1 305.5 305.6	332.5 359.2 428.2 495.5 518.3	50.6 55.2 60.1 72.2 77.4 86.0 89.4 105.0 113.3 124.5 124.8 168.7 195.3 204.2 214.1	93.5 106.1 118.7 133.3 144.5 155.4 172.3 184.4 215.2 239.0 266.7 284.2 336.8 361.7 388.9	495.8 121.2 132.4 144.0 173.0 185.7 206.0 214.3 251.7 271.6 298.6 299.1 404.4 468.1 489.6 513.3

LEGEND

Capacity, Tons of Refrigeration Compressor Motor Input Power at Rated Voltages Leaving Chilled-Water Temperature (F)

43



## COMBINATION RATINGS (cont)

60 Hz, ENGLISH (cont)

				1						ER ENTI		IR TEMP	FRATIII	DE (E)	-			
LCWT	UNIT	AIR-C	DK OOLED		85			95			105	int remi	LITATO	115		1	125	
(F)	SIZE 30HXA	Unit	(Qty)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	(Gpm)	Cap,	Input kW	Cooler Flow Rate (Gpm)
45	076 086 096 116 126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) an 074 (1) an 074 084 084 084 084 084 094 094	(2) (2) (2) (2) (2) (3) (3) (3)	90.8	73.3 83.1 94.4 104.4 112.9 121.2 137.4 144.8 152.1 167.6 191.0 196.9 234.7 251.7 271.6	178.1 194.6 217.7 250.0 268.1 295.4 320.7 356.8 365.1 392.2 425.6 499.8 579.6 607.9 639.4	68.9 75.3 84.2 97.1 104.1 115.0 124.4 139.2 146.3 157.1 169.4 201.4 233.8 245.0 257.0	77.6 87.8 99.7 110.4 119.5 128.4 144.9 152.9 166.1 183.1 207.5 215.5 226.3 274.7 295.1	165.2 180.6 202.0 232.8 249.7 275.7 298.3 333.7 350.8 406.1 482.8 560.7 587.5 616.3	63.3 69.0 77.3 89.3 95.7 105.9 114.7 128.6 139.2 148.8 160.6 192.9 222.1 231.8 242.4	81.9 92.8 105.7 116.5 126.3 135.8 153.5 161.2 181.4 199.9 225.8 236.4 280.0 300.4 322.5	151.8 165.6 185.3 214.2 229.4 254.0 275.0 308.4 333.8 356.9 385.2 462.5 532.7 555.9 581.3	57.3 62.4 70.2 81.2 87.0 96.5 104.8 117.6 131.7 141.1 152.4 181.7 210.2 219.9 230.6	87.0 99.2 112.9 124.5 135.4 145.3 164.2 172.2 199.3 219.2 248.7 259.7 306.3 328.0 352.8	137.4 149.7 168.2 194.8 208.6 231.5 251.2 281.9 315.9 338.3 365.4 435.8 504.2 527.2	51.6 56.4 60.5 73.7 79.0 87.7 90.2 107.2 114.2 125.6 124.8 171.6 198.6 207.7 217.7	93.8 106.7 119.1 133.9 145.5 156.4 172.7 185.6 215.6 239.7 266.6 285.8 338.8 364.1 391.8	123.8 135.1 145.1 176.8 189.4 210.3 257.0 273.8 301.1 299.3 411.5 476.3 498.0 522.0
46	096 106 116 126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 084 (2) and 094 094	(2) (2) (2) (2) (2) (3) (3) (3)	75.6 82.7 92.4 106.2 113.8 125.5 136.2 151.6 154.7 166.1 180.4 211.8 245.5 257.4 270.9	74.2 84.0 95.5 105.5 114.1 122.5 138.9 146.3 153.3 169.1 192.6 198.3 236.5 253.9 273.7	181.4 198.3 221.7 254.6 272.9 301.0 326.6 363.5 371.0 398.5 432.6 507.9 588.9 617.4 649.8	70.3 76.7 85.8 99.0 106.1 117.1 126.8 141.8 148.7 159.7 172.3 204.7 237.7 249.1 261.6	78.4 88.8 100.7 111.5 120.8 129.7 146.4 167.4 184.7 209.4 217.2 258.2 276.9 297.3	168.6 184.0 205.9 237.4 254.5 280.9 304.1 356.8 383.0 413.4 491.1 570.3 597.4 627.5	64.6 70.4 78.7 91.0 97.5 108.2 116.9 131.2 141.6 151.5 163.2 196.0 226.1 235.9 246.5	82.8 93.7 106.7 117.8 127.7 137.1 155.0 162.9 183.0 201.6 228.0 238.2 282.1 303.1 325.4	154.9 168.7 188.9 218.4 233.9 259.5 280.3 314.7 339.6 363.3 391.5 470.2 542.4 565.8 591.2	58.5 63.8 71.6 82.8 88.8 98.6 120.0 134.0 143.4 154.9 185.0 213.6 223.6 234.6	87.8 99.9 113.8 125.6 136.4 146.4 165.5 200.6 220.9 250.4 261.5 308.6 330.6 354.9	140.2 152.9 171.7 198.7 213.1 236.5 256.2 287.9 321.4 341.1 371.6 443.8 512.9 536.4 562.6	52.7 57.6 61.1 75.1 80.6 89.5 91.0 109.3 115.1 126.6 124.9 174.6 200.9 210.0 217.7	94.3 107.2 119.3 134.9 146.5 157.5 173.2 186.7 215.9 240.3 266.6 287.5 340.0 365.4 391.9	126.4 138.1 146.5 180.2 193.2 214.6 218.3 262.2 276.1 303.7 299.5 418.7 481.8 503.8 502.3
48	076 086 096 106 1126 126 136 146 161 171 186 206 206 246 261	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 094 994	(1) (1) (1) (1) (1) (1) (2) (2) (2) (2)	78.5 85.7 95.8 110.1 118.0 130.0 141.1 157.1 159.5 171.4 186.0 218.6 253.2 265.4 279.3	75.9 85.8 97.6 107.7 116.4 125.2 142.0 149.4 155.8 172.0 196.0 201.1 239.9 257.8 278.1	188.4 205.7 229.9 264.2 283.1 312.0 338.6 376.9 382.9 411.3 446.5 524.7 607.7 637.0	73.0 79.7 89.1 102.7 110.0 121.6 131.6 147.2 153.8 165.1 178.4 211.6 245.5 245.5	80.0 90.6 102.9 113.9 123.5 132.4 149.4 157.6 170.0 187.7 213.0 220.5 262.1 281.5 302.7	175.3 191.3 213.8 246.5 264.0 291.9 315.9 353.2 369.1 396.1 428.1 507.8 589.3 617.1 648.1	67.3 73.2 81.9 94.7 101.4 112.3 121.5 136.4 146.5 156.7 168.6 202.4 234.3 244.5	84.4 95.6 108.6 120.2 130.3 140.0 157.8 166.2 185.8 205.1 232.2 242.0 286.6 308.0 331.0	161.4 175.6 196.6 227.4 243.4 269.6 291.7 327.4 351.5 376.0 404.6 485.8 562.4 586.7	61.0 66.4 74.4 86.3 92.5 102.6 111.0 125.0 125.0 121.0 191.8 221.0 231.1 242.3	89.1 101.4 115.7 127.6 138.5 148.7 168.0 203.5 224.3 254.0 264.9 313.3 336.0 360.5	146.4 159.4 178.7 207.0 221.9 246.2 266.4 299.9 332.2 355.7 383.9 460.2 530.5 554.6	54.7 59.8 62.1 78.1 83.7 93.1 92.7 113.6 128.8 124.9 178.2 205.3 214.7 217.9	95.7 108.7 120.0 136.7 148.6 159.6 174.0 189.4 216.7 241.3 266.6 289.9 342.2 368.1 391.7	131.3 143.5 149.1 187.4 200.9 223.4 222.5 272.7 280.6 309.1 299.8 427.6 492.6 492.6 515.2 522.9

LEGEND

Capacity, Tons of Refrigeration Compressor Motor Input Power at Rated Voltages Leaving Chilled-Water Temperature (F)



### **COMBINATION RATINGS (cont)**

60 Hz, ENGLISH (cont)

		1 000	DI/						ONDENS			IR TEMP	FRATUI	RF (F)				
LCWT	UNIT	AIR-CC	OCLED		85			95			105		T	115		1	125	
(F)	SIZE 30HXA	Unit	(Qty)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)
50	076 086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 074 (1) and 074 074 084 084 084 084 084 094 094	1054 (1) (2) (2) (2) (2)		77.7 87.7 99.7 110.3 119.3 128.0 145.2 152.8 158.3 174.9 199.6 204.2 243.3 261.7 282.7	195.1 213.1 238.4 273.8 293.1 323.3 350.7 390.8 395.0 424.2 460.5 541.5 626.5 626.5 656.6 690.4	75.8 82.6 92.4 106.5 114.0 126.0 136.4 152.6 158.8 170.4 184.6 218.2 253.2 265.2 278.5	81.7 92.6 105.1 116.3 126.2 135.2 152.6 160.8 172.7 190.9 216.7 224.2 266.4 286.3 308.4	181.9 198.4 221.9 255.7 273.7 302.6 327.6 366.5 381.4 409.2 443.3 523.9 607.9 636.7 668.7	69.9 76.1 85.0 98.5 105.4 116.2 141.7 151.2 161.9 173.9 209.1 242.7 253.2 264.6	86.1 97.6 110.8 122.7 133.1 142.8 160.7 169.6 189.0 208.8 236.5 245.8 291.1 313.0 336.6	167.9 182.7 204.2 236.4 253.0 280.5 303.0 340.3 363.0 388.8 417.6 502.1 582.6 608.0 635.3	63.6 69.1 77.3 89.8 96.1 106.8 115.3 130.0 143.0 153.1 165.3 198.6 228.4 238.6 250.2	103.2 117.8 129.8	152.6 165.8 185.7 215.7 230.8 256.4 276.8 312.1 343.4 367.5 396.8 476.9 548.4 573.0 600.7	57.1 60.9 63.4 81.2 87.0 96.7 94.4 118.0 117.6 129.9 123.9 181.8 209.8 219.4 217.9	97.2 109.5 120.8 138.8 150.6 161.9 175.1 192.0 217.4 241.9 266.7 292.5 344.7 370.7 392.0	137.1 146.3 152.3 194.9 208.9 232.2 226.6 283.4 282.5 311.9 297.6 436.5 503.8 526.8 523.2
55	261 271	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 084 094 094	(2) (2) (2) (2) (2) (2) (3) (3) (3)	85.1 93.6 103.6 120.2 129.5 142.9 153.5 172.6 173.2 184.9 200.5 235.4 270.2 285.8 300.4	79.8 90.7 102.3 114.0 124.0 132.6 149.5 158.2 162.5 179.5 204.5 208.5 247.4 267.4 289.1	204.6 224.9 248.9 289.0 311.3 343.4 368.9 414.9 416.2 444.5 482.0 565.7 649.5 687.0 722.0	79.3 87.1 96.6 111.6 119.9 133.8 143.6 162.0 167.4 178.7 193.6 227.9 262.4 277.5 291.5	83.8 95.6 107.9 119.6 129.8 139.9 157.2 166.3 177.6 196.1 222.8 229.5 271.7 293.4 316.6	190.7 209.5 232.1 268.3 288.1 321.5 345.1 389.4 402.3 429.6 465.3 547.7 630.7 666.9 700.6	73.3 79.7 88.9 103.4 111.0 124.2 132.9 150.8 158.1 170.4 182.9 219.0 252.1 266.6 278.6	88.5 100.1 113.8 126.2 137.0 147.8 165.4 175.5 193.2 214.5 243.2 251.4 297.1 320.7 345.2	176.1 191.6 213.8 248.8 266.8 298.6 319.4 362.5 380.1 409.5 439.6 526.4 606.0 640.8 669.7	66.8 72.6 81.2 93.5 101.5 113.0 121.6 138.7 150.1 160.6 171.8 208.2 237.8 247.8 262.3	93.3 105.5 120.4 132.1 144.1 155.2 176.6 184.7 211.0 233.7 263.1 275.6 325.1 348.9 377.2	160.6 174.6 195.1 224.6 243.8 271.5 292.4 333.5 360.8 386.0 413.0 500.4 571.5 595.7 630.4	60.2 62.1 65.4 90.0 101.3 97.5 125.1 121.4 129.0 124.1 184.4 214.4 222.0 218.1	99.1 110.4 121.9 140.3 152.6 164.6 176.6 196.1 220.0 241.9 266.5 294.1 348.3 372.3 391.9	144.6 149.4 157.1 200.5 216.2 243.4 234.2 300.7 291.8 310.0 298.4 443.1 515.4 533.5 524.3
60	086 096 106 116 126 136 146 161 171 186 206 246	084 084 074 (1) and 074 (1) and 074 074 084 084 084 084 084 084 094	(1) (1) (1) (1) (2) (2) (2) (2) (3) (3) (3) (3) (3) (3) (3) (3) (3) (3	85.2 93.6 103.7 119.6 128.3 143.0 153.7 172.8 171.9 185.1 200.7 235.5 270.4 286.0 300.6	79.9 90.8 102.4 113.7 123.3 132.7 149.5 158.3 161.7 179.6 205.0 208.6 247.6 267.5 289.2	204.9 225.1 249.4 287.6 308.7 344.1 369.7 415.7 415.7 445.2 482.8 566.6 650.5 688.0 723.1	79.4 86.4 96.5 111.7 120.0 133.9 143.8 162.2 166.1 178.9 193.7 228.0 262.6 277.7 291.7	83.9 95.1 108.1 119.7 129.9 139.9 157.2 166.4 176.7 196.1 223.1 229.5 271.9 293.5 316.7	190.9 208.0 232.2 268.7 288.6 322.2 345.9 390.1 399.6 430.4 465.9 548.6 631.6 668.0 701.7	73.4 79.7 89.0 102.3 111.1 124.4 133.1 151.0 158.3 170.5 181.5 219.2 252.3 264.0 278.9	88.5 100.2 113.8 125.5 137.0 147.9 165.4 175.5 193.3 214.6 242.2 251.5 297.2 319.3 345.4	176.5 191.8 214.2 246.1 267.2 299.1 320.1 363.6 380.8 410.2 436.7 527.2 607.0 635.1 670.8	66.9 72.0 81.2 93.5 100.8 113.1 121.8 137.8 150.2 160.7 171.9 208.3 238.0 248.0 262.5	93.3 105.1 120.5 132.2 143.6 155.2 175.6 184.0 211.1 233.8 263.3 275.7 325.2 349.0 377.3	161.0 173.3 195.4 225.0 242.4 272.0 293.0 331.4 361.4 386.6 413.6 501.2 572.4 596.5	59.6 62.3 65.4 83.5 90.0 101.4 98.6 125.2 120.6 130.1 124.2 184.5 214.6 222.1 218.2	98.8 110.3 121.9 140.4 152.6 164.6 177.4 196.1 219.3 241.8 266.6 294.1 348.5 392.3	524.3 149.8 149.8 216.5 243.8 237.1 301.2 290.0 313.0 298.7 443.9 516.2 534.3 524.9

LEGEND



### **COMBINATION RATINGS (cont)**

60 Hz, SI

						54			, 112, 3									
*		09	DK						NDENSE	RENTE	RING A	IR TEMP	ERATUR	RE (C)	***********			
LCWT	UNIT	AIR-CO	DK DOLED		30	0		35	T		40			45			50	
(C)	30HXA	Unit	(Qty)	Cap.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)
4	261 271	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 084 094 094	d 054 (1) (2) (2) (2) (2) (2) (2) (3) (3) (3)	231.7 254.3 284.3 326.4 350.2 386.0 418.9 466.3 485.5 521.1 564.4 665.3 772.8 810.1 851.7	69.2 78.4 89.1 98.8 107.1 114.9 130.0 137.5 146.3 161.4 182.9 190.3 226.4 242.7 260.9	9.9 10.8 12.1 13.9 16.4 17.8 19.9 20.7 22.2 24.0 28.3 32.5 36.3	216.1 236.2 264.7 304.5 326.4 360.7 391.3 436.6 465.8 498.8 536.9 641.2 777.0 812.7	72.9 82.6 93.6 103.9 112.7 121.2 136.5 144.4 158.5 174.5 197.1 206.8 245.0 262.6 282.1	9.2 10.1 11.3 13.0 15.4 16.7 18.6 19.8 21.2 22.9 27.3 31.7 33.1 34.6	198.6 217.3 243.5 281.1 301.7 333.7 362.0 405.3 444.4 476.3 514.8 613.6 707.4 740.5 777.3	76.7 87.5 99.6 109.9 119.4 128.2 144.8 152.1 171.7 189.0 213.2 224.2 265.1 283.8 304.2	8.5 9.3 10.4 12.0 12.8 14.2 15.4 17.3 18.9 20.3 21.9 26.1 30.1 31.5 33.1	181.2 198.8 223.3 258.4 277.4 307.5 334.2 373.9 424.1 454.6 490.5 583.6 676.2 707.8 742.6	81.9 93.6 106.5 117.4 127.9 137.1 154.9 162.7 187.5 206.6 233.9 244.7 288.4 309.5 333.0	7.7 8.5 9.5 11.0 11.8 13.1 14.2 15.9 18.1 19.4 20.9 24.9 28.8 30.1 31.6	166.4 182.0 204.7 237.3 254.4 282.6 307.2 345.0 402.9 432.3 465.6 555.1 643.0 673.0 705.9	88.5 100.5 114.1 126.2 137.0 147.2 165.9 174.5 206.8 228.5 258.3 268.7 317.4 340.6 365.4	7.1 7.8 8.7 10.1 10.8 12.0 13.1 14.7 17.2 18.4 19.8 23.6 27.4 28.7 30.1
5	096 106 116 126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 (2) and 094 094	1 054 (1) (2) (2) (2) (2) (2)	240.0 263.1 294.6 337.9 362.3 399.2 433.6 482.3 500.7 537.5 583.3 685.0 795.7 834.1 876.6	70.5 79.9 90.7 100.6 109.1 117.1 132.3 140.0 148.2 163.6 185.5 193.1 229.6 246.1 265.1	10.2 11.2 12.6 14.4 15.4 17.0 18.5 20.6 21.3 22.9 24.9 29.2 33.9 35.5 37.4	224.4 245.1 274.0 315.8 338.4 373.8 405.4 453.2 480.3 515.1 553.9 661.5 768.7 803.7 840.2	74.2 84.1 95.5 105.8 114.8 123.4 138.8 146.9 160.8 200.3 209.5 248.3 266.1 286.1	9.6 10.4 11.7 13.5 14.4 15.9 17.3 19.3 20.5 22.0 23.6 28.2 32.8 34.3 35.8	206.6 225.6 252.7 292.1 313.1 346.8 470.8 458.9 491.5 531.2 634.3 730.8 801.4	78.2 89.0 101.2 111.5 121.2 129.9 147.0 154.3 174.0 191.4 215.9 227.3 268.9 268.9 309.0	8.8 9.6 10.8 12.5 13.3 14.8 16.0 17.9 19.6 20.9 22.6 27.0 31.1 32.6 34.2	188.7 206.4 232.1 268.2 287.7 318.8 346.9 437.5 469.0 506.4 602.6 697.8 730.3 766.4	83.1 94.9 107.9 119.0 129.6 138.9 157.0 164.7 189.8 208.9 236.8 247.8 291.8 312.9 336.7	8.0 8.8 9.9 11.4 12.3 13.6 14.8 16.5 18.6 20.0 21.6 25.7 29.7 31.1 32.7	172.7 188.7 212.1 246.2 264.2 293.0 318.5 357.9 415.5 445.7 480.2 573.0 663.4 728.4	89.4 101.7 115.6 127.7 138.6 149.0 168.0 176.6 208.6 230.1 260.1 270.7 320.5 344.2 369.5	7.4 8.0 9.0 10.5 11.3 12.5 13.6 15.3 17.7 19.0 20.5 24.4 28.3 29.6 31.0
6	086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 074 (1) and 074 074 084 084 084 084 084 084 094	(1) (1) (1) (1) (2) (2) (2) (2) (2) (2) (2)	248.7 272.2 304.7 349.7 374.6 413.1 448.7 499.0 515.5 554.1 601.2 705.3 818.3 858.6 902.4	71.8 81.5 92.6 102.5 111.2 134.7 142.5 150.5 165.8 188.5 195.7 232.9 249.6 269.1	16.0 17.6 19.1 21.3 22.0 23.6 25.6 30.1 34.9 36.6	232.3 253.8 283.9 327.3 350.9 387.7 419.9 469.4 495.6 531.9 572.4 682.2 792.6 830.9 868.5	75.7 85.8 97.4 107.9 116.9 125.6 141.4 149.5 163.1 179.6 203.5 212.3 251.9 269.6 290.2	9.9 10.8 12.1 14.0 15.0 16.5 17.9 20.0 21.1 22.7 24.4 29.1 33.8 35.4	214.3 234.3 262.2 302.8 324.9 359.6 436.3 473.6 506.7 547.4 655.5 788.3 825.8	79.7 90.4 103.0 113.5 122.9 132.0 149.5 156.9 176.7 194.4 219.6 230.4 292.3 313.8	9.1 10.0 11.2 12.9 15.3 16.6 18.6 20.2 21.6 23.3 28.0 32.2 33.6 35.2	196.1 214.5 240.4 278.2 298.2 330.6 359.2 402.3 451.2 483.4 522.4 621.8 779.8 753.2 790.1	84.3 96.1 109.5 120.6 131.2 140.8 159.1 167.0 192.3 211.4 239.9 251.0 295.8 316.6 340.6	8.4 9.1 10.3 11.9 12.7 14.1 15.3 17.2 19.2 20.6 22.3 26.5 30.7 32.1 33.7	179.0 196.0 219.7 255.4 273.9 303.9 330.0 371.1 428.7 459.2 495.6 591.4 684.8 716.4 751.3	90.4 102.7 117.0 129.1 140.3 150.8 170.2 178.7 210.7 232.3 262.9 273.4 324.0 347.9 374.1	7.6 8.4 9.4 10.9 11.7 13.0 14.1 15.8 18.3 19.6 21.1 25.2 29.2 30.6 32.0



# COMBINATION RATINGS (cont) 60 Hz, SI (cont)

		09DK						CO	NDENSE	R ENTE	RING A	R TEMPI	ERATUR	RE (C)		-		
LCWT	UNIT	AIR-COOL			30	1		35			40			45			50	
(C)	SIZE 30HXA		SER Oty)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар,	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Flow Rate (L/s)
7	126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 04 074 (1) and 05 074 084 084 084 084 084 084 (2) and 09 094 094	(N)(N)(N)(N)(N)(N)(N)(N)(N)(N)(N)(N)(N)(	257.3 281.2 314.9 361.6 387.5 427.4 464.0 516.2 530.3 569.9 618.9 842.4 883.5 928.9	73.4 83.2 94.5 104.5 113.2 121.3 137.4 144.9 152.9 168.3 191.7 198.3 236.1 253.1 273.1	11.0 12.0 13.4 15.4 16.5 18.2 19.8 22.6 24.3 26.4 31.0 35.9 37.7 39.6	240.4 262.8 293.7 338.7 363.4 401.3 434.3 485.8 511.1 548.7 591.2 703.4 816.8 856.0 897.4	77.3 87.5 99.3 109.9 119.1 127.9 144.2 152.3 165.5 182.4 206.9 214.9 255.5 273.8 294.3	10.3 11.2 12.5 14.5 15.5 17.1 18.5 20.7 21.8 23.4 25.2 30.0 34.9 36.5 38.3	222.6 243.1 272.3 314.4 336.6 372.7 403.5 452.5 488.9 522.9 564.0 676.6 780.1 814.0 850.9	81.2 91.9 104.6 115.4 125.2 134.6 152.0 159.8 179.2 197.5 223.1 233.5 276.7 296.9 318.6	9.5 10.4 11.6 13.4 14.4 15.9 17.2 19.3 20.9 22.3 24.1 28.9 33.3 34.7 36.3	204.0 222.5 249.7 288.8 309.3 343.2 372.3 417.7 465.0 498.1 538.3 642.4 742.3 776.4 814.4	85.5 97.4 110.9 122.4 133.2 142.8 161.3 169.3 195.0 214.6 243.0 254.0 299.7 321.1 344.5	8.7 9.5 10.7 12.3 13.2 14.6 15.9 17.8 19.8 21.3 23.0 27.4 31.7 33.1 34.8	185.3 202.9 227.8 264.7 283.7 315.1 341.9 384.5 433.5 473.4 498.3 610.2 706.3 738.8 774.3	91.3 103.9 118.3 130.6 142.1 152.6 172.3 180.9 211.2 234.9 263.3 276.6 327.5 351.8 378.9	7.9 8.7 9.7 11.3 12.1 13.4 14.6 16.4 18.5 20.2 21.3 26.0 30.1 31.5 33.0
8	086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 04- 074 (1) and 05- 074 084 084 084 084 084 (2) and 094 094 094	<u> </u>	266.1 290.7 325.4 373.6 400.4 441.4 479.9 533.4 545.7 586.2 747.2 866.5 908.4 955.8	74.9 84.8 96.4 106.6 115.3 123.7 140.2 147.7 155.2 171.0 194.8 200.8 239.4 256.8 277.1	11.4 12.4 13.9 16.0 17.1 18.8 20.5 22.8 23.3 25.0 27.2 31.9 37.0 38.8 40.8	249.0 272.2 304.2 350.5 375.8 415.2 449.4 502.7 526.7 565.6 610.4 724.7 841.8 881.8 926.2	78.7 89.1 101.2 112.0 121.3 130.2 147.0 155.0 167.9 185.1 210.1 217.9 258.9 277.8 298.3	10.6 11.6 13.0 15.0 16.0 17.7 19.2 21.5 22.5 24.1 26.1 30.9 35.9 37.6 39.5	231.1 251.7 281.9 325.7 348.8 386.4 417.9 504.1 539.3 580.6 696.5 805.9 840.6 878.7	82.6 93.6 106.3 117.6 127.5 137.0 154.5 162.7 181.9 200.6 226.9 236.9 280.4 301.3 323.6	9.9 10.7 12.0 13.9 14.9 16.5 17.8 20.0 21.5 23.0 24.8 29.7 34.4 35.9 37.5	211.8 230.7 258.6 299.8 321.1 356.3 385.3 433.4 479.4 513.6 663.6 765.1 800.1 839.2	86.7 98.9 9112.7 124.2 135.0 144.8 163.6 171.7 197.3 217.4 246.0 257.1 303.8 325.9 349.4	9.0 9.8 11.0 12.8 13.7 15.2 16.5 18.5 20.5 21.9 23.7 28.3 32.7 34.2 35.8	192.3 210.1 236.2 274.2 294.2 326.5 350.2 398.3 442.7 479.5 505.2 629.3 728.3 761.5 798.3	92.4 105.3 119.9 132.3 143.8 154.4 173.8 183.1 212.7 235.7 264.9 280.3 330.9 355.8 383.3	8.2 9.0 10.1 11.7 12.6 13.9 17.0 18.9 20.5 21.6 26.9 31.1 32.5 34.1
9	086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 084 074 (1) and 044 0774 074 074 084 084 084 084 084 084 (2) and 094 094		275.1 300.5 335.9 386.0 431.7 456.1 494.5 551.0 561.1 602.7 654.2 768.8 890.8 933.8 982.8	76.5 86.5 98.4 108.6 117.4 126.1 143.1 150.4 157.4 173.7 198.0 203.3 242.6 260.5 281.0	32.8 38.0 39.9	257.6 281.4 314.5 362.6 388.2 429.0 464.7 519.5 542.7 582.3 629.7 746.5 866.2 997.2	80.2 90.8 103.1 114.1 123.8 132.7 149.8 157.9 170.2 188.0 213.4 220.8 262.6 282.0 303.3	11.0 12.0 13.4 15.5 16.6 18.3 19.8 22.2 23.2 24.9 26.9 31.9 37.0 38.7	239.9 260.8 291.8 337.6 361.0 400.3 432.5 485.5 519.4 556.0 597.5 717.4 832.1 868.2	84.1 95.3 108.2 119.8 130.0 139.5 157.1 165.7 184.5 203.6 230.8 240.3 284.4 305.7 328.6	10.2 11.1 12.5 14.4 15.4 17.1 18.5 20.7 22.2 23.7 25.5 30.6 35.5 37.1	219.8 239.2 267.8 310.8 332.7 369.4 399.1 449.4 494.3 528.9 571.1 685.2 788.5 824.0 863.9	88.3 100.4 114.5 126.2 136.9 146.8 165.9 174.1 199.8 220.3 248.8 260.6 308.4 331.0 355.2	9.4 10.2 11.4 13.3 14.2 15.8 17.0 19.2 21.1 22.6 24.4 29.3 33.7 35.2	199.6 217.9 239.6 284.1 304.2 338.3 355.2 412.8 447.6 489.7 503.8 648.6 750.2 784.1	93.9 106.7 120.5 134.1 145.7 156.4 174.5 185.5 213.5 237.6 264.6 283.8 334.7 359.5 387.3	8.5 9.3 10.2 12.1 13.0 14.5 15.2 17.6 19.1 20.9 21.5 27.7 32.0 33.5 35.1

LEGEND
Capacity, kW
Compressor Motor Input Power at Rated Voltages
Leaving Chilled-Water Temperature (C)



## **COMBINATION RATINGS (cont)**

60 Hz, SI (cont)

	T .			T	7	-		CC	NDENSE	RENTE	RING A	R TEMP	FRATUE	E (C)				
LCWT	UNIT	09DK AIR-COOLE	D		30			35			40		101101	45		Т	50	
(c)	SIZE 30HXA	CONDENSE Unit (Q	R ty)	Cap.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)
10	076 086 096 106 116 126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 044 074 (1) and 054 074 084 084 084 084 084 (2) and 094 094	100000000	284.2 310.3 346.9 398.6 426.7 470.7 510.4 568.7 672.1 790.8 915.2 1008.9	78.1 88.2 100.3 110.7 119.8 128.6 145.9 153.5 159.8 176.5 201.3 206.1 245.7 264.2 285.2	12.1 13.3 14.8 17.0 18.2 20.1 21.8 24.6 26.5 28.7 33.8 39.1 41.0 43.1	266.5 290.6 325.0 374.6 401.1 443.3 479.9 536.8 558.7 599.3 649.3 767.5 890.5 932.5 979.6	81.7 92.6 105.1 116.3 126.1 135.2 152.7 160.8 172.7 190.9 216.8 224.1 266.4 286.4 308.3	11.4 12.4 13.9 16.0 17.1 18.9 20.5 22.9 23.9 25.6 27.7 32.8 38.1 39.8 41.9	248.0 269.7 301.7 349.0 373.7 414.7.3 502.6 534.3 572.6 615.1 738.9 857.9 936.4	85.7 97.2 110.3 122.2 132.4 142.1 159.8 168.7 187.5 206.9 234.6 243.5 288.7 310.3 333.6	10.6 11.5 12.9 14.9 16.0 17.7 19.1 21.5 22.8 24.5 26.3 31.6 38.3 40.0	227.8 248.1 277.7 322.0 344.7 382.6 413.0 465.4 509.3 544.3 587.5 707.1 813.3 848.2 889.2	90.0 101.9 116.4 128.2 138.8 149.2 168.8 176.9 202.8 223.4 252.8 264.3 313.2 336.1 361.0	9.7 10.6 11.9 13.8 14.7 16.3 17.6 19.9 21.8 23.3 25.1 30.2 34.8 36.2 38.0	207.6 225.6 243.2 294.5 315.0 350.5 363.9 427.5 452.6 496.1 502.1 668.2 772.5 807.4	95.1 108.1 121.0 135.9 147.5 158.5 176.1 188.0 214.5 238.4 264.2 287.4 339.3 363.4 391.7	8.9 9.6 10.4 12.6 13.5 15.0 15.0 18.3 19.3 21.2 21.5 28.6 33.0 34.5 36.2
13	146 161 171 186 206 246 261 271	084 084 074 074 (1) and 044 074 (1) and 054 074 074 084 084 084 084 084 (2) and 094 094 094	(1) (1) (1) (1) (1) (1) (1) (1) (1) (1)	299.4 323.6 364.2 415.6 448.0 540.0 607.6 602.0 652.2 702.1 830.4 994.1 1054.9	80.6 90.6 103.4 113.9 123.8 133.3 150.9 159.7 163.2 181.8 206.4 211.1 250.6 268.9 292.0	12.8 13.8 15.6 17.8 19.2 21.3 23.1 26.0 25.8 27.9 30.0 35.5 40.8 42.5 45.1	281.1 303.6 341.7 391.0 421.5 470.1 508.5 569.3 583.5 632.3 679.4 799.3 928.3 967.6 1016.3	84.2 94.9 108.5 119.3 129.9 139.8 157.9 166.2 176.8 196.8 222.8 229.4 272.6 291.9 315.0	12.0 13.0 14.6 16.7 18.0 20.1 21.8 24.4 25.0 29.1 34.2 39.7 41.4 43.5	259.5 282.4 318.0 365.1 393.7 440.1 5534.3 559.2 606.9 646.0 766.7 896.6 933.4 976.4	88.0 99.6 113.6 125.3 136.3 147.0 165.3 174.4 191.6 213.3 241.0 247.9 295.3 316.3 340.4	11.1 12.1 13.6 15.6 16.8 18.8 20.3 22.9 23.9 23.9 26.0 27.6 32.8 38.4 39.9 41.8	237.1 259.8 290.2 337.3 363.7 404.0 439.8 496.5 534.0 575.2 614.6 733.9 852.3 883.4 923.8	91.7 104.2 118.8 131.1 142.5 153.1 173.9 182.7 207.4 230.6 259.8 269.3 320.3 343.1 368.7	10.1 11.1 12.4 14.4 15.6 17.3 18.8 21.2 22.8 24.6 26.3 31.4 36.5 37.8 39.5	216.0 237.0 249.7 308.7 332.9 370.4 373.2 452.0 461.6 503.4 501.8 688.8 798.6 834.6 866.1	96.5 110.1 122.1 138.6 150.8 161.8 177.4 191.9 216.1 240.1 264.1 291.1 344.8 369.6 395.5	9.2 10.1 10.7 13.2 14.2 15.8 16.0 19.3 19.7 21.5 21.5 29.5 34.2 35.7 37.0
16	086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 074 (1) and 044 074 (1) and 054 074 074 084 084 084 084 084 084 084 094 1994		296.7 326.1 360.9 419.2 451.6 498.3 535.3 602.2 605.9 647.1 701.7 823.5 954.7 1000.6 1051.8	80.1 91.0 102.8 114.4 124.4 133.1 150.1 158.7 163.9 181.0 206.4 210.4 250.5 269.7 291.5	12.7 14.0 15.5 17.9 19.3 21.3 22.9 25.8 25.9 27.7 30.0 35.3 40.9 42.8 45.0	278.3 305.8 338.7 394.1 420.8 469.5 503.9 568.5 587.4 627.5 679.4 799.7 920.9 973.9 1023.1	83.7 95.4 107.8 119.9 129.6 139.6 156.9 166.1 177.6 195.8 222.5 229.2 271.4 293.1 316.2	11.9 13.1 14.5 16.9 18.0 20.1 21.6 24.3 25.2 26.9 29.1 34.2 39.4 41.7 43.8	259.3 282.0 315.0 368.4 392.6 439.4 470.3 533.4 558.1 601.7 646.1 772.2 888.8 939.9 983.7	87.9 99.5 112.9 125.8 136.1 146.8 164.3 174.3 191.2 212.3 240.7 248.6 294.2 317.5 341.6	11.1 12.1 13.5 15.8 16.8 16.8 20.1 22.8 23.9 25.8 27.7 33.1 38.1 40.2 42.1	239.2 259.5 290.4 333.8 362.5 407.2 435.1 495.7 532.9 570.0 609.4 739.4 844.4 890.2 930.1	92.1 104.2 118.8 130.4 142.3 153.9 173.1 182.5 207.2 229.7 258.7 270.0 344.2 370.1	10.2 11.1 12.4 14.3 15.5 17.4 18.6 21.2 22.8 24.4 26.1 31.7 36.2 38.1 39.8	217.9 236.8 236.8 305.7 331.9 373.7 376.2 456.0 503.0 501.3 689.3 791.6 827.6 867.7	96.9 109.9 121.9 137.9 150.6 162.4 178.0 192.5 216.8 240.1 264.1 291.2 343.3 367.9 396.1	9.3 10.1 10.7 13.1 14.2 16.0 16.1 19.9 21.5 21.5 29.5 33.9 35.4 37.2



# COMBINATION RATINGS (cont) 50 Hz, ENGLISH

		T						- No. 100.00	z, ENGL	14								
	LINUT	09	DK		85		_	95	ONDENS	RENTE		IR TEMP	ERATU					
LCWT (F)	UNIT SIZE 30HXA	AIR-CO CONDI Unit	OOLED ENSER (Qty)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate
40		084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 094 094	(2) (2) (2) (2) (2) (3) (3) (3)	83.1	68.0 78.3 88.1 97.2 106.5 113.7 127.9 134.8 145.3 159.6 180.5 188.1 224.7 240.4 258.4	162.4 178.2 198.9 226.9 243.7 267.9 289.6 320.5 333.7 357.5 386.2 455.4 529.1 553.6 580.2	62.8 68.8 76.8 87.9 94.3 104.0 112.4,9 132.9 142.1 151.8 182.8 212.1 221.3 230.5	72.0 82.9 93.2 102.9 112.9 120.6 135.1 142.6 159.0 174.4 196.8 206.2 245.3 262.2 281.6	150.5 164.6 183.7 210.4 225.7 249.1 269.0 299.0 318.2 340.2 363.5 437.5 507.8 529.7 551.7	57.2 62.7 70.0 80.5 86.4 95.5 103.3 115.2 126.1 135.0 144.8 174.0 200.0 209.2 218.7	76.3 88.3 99.7 109.4 120.3 128.2 144.1 151.0 174.1 190.6 215.2 226.0 268.4 286.7 307.5	137.0 150.1 167.6 192.6 206.8 228.6 247.2 275.7 301.8 323.1 346.5 416.5 478.8 500.8 523.5	51.6 56.8 63.6 73.1 78.6 87.1 94.6 105.4 119.0 127.4 136.0 164.1 189.6 198.1 206.4	82.0 95.2 107.4 117.8 129.9 138.4 155.2 162.7 191.3 209.9 236.6 248.0 294.8 315.1 338.4	123.6 135.9 152.3 175.1 188.3 208.5 226.5 252.4 284.9 305.1 325.5 392.9 453.8 474.3	47.1 51.4 57.7 66.6 71.3 79.1 86.4 96.3 110.5 119.8 125.9 154.4 177.8 185.9 193.0	89.3 103.2 115.5 127.4 139.9 149.4 166.4 175.6 211.8 233.3 261.7 274.9 326.1 348.4 372.9	(Gpm) 112.7 123.1 138.1 159.4 170.7 189.5 206.7 230.6 264.6 286.8 301.5 369.7 425.5 444.9 462.1
42	096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 084 094 094	<u> </u>	70.5 77.3 86.3 98.4 105.7 116.3 125.7 139.0 143.9 154.3 166.6 196.5 228.1 238.9 250.3	69.4 80.0 90.2 99.3 108.8 115.9 130.5 137.5 147.8 162.3 184.0 191.0 228.2 2243.9 262.6	168.9 185.2 206.6 235.7 253.1 278.6 301.1 333.1 344.7 369.7 399.0 470.7 546.5 572.2 599.7	65.4 71.5 79.8 91.5 98.2 108.3 116.9 130.1 137.6 147.3 157.4 189.5 219.5 229.6 239.2	73.6 84.7 95.3 105.0 115.2 123.0 137.8 145.3 161.6 177.3 200.5 209.1 249.1 266.1 286.0	156.6 171.3 191.1 219.2 235.2 259.4 280.1 311.6 352.9 377.2 453.2 525.9 550.1 572.9	59.8 65.4 72.9 83.9 90.1 99.5 107.5 119.9 130.5 139.7 149.8 180.5 207.4 216.3 226.0	77.9 89.9 101.6 111.3 122.2 130.3 146.6 153.5 176.9 193.6 218.7 229.2 272.5 291.0 312.3	143.2 156.6 174.7 201.1 215.8 238.4 257.6 287.3 312.7 334.6 358.8 432.4 496.7 518.3 541.3	54.0 59.1 66.3 76.3 82.0 90.6 98.4 109.7 123.2 131.9 140.8 170.0 196.4 205.2 213.9	83.3 96.6 109.1 119.5 131.5 140.3 157.5 164.9 194.1 212.6 240.4 251.7 298.6 319.2 343.0	129.3 141.6 158.7 182.8 196.3 217.1 235.8 262.9 295.1 316.1 337.4 407.3 470.5 491.6 512.4	48.9 53.5 59.3 69.3 74.3 82.5 89.7 100.4 111.2 122.9 126.0 160.0 184.1 192.5	90.5 104.5 116.8 129.1 141.8 151.4 169.1 177.8 212.3 234.8 261.7 277.3 329.9 352.5	117.2 128.3 141.9 166.0 178.0 197.5 214.8 240.5 266.4 294.4 301.9 383.9 441.1 461.2 478.9
44	096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 084 094 994	044 (1) 054 (1) 054 (1) 054 (1) 0054 (1) 0054 (1) 0054 (1) 0054 (1) 0054 (1) 0054 (1)	73.3 80.2 89.5 102.2 109.7 120.7 130.4 144.4 148.5 159.2 171.8 202.9 235.4 246.5 258.4	71.0 81.8 92.2 101.4 111.0 118.4 133.5 140.3 150.4 165.1 187.6 193.7 231.8 247.8 267.0	175.7 192.3 214.6 245.0 262.9 289.4 312.5 346.0 356.0 381.7 411.9 486.5 564.2 590.9	68.0 74.3 82.9 95.1 102.1 112.6 121.5 135.1 142.4 152.6 163.3 195.7 227.0 237.6 248.0	75.3 86.6 97.5 107.3 117.6 125.5 140.9 164.2 180.2 203.9 212.1 253.2 270.5 290.5	162.9 178.2 198.8 228.0 244.8 269.9 291.2 323.9 341.3 365.8 391.4 469.2 544.2 569.6	62.3 68.0 76.0 87.3 93.8 103.7	79.5 91.7 103.5 113.4 124.2 132.7 149.3 156.5 179.7	149.4 163.1 182.2 209.4 224.8 248.5 268.5 299.5 323.9 346.1 370.7 448.4 515.1 536.9	56.4 61.7 69.0 79.5 85.2 94.3 102.5 114.4 127.5 136.5 145.8 176.1 203.2 212.4 221.5	84.7 98.1 110.8 121.3 133.5 142.4 159.9 167.3 197.1 215.5 244.3 255.3 303.1 323.5 347.8	135.1 147.8 165.3 190.5 204.3 226.1 245.6 274.3 305.7 327.1 349.5 422.2 487.1 509.3 530.9	50.9 55.7 60.3 72.2 77.4 85.8 90.4 104.5 114.0 126.1 165.7 190.7 190.3 207.0	91.6 105.8 117.4 130.8 117.4 130.8 143.7 153.4 169.0 180.2 213.6 236.1 261.8 280.5 334.4 357.5 383.2	122.0 133.5 144.5 173.0 185.5 205.7 216.8 250.5 273.2 299.6 302.3 397.2 457.2 477.7 496.3



## COMBINATION RATINGS (cont)

50 Hz, ENGLISH (cont)

37.31		- 00	DK			8		CC	ONDENS	R ENTI	RING A	IR TEMP	ERATUR	RE (F)				
LCWT	UNIT	AIR-CO	OOLED		85	1		95			105			115		T	125	
(F)	SIZE 30HXA	Unit	(Qty)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Сар,	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)
45	271	084 084 074 (1) and 074 (1) and 074 074 084 084 084 084 084 (2) and 094 094	(2) (2) (3) (3) (3) (3) (3) (3) (3) (3) (3) (3	74.8 81.7 91.2 104.1 111.8 123.0 132.8 147.1 150.8 161.7 174.5 206.2 239.1 250.4 262.5	71.8 82.7 93.3 102.5 112.1 119.6 135.0 141.8 151.7 166.6 189.4 195.2 233.5 249.8 269.0	179.3 195.9 218.6 249.7 268.0 294.9 318.4 352.7 361.7 387.8 418.5 494.4 573.3 600.3 629.5	69.3 75.8 84.5 97.0 104.1 114.8 123.8 137.7 144.8 155.2 166.2 199.0 230.8 241.6 252.5	76.1 87.5 98.5 108.4 118.7 126.8 142.4 149.8 165.6 181.6 205.7 213.6 255.1 272.7 292.7	166.2 181.9 202.7 232.5 249.7 275.2 296.8 330.3 347.1 372.2 398.5 477.3 553.5 579.2 605.4	63.7 69.5 77.5 89.2 95.6 105.7 114.2 127.5 137.4 146.9 157.1 190.3 218.7 228.0 237.0	80.3 92.4 104.5 114.5 125.4 134.2 150.7 158.1 181.1 198.6 224.3 234.1 278.9 298.1 319.7	152.8 166.7 186.0 213.9 229.4 253.5 274.0 305.8 329.5 352.3 376.8 456.4 524.5 546.7 568.3	57.7 63.0 70.4 81.1 87.0 96.3 104.4 116.8 129.7 138.8 148.3 179.2 206.7 216.1 225.4	85.3 98.8 111.6 122.3 134.5 143.5 161.2 168.7 217.3 246.1 257.2 305.4 326.0 350.2	138.3 151.1 168.9 194.6 208.7 231.0 250.5 280.0 311.0 332.8 355.7 429.7 495.6 518.1 540.4	52.0 56.7 60.8 73.6 79.0 87.5 91.1 106.6 114.9 126.0 126.2 168.6 194.1 202.8 210.7	92.0 106.5 117.6 131.6 144.6 154.5 169.5 181.3 214.0 236.6 261.7 282.2 336.5 359.8 385.9	124.6 136.1 145.8 176.5 189.4 209.9 218.6 255.7 275.4 302.2 302.5 404.2 465.5 486.3 505.2
46	096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 084 094 094	(1) (1) (1) (1) (1) (2) (2) (2) (2) (2) (2)	76.1 83.2 92.8 106.0 113.8 125.2 149.8 153.2 164.3 177.3 209.5 242.8 254.2 266.7	72.7 83.7 94.3 103.6 113.3 120.9 136.5 143.2 152.9 168.0 190.9 196.4 235.2 251.8 271.1	182.5 199.6 222.7 254.3 272.9 300.4 324.2 359.4 367.5 394.0 425.3 502.6 582.5 609.8 639.6	70.7 77.2 86.1 98.8 106.1 116.9 126.1 140.3 147.2 157.8 169.2 202.4 234.7 245.5 256.8	76.8 88.4 99.6 109.6 120.0 128.1 143.9 151.4 166.9 183.2 207.4 215.3 257.0 295.2	169.6 185.3 206.6 237.1 254.5 280.4 302.5 336.6 353.0 378.5 405.8 485.4 562.9 588.8 615.9	65.0 70.9 79.1 90.9 97.6 107.9 116.4 130.1 139.7 149.4 159.6 193.4 222.6 232.1 241.2	81.1 93.2 105.4 115.8 126.7 135.5 152.2 159.7 182.5 200.3 226.2 235.8 280.9 300.4 322.4	155.8 170.0 189.7 218.1 234.0 258.8 279.2 312.1 335.2 358.4 382.8 463.9 533.9 556.6 578.5	58.9 64.2 71.9 82.7 88.7 98.4 106.6 119.2 150.9 182.5 210.1 219.7 229.3	86.0 99.6 112.4 123.3 135.6 144.6 162.3 170.0 200.1 219.0 247.9 259.0 307.7 328.4 352.7	141.2 154.0 172.4 198.5 212.9 236.1 255.7 286.0 316.5 338.6 361.9 437.9 504.1 527.1 549.9	53.0 58.0 61.3 75.0 80.5 89.3 91.9 108.8 115.7 127.1 126.2 171.5 197.6 206.3 214.4	92.5 107.0 117.9 132.5 145.7 155.5 170.0 182.5 214.4 237.3 261.8 283.9 338.6 362.2 388.8	127.2 139.0 147.1 180.0 193.0 214.1 220.5 260.9 277.6 304.8 302.7 411.4 473.9 494.9 514.2
48	086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 0774 (1) and 0774 (1) and 0774 0774 084 084 084 084 084 (2) and 094	(1) (1) (1) (1) (2) (2) (2) (2) (2) (2) (2) (2)	78.9 86.3 96.2 110.0 118.0 129.8 140.1 155.3 158.0 169.4 182.9 216.3 250.4 262.0 274.7	74.4 85.4 96.5 105.8 115.6 123.6 139.6 146.5 155.3 170.9 194.2 238.5 255.8 275.5	189.5 207.2 230.8 263.9 283.1 311.4 336.3 372.6 379.2 406.5 438.8 519.0 600.8 628.8 659.2	73.5 80.3 89.4 102.6 110.0 121.4 131.0 145.6 152.2 163.0 175.0 209.0 242.2 253.2 264.8	78.4 90.2 101.7 111.9 122.7 130.8 154.5 169.4 186.2 211.1 218.7 261.2 279.7 300.7	176.3 192.6 214.6 246.2 263.9 291.3 314.3 349.5 365.2 391.2 420.0 501.6 581.2 607.8	67.7 73.7 82.2 94.7 101.4 112.2 121.1 135.3 144.5 154.5 164.6 199.7 240.5 240.9	82.8 95.2 107.4 118.1 129.5 138.3 154.9 185.2 203.5 229.9 239.5 229.9 239.5 239.5 239.5 239.5 239.5 239.5	162.4 177.0 197.4 227.2 243.3 269.3 290.6 324.8 346.7 370.7 395.0 479.4 553.7 577.1 599.8	61.4 66.9 74.7 86.2 92.4 102.5 110.8 124.2 136.4 146.0 156.0 189.3 221.0 226.9 236.5	87.4 101.2 114.3 137.8 146.8 164.7 172.6 203.1 222.3 251.4 262.6 312.3 333.7 358.6	147.3 160.5 179.3 207.0 221.7 245.9 266.0 298.0 327.3 350.3 374.4 454.2 520.8 544.5 567.6	55.0 60.2 62.5 78.0 83.6 92.8 93.6 113.1 116.5 128.2 126.3 177.5 203.1 212.1 218.0	93.8 108.5 118.5 134.3 147.8 157.7 170.9 185.0 261.8 288.0 341.9 365.5 391.2	132.1 144.5 150.0 187.2 200.7 222.8 224.5 271.4 279.7 307.6 303.1 425.9 487.5 509.1 523.3

LEGEND

 Cap.
 —
 Capacity, Tons of Refrigeration

 kW
 —
 Compressor Motor Input Power at Rated Voltages

 LCWT
 —
 Leaving Chilled-Water Temperature (F)



### **COMBINATION RATINGS (cont)**

50 Hz, ENGLISH (cont)

		091	nk			(*)			ONDENS	20701 10		IR TEMP	ERATU	RE (F)			-	
LCWT	UNIT	AIR-CO	OOLED		85	12.		95			105			115			125	
(F)	SIZE 30HXA	Unit	(Qty)	Сар.	Input kW	(Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Сар.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)	Cap.	Input kW	Cooler Flow Rate (Gpm)
50	076 086 096 106 116 126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 094 094 094	(2) (2) (2) (2) (2) (2) (3) (3) (3)	81.8 89.3 99.6 113.9 122.1 134.4 145.2 160.9 174.6 188.4 223.0 257.9 269.9 282.7	76.1 87.3 98.6 108.3 118.5 126.5 142.6 149.8 157.7 173.6 197.7 202.3 241.8 259.6 280.1	196.3 214.5 239.2 273.5 293.1 322.7 348.5 386.3 391.1 419.3 452.4 535.4 617.9 678.9	76.2 83.2 92.7 106.4 114.1 125.8 135.8 151.1 168.3 181.0 215.6 249.7 261.1 273.0	80.0 92.2 103.9 114.3 125.2 133.5 150.0 157.6 172.1 189.4 214.7 222.0 265.2 284.2 306.0	183.0 199.7 222.6 255.4 273.9 302.1 326.0 362.8 377.2 404.0 434.6 517.6 599.6 627.0 655.5	70.4 76.6 85.4 98.3 105.4 116.6 125.8 140.6 149.2 159.6 169.7 206.4 238.8 249.0 258.8	84.4 97.2 109.5 120.6 132.2 141.1 157.8 166.3 188.3 206.7 234.0 243.2 289.8 310.3 333.4	169.0 183.9 205.0 236.1 253.0 279.9 302.0 337.6 358.2 383.1 407.6 495.5 573.3 597.9 621.4	63.9 69.5 77.6 89.8 96.1 106.6 115.1 129.2 141.0 150.7 161.1 195.8 224.2 234.0 243.8	127.5 139.9 149.2 167.5	153.5 166.9 186.4 215.5 230.8 256.0 276.4 310.1 338.4 361.9 386.7 470.1 538.4 561.8 585.4	57.4 60.7 63.7 81.1 86.9 96.5 95.3 117.6 118.4 130.4 126.4 181.1 207.7 216.8 218.1	95.4 109.0 119.4 136.4 150.0 159.9 171.8 187.5 215.4 239.0 261.8 290.4 344.7 368.5 391.3	137.9 145.9 152.9 194.6 208.6 231.8 228.8 282.3 284.3 313.0 303.4 434.9 498.7 520.5 523.6
55	096 106 116 126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 074 (1) and 074 084 084 084 084 084 084 084 094	(N) (N) (N) (N) (N) (N) (N) (N) (N) (N)	85.6 94.2 103.9 120.0 129.5 142.6 152.5 170.7 171.3 182.7 196.8 232.7 267.2 282.0 295.3	78.2 90.2 101.1 112.1 123.2 131.0 146.9 155.1 162.0 178.3 203.0 206.5 245.8 265.2 286.3	205.7 226.4 249.8 288.5 311.3 342.8 366.6 410.3 411.8 439.0 473.1 559.2 642.1 677.8 709.7	79.9 87.7 96.9 111.5 119.8 133.5 143.0 160.5 164.0 176.3 189.4 2258.7 273.2 285.6	82.1 95.1 106.8 117.5 129.0 138.2 154.4 163.1 176.1 194.4 220.7 227.3 270.5 291.1 314.0	191.9 210.9 232.8 268.0 288.0 321.0 343.6 385.7 394.1 423.7 455.2 540.9 621.8 656.6 686.6	73.7 80.2 89.3 103.3 111.0 124.0 132.5 149.6 156.1 167.9 177.2 216.1 248.0 261.9 272.4	86.8 99.8 112.4 124.0 136.1 146.1 162.6 172.0 192.4 212.5 239.2 248.5 295.6 317.7 341.5	177.2 192.8 214.7 248.3 266.8 298.1 318.5 359.7 375.2 403.5 425.9 519.4 596.1 654.8	67.2 73.1 81.4 93.4 101.4 112.7 121.6 137.9 147.3 157.0 166.1 204.8 233.0 242.5 254.4	91.5 105.4 119.1 129.8 143.3 153.3 172.1 180.9 224.5 255.2 286.4 279.9 329.5 352.8 352.8 391.2	161.6 175.7 195.7 195.7 224.4 243.8 270.9 292.3 331.4 354.0 377.3 399.3 492.1 559.9 582.8 611.4	60.5 62.0 65.7 84.2 90.9 101.1 98.4 124.6 122.1 130.4 125.5 183.7 211.5 219.3	97.2 109.7 120.4 138.5 152.7 162.6 173.3 191.5 218.1 239.1 261.4 292.1 365.7 370.2	145.5 149.1 157.8 202.4 218.5 243.0 236.5 299.5 313.5 301.6 441.4 508.4 527.1
60	086 096 106 116 126 136 146 161 171 186 206 246 246	084 084 074 (1) and 074 (1) and 074 (1) and 074 084 084 084 084 084 084 094	(1) (1) (1) (1) (1) (1) (1) (1) (1) (1)	85.7 94.2 104.0 120.2 128.3 142.7 152.7 170.9 170.2 182.8 196.9 232.9 267.3 282.3 295.5	78.3 90.3 101.2 112.1 122.4 131.1 147.0 155.2 161.2 178.4 203.3 206.5 246.0 265.2 286.3	206.1 226.7 250.3 289.1 308.7 343.4 367.3 411.1 409.3 439.8 473.7 560.1 643.1 679.0 710.9	79.8 87.0 96.9 111.6 119.9 133.7 143.0 160.6 164.1 176.4 188.2 225.2 225.8 273.4 285.9	82.2 94.6 106.9 117.6 129.1 138.2 154.6 163.2 176.1 194.5 219.8 227.3 270.7 291.2 314.1	192.0 209.3 233.0 268.4 288.5 321.6 344.1 386.4 394.8 424.4 452.6 541.7 622.7 657.6	73.8 80.2 89.4 102.2 111.1 124.2 132.7 149.8 156.2 168.1 177.3 216.2 248.2 259.6 272.7	86.8 99.9 112.4 123.3 136.2 146.2 162.6 172.1 192.5 212.5 239.3 248.6 295.6 316.1 341.6	177.6 192.9 215.1 246.0 267.2 298.7 319.2 360.4 375.8 404.3 426.6 520.1 597.1 624.5 655.9	67.3 72.5 81.6 93.4 101.5 112.9 121.7 136.9 147.3 157.0 166.2 204.9 233.1 242.6 252.4	91.5 104.9 119.1 129.8 143.3 153.4 172.1 180.2 226.2 2258.0 289.1 279.9 329.8 353.1 382.0	161.9 174.5 196.2 224.8 244.3 271.5 292.8 329.3 354.4 377.7 399.7 492.9 560.8 583.7	59.9 62.1 65.7 84.3 90.0 101.2 99.3 124.7 122.2 130.6 125.5 184.9 211.6 219.5 218.4	96.9 109.8 120.5 138.6 152.0 162.6 174.3 191.6 218.1 239.0 261.5 293.0 367.0 370.2 391.5	524.7 144.2 149.3 158.1 202.7 216.5 243.5 238.8 300.0 294.0 314.1 302.0 444.9 509.0 509.0 525.3

LEGEND



### **COMBINATION RATINGS (cont)**

50 Hz, SI

					(8)			50	Hz, SI									
		0	9DK		30	V		35	NDENSE	RENTE		R TEMP	ERATUR	- view				
(C)	UNIT SIZE 30HXA	CONI Unit	COOLED DENSER (Qty)	Сар.	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Coole Flow Rate (L/s)
4	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	084 084 094 074 (1) a 074 (1) a 074 074 084 084 084 084 084 084 (2) a 094 094	nd 054 (1) (2) (2) (2) (2) (2)	233.3 256.1 285.3 325.9 350.4 385.3 416.0 460.8 481.6 515.7 658.2 764.7 800.1 838.6	67.8 78.0 88.0 97.0 106.2 113.4 127.7 134.6 145.8 160.1 181.1 188.5 225.3 240.9 258.7	9.9 10.9 12.2 13.9 14.9 16.4 17.7 19.6 20.5 22.0 23.7 28.0 32.6 34.1 35.7	217.4 238.1 265.5 304.1 326.5 360.0 388.8 492.1 460.8 492.8 526.6 634.0 735.0 766.7 799.0	71.4 82.2 92.5 102.0 111.9 119.6 134.1 141.5 153.4 195.6 204.9 243.8 260.6 279.6	9,3 10.1 11.3 13.0 13.9 15.3 16.6 18.4 19.0 22.4 27.0 31.3 32.7 34.0	199.8 218.8 244.3 280.8 301.7 333.1 360.3 401.7 439.6 470.4 504.7 606.5 697.4 729.4 762.6	75.2 87.1 98.4 107.9 118.6 126.5 142.2 148.9 171.5 187.9 211.9 222.6 264.3 302.8	8.5 9.3 10.4 12.0 12.9 14.2 15.3 17.1 18.7 20.0 21.5 25.8 29.7 31.1 32.5	182.1 200.2 224.3 258.1 277.5 306.7 331.2 371.0 447.3 477.4 575.5 665.3 695.2 725.0	80.2 93.2 105.2 115.3 127.1 135.5 152.1 159.3 186.6 204.6 231.0 242.1 287.4 307.3 330.0	7.8 8.5 9.6 11.0 11.8 13.1 14.2 15.8 17.8 19.1 20.3 24.5 28.3 29.6 30.9	167.5 183.4 205.6 237.0 254.3 282.1 307.1 342.9 394.8 423.6 449.9 545.6 657.3 683.3	86.7 100.2 112.7 123.9 136.1 145.3 162.4 170.7 204.7 225.0 252.6 264.7 314.6 336.1 359.5	7.1 7.8 8.8 8.8 10.1 10.8 12.0 13.1 14.6 16.8 18.0 19.2 23.2 26.8 28.0 29.1
5	096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) ar 074 (1) ar 074 084 084 084 084 084 (2) ar 094 094	(1) (1) (1) (1) (1) (2) (2) (2) (2) (2)	241.6 265.0 295.6 337.4 362.4 398.6 476.7 496.4 531.8 574.1 677.7 787.3 823.8 863.3	69.1 79.6 89.6 98.8 108.3 115.5 130.0 137.0 147.8 162.5 183.7 191.2 228.4 244.3 262.7	10.3 11.3 12.6 14.4 15.4 17.0 18.4 20.3 21.2 22.7 24.5 28.9 33.6 35.1 36.8	225.5 246.8 275.2 315.4 338.4 373.4 4403.3 475.6 508.7 543.9 654.0 654.0 759.2 792.9 826.2	72.8 83.8 94.3 104.0 114.0 121.8 136.3 144.0 160.4 175.7 198.7 207.7 207.7 247.1 264.1 283.7	9.6 10.5 11.7 13.4 14.4 15.9 17.2 19.1 20.3 21.7 23.2 27.9 32.4 33.8 35.2	207.6 227.4 253.6 291.7 313.1 346.0 417.0 453.8 485.6 520.9 626.7 7720.4 751.8 785.5	76.7 88.5 100.1 109.6 120.3 128.3 144.4 151.2 173.9 190.3 214.8 225.5 268.1 286.2 307.1	8.8 9.7 10.8 12.4 13.3 14.7 15.9 17.8 19.3 20.7 22.2 26.7 30.7 32.0 33.5	189.8 207.9 232.7 267.9 287.8 318.2 345.7 384.8 430.8 461.6 493.0 594.2 686.6 717.6 748.5	81.4 94.4 106.7 116.9 128.6 137.1 154.1 161.3 189.2 207.0 234.1 245.3 291.0 310.8 334.0	8.1 8.9 9.9 11.4 12.3 13.6 14.7 16.4 18.4 19.7 21.0 25.3 29.3 30.6 31.9	173.9 190.3 213.0 246.2 264.3 292.5 318.4 355.6 407.4 436.8 463.7 563.2 649.2 678.6 705.6	87.6 101.3 114.2 125.3 137.7 147.1 164.6 172.8 206.6 226.9 255.1 267.3 318.2 340.2 364.2	7.4 8.1 10.5 11.3 12.5 13.6 15.2 17.4 18.6 19.8 24.0 27.7 28.9 30.1
6	086 096 106 116 126 136 146 161 171 171 186 206 246 261	084 084 094 074 (1) an 074 (1) an 074 084 084 084 084 084 (2) an 094	d 054 (1) (2) (2) (2) (2) (2) (2)	250.3 274.2 305.8 349.2 374.7 412.2 445.7 493.3 510.8 547.8 591.1 697.8 809.9 848.0 888.3	70.3 81.1 91.4 100.6 110.3 117.6 132.4 139.4 150.1 164.7 186.9 193.9 231.7 247.7 266.7	34.5 36.2	233.6 255.7 284.8 326.9 350.9 417.5 464.6 490.6 525.6 674.3 782.6 819.2 853.6	74.2 85.4 96.2 105.9 116.1 124.0 139.0 146.5 162.7 178.4 201.9 210.4 250.8 267.7 287.7	34.9	215.8 236.0 263.2 302.7 324.9 358.9 432.5 468.1 500.2 536.1 647.5 744.2 775.7 808.8	78.1 90.0 101.8 111.4 122.1 130.4 146.8 176.4 193.3 218.4 228.5 271.8 290.4 311.5	9.2 10.1 11.2 12.9 13.9 15.3 16.5 18.4 20.0 21.3 22.9 27.6 31.7 33.1	197.2 216.1 241.7 278.1 298.0 330.1 358.3 358.3 399.5 444.7 475.9 508.8 613.6 7740.5 772.6	82.7 95.7 108.1 118.5 130.3 139.0 156.2 163.6 191.7 209.6 237.4 248.4 295.0 314.6 338.1	8.4 9.2 10.3 11.9 12.7 14.1 15.3 17.0 19.0 20.3 21.7 26.2 30.2 31.6	180.1 196.9 220.9 255.0 273.7 303.4 330.0 420.2 450.4 478.8 581.5 670.2 770.4 728.4	88.6 102.6 115.5 126.9 139.5 148.8 166.7 174.9 209.2 229.1 258.0 270.0 322.0 342.2 369.0	7.7 8.4 9.4 10.9 11.7 12.9 14.1 15.7 17.9 19.2 20.4 24.8 28.6 29.9 31.1



# COMBINATION RATINGS (cont) 50 Hz, SI (cont)

		09DK	9					CC	NDENSE	R ENTE	RING A	IR TEMP	ERATUR	RE (C)				
LCWT	UNIT	AIR-COOL			30		1,	35			40	T		45	-		50	
(c)	SIZE 30HXA		GER Oty)	Сар,	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)
7	076 086 096 1106 116 126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 09 074 (1) and 09 074 084 084 084 084 084 (2) and 09 094	54 (1) (1) (2) (2) (2) (3) (4) (4) (5) (6) (6) (7) (7) (7) (7) (7) (7) (7) (7) (7) (7	258.9 283.3 316.1 361.1 387.5 426.5 460.7 510.3 525.4 563.5 607.7 718.2 833.1 872.4 914.2	71.9 82.8 93.3 102.6 112.4 119.8 135.0 141.9 152.5 167.3 190.2 196.5 234.9 251.2 270.6	11.0 12.1 13.5 15.4 16.5 18.2 19.7 21.8 22.4 24.0 25.9 30.6 35.6 37.2 39.0	241.9 264.6 294.8 338.4 363.5 432.1 480.8 505.9 542.0 580.5 695.3 806.5 844.0 881.7	75.7 87.1 98.1 108.0 118.2 126.3 141.8 149.2 165.0 181.2 205.0 213.1 254.3 271.8 291.8	10.3 11.3 12.6 14.4 15.5 17.1 18.4 20.5 23.1 24.8 29.7 34.4 36.0 37.6	224.0 244.8 273.4 314.0 336.6 372.0 402.0 448.7 515.9 551.8 667.8 768.3 800.9 833.0	79.6 91.5 103.3 1134.3 132.9 149.3 156.6 178.9 196.3 221.6 231.3 275.5 294.6 315.8	9.6 10.4 11.7 13.4 14.4 15.9 17.2 19.1 20.6 22.0 23.5 28.5 32.8 34.2 35.5	205.4 224.1 250.8 288.5 309.1 342.8 371.5 415.0 458.7 490.9 525.1 634.1 730.0 763.3 796.9	83.8 97.1 109.6 120.3 132.3 141.0 158.3 165.7 194.3 212.5 240.6 251.6 298.8 319.1 342.5	8.8 9.6 10.7 12.3 13.2 14.6 15.9 17.7 19.6 20.9 22.4 27.1 31.2 32.6 34.0	186.6 204.3 228.7 264.2 283.5 314.5 341.9 382.5 463.5 464.2 493.9 600.1 691.8 722.6 751.4	89.5 103.7 116.9 128.4 141.3 150.7 168.7 176.9 211.7 232.0 261.9 273.4 325.7 348.3 374.0	8.0 8.7 9.8 11.3 12.1 13.4 14.6 16.3 18.5 19.8 21.1 25.6 29.5 30.8 32.1
8	096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 04 074 (1) and 05 074 074 084 084 084 084 084 084 084 (2) and 09- 094	4 (1)	267.6 292.9 326.6 373.0 400.4 440.6 527.3 540.3 579.4 625.1 739.2 856.8 896.9 940.5	73.5 84.4 95.3 104.7 114.5 122.1 137.8 144.6 154.8 170.0 193.2 198.9 238.0 254.8 274.4	11.4 12.5 13.9 15.9 17.1 18.8 20.3 22.5 23.1 24.7 26.7 31.6 36.6 38.3 40.2	250.8 273.9 305.4 350.2 375.9 414.3 446.9 497.2 521.2 558.6 598.8 716.4 830.8 869.0 908.6	77.1 88.7 100.0 110.0 120.5 128.6 144.5 152.0 167.4 183.8 208.3 215.9 257.8 296.4	10.7 11.7 13.0 15.0 16.0 17.7 19.1 21.2 22.3 23.8 25.6 30.6 35.5 37.1 38.8	232.5 253.4 283.0 325.4 348.6 385.7 416.4 497.6 531.9 567.5 687.5 793.9 827.4 860.1	81.0 93.1 105.1 115.6 126.7 135.3 151.7 159.5 181.2 199.1 224.9 234.4 279.1 298.8 320.7	9.9 10.8 12.1 13.9 14.9 16.5 17.8 19.8 21.2 22.7 24.2 29.4 33.9 35.3 36.7	213.0 232.2 259.6 299.5 321.2 355.5 384.7 430.3 472.8 505.7 541.3 655.1 751.9	85.0 98.6 111.3 122.0 134.1 143.0 160.4 196.9 215.8 243.9 254.9 302.9 302.9 303.8 347.6	9.1 9.9 11.1 12.8 13.7 15.2 16.4 18.4 20.2 21.6 23.1 28.0 32.1 33.6 35.0	193.5 211.6 237.2 273.7 293.9 325.8 354.0 396.2 442.7 478.5 505.0 619.1 713.8 745.5 775.3	90.6 105.0 118.5 130.0 143.0 152.5 170.9 179.1 213.3 234.8 264.7 277.1 329.5 352.4 378.8	8.3 9.0 10.1 11.7 12.5 13.9 15.1 16.9 18.9 20.4 21.6 26.4 30.5 31.8
9	086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 094 074 (1) and 042 074 (1) and 052 074 074 084 084 084 084 (2) and 094 094	(1) (1) (1) (1) (1) (2) (2) (2) (2) (1) (3)	276.7 302.6 337.5 385.5 413.6 455.2 491.5 544.7 555.6 595.7 642.6 880.7 921.6 966.2	75.0 86.1 97.2 106.6 116.5 124.5 140.6 147.5 156.9 172.6 196.3 201.4 241.1 258.5 278.5	27.4 32.5 37.6 39.4	259.2 283.3 315.5 362.1 388.4 428.3 462.3 514.2 536.9 575.1 617.7 737.3 854.4 893.4	78.6 90.4 102.0 112.2 122.9 131.1 147.2 154.8 169.6 186.6 211.5 219.0 261.5 280.1 301.2	11.1 12.1 13.5 15.5 16.6 18.3 19.7 22.0 22.9 24.6 26.4 31.5 36.5 38.2	241.1 262.6 292.9 337.2 360.9 399.5 431.1 481.7 512.5 548.0 583.4 708.1 819.9 854.2 888.1	82.5 94.9 94.9 106.9 117.7 129.1 137.8 154.2 162.4 183.7 201.9 228.2 237.8 283.0 303.1 325.5	10.3 11.2 12.5 14.4 15.4 17.1 18.4 20.6 21.9 23.4 24.9 30.2 35.0 36.5 37.9	221.2 240.9 269.0 310.5 332.4 368.7 398.0 446.5 447.3 521.2 557.5 675.9 775.9 775.9 808.6 843.0	86.6 100.1 113.2 123.9 136.1 145.0 162.9 170.6 199.7 247.2 258.3 307.3 328.5 352.7	9.4 10.3 11.5 13.3 14.2 15.7 17.0 19.1 20.8 22.3 23.8 28.9 33.1 34.5 36.0	779.3 201.1 219.4 240.6 283.8 304.0 337.6 358.8 410.4 447.6 448.6 503.5 638.1 735.3 767.8 798.1	92.0 106.5 119.0 131.8 144.9 154.5 171.6 181.4 214.1 236.7 264.3 280.8 333.4 356.3 383.2	33.1 8.6 9.4 10.3 12.1 13.0 14.4 15.3 17.5 19.1 20.9 21.5 27.3 31.4 32.8 34.1




## **COMBINATION RATINGS (cont)**

50 Hz, SI (cont)


	UNIT SIZE 30HXA	09DK AIR-COOLED CONDENSER Unit (Qty)		T	CONDENSER ENTERING AIR TEMPERATURE (C)													
LCWT (C)				30			35			40			45			50		
				Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Cap.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)	Сар.	Input kW	Cooler Flow Rate (L/s)
10	076 086 096 106 116 126 136 146 161 171 186 206 246 246 271	084 084 094 074 (1) and 04- 074 (1) and 05- 074 074 084 084 084 084 084 (2) and 09- 094	<u> </u>	285.8 312.4 348.1 398.1 426.8 469.9 507.2 562.5 570.9 612.1 660.2 781.9 904.6 946.5 991.6	76.5 87.8 99.1 108.8 119.0 127.1 143.4 150.5 159.2 175.2 199.5 204.2 244.2 262.1 282.7	12.2 13.3 14.9 17.0 18.2 20.1 21.7 24.4 26.2 28.2 33.4 40.4 42.4	268.1 292.3 326.1 374.1 401.2 442.5 477.6 531.5 552.6 591.8 636.5 758.1 878.4 918.3 960.3	80.1 92.2 103.9 114.3 125.3 133.5 150.0 157.6 172.0 189.3 214.7 222.1 265.2 284.2 305.9	11.5 12.5 13.9 16.0 17.1 18.9 20.4 22.7 23.6 27.2 32.4 37.5 39.2 41.0	249.4 271.8 302.8 348.6 373.6 413.4 445.8 445.5 527.5 564.5 601.1 729.3 843.8 881.3 916.2	84.1 96.7 109.0 120.0 131.5 140.4 157.0 165.4 186.7 205.0 232.1 240.9 287.4 307.5 330.5	10.7 11.6 12.9 14.9 16.0 17.7 19.1 21.3 22.5 24.1 25.7 31.2 36.1 37.7 39.2	229.2 249.6 278.6 321.7 344.5 381.8 412.4 462.4 501.8 536.0 572.7 697.0 798.8 831.8 866.3	88.2 101.8 115.0 125.9 138.1 147.4 165.6 173.3 202.6 222.0 251.2 261.8 311.6 333.2 357.8	9.8 10.7 11.9 13.7 16.3 17.6 19.8 21.4 22.9 24.5 29.8 34.1 35.5 37.0	208.7 227.3 244.1 294.0 315.1 349.9 363.9 425.5 452.7 494.8 502.0 657.5 756.7 790.5	93.4 108.0 119.6 133.6 146.8 156.6 172.4 183.8 215.0 237.5 263.9 284.3 337.9 360.6 388.0	8.9 9.7 10.4 12.6 13.5 15.0 15.6 18.2 19.3 21.1 21.5 28.1 32.3 33.8 35.1
13	126 136 146 161 171 186 206 246 261 271	084 084 094 074 (1) and 04/ 074 (7) and 05/ 074 074 084 084 084 084 084 084 (2) and 094 094	<u> </u>	301.0 325.8 365.6 415.1 448.1 501.9 536.7 601.1 595.9 644.1 689.4 813.4 942.1 980.7 1027.0	79.0 90.1 102.2 111.9 122.3 132.3 156.5 162.6 180.5 204.5 208.5 249.0 266.7 287.8	12.9 13.9 15.6 17.8 19.2 21.5 23.0 25.7 25.5 29.5 34.8 40.3 42.0 43.9	282.8 305.6 342.9 390.6 421.4 469.3 506.2 563.7 576.5 623.5 665.0 784.4 915.2 996.0	82.5 94.5 107.3 117.3 129.0 138.1 155.2 163.0 176.2 195.1 220.6 226.3 271.4 289.6 312.4	12.1 13.1 14.7 16.7 18.0 20.1 21.7 24.1 24.7 26.7 28.4 33.6 39.2 40.8 42.6	258.8 284.2 319.1 364.7 393.6 439.6 5530.0 552.0 598.2 631.1 756.6 882.0 917.2 955.0	85.8 99.2 112.3 123.1 135.4 145.2 162.5 171.0 190.8 211.2 238.2 245.1 293.9 313.5 336.8	11.1 12.2 13.7 15.6 16.8 18.8 20.2 22.7 23.6 25.6 27.0 32.4 37.7 39.2 40.9	238.6 261.4 291.3 337.4 363.7 403.2 439.0 523.4 560.7 593.9 722.8 831.4 866.0 898.5	89.9 104.1 117.4 128.8 141.8 151.3 170.7 179.1 1222.3 231.8 286.1 267.0 318.3 340.5 365.5	10.2 11.2 12.5 14.4 15.6 17.2 18.8 21.1 22.4 24.0 25.4 30.9 35.6 37.0 38.4	217.2 238.4 250.7 308.4 332.8 369.9 377.1 450.1 502.2 501.6 678.2 780.6 814.5 841.9	94.8 110.1 120.7 136.2 150.1 159.8 174.4 187.5 216.8 239.1 263.8 288.2 355.4 386.4 392.4	9.3 10.2 10.7 13.2 14.2 15.8 16.1 19.3 19.7 21.5 21.5 29.0 33.4 34.8 36.0
16	086 096 106 116 126 136 146 161 171 186 206 246 261	084 084 074 (1) and 044 074 (1) and 054 074 074 074 084 084 084 084 084 (2) and 094 094	111111111111111111111111111111111111111	298.2 328.3 362.2 418.6 451.6 532.0 95.7 599.7 639.3 689.0 943.4 987.1 1033.6	78.5 90.6 101.6 112.4 123.6 131.5 147.5 155.6 163.3 179.7 204.6 208.4 249.0 267.6 288.8	12.8 14.1 15.5 17.9 19.3 21.3 22.8 25.5 25.7 27.4 29.5 34.9 40.4 42.3 44.3	279.8 307.8 339.9 393.6 420.5 468.7 501.6 563.0 580.4 618.9 664.8 789.7 907.8 958.9 1002.6	82.0 95.0 106.6 117.8 128.8 137.9 154.2 162.9 176.8 194.1 220.5 270.0 270.3 290.7 313.6	12.0 13.2 14.6 16.9 18.0 20.1 21.5 24.1 24.9 26.5 28.5 33.8 38.9 41.1	260.8 283.8 316.0 367.9 392.7 438.7 468.9 529.4 550.9 593.2 631.1 761.8 874.6 923.5 962.2	86.2 99.1 111.7 123.7 135.2 145.0 161.5 170.8 190.5 210.2 238.0 245.9 292.6 314.6 338.0	11.2 12.2 13.5 15.8 16.8 18.8 20.1 22.7 23.6 25.4 27.0 32.6 37.4 39.5 41.2	240.6 261.4 291.6 333.4 362.3 406.6 434.5 492.5 524.0 559.5 591.7 728.2 828.4 862.8 905.2	90.3 104.0 117.4 128.1 141.6 152.0 169.8 213.0 238.2 267.0 267.0 267.2 339.7 366.1	10.3 11.2 12.5 14.3 15.5 17.4 18.6 21.1 22.4 24.0 25.3 31.2 35.5 36.9 38.8	219.1 238.4 250.5 305.4 331.8 373.0 376.2 465.0 501.9 501.1 683.3 778.9 813.5	95.1 109.9 120.5 135.5 150.0 160.5 174.3 188.2 217.4 239.0 263.7 289.5 350.0 374.1	9.4 10.2 10.7 13.1 14.2 16.0 16.1 19.4 19.9 21.5 21.5 29.3 33.3 34.8





# Performance data (cont






## Typical piping and wiring


Cooler (30HXA, HXC) and condenser (30HXC only





## Typical piping and wiring (cont





## **Electrical data**



### **ELECTRICAL DATA, 30HXC UNITS**

	UNIT V	OLTA	GE	POWER	NO. POWER			UNIT	VOLTAG	Ε			ONT	ROL CI	RCUIT
UNIT 30HXC	V-Hz	Su	pplied	SUPPLY	SUPPLY				ICF	Rec F	use Size		_	pplied	
	(3 Ph)	Min	Max	QTY. REQD.	CONDUCTORS	MCA	MOCP	XL	WD	XL	WD	(Single		<del>'</del>	MCA and MOCP
076	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1	3 3 3 3 3 3 3	198.7 220.7 99.7 79.7 120.8 125.6 207.2	250 300 125 110 150 175 250	374.3 299.4 418.7 399.8	118.4		225 250 125 90 150 150 250	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 254 254	15 15 15 15 15 15
086	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1	3 3 3 3 3 3 3	221.7 246.4 111.3 88.9 134.8 140.4 231.9	300 350 150 125 175 200 300	374.3 299.4 418.7 478.8	118.4 168.7	125 100 175 175	250 300 125 100 175 175 300	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254	15 15 15 15 15 15 15
096	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	3 3 3 3 3 3 3	251.3 279.2 126.2 100.8 152.7 157.9 260.7	350 400 175 150 225 225 350	449.3 359.4 501.7 561.8	137.4 194.7	150 125 175 200	300 350 150 125 175 200 300	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
106	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1	3 3 3 3 3 3 3	285.6 317.4 143.3 114.5 173.6 178.1 294.2	400 450 200 175 250 250 450	529.3 423.4 589.7 660.8	395.3 405.1 197.3 158.4 222.7 246.8 397.1	175 150 200 225	350 400 175 150 200 225 350	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
116	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	3 3 3 3 3 3 3	304.1 337.9 152.6 121.9 184.8 190.0 313.9	450 500 225 175 250 250 450	538.6 430.8 600.9 672.7	413.7 425.6 206.6 165.8 233.9 258.7 416.8	175 150 225 225	350 400 175 150 225 225 400	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
126	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1	333333	327.7 364.2 164.5 131.4 199.1 204.0 337.0	450 500 225 175 250 300 450	550.5 440.3 615.2 686.7	437.4 451.9 218.5 175.3 248.2 272.7 439.9	200 150 225 250	400 450 200 150 225 250 400	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
136	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	3 6 3 3 3 3 6	366.7 407.4 183.8 147.1 222.8 230.2 380.3	500 600 250 200 300 300 500	645.5 536.3 720.2 796.7	497.4 511.9 248.5 199.3 282.2 307.7 495.9	225 175 300 300	450 500 225 175 300 300 450	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
146	460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	6 6 3 3 3 3 6	394.1 437.9 197.5 158.1 239.5 246.3 407.1	500 600 250 225 350 350 600	 659.2 547.3 736.9 812.8	524.9 542.4 262.2 210.3 298.9 323.8 522.7	225 200 300 300	450 500 225 200 300 300 500	115-60 115-60 115-60 115-60 230-60 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
161	208/230-60 460-60 575-60 380-60 380/415-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1 1	3 3 3	398.7 443.0 200.1 159.9 242.2 249.0 411.3	225 350		574.8 590.6 287.2 229.9 325.2 358.2 577.7		200 300 300	115-60 115-60 115-60 230-60 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15



### ELECTRICAL DATA, 30HXC UNITS (cont)

	UNIT VO	LTAG	E	POWER	NO, POWER			UNIT	OLTAG	E		C	ONTE	OL CI	CUIT
UNIT 30HXC	V-Hz	Sup	plied	SUPPLY	SUPPLY			1	F	1	ise Size	V-Hz		pplied	
-	(3 Ph)	Min	Max	QTY. REQD.	CONDUCTORS	MCA	MOCP	XL	WD	XL	WD	(Single	Min	<del></del>	MCA and MOCP
171	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	6 6 3 3 3 3 6	428.4 476.0 215.0 171.8 260.2 266.6 440.4	600 700 300 250 350 350 600	771.1 616.8 861.2 961.8	604.5 623.6 302.1 241.8 343.2 375.8 606.8	250 200 300 300	500 600 250 200 300 300 500	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
186	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	6 6 3 3 3 6	462.3 513.7 232.0 185.4 280.8 289.4 478.1	600 700 300 250 400 400 600	788.1 630.4 881.8 984.6	638.5 661.3 319.1 255.4 363.8 398.6 644.5	300 225 350 350	600 600 300 225 350 350 600	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
206	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1	6633336	524.5 582.8 263.2 210.4 318.6 326.8 539.8	700 800 350 250 400 450 700	819.3 655.4 919.6 1022.0	700.7 730.4 350.3 280.4 401.6 436.0 706.2	300 250 350 400	600 700 300 250 350 400 600	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
246		207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1	6633336	604.1 671.3 303.2 242.3 367.0 377.6 623.8	800 800 400 300 450 500 800	859.3 687.3 968.0 1072.8	780.3 818.9 390.3 312.3 450.0 486.8 790.2	350 300 400 450	700 800 350 300 400 450 700	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
261	208/230-60 460-60 575-60 380-60 380/415-50 230-50	342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	6633666	633.8 704.3 318.1 254.2 385.0 395.2 652.9	800 800 400 300 500 500	874.2 699.2 986.0 1090.4	810.0 851.9 405.2 324.2 468.0 504.4 819.3	350 300 450 450	700 800 350 300 450 450 800	115-60 115-60 115-60 115-60 230-60 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
271	208/230-60 460-60 575-60 380-60 380/415-50	187 414 518 342 342	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1 1	3 3 6	667.8 742.0 335.1 267.8 405.6 418.0 690.6		 891.2 712.8 1006.6 1113.2	843.9 889.6 422.2 337.8 488.6 527.2 857.0		800 800 400 300 450 500	115-60 115-60 115-60 115-60 230-60 230-50	104 104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15

#### LEGEND

Maximum Instantaneous Current Flow during start-up (the point in the starting sequence where the sum of the LRA for the start-up compressor, plus the total RLA for all running compressors is at a maximum)
Locked Rotor Amps
Minimum Circuit Ampacity (for wire sizing)
Maximum Overcurrent Protection
Rated Load Amps ICF

LRA MCA MOCP

RLA WD XL Rated Load Amps Wye-Delta Start Across-the-Line Start

NOTES:

1. Each main power source must be supplied from a field-supplied fused electrical service with a (factory-installed or field-installed) disconnect located in sight from the unit.

2. Control circuit power must be supplied from a separate source through a field-supplied disconnect (except for 380/415-50 units). An accessory control transformer may be used to provide control circuit power from the main unit power supply.

- Maximum incoming wire size for each terminal block is 500 kcmil. Maximum allowable phase imbalance is: voltage, 2%; amps, 5%. Use copper conductors only. The MOCP is calculated as follows:

MOCP = (2.25) (largest RLA) + the sum of the other RLAs. Size the fuse one size down from the result. The RLAs are listed on the nameplate.

The recommended fuse size in amps (RFA) is calculated as follows: RFA = (1.50) (largest RLA) + the sum of the other RLAs. Size the fuse one size up from the result. The RLAs are listed on the nameplate.







### ELECTRICAL DATA, 30HXA UNITS

	UNIT V	OLT	AGE	POWER	NO. POWER			UNI	T VOLTAG	E		Т (	CONTI	ROL CI	CUIT
UNIT 30HX	Δ V-Hz		upplie	SUPPLY	SUPPLY	MCA	мос		ICF		use Siz	e V-Hz	Su	pplied	MCA and
	(3 Ph)	Mi		^	A SASTANDAM			XL	WD	XL	WD	(Singl	Mir	Max	MOCP
076	208/230-60 460-60 575-60 380-60 380/415-50 230-50	41 51 34 34 20	7 25 4 50 8 63 2 41 2 44 7 25	3 1 6 1 3 1 8 1 0 1	3 3 3 3 3 3 3	291.2 323.6 146.0 116.8 177.1 183.4 303.3	450 200 3 150 250 4 250	549 439 614 686	.9 174.9 .7 247.7	175 150 200 225	350 400 175 150 200 225 350		104 104 104 104 108 198	127 127 127 127 254 254	15 15 15 15 15 15
086	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	51 34	7 25 4 50 8 63 2 41 2 44	3 1 3 1 3 1	3 3 3 3 3 3 3	322.8 358.7 161.9 129.5 196.2 205.5 339.7	500 225 175 250 300		9 198.9 7 281.7	200 150 225 250	400 450 200 150 225 250 400	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198	127 127 127 127 127 254	15 15 15 15 15 15 15
096	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	414 518 342 342 207	7 25: 4 50: 3 63: 2 41: 2 44: 2 25:	1 1 1 1 1 1	3633336	365.4 406.1 183.4 146.5 222.1 231.4 382.6	600 250 200 300 350 500	749. 599. 835. 937.	562.4 576.8 9 280.9 9 224.9 7 317.7	_	450 500 225 175 300 300 450	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
106	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 506 633 418 440	1 1 1	6 6 3 3 3 6	416.9 463.2 209.2 167.2 253.3 263.3 435.1	600 700 300 250 350 400 600	884.9 707.9 984.7	258.9	250 200 300 300	500 600 250 200 300 300 500	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15
116	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	506 633 418 440 253	1 1 1 1 1 1	6 6 3 3 3 3 6	442.1 491.3 221.9 177.4 268.6 281.0 464.2	600 700 300 250 400 400 700	897.6 718.1 1000.0 1059.2	672.7 689.9 336.6 269.1 380.0	300 225 350 350	500 600 300 225 350 350 600	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
126	230-60 208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	6633336	476.3 529.2 239.1 191.0 289.3 301.7 498.5	700 700 350 250 400 400 700	914.8 731.7 1020.7 1079.9	706.8 727.8 353.8 282.7 400.7	300 225 350 350	600 600 300 225 350 350 600	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
136		207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	6633336	539.1 599.1 270.7 216.2 327.5 343.4 567.3	800 800 400 300 450 500 800	1014.8 811.7 1131.7 1345.9	769.8 790.8 385.8 308.7 435.7 506.9 817.2	350 250 400 400	700 700 350 250 400 400 700	115-60 115-60 115-60 115-60 230-60 230-50 230-50	104 104 104 104 207 198 207	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
146	208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1 1	6633336	580.3 644.8 291.3 232.7 352.5 368.9 609.3	800 800 400 300 500 500 800	1035.4 828.2 1156.7 1371.4	811.0 836.5 406.4 325.2 460.7 532.4 859.2	350 300 400 450	700 800 350 300 400 450 700	115-60 115-60 115-60 115-60 230-60 230-50	104 104 104 104 207 198	127 127 127 127 127 254 254 254	15 15 15 15 15 15 15
161	208/230-60 460-60 575-60 380-60 380/415-50 230-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1 1 1 1		605.6 672.9 304.0 242.9 368.0 384.9 635.7	800 1000 450 350 500 500 800	1281.6 1025.1 1428.0 1398.4	955.3 978.9 477.6 382.1 539.0 533.4 858.3	350 300 450 450	700 800 350 300 450 450 800	115-60 115-60 115-60 115-60 230-60 230-50	104 104 104 104 207 198	127 127 127 127 127 127 254 254	15 15 15 15 15 15 15
171	208/230-60 460-60 575-60 380-60 380/415-50	207 187 414 518 342 342 207	253 253 506 633 418 440 253	1 1 1 1 1 1	6 3 3 6 6	651.5 723.9 327.0 261.4 395.9 413.2 682.6	350 500	1304.6 1043.6 1455.9 1426.7	1001.2 1029.9 500.6 400.6 566.9 561.7 905.2	 400 300 450 500	800 1000 400 300 450 500 800	115-60 115-60 115-60 115-60 230-60 230-50	104 104 104 104 207 2198	127 127 127 127 127 127 254 254	15 15 15 15 15 15 15 15



#### ELECTRICAL DATA, 30HXA UNITS (cont)

	UNITV	OLTA	GE	DOWER	No Ferri	1	-	UNIT	VOLTAGI	Ē			ONTO	OL CII	PCUIT
UNIT 30HXA	V-Hz	Su	pplied	POWER	NO. POWER SUPPLY		1		CF		use Size			oplied	
JUITA	(3 Ph)	Min	Max	QTY. REQD.	CONDUCTORS	MÇA	МОСР	XL	WD	XL	WD	(Single		_	MCA and MOCP
	230-60 208/230-60 Ckt A Ckt B	207 187 187	253 253	1 1 1	6 6 6	707.9 437.0 437.0	700 700 700	=	1057.6 743.0 743.0	_	800 600 600	115-60 115-60	104 104		15 15
186	460-60 575-60 380-60 380/415-50 230-50	414 518 342 342 207	633 418	1 1 1 1	3 3 6 6 6	355.3 284.0 430.2 452.7 747.7	500 400 600 600 1000	1332.9 1066.2 1490.2 1466.2	528.9 423.2 601.2	400 350 500 600	400 350 500 600 1000	115-60 115-60 230-60 230-50 230-50	104 104 207 198 207	127 127 254 254 254	15 15 15 15 15
	230-60 Ckt A Ckt B 208/230-60	207 207	253 253	1	6 3	468.6 379.8	700.0 600.0	=	726.8 743.0	1.	600 500	115-60	104	127	15
206	Ckt A Ckt B 460-60 575-60 380-60 380/415-50 230-50	187 187 414 518 342 342	253 253 506 633 418 440	1 1 1 1 1	6 6 3 6	520.6 422.0 400.1 319.9 484.4 505.2	800.0 700.0 500.0 400.0 600.0 700.0	1377.7 1102.1 1544.4 1518.7	743.0 743.0 573.7 459.1 655.4 653.7	 450 400 600 600	600 600 450 400 600 600	115-60 115-60 115-60 230-60 230-50	104 104 104 207 198	127 127 127 254 254	15 15 15 15 15
	Ckt A Ckt B	207 207	253 253	1	6 6	486.0 415.4	700.0 700.0	=	771.0 638.0		600 500	230-50	207	254	15
	230-60 Ckt A Ckt B 208/230-60	207 207	253 253	- 1	6 3	592.1 379.8	800.0 600.0	=	955.3 743.0	1.1	700 500	115-60	104	127	15
246	Ckt A Ckt B 460-60 575-60 380-60 380/415-50 230-50	187 187 414 518 342 342	253 253 506 633 418 440	1 1 1 1 1	666366	657.9 422.0 461.9 369.1 559.2 586.1	800.0 700.0 600.0 450.0 700.0 700.0	1439.5 1151.3 1619.2 1599.6	978.9 743.0 635.5 508.3 730.2 734.6	 600 450 700 700	800 600 600 450 700 700	115-60 115-60 115-60 230-60 230-50	104 104 104 207 198	127 127 127 254 254	15 15 15 15
	Ckt A Ckt B	207 207	253 253	1 1	6 6	635.7 415.4	800.0 700.0		858.3 638.0	_	800 500	230-50	207	254	15
	230-60 Ckt A Ckt B 208/230-60	207 207	253 253	1 1	6· 3	638.0 379.8	800.0 600.0	=	1001.2 743.0	=	800 500	115-60	104	127	15
261	Ckt A Ckt B 460-60	187 187 414	253 253 506	1	6 6 6	708.9 422.0 484.9	1000.0 700.0 600.0	 1462.5	1029.9 743.0 658.5	_ 600	800 600 600	115-60 115-60	104	127	15 15
	575-60 380-60 380/415-50 230-50	518 342 342	633 418 440	1	6 6 6	387.6 587.1 614.4	500.0 700.0 800.0	1169.8 1647.1 1627.9	526.8 758.1 762.9	450 700 700	450 700 700	115-60 230-60 230-50 230-50	104 207 198 207	127 254 254	15 15 15 15
	Ckt A Ckt B	207 207	253 253	1	6 6	682.6 415.4	1000.0 700.0	='	905.2 638.0	=	800 500	230-30	207	254	15
	208/230-60	207 207	253 253	1 1		683.6 379.8	800.0 600.0	=	1046.8 743.0	=	800 500	115-60	104	127	15
271	Ckt B	187 187 414	253 253 506	1	6	759.6 422.0	1000.0 700.0		1080.6 743.0	=	1000 600	SMACCO CONTRACT	2000	127	15
	575-60 380-60 380/415-50 230-50	518 342 342	633 418 440	1	6 6 6	513.2 410.2 621.4 653.9	5 -5 5 5 5 5 5 5 5	1490.8 1192.4 1681.4 1667.4	686.8 549.4 792.4 802.4	600 450 700 800	600 450 700 800	115-60 230-60 230-50	104 207 198	127 127 254 254 254	15 15 15 15 15
		207	253 253	1		747.7 415.4	1000.0 700.0	_	970.3 638.0	=	1000 500				10

#### LEGEND

Maximum Instantaneous Current Flow during start-up (the point in the starting sequence where the sum of the LRA for the start-up compressor, plus the total RLA for all running compressors is at a maximum)
Locked Rotor Amps
Minimum Circuit Ampacity (for wire sizing)
Maximum Overcurrent Protection
Retad Load Amps ICF

LRA MCA MOCP

RLA WD XL Rated Load Amps Wye-Delta Start Across-the-Line Start

NOTES:
1. Each main power source must be supplied from a field-supplied fused electrical service with a (factory-installed or field-installed) disconnect located in sight from the unit.
2. Control circuit power must be supplied from a separate source through a field-supplied disconnect (except for 380/415-50 units). An accessory

control transformer may be used to provide control circuit power from the control transformer may be used to provide control circuit power in main unit power supply.

3. Maximum incoming wire size for each terminal block is 500 kcmil.

4. Maximum allowable phase imbalance is: voltage, 2%; amps, 5%.

5. Use copper conductors only.

6. The MOCP is calculated as follows:

 $\label{eq:mocp} \begin{array}{l} \text{MOCP} = (2.25) \text{ (largest RLA)} + \text{the sum of the other RLAs. Size the fuse} \\ \text{one size down from the result. The RLAs are listed on the nameplate.} \end{array}$ The recommended fuse size in amps (RFA) is calculated as follows: RFA = (1.50) (largest RLA) + the sum of the other RLAs. Size the fuse one size up from the result. The RLAs are listed on the nameplate.







### COMPRESSOR ELECTRICAL DATA, 30HXC UNITS

JNIT SIZE 30HXC	NAMEPLATE V-Hz		N1	SOR NUMBERS	
	(3 Phase)	RLA	LRA		31
	208/230-60	*	*	RLA	LRA
	230-60			•	*
i i	460-60	44.3	330	44.3	
076-XL	575-60	35.4	264	35.4	330
	380-60	53.7	365	53.7	264
İ	230-50	*	*	\$ \$3.7	365
	380/415-50	55.8	344	55.8	344
	208/230-60	98.1	209	98.1	209
	230-60	88.3	209	88.3	209
	460-60	44.3	104	44.3	104
076-WD	575-60	35.4	83	35.4	83
	380-60	53.7	115	53.7	115
	230-50	92.1	174	92.1	174
	380/415-50	55.8	109	55.8	109
	208/230-60	*	*	*	*
	230-60	*:	*		*
	460-60	53.6	330	44.3	330 .
086-XL	575-60	42.8	264	35.4	264
	380-60	64.9	365	53.7	365
	230-50	*		*	*
	380/415-50	67.7	423	55.8	344
	208/230-60	118.6	209	98.1	209
	230-60	106.7	209	88.3	209
	460-60	53.6	104	44.3	104
086-WD	575-60	42.8	83	35.4	83
	380-60	64.9	115	53.7	115
	230-50	111.8	213	92.1	174
	380/415-50	67.7	134	55.8	109
_	208/230-60				
_	230-60	*	*		*
	460-60	65.5	405	44.3	330
096-XL	575-60	52.3	324	35.4	264
	380-60	79.2	448	53.7	365
	230-50	*	*	*	*
	380/415-50	81.7	506	55.8	344
	208/230-60	144.9	256	98.1	209
-	230-60	130.4	256	88.3	209
	460-60	65.5	128	44.3	104
096-WD	575-60	52.3	102	35.4	83
⊢	380-60 230-50	79.2	141	53.7	115
-	380/415-50	134.9	255	92.1	174
	208/230-60	81.7	160	55.8	109
-	230-60		•	*	•
	460-60	79.2		*	•
106-XL	575-60		485	44.3	330
	380-60	63.3 95.9	388	35.4	264
<del>-</del>	230-50	95.9	536	53.7	365
	380/415-50	97.8			*
	208/230-60	175.4	605	55.8	344
-	230-60	157.9	307	98.1	209
	460-60	79.2	307	88.3	209
106-WD	575-60	63.3	153	44.3	104
	380-60	95.9	123	35.4	83
-	230-50	161.7	169	53.7	115
	380/415-50	97.8	305 191	92.1	174

LEGEND

LRA RLA WD XL Locked Rotor Amps
 Rated Load Amps
 Wye-Delta Start
 Across-the-Line Start

<sup>\*</sup>Units are shipped with wye-delta start as standard. Across-the-line start is not available.



### COMPRESSOR ELECTRICAL DATA, 30HXC UNITS (cont)

UNIT SIZE 30HXC	NAMEPLATE V-Hz		A1	OR NUMBERS	
	(3 Phase)	RLA	LRA		B1
	208/230-60		± that	RLA	LRA
	230-60	*	*	*	
	460-60	79.2	485	53.6	
116-XL	575-60	63.3	388	42.8	330
	380-60	95.9	536	64.9	264
	230-50	*	*	*	365
	380/415-50	97.8	605	67.7	
	208/230-60	175.4	307	118.6	423
1	230-60	157.9	307	106.7	209
	460-60	79.2	153	53.6	209
116-WD	575-60	63.3	123	42.8	104
,,,,,,,,,	380-60	95.9	169	64.9	83
	230-50	161.7	305		115
	380/415-50	97.8	191	111.8	213
	208/230-60	*	191	67.7	134
-	230-60	<del></del>		*	
	460-60	79.2	485	65.5	
126-XL	575-60	63.3	388	52.3	405
	380-60	95.9	536	79.2	324
	230-50		*	15.2	448
	380/415-50	97.8	605	81.7	
	208/230-60	175.4	307	144.9	506
	230-60	157.9	307	130.4	256
	460-60	79.2	153	65.5	256
126-WD	575-60	63.3	123	52.3	128
	380-60	95.9	169	79.2	102
	230-50	161.7	305	134.9	141
	380/415-50	97.8	191	81.7.	255
	208/230-60	*	*	*	160
	230-60	•		,	*
	460-60	94.6	580	65.5	405
136-XL	575-60	75.8	484	52.3	324
	380-60	114.9	641	79.2	448
	230-50	•	*	*	+
	380/415-50	118.8	715	81.7	506
	208/230-60	210.0	367	144.9	256
	230-60	189.0	367	130.4	256
	460-60	94.6	183	65.5	128
136-WD	575-60	75.8	147	52.3	102
	380-60	114.9	203	79.2	141
	230-50	196.3	361	134.9	255
	380/415-50	118.8	226	81.7	160
	208/230-60	•	*		*
	230-60	*	*		*
	460-60	94.6	580	79.2	485
146-XL	575-60	75.8	484	63.3	388
	380-60	114.9	641	95.9	536
	230-50	*	•	-	*
	380/415-50	118.8	715	97.8	605
	208/230-60	210.0	367	175.4	307
	230-60	189.0	367	157.9	307
	460-60	94.6	183	79.2	153
146-WD	575-60	75.8	147	63.3	123
	380-60	114.9	203	95.9	169
×	230-50	196.3	361	161.7-	305
	380/415-50	118.8	226	97.8	191

LEGEND

<sup>\*</sup>Units are shipped with wye-delta start as standard. Across-the-line start is not available.



### COMPRESSOR ELECTRICAL DATA, 30HXC UNITS (cont)

HAUT CITE COLUVO	NAMEPLATE		COMPRESSO	R NUMBERS	
UNIT SIZE 30HXC	V-Hz	A		В	1
	(3 Phase)	RLA	LRA	RLA	LRA
<u> </u>	208/230-60			•	
_	230-60	*	•	•	
4C4 VI	460-60	103.1	685	71.2	525
161-XL	575-60	82.4	548	56.9	420
-	380-60	124.8	757	86.2	580
	230-50	*	*	•	
	380/415-50	128.6	856	88.2	. 600
-	208/230-60	228.8	433	157.6	350
	230-60	205.5	433	141.8	350
	460-60	103.1	216	71.2	175
161-WD	575-60	82.4	173	56.9	140
_	380-60	124.8	239	86.2	193
-	230-50	212.5	432	145.7	348
	380/415-50	128.6	270	88.2	200
<u> </u>	208/230-60	*	_	*	*
	230-60			*	
171 VI	460-60	86.1	580	103.1	685
171-XL	575-60	68.8	484	82.4	548
-	380-60	104.2	641	124.8	757
~ 1	230-50		*	*	*
	380/415-50	105.8	715	128.6	856
-	208/230-60	190.6	367	228.8	433
· -	230-60	171.5	367	205.5	433
1000 0000	460-60	86.1	183	103.1	216
171-WD	575-60	68.8	147	82.4	173
-	380-60	104.2	203	124.8	239
-	230-50	174.8	361	212.5	432
	380/415-50	105.8	233	128.6	270
	208/230-60	*			
	230-60	*	•	*	
112120000000000000000000000000000000000	. 460-60	103.1	685	103.1	685
186-XL	575-60	82.4	548	82.4	548
	380-60	124.8	757	124.8	757
	230-50	*		*	
	380/415-50	128.6	856	128.6	856
-	208/230-60	228.8	433	228.8	433
	230-60	205.5	433	205.5	433
	460-60	103.1	216	103.1	216
186-WD	575-60	82.4	173	82.4	173
	380-60	124.8	239	124.8	239
	230-50	212.5	432	212.5	432
	380/415-50	128.6	270	128.6	270

LEGEND

LRA — Locked Rotor Amps
RLA — Rated Load Amps
WD — Wye-Delta Start
XL — Across-the-Line Start

\*Units are shipped with wye-delta start as standard. Across-the-line start is not available.



### COMPRESSOR ELECTRICAL DATA, 30HXC UNITS (cont)

<b>UNIT SIZE</b>	NAMEPLATE				OR NUMBERS		
30HXC	V-Hz (3 Phase)	RLA	A1		A2		31
	208/230-60	nLA *	LRA	RLA	LRA	RLA	LRA
	230-60	*		-	*	*	*
	460-60	86.1	580			*	*
206-XL	575-60	68.8	484	48.2	350	103.1	685
	380-60	104.2	641	38.6	280	82.4	548
	230-50	*	*	58.4	390	124.8	757
	380/415-50	105.8	715				*
	208/230-60	190.6	367	55.8 106.8	344	128.6	856
	230-60	171.5	367	96.1	233	228.8	433
	460-60	86.1	183	48.2	117	205.5	433
206-WD	575-60	68.8	147	38.6	93	103.1	216
	380-60	104.2	203	58.4	130	82.4 124.8	173
	230-50	174.8	361	99.4	260	212.5	239
	380/415-50	105.8	226	60.2	150	128.6	432
	208/230-60	*	*	•	*	120.0	270
	230-60	*	•				*
	460-60	103.1	685	71.2	485	103,1	685
246-XL	575-60	82.4	548	56.9	388	82,4	548
	380-60	124.8	757	86.2	536	124.8	757
	230-50			*	*	124.0	*
	380/415-50	128.6	856	88.2	605	128.6	856
	208/230-60	228.8	433	157.6	307	228.8	433
	230-60	205.5	433	141.8	307	205.5	433
	460-60	103.1	216	71.2	153	103.1	216
246-WD	575-60	82.4	173	56.9	123	82.4	173
	380-60	124.8	239	86.2	169	124.8	239
	230-50	212.5	432	145.7	305	212.5	432
	380/415-50	128.6	270	88.2	191	128.6	270
	208/230-60	*	•	•	*		
	230-60	•	•		*		•
004 VI	460-60	103.1	685	86.1	580	103.1	685
261-XL	575-60	82.4	548	. 68.8	484	82.4	548
	380-60	124.8	757 .	104.2	641	124.8	757
	230-50 380/415-50			•	*	•	•
	208/230-60	128.6 228.8	856	105.8	715	128.6	856
	230-60	205.5	433	190.6	367	228.8	433
	460-60	103.1	433	171.5	367	205.5	433
261-WD	575-60	82,4	216 173	86.1	183	103.1	216
	380-60	124.8	239	68.8	147	82.4	173
t	230-50	212.5	432	104.2 174.8	203	124.8	239
ŀ	380/415-50	128.6	270	105.8	361	212.5	432
	208/230-60	*	*	105.6	226	128.6	270
1	230-60	*	*		*	-	
	460-60	103.1	685	103.1	685		000
271-XL	575-60	82.4	548	82.4	548	103.1	685
Ī	380-60	124.8	757	124.8	757	124.8	548
	230-50	•	*	*	*	124.8	757
	380/415-50	128.6	856	128.6	856	128.6	
	208/230-60	228.8	433	228.8	433	228.8	856 433
	230-60	205.5	433	205.5	433	205.5	433
	460-60	103.1	216	103.1	216	103.1	216
271-WD	575-60	82.4	173	82.4	173	82.4	173
	380-60	124.8	239	124.8	239	124.8	239
	230-50	212.5	432	212.5	432	212.5	432
	380/415-50	128.6	270	128.6	270	128.6	270

**LEGEND** 

<sup>\*</sup>Units are shipped with wye-delta start as standard. Across-the-line start is not available.



### COMPRESSOR ELECTRICAL DATA, 30HXA UNITS

UNIT SIZE 30HXA	NAMEPLATE V-Hz	<b> </b>	COMPRESSO		
omi onen omini	(3 Phase)	RLA	1	B	
	208/230-60	MLA .	LRA	RLA	LRA
<u> </u>	230-60				*
	460-60	64.9			
076-XL	575-60	51.9	485 388	64.9	48
	380-60	78.7	536	51.9	388
	230-50	*	*	78.7	536
	380/415-50	81.5	605		
	208/230-60	143.8	307	81.5	605
	230-60	129,4	307	143.8 129.4	307
	460-60	64.9	153	64.9	307
076-WD	575-60	51.9	123	51.9	153
AUT 4.10 _ 1450.50 P	380-60	78.7	169	78.7	123
	230-50	134.8	305	134.8	169
1.5	380/415-50	81.5	191	81.5	305
1000	208/230-60	*	101	*	191
	230-60		*	*	
	460-60	77.6	580	64.9	
086-XL	575-60	62.1	484	51.9	485 388
	380-60	94.0	641	78.7	536
	230-50		*	*	#
	380/415-50	99.2	715	81.5	605
	208/230-60	171.9	367	143.8	307
	230-60	154.7	367	129.4	307
	460-60	77.6	183	64.9	153
086-WD	575-60	62.1	147	51.9	123
	380-60	94.0	203	78.7	169
	230-50	163.9	361	134.8	305
	380/415-50	99.2	226	81.5	191
	208/230-60	•	*	*	191
	230-60		*		-
	460-60	94.8	685	64.9	485
096-XL	575-60	75.7	548	51.9	388
	380-60	114.7	757	78.7	536
	230-50		*	•	*
	380/415-50	119.9	856	81.5	605
	208/230-60	209.8	433	143.8	307
	230-60	188.8	433	129.4	307
	460-60	94.8	216	64.9	153
096-WD	575-60	75.7	173	51.9	123
¥	380-60	114.7	239	78.7	169
	230-50	198.2	432	134.8	305
	380/415-50	119.9	270	81.5	191
	208/230-60		•		*
	230-60		•	*	*
400 VI	460-60	115.4	820	64.9	485
106-XL	575-60	92.2	656	51.9	388
-	380-60	139.7	906	78.7	536
ļ <del></del>	230-50	*	•	*	
	380/415-50	145.4	960	81.5	605
	208/230-60	255.5	518	143.8	307
	230-60	230.0	518	129.4	307
106-WD	460-60	115.4	259	64.9	153
100-170	575-60	92.2	207	51.9	123
	380-60	139.7	286	78.7	169
	230-50	240.2	485	134.8	305
	380/415-50	145.4	303	81.5	191

LEGEND

LRA — Locked Rotor Amps
RLA — Rated Load Amps
WD — Wye-Delta Start
XL — Across-the-Line Start

\*Units are shipped with wye-delta start as standard. Across-the-line start is not available.



### COMPRESSOR ELECTRICAL DATA, 30HXA UNITS (cont)

UNIT SIZE 30HXA	NAMEPLATE V-Hz	. А	COMPRESSO		
OMIT OIZE GOTIAN	(3 Phase)	RLA		В	
	208/230-60	nLA +	LRA	RLA	LRA
-	230-60		*		*
	460-60	115.4			
116-XL	575-60	92.2	820	77.6	580
110-XL	380-60	139.7	656	62.1	484
-	230-50	109.7	906	94.0	641
	380/415-50	145,4			
	208/230-60	255.5	960	99.2	715
3	230-60	230.0	518	171.9	367
_	460-60	115.4	518 259	154.7	367
116-WD	575-60	92.2		77.6	183
110 110	380-60	139.7	207	62.1	147
_	230-50	240.2	286	94.0	203
-	380/415-50	145.4	485	163.9	361
	208/230-60	145.4	303	99.2	226
	230-60	*	<u> </u>		*
· ·	460-60	115.4			
126-XL	575-60	92.2	820	94.8	685
120-AL	380-60	139.7	656	75.7	548
	230-50	139.7	906	114.7	757
-	380/415-50	145.4			
	208/230-60	255.5	960	119.9	856
* <del> </del>	230-60		518	209.8	433
<del>-</del>	460-60	230.0 115.4	518	188.8	433
126-WD	575-60	92.2	259	94.8	216
120-110	380-60	139.7	207	75.7	173
	230-50	240.2	286	114.7	239
_	380/415-50	145.4	485	198.2	432
	208/230-60	*	303	119.9	270
-	230-60	*			- :
	460-60	140,7	920		
136-XL	575-60	112,4	736	94.8	685
130-71	380-60	170.2	1017	75.7	548
	230-50	*	*	114.7	757
	380/415-50	178.8	1226		
	208/230-60	311.4	581	119.9 209.8	856 433
	230-60	280.3	581	188.8	433
	460-60	140.7	291	94.8	The second second
136-WD	575-60	112.4	233	75.7	216 173
	380-60	170.2	321	114.7	239
	230-50	295.3	619	198.2	
1	380/415-50	178.8	387	119.9	432 270
	208/230-60	*	*	*	*
	230-60			*	
/	460-60	140.7	920	115.4	
146-XL	575-60	112.4	736	92.2	820
	380-60	170.2	1017	139.7	656 906
	230-50	*	*	*	906
	380/415-50	178.8	1226	145.4	
	208/230-60	311.4	581	255.5	960 518
3	230-60	280.3	581	230.0	518
	460-60	140.7	291	115.4	259
146-WD	575-60	112.4	233	92.2	207
and the second s	380-60	170.2	321	139.7	286
	230-50	295.3	619	240.2	485
<u> </u>	380/415-50	178.8	387	145.4	303

LEGEND

<sup>\*</sup>Units are shipped with wye-delta start as standard. Across-the-line start is not available.



### COMPRESSOR ELECTRICAL DATA, 30HXA UNITS (cont)

LINIT CITE COLLYA	NAMEPLATE			OR NUMBERS	
UNIT SIZE 30HXA	V-Hz		A1	В	1
	(3 Phase)	RLA	LRA	RLA	LRA
<b>!</b>	208/230-60	*	+	*	*
<u> </u>	230-60	•	•	* *	
404.7/1	460-60	157.9	1175	106.6	790
161-XL	575-60	126.2	940	85.1	630
	380-60	191.2	1299	129.0	870
<u></u>	230-50	,		*	
	380/415-50	201.2	1265	133.4	. 1045
<u></u>	208/230-60	349.6	743	235.9	527
	230-60	314.6	743	212.3	527
	460-60	157.9	371	106.6	263
161-WD	575-60	126.2	297	85.1	211
• -	380-60	191.2	410	129.0	290
	230-50	332.3	638	220.3	607
	380/415-50	201.2	400	133.4	348
	208/230-60		*		
· <u> </u> _	230-60	•	*		
L Service and Company	460-60	129.6	920	157.9	1175
171-XL	575-60	103.6	736	126.2	940
	380-60	156.9	1017	191.2	1299
	230-50	*	•		*
	380/415-50	161.7	1226	201.2	1265
	208/230-60	286.9	581	349.6	743
	230-60	258.2	581	314.6	743
NAME OF THE PARTY	460-60	129.6	291	157.9	371
171-WD	575-60	103.6	233	126.2	297
	380-60	156.9	321	191.2	410
	230-50	267.2	619	332.3	638
	380/415-50	161.7	387	201.2	400
	208/230-60	,	*		*
	230-60	•	+		*
	460-60	157.9	1175	157.9	1175
186-XL	575-60	126.2	940	126.2	940
	380-60	191.2	1299	191.2	1299
	230-50	,	*	*	1233
	380/415-50	201.2	1265	201.2	1265
	208/230-60	349.6	743	349.6	743
	230-60	314.6	743	314.6	743
	460-60	157.9	371	157.9	371
186-WD	575-60	126.2	297	126.2	297
4	380-60	191.2	410	191,2	410
	230-50	332.3	638	332.3	
	380/415-50	201.2	400	201.2	638 400

LEGEND

LRA — Locked Rotor Amps
RLA — Rated Load Amps
WD — Wye-Delta Start
XL — Across-the-Line Start

\*Units are shipped with wye-delta start as standard. Across-the-line start is not available.



### COMPRESSOR ELECTRICAL DATA, 30HXA UNITS (cont)

UNIT SIZE	NAMEPLATE V-Hz		A1		OR NUMBERS		
30HXA	(3 Phase)	RLA			A2		31
	208/230-60	*	LRA	RLA	LRA	RLA	LRA
	230-60	*	*	*	*	*	•
6	460-60				•	•	
000 144	575-60	129.6	920	73.1	580	157.9	1175
206-XL		103.6	736	58.5	484	126.2	94
	380-60	156.9	1017	88.5	641	191.2	129
	230-50 380/415-50	404.7		*		*	*
		161.7	1226	92.0	715	201.2	126
#9	208/230-60	286.9	581	162.0	367	337.6	743
×	230-60	258.2	581	145.8	367	303.8	743
000 1115	460-60	129.6	291	73.1	183	157.9	371
206-WD	575-60	103.6	233	58.5	147	126.2	297
	380-60	156.9	321	88.5	203	191.2	410
	230-50	267.2	619	152.0	361	332.3	638
	380/415-50	161.7	387	92.0	226	201.2	400
	208/230-60		•		*	*	*
	230-60		*	•			
551	460-60	157.9	1175	106.6	820	157.9	1175
246-XL	575-60	126.2	940	85.1	656	126.2	940
	380-60	191.2	1299	129.0	906	191.2	1299
	230-50	•	•	•	*	191.2	1299
	380/415-50	201.2	1265	133.4	960	201.2	
	208/230-60	337.6	743	235.9	518	337.6	1265 743
	230-60	303.8	743	212,3	518		
	460-60	157.9	371	106.6	259	303.8	743
246-WD	575-60	126.2	297	85.1	207	157.9	371
	380-60	191.2	410	129.0	286	126.2	297
	230-50	332.3	638	220.3		191.2	410
	380/415-50	201.2	400	133.4	485	332.3	638
	208/230-60	1 1 1 1 1 1	*	100.4	303.	201.2	400
	230-60	*	*	-	*	*	
	460-60	157.9	1175			N	•
261-XL	575-60	126.2	940	129.6	920	157.9	1175
	380-60	191.2	1299	103.6	736	126.2	940
*	230-50	*	1299	156.9	1017	191.2	1299
	380/415-50	201.2	1005		*	*	
	208/230-60	337.6	1265 743	161.7	1226	201.2	1265
1	230-60	303.8	-	286.9	581	337.6	743
1	460-60		743	258.2	581	303.8	743
261-WD	575-60	157.9 126.2	371	129.6	291	157.9	371
	380-60		297	103.6	233	126.2	297
ŀ	230-50	191.2	410	156.9	321	191.2	410
ŀ	380/415-50	332.3	638	267.2	619	332.3	638
		201.2	400	161.7	387	201.2	400
ŀ	208/230-60	-	*	*	•		*
H	230-60			•	*	*	*
,,, ,, ,	460-60	157.9	1175	157.9	1175	157.9	1175
271-XL	575-60	126.2	940	126.2	940	126.2	940
1	380-60	191.2	1299	191.2	1299	191.2	1299
L	230-50		*	*	*	•	*
	380/415-50	201.2	1265	201.2	1265	201.2	1265
	208/230-60	337.6	743	337.6	743	337.6	743
L	230-60	303.8	743	303.8	743	303.8	743
L	460-60	157.9	371	157.9	371	157.9	371
71-WD	575-60	126.2	297	126.2	297	126.2	297
	380-60	191.2	410	191.2	410	191.2	410
	230-50	332,3	638	332.3	638	332.3	638
· F	380/415-50	201.2	400	201.2	400	201.2	400

LEGEND

<sup>\*</sup>Units are shipped with wye-delta start as standard. Across-the-line start is not available.

### **Controls**

The standard microprocessor-based control in the 30HX units provides the following functions:

- leaving fluid temperature control (using both entering and leaving fluid sensors)
- · 7-day time sequence of both pump and chiller
- temperature reset from return fluid (standard) or from outdoor ambient (accessory), occupied space temperature (accessory), 4 to 20 mA signal (accessory), or via the optional Carrier Comfort Network (CCN)
- automatic compressor lead-lag switching based on compressor accumulated run times and number of cycles
- automatic temperature range across the cooler adjustment
- · fully automatic control of the chiller components


A 4-line, 20-character per line display is used to accomplish the following (see figure below):

- · 'set schedules and set points
- · identify operating mode
- display current temperatures and pressures being used by the control for internal calculations
- · identify abnormal (alarm or alert) conditions

#### Sequence of operation

The control has a 44 F (6.2 C) leaving fluid temperature (LWT) set point as shipped from the factory. If temperature reset or demand limiting is in effect, this set point may change.

**Start-up** — The chiller will start when the circulating pump is energized. (If the flow switch is applied, the chiller starts after the flow has been proven.) The compressor starts unloaded.





NOTE: Which compressor starts first is determined by the automatic lead/lag feature.

If the entering fluid temperature is 85 F (29 C) or higher, the maximum operating pressure (MOP) feature limits the suction pressure to keep the chiller on line.

**Normal operation** — The entering fluid temperature sensor monitors changes in entering fluid temperature to anticipate changes in the cooling load. Based on leaving fluid temperature, the control adds or subtracts capacity to maintain a constant leaving fluid temperature.

**Dual chiller control** — The Dual Chiller Routine is available for the control of two units supplying chilled fluid on a common loop.

In parallel flow applications, an additional leaving fluid temperature thermistor must be installed and connected to the lead chiller.

**Transition to off** — The chiller unloads once the "time-to-stop" signal has been given. This signal can be either internal or external.

**Safeties** — The 30HX control as shipped from the factory automatically deenergizes any active compressor that experiences any of the following:

- electrical overload
- thermal overload protection
- high pressure
- · low oil pressure
- · loss of refrigerant charge
- loss of phase protection
- reverse rotation (control prevents compressor start)
- current imbalance
- ground current
- · low chilled fluid temperature

#### Additional information

Detailed information on controls and operation is available in the Controls, Start-Up, Operation and Troubleshooting guide included with each unit. Packaged Service Training programs are also available. Contact your Carrier representative for more information.

### **Guide specifications**

## Water-Cooled and Condenserless HVAC Guide Specifications

Size Range: 75 to 265 Tons (264 to 931 kW)

Carrier Model Number: 30HXA — Condenserless 30HXC — Water-Cooled

#### Part 1 — General

#### 1.01 SYSTEM DESCRIPTION

Microprocessor controlled water-cooled (30HXC) or condenserless (30HXA) liquid chiller utilizing screw compressors and electronic expansion valves.

#### 1.02 QUALITY ASSURANCE

- A. Unit shall be rated in accordance with ARI Standard 550/590-98 (U.S.A.). The 60 Hz 30HXC units shall be ARI certified for performance.
- B. Unit construction shall comply with ASHRAE 15 Safety Code, NEC, and ASME applicable codes (U.S.A. codes).
- Unit shall be manufactured at an ISO 9001:2000 registered facility.
- D. 208/230 v, 230 v, 460 v, 575 v, 60 Hz units shall be constructed in accordance with UL or UL Canada standards and shall be tested and listed by ETL or ETL, Canada, as conforming to those standards. Units shall carry the ETL and ETL, Canada, labels.

#### 1.03 DELIVERY, STORAGE, AND HANDLING

- A. Unit controls shall be capable of withstanding 150 F (66 C) storage temperatures in the control compartment.
- B. Unit shall be stored and handled per unit manufacturer's recommendations.

#### Part 2 — Products

#### 2.01 EQUIPMENT

#### A. General:

Factory assembled, single-piece, water-cooled (30HXC) or condenserless (30HXA) liquid chiller with dual (2) independent refrigerant circuits. Contained within the unit cabinet shall be all factory wiring, piping, controls, refrigerant charge (HFC-134a) (30HXA units shipped with holding charge only), and special features required prior to field start-up.

#### B. Compressors:

- Semi-hermetic twin-screw compressors with internal muffler and check valve.
- Each compressor shall be equipped with a discharge shutoff valve.

#### C. Cooler (Evaporator):

 Shall be tested and stamped in accordance with ASME Code (U.S.A.) for a refrigerant workingside pressure of 220 psig (1408 kPa). Waterside pressure rating shall be 300 psig (2068 kPa). In Canada, maximum waterside pressure shall be 250 psig (1725 kPa), per the Canadian National Registry.



- 2. Shall be mechanically cleanable shell-and-tube type with removable heads.
- Tubes shall be internally enhanced, seamlesscopper type, and shall be rolled into tube sheets.
- Shall be equipped with Victaulic fluid connections.
- Shell shall be insulated with <sup>3</sup>/<sub>4</sub>-in. (19-mm) closed-cell, polyvinyl chloride foam with a maximum K factor of 0.28. Heads may require field insulation.
- Shall have a cooler drain and vent.
- Design shall incorporate 2 independent refrigerant circuits.
- Shall include isolation valves to allow isolation of the refrigerant charge in either the evaporator or the condenser.
- Shall be equipped with factory-installed thermal dispersion chilled fluid flow switch.

#### D. Condenser (30HXC units):

- Shall be tested and stamped in accordance with ASME code (U.S.A.) for a refrigerant workingside pressure of 220 psig (1408 kPa). Waterside pressure rating shall be 300 psig (2068 kPa). In Canada, maximum waterside pressure shall be 250 psig (1725 kPa), per the Canadian National Registry.
- Shall be mechanically cleanable shell-and-tube type with removable heads.
- Tubes shall be internally enhanced, seamlesscopper type, and shall be rolled into tube sheets.
- Shall be equipped with Victaulic water connections.
- Design shall incorporate 2 independent refrigerant circuits.

#### E. Oil Separator (30HXA Units):

- Shall be tested and stamped in accordance with ASME Code (U.S.A.) for a refrigerant workingside pressure of 320 psig (2206 kPa).
- 2. Design shall incorporate 2 independent refrigerant circuits.

#### F. Refrigeration Components:

Refrigerant circuit components shall include oil separator, high and low side pressure relief devices, discharge and liquid line shutoff valves, filter drier, moisture indicating sight glass, expansion valve, refrigerant economizer (unit sizes 161-271), and complete charge of compressor oil. The 30HXC units shall have a complete operating charge of refrigerant HFC-134a; 30HXA units shall have a holding charge only.



- G. Controls, Safeties, and Diagnostics:
  - 1. Controls:
    - Unit controls shall include the following minimum components:
      - Microprocessor with non-volatile memory. Battery backup system shall not be accepted.
      - Power and control circuit terminal blocks.
      - 3) ON/OFF control switch.
      - 4) Replaceable solid-state relay panels.
      - 5) Thermistor installed to measure saturated condensing temperature, cooler saturation temperature, compressor return gas temperature, and cooler entering and leaving fluid temperatures.
      - 6) Chilled fluid flow switch.
    - b. Unit controls shall include the following functions as standard:
      - 1) Automatic circuit lead/lag.
      - Capacity control based on leaving chilled fluid temperature and compensated by rate of change of return-fluid temperature with temperature setpoint accuracy to 0.1 ° F (0.06° C).
      - 3) Limiting the chilled fluid temperature pull-down rate at start-up to an adjustable range of 0.2° F to 2° F (0.11° C to 1.1° C) per minute to prevent excessive demand spikes at start-up.
      - 4) Seven-day time schedule.
      - Leaving chilled fluid temperature reset from return fluid, outdoor-air temperature, space temperature, or 4 to 20 mA input.
      - Demand limit control with 2-stage control (0 to 100% each) or through 4 to 20 mA input (0 to 100%).
      - 7) Chilled and condenser water pump start/stop control.
      - Dual chiller control for series chiller applications without addition of hardware modules or additional thermistors.
      - Dual chiller control for parallel flow applications use one additional sensor.
      - Amperage readout per compressor with %MTA per compressor.
  - c. The control panel shall include, as standard, a portable hand held display module with a minimum of 4 lines and 20 characters per line, of clear English, Spanish, Portuguese or French language. Display menus shall provide clear language descriptions of all menu items, operating modes, configuration points and alarm diagnostics. Reference to factory codes shall not be accepted. An industrial grade coiled extension cord shall allow the display module to be moved around the chiller. Magnets shall hold the display module to any sheet metal panel to

allow hands-free operation. Display module shall have NEMA 4x housing suitable for use in outdoor environments. Display shall have back light and contrast adjustment for easy viewing in bright sunlight or night conditions. The display module shall have raised surface buttons with positive tactile response.

- d. The chiller controller shall include multiple connection ports for communicating with the local equipment network, the Carrier Comfort Network (CCN) and the ability to access all chiller control functions from any point on the chiller.
- The control system shall allow software upgrade without the need for new hardware modules.

#### 2. Safeties:

Unit shall be equipped with thermistors and all necessary components in conjunction with the control system to provide the unit with the following protections:

- a. Loss of refrigerant charge.
- b. Reverse rotation.
- c. Low chilled fluid temperature.
- d. Low oil pressure (each compressor circuit).
- e. Voltage imbalance.
- f. Ground current fault.
- g. Thermal overload.
- h. High pressure.
- i. Electrical overload.
- j. Loss of phase.
- k. Current imbalance.
- l. Loss of flow.

#### 3. Diagnostics:

- a. The display module shall be capable of indicating the safety lockout condition by displaying the information in clear language at the display. Information included for display shall be:
  - 1) Compressor lockout.
  - 2) Loss of charge.
  - 3) Low fluid flow.
  - 4) Low oil pressure.
  - 5) Cooler freeze protection.
  - 6) High or low suction superheat.
  - 7) Thermistor malfunction.
  - 8) Entering and leaving-fluid temperature.
  - 9) Evaporator and condenser pressure.
  - 10) Electronic expansion valve positions.
  - 11) All set points.
  - 12) Time of day.

## **Guide specifications (cont**

- b. Display module, in conjunction with the microprocessor, must also be capable of displaying the output results of a service test. Service test shall verify operation of every switch, thermistor, and compressor before chiller is started. User shall be able to force each output device.
- c. Diagnostics shall include the ability to review a list of the 20 most recent alarms with clear language descriptions of the alarm event. Display of alarm codes without the ability for clear language descriptions shall be prohibited.
- d. An alarm history buffer shall allow the user to store no less than 20 alarm events with clear language descriptions, time and date stamp event entry.

#### H. Operating Characteristics:

Unit shall be capable of starting up with 95 F (35 C) entering fluid temperature to the cooler.

#### I. Electrical Requirements:

- 1. Unit primary electrical power supply shall enter the unit at a single location (some units have multiple power poles).
- 2. Unit shall operate on 3-phase power at the voltage shown in the equipment schedule.
- 3. Control voltage shall be 115-v (60 Hz) or 230-v (50 Hz), single-phase, separate power supply.
- Unit shall be shipped with factory control and power wiring installed.

#### J. Special Features:

Certain standard features are not applicable when the features designated by \* are specified. For assistance in amending the specifications, contact your local Carrier Sales office.

#### \* 1. Wye-Delta Starter:

Unit shall have a factory-installed, Wye-Delta starter to minimize electrical inrush current.

#### 2. Sound Reduction Enclosure:

Unit shall have field-installed sound reduction enclosure which covers the entire unit to muffle compressor noise.

#### 3. Vibration Isolation:

Unit shall be supplied with rubber-in-shear vibration isolators for field installation.



#### 4. Control Power Transformer:

Unit shall be supplied with a field-installed transformer that will supply control circuit power from the main unit power supply.

#### 5. Temperature Reset Sensor:

Unit shall reset leaving chilled fluid temperature based on outdoor ambient temperature or space temperature when this sensor is installed.

#### \* 6. Brine Option:

Unit shall be factory modified to start and operate at leaving chilled fluid temperatures of between 15 F (-9 C) and 40 F (4.4 C).

#### \* 7. Minimum Load Control:

Unit shall be equipped with factory (or field) installed, microprocessor-controlled, minimum load control that shall permit unit operation down to 10% of full capacity.

#### 8. Multi-Chiller Control:

Control shall enable management of multiple parallel chillers (up to 8) or two (2) chillers in series in a single system.

#### 9. Minus-One-Pass Cooler:

Factory-installed option shall reduce pressure drop for high flow applications. Shall also provide same end inlet and outlet for 076-106 sizes and opposite end inlet for 116-271 sizes.

#### 10. Plus-One-Pass Cooler:

Factory-installed option shall enhance low temperature brine performance.

#### 11. Suction Service Valves:

Unit shall be supplied with factory-installed suction service valves.

#### 12. Cooler Head Insulation:

Unit shall be supplied with field-installed cooler insulation that shall cover the cooler heads.

#### 13. Energy Management Module:

A factory or field installed module shall provide the following energy management capabilities: 4 to 20 mA signals for leaving fluid temperature reset, cooling set point reset or demand limit control; 2-point demand limit control (from 0 to 100%) activated by a remote contact closure; and discrete input for "Ice Done" indication for ice storage system interface.